


### **Photoelectric Sensors**

MultiTask photoelectric sensors, miniature photoelectric sensors, small photoelectric sensors, compact photoelectric sensors, cylindrical photoelectric sensors, fiber-optic sensors and fibers



### www.mysick.com - select and order online

#### Search online quickly and safely - with the SICK "Finders"



**Product Finder:** We can help you to quickly target the product that best matches your application.

**Applications Finder:** Select the application description on the basis of the challenge posed, industrial sector, or product group.

**Literature Finder:** Go directly to the operating instructions, technical information, and other literature on all aspects of SICK products.

#### Efficiency - with the e-commerce tools from SICK




**Find out prices and availability:** Determine the price and possible delivery date of your desired product simply and quickly at any time.

**Request or view a quote:** You can have a quote generated online here. Every quote is confirmed to you via e-mail.


**Order online:** You can go through the ordering process in just a few steps.

### Navigation in the PDF document - Links to online ordering system


#### By bookmarks and tables of contents



#### By page references



#### By links, QR codes and part numbers







### **Guidance system pictograms**

### **Housing properties**





















Tictograms marked with a star describe special properties that are necessary for special applications.

Sensor properties











Stainless steel PTFE coating





**Optics properties** 

















**DELTA-S** 

**Special applications** 





















Zero gap detection

**Fibers** 

### Fiber properties





























Sensor properties



















LCDs/









### **Smart Sensor Solutions**











### Quickly and easily choose from a wide range of variants

With its comprehensive portfolio of photoelectric sensors, SICK offers a wide range of solutions for all kinds of tasks.

The guidance system used in this catalog features a range of pictograms presented in various colors, which enables you to quickly locate the right sensor for you. The pictograms direct you to the key properties such as the housing, sensor principle, and optics, and form the "building blocks" for finding the right sensor solution. Since special applications often require special properties, these are marked with a star  $\star$ .


At the start of each chapter, you will find selection guides that will provide you with a quick general overview of the products to help you choose the appropriate solution.

### Housing properties

- Design, page B-18
- Materials, page B-20
- Special housing types, page B-21

### Sensor properties

- Photoelectric proximity sensors, page B-24
- Photoelectric retro-reflective sensors, page B-25
- Through-beam photoelectric sensors, page B-26
- Special sensor properties, page B-27



### Special applications

- Hygienic and washdown zones, page B-42
- ZoneControl, page B-45
- Detecting transparent objects, page B-46
- Detecting perforated objects, page B-49 - Detecting small objects, page B-50
- Detecting uneven, shiny objects, page B-52
- Detecting objects wrapped in film, page B-53
- Detecting objects with position tolerances, page B-54
- Detecting high-speed objects, page B-55
- Explosive areas, page B-56
- Zero gap detection, page B-57

	General information About SICK	A
	Technology	В
	Smart Sensor Solutions	C
on the state of th	Applications	D
	MultiTask photoelectric sensors	E
	Miniature photoelectric sensors	F
	Small photoelectric sensors	G
	Compact photoelectric sensors	н
	Cylindrical photoelectric sensors	1
	Fiber-optic sensors and fibers	J
ny product	Tailored solutions	K
	Accessories	L
	Appendix Index	M



### We deliver "Sensor Intelligence."

SICK sensor solutions for industrial automation are the result of exceptional dedication and experience. From development all the way to service: The people at SICK are committed to investing all their expertise in providing with the very best sensors and system solutions possible.

### A company with a culture of success

Over 6,000 people are on staff, with products and services available to help SICK sensor technology users increase their productivity and reduce their costs. Founded in 1946 and headquartered in Waldkirch, Germany, SICK is a global sensor specialist with more than 40 subsidiaries and representations worldwide. Our exemplary corporate culture fosters an optimum

work-life balance, thus attracting the best employees from all over the world. SICK is one of the best employers – we have been among the winners of the prestigious German "Great Place to Work" award for many years in succession.



### Innovation for the leading edge

SICK sensor systems simplify and optimize processes and allow for sustainable production. SICK operates at many research and development centers all over the world. Co-designed with customers and universities, our innovative sensor products and solutions are made to give a decisive edge. With an impressive track record of innovation, we take the key parameters of modern production to new levels: reliable process control, safety of people and environmental protection.

### A corporate culture for sustainable excellence

SICK is backed by a holistic, homogeneous corporate culture. We are an independent company. And our sensor technology is open to all system environments. The power of innovation has made SICK one of the technology and market leaders – sensor technology that is successful in the long term.











### "Sensor Intelligence." for all requirements

SICK is a renowned expert in many industries, and is entirely familiar with the critical challenges they face. While speed, accuracy and availability take center stage in all industries, technical implementations vary greatly. SICK puts its vast experience to use to provide with precisely the solution you need.

### For applications worldwide

Hundreds of thousands of installations and applications go to prove that SICK knows the different industries and their processes inside out. This tradition of uncompromising expertise is ongoing: As we move into the future, we will continue to design, implement and optimize customized solutions in our application centers in Europe, Asia and North America. You can count on SICK as a reliable supplier and development partner.









### For your specific industry

With a track record of proven expertise in a great variety of industries, SICK has taken quality and productivity to new heights. The automotive, pharmaceutical, electronics and solar industries are just a few examples of sectors that benefit from our know-how. In addition to increasing speed and improving traceability in warehouses and distribution centers, SICK solutions provide accident protection for automated guided vehicles. SICK system solutions for analysis and flow measurement of gases and liquids enable environmental protection and sustainability in, for example, energy production, cement production or waste incineration plants.

### For performance across the board

SICK provides the right technology to respond to the tasks involved in industrial automation: measuring, detecting, monitoring and controlling, protecting, networking and integrating, identifying, positioning. Our development and industry experts continually create groundbreaking innovations to solve these tasks.

www.sick.com/industries











# For safety and productivity: SICK LifeTime Services

SICK LifeTime Services is a comprehensive set of high-quality services provided to support the entire life cycle of products and applications from plant walk-through all the way to upgrades. These services increase the safety of people, boost the productivity of machines and serve as the basis for our customers' sustainable business success.



### The benefit of SICK services

Each of our products and solutions is accompanied by a comprehensive range of services tuned precisely to the requirements of the product or solution – along its entire life cycle. Backed by extensive industry expertise and more than 60 years

of experience, LifeTime Services stand for maximum availability and an exceptional service life of our products and solutions.





## Consulting & Design

CHECH

## Verification & Optimization



## Training & Education



- Plant walk-through
- Risk assessment
- Safety concept
- · Feasibility studies
- Software and hardware design
- Inspection
- Maintenance
- Barcode checks
- · Accident investigation
- Stoptime measurement
- · Machine safety inspection
- User training
  - Seminars
- WebTraining



## Product & System Support

- Commissioning
- Exchange units and repairs
- Remote support
- Hotline



## Upgrade & Retrofits

- Machine conversion
- · Sensor upgrades
- · Retrofitting of technology

www.sick.com/services











### Versatile product range for industrial automation

From the simple acquisition task to the key sensor technology in a complex production process: With every product from its broad portfolio, SICK offers a sensor solution that best combines cost effectiveness and safety.

www.sick.com/products

### **Photoelectric sensors**



- Miniature photoelectric sensors
- Small photoelectric sensors
- Compact photoelectric sensors
- · Fiber-optic sensors and fibers
- · Cylindrical photoelectric sensors
- MutliTask photoelectric sensors

### **Proximity sensors**



- Inductive proximity sensors
- · Capacitive proximity sensors
- Magnetic proximity sensors

### **Magnetic cylinder sensors**



- Analog positioning sensors
- Sensors for T-slot cylinders
- · Sensors for C-slot cylinders
- Sensor adapters for other cylinder types

### **Identification solutions**



- Bar code scanners
- Image-based code readers
- Hand-held scanners
- RFID

### **Detection and ranging solutions**



· Laser measurement technology

### **System solutions**





- Volume measurement systems
- Code reading systems
- Dimension weighing scanning systems
- · Vision systems

### **Fluid sensors**



- · Level sensors
- Pressure sensors
- Flow sensors
- Temperature sensors

### **Registration sensors**



- · Contrast sensors
- · Color sensors
- Luminescence sensors
- · Fork sensors

- Array sensors
- · Register sensors
- · Markless sensors

### **Distance sensors**



- Short range distance sensors (displacement)
- Mid range distance sensors
- Long range distance sensors
- Linear measurement sensors
- · Ultrasonic sensors
- · Double sheet detector
- · Optical data transmission
- · Position finders

### A

### **Automation light grids**



- · Advanced automation light grids
- · Standard automation light grids
- Smart light grids

### **Vision**



- · Vision sensors
- · Smart cameras
- 3D cameras

### **Opto-electronic protective devices**



- · Safety laser scanners
- Safety camera systems
- Safety light curtains
- Multiple light beam safety devices
- Single-beam photoelectric safety switches
- Mirror and device columns
- · Upgrade kits

### **Safety switches**



- Electro-mechanical safety switches
- Non-contact safety switches
- · Safety command devices

### sens:Control - safe control solutions



- Safety relays
- Safety controllers
- · Network solutions

### **Motor feedback systems**











- · Interfaces: incremental, HIPERFACE® and HIPERFACE
- Safety motor feedback systems
- · Rotary and linear motor feedback systems for asynchronous, synchronous motors and linear motors

### **Encoders**



- Absolute encoders
- Incremental encoders
- · Linear encoders
- Wire draw encoders

### **Analyzers and systems**









- Gas analyzers
- Dust measuring devices
- Analyzer systems
- Liquid analyzers
- · Data acquisition systems
- Tunnel sensors

### Gas flow measuring devices



- Gas flow meters
- Mass flow meters
- Volume flow measuring devices

### **Software**



• Safexpert® safety software


B

### Overview of sensor selection

Today's automation industry covers a broad range of applications. SICK is determined to meet the market's requirements and, as a result, offers a wide range of sensor solutions.

To ensure you have a clear overview when it comes to selecting a product, we take you quickly and directly to the right sensor.

- Housing properties, page B-17
- Sensor properties, page B-23
- Optical properties, page B-33
- Special applications, page B-41



B



### Appearances do matter

Each field of application places high demands on the sensor solution it requires. This starts right from the housing: to ensure that the sensors are seamlessly installed and provide reliable results, they have to be able to withstand a wide variety of environmental conditions. Because each core is only as good as its shell.



### Housing properties

- Design, page B-18
- Materials, page B-20
- Special housing types, page B-21











SICK's portfolio offers a wide variety of sensors for different installation situations. The rectangular designs, in particular, are available in a wide range of different sizes, providing ideal automation solutions even if there is only a small amount of space.

Cylindrical photoelectric sensors in standard or short designs and flexible hybrid designs complete the portfolio and expand the application options thanks to their range of variants (for details see Chapter I, cylindrical photoelectric sensors, from page I-683).

### Rectangular design

MultiTask photoelectric sensors . . . Chpt. E Miniature photoelectric sensors... Chpt. F Small photoelectric sensors . . . . . Chpt. G Compact photoelectric sensors . . . Chpt. H

### Cylindrical design

Cylindrical photoelectric sensors . . . Chpt. I

### Hybrid design

Cylindrical photoelectric sensors . . . Chpt. I

#### **Fibers**

Fibers provide a "slim line" connection between the sensor and the sensing target. They are a key feature of sensor solutions. When only a small space is available or when sensors must be installed in harsh environments, fibers are often the only way of detecting objects, details, positions, or marks.



The starting point for finding the ideal sensor solution for your application is choosing the right fiber and design. At SICK, the broad range of plastic and glass fibers permits optimal automation solutions. This applies, in particular, to tasks where the fiber must be specifically adapted to the application, where flexible cable installation is crucial, where high temperatures are common, or where a particular material compatibility is important. Plastic fibers are characterized by the smallest bend radii and maximum flexibility, and can be cut to any length. Glass fibers are more chemically resistant and are suitable for a high temperature range. The wide variety of end sleeves or individual special sleeves can handle virtually any installation requirement. Depending on the application, the protective cladding of the fibers can be made from plastic, metal, or PTFE (for exposure to aggressive chemicals).

In addition to a wide range of fiber-optic sensors, (amplifiers such as the WLL180T), world-leading response times of up to  $16~\mu s$  and sensing ranges of up to 20~m can be achieved with the corresponding fibers.

Fibers are available as **through-beam** or **proximity sensors** and cover an extremely wide range.

#### Through-beam system



- Sender and receiver fibers are mounted separately from one another
- Detection of objects by moving the optical axis between sender and receiver
- Very large sensing ranges
- Accurate positioning
- Stable measuring position
- Optically opaque objects can be detected regardless of their shape, color, or material
- · Strong light beam

#### **Proximity system**



- Sender and receiver fibers are combined in a single sensor head
- Recognition of object by detecting the light beam reflected from the object
- · Optical axis does not need to be adjusted
- · Reflective or transparent objects can be detected
- Easy mounting
- Ideal for color and position markings

Fiber-optic sensors and fibers..... Chpt. J







### **Materials**

VISTA

Stainless steel PTFE coating

## In addition to plastic and metal housings, SICK offers other special housing materials for the most challenging environments.

### **VISTAL®**



SICK is the only sensor manufacturer that uses the extremely rugged VISTAL® housing material. VISTAL® is a highly rigid fiber-glass reinforced plastic that is characterized by significantly enhanced mechanical properties com-

pared with standard plastic materials (e.g., +900% E modulus in accordance with ISO 527, or +400% Brinell hardness in accordance with ISO 2039-1). This results in a highly rugged sensor housing. Another benefit of VISTAL®: the material is resistant to chemicals and therefore does not react adversely to cleaning agents and production chemicals.

#### Stainless steel



It's all about using sensors that offer maximum reliability under the harshest of conditions to safeguard productivity! Sensors enclosed in a stainless steel housing are chemically resistant, rust-proof, and durable. The chemically

resistant stainless steel housing makes these sensors suitable for applications requiring frequent intensive cleaning and disinfection. This is a key benefit for use in hygienic and washdown zones, particularly in the pharmaceutical and the food and beverage industries, but also in the packaging, electronics, and solar industries.

Special application:
 Hygienic and washdown zones, page B-44



W9-3 G-	448	W9L-3	G-470
W9-3 Glass G-	462	W9LG-3	G-484

You can find selection guides for sensors with stainless steel housings at the start of each chapter.





The PTFE housing material is unaffected by solvents and other aggressive chemicals. It shows no change whatsoever following contact with most chemicals. Its surface is so smooth and slippery that hardly any external substance can stick to it. It has the ideal properties for use in hygienic and washdown zones.

 Special application: Hygienic and washdown zones, page B-44



W4-3 PTFE F-250	W12G G-520
W12-2 Laser G-510	W12-3G-528







### Special housing types

69K Explo





In addition to ensuring dust particles don't enter the housing, the IP 69K design guarantees that the sensors and their accessories can withstand intensive cleaning processes.

- 100 bar high-pressure jet cleaning
- 16 liters per minute
- 80 °C water temperature
- 100 mm distance to unit under test
- Test with spray angle of 0°, 30°, 60°, and 90° with the unit under test rotating (5 revolutions per minute)

The IP 69K enclosure rating is the result of a sophisticated design and durable materials. It enables SICK sensors to easily withstand chemicals from high-pressure jet cleaning processes. This process, which is known as "washdown" is used particularly in the food and beverage industry as well as in the pharmaceutical industry to protect against bacteria and microorganisms. Sensors with the IP 69K enclosure rating are therefore not impaired by such organisms.

 Special application: Hygienic and washdown zones, page B-44



You can find selection guides for sensors with an IP 69K enclosure rating at the start of each chapter.



### Explosion protection housing

Explosive areas are divided into zones. Using a sensor with this type of housing depends on the frequency and duration of a potentially explosive occurrence. Each zone defines what measures need to be taken and specifies the requirements for the sensors that should be applied.

**Zone 2G:** Sensors must guarantee a high level of safety. The W24-2 Ex sensor is therefore equipped with a rugged housing and specially designed NAMUR switching outputs.

**Zone 3D/3G:** Sensors must guarantee a normal level of safety. For these zones, SICK offers the W18-3 Ex and the W27-3 Ex in ready-to-install versions that comply with the standards (sensors with protective housing).

 Special application: Explosive areas, page B-56





Category 2G

W24-2 Ex ..... H-602

Category 3D/3G

W18-3 Ex . . . . . . . . G-556 W27-3 Ex . . . . . . . . . H-632

8015327/2014-02-08 Subject to change without notice



### It's what's inside that counts

Ensuring reliable detection on a wide range of surfaces relies on choosing the right sensor properties. Three basic sensor principles and their properties determine the sensing range, switching frequency, and switching threshold.




### Sensor properties

- Photoelectric proximity sensors, page B-24
- Photoelectric retro-reflective sensors, page B-25
- Through-beam photoelectric sensors, page B-26
- Special sensor properties, page B-27
- IO-Link, page B-28
- AutoAdapt, page B-30

### Photoelectric proximity sensors

\_\_\_\_



With photoelectric proximity sensors, the sender and receiver are in a single housing. The separate optics are angled towards each other, meaning that the point of intersection forms the upper limit for the sensing range. Photoelectric proximity sensors detect an object as soon as the reflected sensor light is received from its surface. When an object is detected, the sensor generates a defined, electrical output signal.

### Energetic



The energetic photoelectric proximity sensor with adjustable sensitivity is the most cost-effective variant. A light-colored surface reflects more light than a dark one and can therefore be detected from a greater distance away. To achieve similar results with a dark surface, the sensitivity of the sensor must be increased. Detecting a dark object against a light background is a challenge for energetic sensors. The object is obscured by the brighter background due to its higher reflectivity. Light-colored objects against dark backgrounds are easier to detect.

### Background suppression (BGS)



Photoelectric proximity sensors with

background suppression operate on the basis of the geometric relation between the sending and receiving elements. The sensor is set to detect the object lying on the sensing range plane. Signals from objects located behind the set sensing range plane are suppressed. In addition, the use of a diffuse LED and patented SIRIC® technology make a kind of "spatial vision" possible. The result is unparalleled detection reliability and ambient light immunity for small, transparent, or reflective objects in the area close to the machine – even with varying brightness or color contrasts.

### Foreground suppression (FGS)



Photoelectric proximity sensors with foreground suppression are able to detect objects at a defined sensing range. All objects between the sensing range (set to the background) and the sensor are detected. The foreground is suppressed as a result of the special configuration of the sending and receiving elements in relation to one another. To ensure these sensors function reliably, the background (for example, a conveyor belt) needs to be relatively bright and should not vary in height. Photoelectric proximity sensors with foreground suppression are particularly well-suited for detecting dark and very shiny objects.

You can find selection guides for photoelectric proximity sensors at the start of each chapter.



### Photoelectric retro-reflective sensors



With photoelectric retro-reflective sensors, the emitted light is returned by a reflector and is received and evaluated by the device. Polarizing filters prevent errors when detecting reflective objects. The use of laser diodes allows greater sensing ranges while simultaneously maintaining a high resolution. Focus ranges can be set with high precision. Photoelectric retro-reflective sensors are particularly suited for detecting transparent objects.

In such cases, it helps to use devices with reduced sensitivity or foreground suppression as well as an AutoAdapt function that dynamically changes the switching threshold based on environmental conditions.

- · Sender and receiver in a single housing
- · Different reflector sizes for various sensing ranges and object sizes
- · Polarizing filters allow reflective objects to be detected
- Automatic sensitivity correction for detecting transparent objects

### Standard optics



With the **dual lens system**, the sent and received beams are physically separated and are positioned at a shallow angle to one another. The sent and received beams only overlap in a certain sensing range segment. At close range, there is a blind

zone where an object cannot be detected. When using sensors with dual lens optics, it is therefore important to note the specified minimum range, which should never be undercut.

### Autocollimation



With the autocollimation principle, which unlike the dual lens principle uses only one optical lens, both the beam of light emitted by the sensor and the beam reflected by the reflector lie on a single optical axis. The emitted light passes through

a semitransparent mirror before exiting the optical unit. After being returned by the reflector, the beam of light is diverted to the receiver with the aid of the same mirror.


The benefit of the autocollimation principle is that, unlike the dual lens principle, there is no blind zone in the area directly in front of the sensor. This enables even those objects that pass directly in front of the sensor to be reliably detected. As a result, photoelectric retro-reflective sensors with the autocollimation principle can also be mounted behind small gaps or openings.

You can find selection guides for photoelectric retro-reflective sensors at the start of each chapter.



### Through-beam photoelectric sensors





Through-beam photoelectric sensors are composed of two devices: a sender and a receiver. They are physically separate from one another and are each contained in their own housing.

The sender contains a light emitting diode (LED) or laser diode, and the receiver detects the incident light with a photodiode. Especially with the use of laser diodes, the separation of sender and receiver allows extremely long sensing ranges with

a simultaneously high resolution and a precise setting of the focus range. Through-beam photoelectric sensors can therefore reliably detect opaque and reflective objects. However, through-beam photoelectric sensors are only suitable for detecting transparent objects to a limited extent.

You can find selection guides for through-beam photoelectric sensors at the start of each chapter.






Switching frequency

AC/DC

### Special sensor properties



Fast response times enable reliable product detection in fast-paced manufacturing processes. This is a crucial feature in the detection of high-speed objects.



### Switching frequency ≥ 2 kHz

Thanks to extremely high switching frequencies ranging from 2 kHz to 32 kHz, combined with extremely fast response times, these sensors are well-equipped for use in a special application: reliably detecting and recognizing the accurate positioning of very fast objects and operations in high-speed processes. Whether in the automotive, electronics, solar, or machine tools industry, these SICK product families are indispensable when speed and precision are required.

Special application:
 Detecting high-speed objects, page B-55



W4S-3 F-260	W12-2 Laser G-510
W8 F-372	WLL170-2J-790
W8 Laser F-398	WLL180TJ-798
W100 Laser F-412	

### AC/DC



In addition to the sensors that operate in the standard voltage range of 10 to 30 V DC, SICK also offers photoelectric sensors with a universal power supply and relay output. These devices can be operated with a supply voltage ranging from

24 to 240 V UC (i.e., V DC or V AC) and can therefore be used flexibly in a wide range of applications – both in industrial and


commercial areas. The relay output also allows higher outputs to be directly connected via the sensor in a safe and reliable manner.

R/IR E-148 G10 G-430 W24-2 H-590	
W27-3H-616	



**IO-Link** 

R



### Clearing the final hurdles

A consistent communication concept right down to the lowest field level is key to using the features and technologies of state-of-the-art sensors and actuators, and making machines and systems more productive as a result. Through IO-Link, leading automation manufacturers have managed to establish a standard that solves the problem of clearing those final tricky hurdles in the communication chain. The standard interfaces that have been used on the sensor/actuator level up to now have not allowed the exchange of any data besides the actual


process value. With sensors and actuators using integrated intelligence to perform increasingly complex functions, these straightforward output state or measured value interfaces have restricted communication and even curbed innovation in this area. In fact, transparent networking on all levels is essential if we want to look at a machine as a whole and, in this context, think about how we can optimize it. It must be possible to represent every component in the entire system network in terms of the information depth that it requires.

### Spurring on innovation: The lowest field level

In an effort to drive productivity, leading automation manufacturers use IO-Link to define an open interface between sensors and actuators on one side and I/O modules on the other. In accordance with current standards for I/O networking via a point-to-point connection, the result is a communication channel that enables consistent transmission of process, parameter, and diagnostics data.

IO-Link involves a point-to-point connection that may be located underneath any given network. Being an integral part of the I/O module, the IO-Link master is installed either in the control cabinet or directly in the field as a remote I/O with an IP 65 and IP 67 enclosure rating. The IO-Link device is coupled with the master using a standard sensor/actuator cable measuring up to 20 m in length. The device – which may be any sensor, any actuator, or a combination of the two – sends and receives signals that are digitally transmitted via IO-Link. These signals can be "binary switching", "analog", "input", or "output", for instance.

To facilitate data transmission between the master and the device, the technology specifies a 3-wire design that is already familiar in the world of standard sensors and actuators. A standard UART protocol is used. The data is represented in what are known as data frames. In order to efficiently support the various forms of implementation for the IO-Link devices, different data frames have been specified. These data frames contain, for example, only service data, only process data, or a mixture of the two. Various transmission rates are available for communication between the master and the device on the physical layer. This makes it possible to implement sensors with configuration properties (receivers of service data or senders of process data) using just a few bits of user data. In addition, the technology allows the representation of signal bundles or complex hybrids such as analog input data or binary input and output data. Plus, IO-Link sensors with one switching bit are consistently compatible with standard sensors.



#### Overview of IO-Link communication

- · Serial, bidirectional point-to-point connection
- No new bus system for signal transmission and power supply
- Backward-compatible with discrete standard PNP output sensors
- Operating modes: standard I/O mode (SIO), IO-Link mode
- Three transmission rates: 4,800 baud (COM 1), 38,400 baud (COM 2), 230,400 baud as an option (COM 3)
- Unshielded, standard 3-wire industrial cable for all connections
- M12 plug connector: 4-pin male connector for sensors, for example; 5-pin male connector for actuators, for example; 5-pin female connector for master

You can find additional information on IO-Link in Chapter C: Smart Sensor Solutions.

- Pin assignment: pin 1 with 24 V, pin 3 with 0 V, pin 4 with switching and communication cable (C/Q)
- · Maximum cable length: 20 m
- Maximum power consumption for power supply: 200 mA
- Process data (such as switching signals or distance values) is transmitted cyclically; service data (such as parameters) is transmitted acyclically

DeltaPac E-114	W4SL-3 F-278
W2S-2 F-216	W4SLG-3V F-350
W2SG-2 F-232	W4SLG-3H F-364
W4S-3 F-260	W12G
W4S-3 Glass F-272	W12-3G-528





B



In the automated world, the aim is to minimize machine downtime. Thanks to the innovative AutoAdapt threshold adaptation, cleaning intervals can be extended and a longer sensor service life and higher system throughput can be achieved. The result: increased productivity.

### The benefits of AutoAdapt at a glance

- When contamination occurs, the sensor automatically adjusts itself to the new conditions
- Maintenance of the devices is only required when contamination is significant
- · The original threshold is automatically reset after cleaning


## Signal attenuation due to an object in the light path

- · Transparent objects weaken the beam of light
- Signal weakening or attenuation varies depending on the transparency of the object
- With the help of continuous threshold adaptation (AutoAdapt) or the autocollimation principle, highly transparent objects such as films and PET bottles are reliably detected

Sensors designed for the detection of transparent objects feature **AutoAdapt**, which allows the sensor to adapt to optical conditions.

For example, if detection is impaired due to contamination, such as dust deposited on the sensor lenses, the sensor signals this and adjusts itself to the new conditions. This is possible thanks to AutoAdapt, guided by microprocessor analysis. Device maintenance is not necessary until contamination is so significant that the sensor's ability to detect transparent objects eventually reaches system limits. This limit is reached significantly later than with conventional sensors.

The signal and the threshold return to the original level automatically after cleaning. This guarantees enhanced performance, even under harsh and highly contaminated application conditions.



## Examples of the signal attenuation of various materials

- Approx. 10% signal attenuation
  - Clean PET bottles, clear glass, thin and clear films (e.g., cellophane), household plastic film, plastic wrapping
- Approx. 18% signal attenuation
  - Clean clear glass bottles, thick films, film and wrapping folded multiple times
- Approx. 40% signal attenuation
  - Green and brown glass, colored glass bottles

• Special application: Detecting transparent objects, page B-46



Reflex Array E-134	W4S-3 Inox Glass F-312
TranspaTect E-142	W4S-3 Inox Hygiene Glass F-334
W2SG-2 F-232	W9-3 Glass
W4-3 Glass F-254	W9LG-3G-484
W4S-3 Glass F-272	W12G
W4SLG-3 F-290	



### Attractive optics are always an advantage

Optics play a key role when it comes to detecting objects – particularly when they have special properties. With the innovative solutions from SICK, you will always be one step ahead with respect to these challenges.



### Optical properties

- Type of light and light senders, page B-34
- Types of optics, page B-35
- Light spot geometries, page B-36
- Special optical technologies, page B-38





### Type of light and light senders


PinPoin

Point LED La

SICK photoelectric sensors use various transmission sources to achieve optimum optical performance, to ensure universal object detection, and for simple and fast commissioning. In addition to standard red LED lights, green LED lights, and infrared LED lights, there are two more light sender technologies to which special attention should be paid.



### PinPoint LED



The PinPoint LED concentrates the energy into a small area, increasing the light intensity and hence also the visibility of the light spot. This makes it much easier for the user to align and commission the sensor. By significantly increasing the sensing ranges, the PinPoint LED also opens up new fields of application for photoelectric sensors.

#### The benefits of the PinPoint LED at a glance

- Simple commissioning due to highly visible, uniform light spot
- Light spot diameter from 1 mm to 12 mm (depending on sensor type and sensing range)
- Increased sensing ranges in the red emitted light range
- No laser safety measures required
- Wide temperature range from -40 °C to +60 °C
- Long service life

You can find selection guides for PinPoint LED products at the start of each chapter.



### Red laser light



Sensors equipped with a laser diode can precisely detect objects or features, no matter how small, thanks to the extremely small laser beam. They are also ideal for applications where the laser beam needs to be guided through small openings or holes.

#### The benefits of the red laser light at a glance

- Extremely small light spot for highly precise detection tasks
- Light spot diameter from 0.1 mm to 2 mm
- Extremely long sensing ranges for photoelectric retroreflective sensors and through-beam photoelectric sensors
- Time-of-flight (ToF) technology for high precision with long sensing range
- Simple commissioning due to highly visible light spot
- Safety through laser classes 1 and 2
- Special application:
   Detecting small objects, page B-50



W4SL-3 F-278	W4SL-3H F-358	W9L-3 G-470	W280L-2 Long Range . H-666
W4SLG-3 F-290	W4SLG-3H F-364	W9LG-3	V18 Laser
W4SL-3V F-342	W8 Laser F-398	W12-2 Laser G-510	
W4SLG-3V F-350	W100 Laser F-412	W27-2 Laser H-610	





## Types of optics



### Focused optics



In sensors with focused optics, the transmitted beam of light is fixed at a defined distance (focused) and therefore has a particularly small light spot diameter in the target range. This property enables the reliable detection of small objects in the focal point or through narrow gaps or holes.


Special application:
 Detecting small objects, page B-50



G2S F-186	
W2S-2 F-216	
W4-3 F-238	
W9-3 G-448	V180-2 I-742
W12-2 Laser G-510	LL3J-804




### V-optics



Standard optics: The energy is greatly reduced on the receiver.

Diffuse reflection: The object reflects the light in every direction, even in the direction of the sender LED and the reflector.



V-optics: 100 % of the light is received from the shiny reflection.


Diffuse reflection: As the light beam is not emitted from the sensor in a straight line, the receiver can receive a higher amount of reflected energy.

SICK sensors with v-optics use an inclined, v-shaped light beam to direct more reflected light into the receiver. This means more energy is received when the detection substrate is in close proximity to the sensor. With shiny or deep-black objects in particular, a sensor with v-optics receives a considerably higher amount of the reflected light.

Special application:
 Detecting uneven, shiny objects, page B-52



W2S-2F	-216
W4-3	-238



# Light spot geometries

B



# Line-shaped light spot



Line-shaped light spots ensure that the sensor reliably recognizes corners, crosspieces, and gaps on the objects as uniform surfaces. This is particularly useful for recognizing irregularly shaped, perforated objects or for detecting shiny, uneven surfaces.

Sensors with a line-shaped light spot demonstrate their full potential in the following fields of application in particular:

- Detecting flat, highly reflective objects on conveyor belts
   (e.g., blister packaging, soup packets, chocolate bars, etc.)
- Detecting structured objects with cutouts, grooves, and openings (e.g., perforated metal sheets and printed circuit boards)
- Detecting reflective and irregularly shaped objects (e.g., coffee packaging)
- Detecting objects on very close, reflective, and high-contrast backgrounds

Special applications:
 Detecting transparent objects, page B-46
 Detecting perforated objects, page B-49
 Detecting flat, uneven, shiny objects, page B-52








MultiLine Sensor E-124	٧
W2S-2 F-216	٧
W4-3 F-238	

W12-3		 G-528
W14-2	٠.	 G-544





In contrast to conventional photoelectric sensors with a dot-shaped light spot, a sensor with a light array can monitor a significantly larger area. The light array is generated by combining a PinPoint LED with special optics. The result is a constant light array up to 50 mm between the photoelectric sensor and reflector. This allows for the position-independent and reliable detection of objects that vary in terms of position or height and pass through the light array.

Sensors with a light array are the ideal option in the following applications:

- Reliable edge detection when edge position is undefined (e.g., curved wooden slats, curved glass, non-rigid parts, bags, etc.)
- Leading edge detection for objects with height tolerances (e.g., pallets or parcels of differing height)
- Detecting transparent objects
- Overhang monitoring for storage and retrieval systems
- Rupture monitoring (e.g., when manufacturing cables and steel pipes)
- "Pick-to-light": Monitoring trays on assembly lines when components are removed manually from different totes

Special applications:
 Detecting transparent objects, page B-46
 Detecting perforated objects, page B-49
 Detecting uneven, shiny objects, page B-52
 Detecting objects with position tolerances, page B-54









Reflex ArrayE-134	Ļ
LL3	






# Special optical technologies

B

### SIRIC®



SIRIC® is the latest generation of ASIC (Application Specific Integrated Circuit) sensors from SICK. Now, for the first time, digital signal processing methods have been integrated into the world of photoelectric sensors. Sensors equipped with this technology are more powerful than ever before and are highly resistant to all known optical and high-frequency influences. Part of SICK's Smart Sensor Solutions, they can be seamlessly integrated into the automation network (you can find additional information on Smart Sensor Solutions in Chapter C).

#### The benefits of SIRIC® at a glance

- Optical reliability regardless of ambient light and light from other sensors at high switching frequencies
- Increased sensing range
- Customization
- Easy configuration via IO-Link
- Miniaturization
- Rugged design for handling shock, vibration, and electromagnetic disturbances

DeltaPac E-114	W4S-3F-260	W4SL-3HF-358	W12-3 G-528
MultiLine Sensor E-124	W4S-3 Glass	W4SLG-3H	W14-2 G-544
MultiPac E-130	W4SL-3F-278	W9-3 G-448	W18-3 G-556
Reflex Array E-134	W4SLG-3F-290	W9-3 Glass G-462	W23-2 H-580
R/IR E-148	W4S-3 InoxF-298	W9L-3 G-470	W27-2 Laser H-610
W2S-2F-216	W4S-3 Inox Glass F-312	W9LG-3 G-484	W27-3 H-616
W2SG-2F-232	W4S-3 Inox HygieneF-320	W11-2 G-492	W27-3 Ex H-632
W4-3F-238	W4S-3 Inox Hygiene GlassF-334	W11G-2 G-504	W15I-766
W4-3 PTFEF-250	W4SL-3VF-342	W12-2 Laser G-510	
W4-3 GlassF-254	W4SLG-3VF-350	W12G G-520	




# $\bigstar$


## Delta-S-Technology®

The patented Delta-S-Technology® is unique: Two high-resolution energy scales with the light beams of four PinPoint².0 LEDs, specific SICK SIRIC® ASIC technology and range measurement. This technology allows seamless detection of corners, folds, and grooves – regardless of color, object size, surface, and background.

There is a key reason for linking PinPoint<sup>2.0</sup> LEDs and SIRIC®: The use of an extremely wide range of sensor principles to counter glare, changes in contrast, unevenness, and reflective interference. This guarantees reliable, comprehensive use for all known items of packaging and folding boxes.



**Detection of different object contours** 




Glued joints are suppressed

Special application:
 Zero gap detection, page B-57



B



# The solution may surprise you

No matter which way you look at it, it's a great feeling when you have the right solution available to deal with a complex task. Our work is only complete when we have the right combination of packaging and sensing technology to provide you with a solution that fits your specific application.























washdown zones

transparent obiects

objects

Detecting small objects

objects wrapped in film

Detecting objects with position tolerances

Detecting high-speed objects

## Special applications

- Hygienic and washdown zones, page B-44
- ZoneControl, page B-45
- Detecting transparent objects, page B-46
- Detecting perforated objects, page B-49
- Detecting small objects, page B-50
- Detecting uneven, shiny objects, page B-52

- Detecting objects wrapped in film, page B-53
- Detecting objects with position tolerances, page B-54
- Detecting high-speed objects, page B-55
- Explosive areas, page B-56
- Zero gap detection, page B-57



# Hygienic and washdown zones

B



Flawless reliability and durability are key requirements when using sensors in hygienic and washdown zones. In the pharmaceutical and the food and beverage industries, washdown environments represent just one type of challenge: The sensors must also be able to withstand the daily high-pressure cleaning process, along with high thermal and mechanical loads.

When a sterile work environment requires daily disinfection of the machines, a high-quality stainless steel housing and maximum durability are needed. The high-performance lnox sensors are designed for harsh washdown and hygienic environments to help you implement specified cleaning schedules without prolonged machine downtimes.



Even though the key properties of all stainless steel sensors are the same, there is one essential feature that distinguishes a washdown sensor from a hygienic sensor: the way it is built.

A hygienically-designed sensor is built for use where it will come into contact with media, i.e., in the vicinity of food. It conforms to common standards and hygiene regulations and is constructed from the appropriate materials (also refer to "Hygienic design and materials" on the following page).

In order to ensure long-term, reliable operation and maximum throughput in hygienic and washdown zones, stainless steel sensors from SICK must satisfy five criteria:

- Chemical resistance
- · Hygienic design and materials
- · Thermal resistance
- Tightness
- · Market standards

#### **Chemical resistance**



A stainless steel sensor by SICK is resistant to high-pressure cleaning, cleaning with foam or P3 cleaning agents, and subsequent rinsing. The PMMA front screen, the LEDs, the teach-in pushbutton with stainless steel membrane and the PTFE sealing ring are resis-

tant to all cleaning agents typically used in this industry.

#### Hygienic design and materials

The stainless steel sensors designed for hygienic applications meet the requirements of applicable standards and guidelines for hygiene. SICK engineers are breaking new ground in hygienic design. Thanks to the use of O-rings, stainless steel sensors no longer have drill holes and metallic contact surfaces. The hygienic mounting system developed by SICK is also characterized by the fact that there are no gaps, dead zones, and undercuts. Food-safe and/or FDA-compliant materials have product properties that are suitable for use in the food and beverage industry.

#### Thermal resistance

Stainless steel sensors must be able to withstand dramatic changes in temperature resulting from cleaning with water at approx. 80 °C in a cold environment at between 5 and 10 °C, for example. Constant changes in temperature cause what is known as the pump effect: The differences in pressure "suck" moisture into the device. With SICK's design experience and proper selection of highly durable plastics and stainless steel materials, the tightly sealed housing suppresses the pump effect.

#### **Tightness**



SICK stainless steel sensors have been proving their worth in practical applications for many years. A laser-welded teach-in membrane made from stainless steel, sealed electrical male connectors or cables, and the precise integration of the display window and front

screen into the housing form the basis for the tightness of the sensors. With a water shock test, tests for enclosure ratings IP 66, IP 67, IP 68, and IP 69K, and a long-life test, tightness is tested on a regular basis.

#### **Market standards**

Thanks to careful material selection and considered design and build, Inox sensors from SICK meet all legal requirements and are aligned with the following standards and directives:

- DIN 10516: 2009-05
- DIN EN ISO 14159: 2008-07
- DIN EN 1672-2: 2005 + A1
- Machinery Directive 2006/42/EC
- Directives 1935/2004/EC and 10/2011
- Designed according to EHEDG guidelines
- ECOLAB-certified
- · Materials meeting FDA requirements

You can find a selection of suitable products for hygienic and washdown zones on page B-44.



# Hygienic and washdown zones

B

# Product selection for hygienic and washdown zones

	Hous	Housing properties							or erties	Optical properties			Page
				nless eel									
	Rectangular	Cylindrical	Washdown	Hygiene	VISTAL®	PTFE coating	IP 69K	AutoAdapt	IO-Link	Red laser light	PinPoint LED	SIRIC®	
W4-3 PTFE	Ų.					PTFE	<b>☆</b> IP 69K				\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\	SIRIC®	F-250
W4S-3 Inox	U		STAIN- LESS STEEL				<b>☆</b> IP 69K		IO-Link		♥.	SIRIC®	F-298
W4S-3 Inox Glass	U		STAIN- LESS STEEL				<b>☆</b> IP 69K	<u>+</u> <u>+</u>			☆ •	SIRIC*	F-312
W4S-3 Inox Hygiene	U			STAIN- LESS STEEL			☆ IP 69K				♥.	SIRIC®	F-320
W4S-3 Inox Hygiene Glass	U			STAIN- LESS STEEL			<b>☆</b> IP 69K	<u>+</u> _ <u>+</u>			¢ •	SIRIC*	F-334
W4SL-3V NEW	U		STAIN- LESS STEEL				☆ IP 69K			A	9	SIRIC*	F-342
W4SLG-3V NEW	U		STAIN- LESS STEEL				<b>☆</b> IP 69K	<u>+-+</u>	IO-Link	A	9	SIRIC*	F-350
W4SL-3H NEW	U			STAIN- LESS STEEL			<b>☆</b> IP 69K			☆ <u>A</u>	9	SIRIC*	F-358
W4SLG-3H NEW	U			STAIN- LESS STEEL			<b>☆</b> IP 69K	<u>+-+</u>	IO-Link	A	9	SIRIC*	F-364
W8 Inox	U		STAIN- LESS STEEL				<b>☆</b> IP 69K						F-386
W9-3	U				V <b>I</b> STAL®		<b>☆</b> IP 69K				Q.	SIRIC*	G-448
W9-3 Glass	U				V <b>I</b> STAL®		<b>☆</b> IP 69K	<u>+</u> !			☆ •	SIRIC®	G-462
W9L-3 NEW	U				V <b>I</b> STAL®		<b>☆</b> IP 69K			☆ A	9	SIRIC®	G-470
W9LG-3 NEW	U				VISTAL®		<b>☆</b> IP 69K	<u>+</u> _+		☆ <u>A</u>	٩	SIRIC*	G-484
MH15V	Ţ		STAIN- LESS STEEL				<b>☆</b> IP 69K				\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\		I-714
V18V	Ţ		STAIN- LESS STEEL	STAIN- LESS STEEL	VISTAL®	PTFE	r 69K	<u> </u>	IO-Link		٩	SIRIC®	I-732



# ZoneControl





ZoneControl solutions are used to control the flow of goods on conveyor belts (zero pressure accumulation). Regardless of whether the belt is powered pneumatically or by motorized rollers, ZoneControl solutions from SICK eliminate the needs for a programmable logic controller (PLC) or another external control system, and can do without a laptop and expensive cabling.

Each product contains one of two types of start-up logic: single feed (with or without sleep function) and block feed (slug). Which start-up logic is used depends on the requirements of the application.

When it comes to mounting options, versions are available that are designed for each type of installation situation: mounting between the rollers, on the side frame, and over the belt.

Installing ZoneControl solutions is plug-and-play: The sensors are connected in series, installed, and then connected to the pneumatic line or the motorized rollers.

There is no need for extensive and cost-intensive installation and cabling work.

You can find additional information on ZoneControl in Chapter E: MultiTask photoelectric sensors, page E-106.

You can find products for ZoneControl in the MultiTask photoelectric sensors chapter, page E-148.



# **Detecting transparent objects**

B



Clear plastic packaging, bottles made of glass or PET, vials and droppers, flat and hollow glass, plastic wrap for securing loads on pallets – providing appropriate solutions that can reliably detect transparent materials is a difficult task for automation specialists. SICK presents two approaches when it comes to solving this challenge – and once again demonstrates its innovative edge.

Reliably detect transparent objects - with a reflector ...



SICK's broad range of photoelectric retro-reflective sensors covers virtually all expectations, requirements, and tasks in the world of automation. Reflectors are the indispensable counterpart for each photoelectric retro-reflective sensor. Together they form a reliable functional unit. Reliable detection of objects is only guaranteed, including under critical application conditions, if both components are optimally coordinated with one another (you can find additional information on reflectors in the Accessories chapter, page L-889).

With the aid of outstanding SICK technologies such as AutoAdapt (continuous threshold adaptation) or the autocollimation principle, highly transparent objects can be reliably detected even if they have a very low signal attenuation in the light path.



# The comprehensive SICK product portfolio for detecting transparent objects offers:

- AutoAdapt continuous threshold adaptation from SICK
- The latest SIRIC® technology and IO-Link capability
- A range of housing styles
- · Variants for use in hygienic and washdown zones
- · Rugged device versions

You can find additional information on AutoAdapt on page B-30.





In addition to the photoelectric sensors with reflectors that are usually used, solutions without reflectors now also allow for reliable detection of transparent objects. It's crystal clear: The SICK portfolio is always the right choice - for reliable packaging, beverage or glass applications.

# ... or without a reflector.





### Out with reflectors - in with machines

Harsh environmental conditions can significantly hinder the effectiveness of reflectors. In addition to special machine designs that can leave little space for mounting, aggressive cleaning agents, for instance, can impair the performance of reflectors and even cause them to break. With this in mind, SICK offers state-of-the-art sensor technologies that allow you to eliminate the reflector. Thanks to new technologies, TranspaTect MultiTask photoelectric sensors are able to detect transparent and semitransparent trays without the need for reflectors.



And with the addition of the AutoAdapt function, the TranspaTect sensor offers maximum reliability in situations where contamination may occur.

Other photoelectric proximity sensors from the SICK portfolio also allow users to benefit from the advantages that the detection of transparent objects without reflectors brings. For example, with the MultiTask photoelectric sensors,

MultiLine Sensor, and MultiPac for the detection of packaging units with highly critical and transparent surfaces.

### The benefits of SICK's innovative, reflector-free sensor solutions at a glance:

- Saves time and costs since there is no need for the additional installation of a reflector
- · New levels of machine design freedom since the defined background can be designed into the environment of the machine, unlike a reflector
- High operational safety since the photoelectric sensor is able to continuously detect objects, even if the background becomes contaminated

You can find a selection of suitable products for the detection of transparent objects on page B-48.



# **Detecting transparent objects**

B


# Product selection for detecting transparent objects

	Housing properties				Sensor properties			Optical properties				Page	
	Rectangular	Cylindrical	Mash-down	Hygiene Hygiene	VISTAL®	Fibers	AutoAdapt	IO-Link	Red laser light	PinPoint LED	Light array	SIRIC®	
Reflex Array	Į.						<u></u>			<b>Q</b>		SIRIC*	E-134
TranspaTect NEW	Ţ						<u>*</u>			<b>Q</b>			E-142
G6	П												F-196
W2SG-2 NEW	Ţ						<u>+</u> <u>+</u>	IO-Link		\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\		SIRIC*	F-232
W4-3 Glass	U						<u></u>			\$ Q		SIRIC®	F-254
W4S-3 Glass	U						<u>+</u> , <u>+</u>	IO-Link		\\ \text{\delta}		SIRIC*	F-272
W4SLG-3	U						<u>+</u> _+		☆ ▲			SIRIC®	F-290
W4S-3 Inox Glass	U		STAIN- LESS STEEL				<u>+</u> _+			×		SIRIC*	F-312
W4S-3 Inox Hygiene Glass	U		STAIN- LESS STEEL	STAIN- LESS STEEL			<u>+</u> <u>+</u>			\$		SIRIC*	F-334
W4SLG-3V NEW			STAIN- LESS STEEL	STAIN- LESS STEEL			<u>.</u>	IO-Link	☆ ▲	٩		SIRIC*	F-350
W4SLG-3H NEW			STAIN- LESS STEEL	STAIN- LESS STEEL					☆ ▲			SIRIC*	F-364
W8G				STAIN- LESS STEEL								SIRIC*	F-380
W100-2 <b>NEW</b>	U												F-404
G10 NEW										Q.			G-430
W9-3 Glass	U				VISTAL®					☆ •		SIRIC*	G-462
W9LG-3 NEW	U				VISTAL®		<u>+</u> _+		☆ ▲			SIRIC®	G-484
W11G-2					VISTAL®		<u>.</u>					SIRIC*	G-504
W12G							<u>+</u> _+	IO-Link		Q.		SIRIC®	G-520
GR18S	Į.						<u>.</u>	IO-Link		<b>☆</b>		SIRIC*	I-698
V18V										٩			I-732
WLL170-2 with LL3							<u></u>						J-790
WLL180T with LL3							<u> </u>						J-798



# **Detecting perforated objects**





The special optical design for the photoelectric proximity sensor is critical for reliably detecting perforated objects such as mesh boxes. Using a line-shaped light spot, gaps in the object being detected are suppressed, preventing multiple switching.

With conventional photoelectric proximity sensors, the tiny light spots are often unable to fully cover the gaps in the perforated objects, meaning that the same object is detected several times. Until now, it was only possible to compensate for this problem by carrying out complex software adaptation or logically linking several photoelectric proximity sensors.

Sensors with a line-shaped light spot are therefore much more

cost- and time-efficient. The light spot is modified in such a way that a highly visible line-shaped light spot is displayed on the object. This line geometry ensures that the sensor reliably detects corners, crosspieces, and gaps on the object as uniform surfaces, meaning that each object is only detected once. The sensor therefore also only emits one switching signal to the control system of the automatic conveying equipment.


# Product selection for detecting perforated objects

	Housing Sensor properties			Optical properties					Page	
	Rectangular	IP 69K	Fibers	IO-Link	PinPoint LED	Infrared light	Light array	Line-shaped light spot	SIRIC®	
MultiLine Sensor	Ţ	IP 69K			<b>Q</b>			<b>☆</b>	SIRIC®	E-124
Reflex Array	Ţ	IP 69K			<b>♦</b>		→ AAAAA		SIRIC®	E-134
W2S-2 NEW	Ţ	IP 69K		IO-Link	\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\			± =	SIRIC*	F-216
W4-3	U	IP 69K			\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\			<b>☆</b>	SIRIC®	F-238
W12-3	Ţ	<b>₩</b> IP 69K			\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\\			☆	SIRIC®	G-528
W14-2	Ţ	IP 69K				<b>/</b>		☆ <b>=</b>	SIRIC*	G-544
WLL170-2 with LL3	Ţ	IP 69K					→ AAAAA		SIRIC®	J-790
WLL180T with LL3	Ţ	IP 69K	: <u>:</u>				  →aaa			J-798



# **Detecting small objects**


B



The reliable detection of small objects represents a major challenge in the automation industry – particularly if these objects are also packed flat or in transparent material. Laser photoelectric sensors, fiber-optic sensors, or photoelectric sensors with focused optics are able to detect small objects reliable. An extremely small light spot provides the ideal starting point for precise object and feature detection in automation. It makes the sensors ideal for pinpoint accurate position, presence,

overhang and height checks involving the smallest objects, even under critical light conditions. The precise laser light spot supports switching with maximum accuracy, thus providing the basis not only for optimum product quality but also for reduced machine downtime as there are fewer switching errors. Fiber-optic sensors and suitable fibers enable small objects up to 15  $\mu m$  to be detected.

# Product selection for detecting small objects





# Detecting uneven, shiny objects

B





The detection of shiny, uneven surfaces presents a particular challenge. Just like when detecting small objects, a small, precise light spot is required to achieve reliable detection results in the automotive industry, for example. Problems arise, however, due to shiny, uneven surfaces, and for surfaces that are coated in oil (e.g., metal sheets). For the detection of shiny and irregularly shaped objects, which can be found in the packaging industry, for instance, photoelectric sensors with a line-shaped light spot are particularly well suited for these types of applications.

# Product selection for detecting uneven, shiny objects

	Hous- ing prop- erties	Sensor prop- erties	Optical p	Page					
	Rectangular	IO-Link	PinPoint LED	Infrared light	Line-shaped light spot	Light array	V-optics	SIRIC®	
MultiLine Sensor			☆ •		\ <u></u>			SIRIC*	E-124
MultiPac								SIRIC*	E-130
Reflex Array			<b>♥</b>					SIRIC®	E-134
TranspaTect NEW			<b>☆</b>						E-142
W2S-2 NEW		IO-Link	<b>☆</b>		<b>☆</b>		<b>H</b> □	SIRIC®	F-216
W4-3	T.		<b>☆</b>		<b>☆</b>			SIRIC*	F-238
W12-3			¢.		<b>☆</b>			SIRIC®	G-528
W14-2				~	<b>☆</b>			SIRIC*	G-544
WLL170-2 with LL3	T				<b>☆</b>				J-790
WLL180T with LL3		IO-Link	9		<b>☆</b>		Ħ	SIRIC®	J-798



# Detecting objects wrapped in film



Reliably detecting six-packs wrapped in PET film on conveying lines is no easy task. Yet the photoelectric sensors from SICK have mastered this challenge and guarantee an unparalleled level of detection reliability.

Dual receivers, powerful LEDs, and a special evaluation function enable the detection of very shiny and uneven surfaces. They are a future-proof solution for efficiently checking and controlling objects, such as packaging units being transported on single or multitrack conveying lines. With mounting heights up to 500 mm above the conveying line, an extremely wide range of packaging unit types and heights can also be detected with only one fixed sensor position. With different packaging unit heights, the mechanical position adjustment that was often required becomes unnecessary, significantly reducing effort and expense for users.


# Product selection for detecting objects wrapped in film

	Housing	; propertie	es	Optical properti	Page	
	Rectangular	Cylindrical	IP 69K	PinPoint LED	Line-shaped light spot	
MultiLine Sensor	T			¢.	\\\ = \	E-124
MultiPac	T					E-130
G10 NEW	T			Q.		G-430
W11-2	T					G-492
W12-3	T			\delta	\\ <b>=</b>	G-528
W14-2	T					G-544
W23-2	T					H-580
W27-3	T		<b>☆</b> IP 69K			H-616
W15				¢.		I-766



# Detecting objects with position tolerances

B




In a wide range of industries, solutions are used for the detection of misshapen objects or objects of varying height. This often leads to high costs, especially through complex and expensive installation. Reliably detecting the leading edge in objects of varying height generally requires the installation of two photoelectric sensor — one on top of the other.

A similar situation occurs when detecting flat and misshapen objects on the same belt – with the added problem of expensive and time-consuming cabling.

The solution is provided by sensors with a special feature – the light array. It enables all objects from a certain minimum size to be detected irrespective of their position.

# Product selection for detecting objects with position tolerances





# Detecting high-speed objects



Extremely fast-paced manufacturing processes require specially adapted sensor solutions. Very high switching frequencies up to 31.2 kHz enable SICK sensors to react with lightning-fast speed and excellent positioning accuracy – especially when it matters most.

The benefit to you: A precise solution for your high-speed processes.

# Product selection for detecting high-speed objects

	Hous	sing erties	Sens prope	or erties	Optic prope	Page		
	Rectangular	IP 69K	Fibers	Switching fre- quency ≥ 2 kHz	Red laser light	Light array	SIRIC®	
W4S-3	Ţ	IP 69K		☆  ≥ 2 kHz			SIRIC®	F-260
W8	Ţ	IP 69K		☆  ≥ 2 kHz				F-372
W8 Laser	Ţ	IP 69K			☆ ▲			F-398
W100 Laser	Ţ	<b>I</b> P 69K		☆  ≥ 2 kHz	☆ A			F-412
W12-2 Laser	Ţ	<b>☆</b> IP 69K			☆ △		SIRIC®	G-510
WLL170-2 with LL3	Ţ	<b>I</b> P 69K	i I	☆  ≥ 2 kHz		  →  }	SIRIC®	J-790
WLL180T with LL3	I.	IP 69K		☆  ≥ 2 kHz		\\ \rightarrow\righta	SIRIC®	J-798



# **Explosive** areas

area

B



Potentially explosive atmospheres can arise wherever dust, flammable gases, or flammable liquids are manufactured, transported, processed, or stored. An explosion can occur if three factors come together at the same time:

- A flammable substance, e.g., in the form of gas, vapor, mist, or dust, is present
- Sufficient oxygen is present (e.g., in the ambient air)
- There is an ignition source. In addition to sparks, this can also include hot surfaces.

SICK offers sensors that have been developed especially for explosive areas. Based on directive 94/9/EC (ATEX), these sensors are designed in accordance with the relevant standards. The devices can be used in the categories 2G/2D or 3G/3D, depending on their design.

Responsibility of the sensor manufacturer	Re	esponsibility of the r				
Category	Can be used in zone (gas)	Can also be used in zone (gas)	Can be used in zone (dust)	Can also be used in zone (dust)	Definition (94/9/EC) Potentially explo- sive atmospheres are present	Certification by
1G/1D	0 (0)	1 and 2	20 (10)	21 and 22	Always, for long periods, or often	Notified body
2G/2D	1 (1)	2	21 (11); zone 22 "conductive dust"	22	Occasionally	Notified body
3G/3D	2 (2)	-	22; zone "non-con- ductive dust" (no equivalent)	22	Occasionally	Notified body

G = gas, D = dust; () = older code in parentheses.

W18-3 Ex	G-556	W27-3 Ex	H-632
W24-2 Ex	H-602		



# Zero gap detection



Zero gap detection is a challenge for sensor solutions in the packaging industry. Ideally, packaging items are correctly grouped in lines to prevent inefficient idling, machine downtime and loss of quality due to crashes. With the aid of a technological world first, SICK can now make such stable, fast, and efficient production processes possible – and all with maximum quality.

Delta-S-Technology® guarantees that the sensor accurately detects the transition between successive packaging items or work pieces. There are no more product jams and package hold ups. And there is no need to separate items before grouping them, reducing mechanical costs. This optimizes product flow and saves resources.

And if that wasn't enough, the sensor solution from SICK is optimally designed for the packaging items typically found in today's packaging industry. Pre-configured, automated sensors detect rectangular and prism-shaped packaging items and folding boxes. All rounded off by IO-Link-compatible sensors, providing maximum flexibility.

You can find additional information on Delta-S-Technology
in the MultiTask photoelectric sensors chapter, page E-103

DeltaPac	1	4
----------	---	---


C

Integrating the lowest field level into communication within a machine makes it possible to achieve a consistent flow of information throughout the automation pyramid. Right down to the smallest elements, such as sensors, actuators, and drives.

Incorporating process data like pressure, temperature, flow, end position, speed, and output state, for example, creates more opportunities for helping automation solutions work at the peak of their capabilities.

With Smart Sensor Solutions, SICK offers innovative sensor technology that allows you to take advantage of innovative additional functions.

Integrating Smart Sensor Solutions seamlessly into automation networks enables you to increase the flexibility, reliability, and efficiency of your machines, while also reducing costs.



Standard functions	C-61
Advanced functions	C-69

C

The benefits of seamlessly integrating Smart Sensor Solutions into automation networks are clear: Increasing machine flexibility, reliability, and efficiency, while reducing costs.

Due to continual performance improvements, sensors can be used in even more applications in machine design or industrial automation and are able to provide more than just discrete switching signals.

DeltaPac F-114	W4S-3 F-260	W4SLG-3V	W12-3 G-528
Dollar dollar L 111	11.10 011111111111111111111111111111111	W 1014 OV 1111111111111111111111111111111111	1112 0111111111111111111111111111111111
W2S-2 F-216	W4S-3 Glass F-272	W4SLG-3H F-364	
W20 2 210	WTO 0 01033 212	WHOLE SITE SOF	
M36C 3 E 333	W4SL-3F-278	W12C C 520	
WZ3G-ZI-Z3Z	W43L-3	W12G G-320	



# **Standard functions**







Function 1	C-62
Easy device replacement	
5 1: 0	0.04
Function 2 Flexible sensor adjustment	C-64
. ionizio coneci adjacament	
Function 3	C-66
Condition monitoring and diagnostics	



### Easy device replacement



Sensors are used at the heart of manufacturing processes, including those taking place in harsh environments. As a result, they are exposed to exceptional levels of stress from high temperatures, vibrations, mechanical impact loads, or contamination. After being subjected to these harsh conditions over a long period of time, these sensors will need to be replaced. High-performance sensors are able to reliably identify failures and report them locally via an LED display. This is useful for machine operators, as pinpointing the location of the defective sensor can be a laborious process if it is installed in a concealed place or if a system is using a large number of sensors.

After a sensor has been replaced, it needs to be configured specifically for the application (by pressing a teach-in button, for example). This can result in the loss of valuable production time.

#### The solution: Easy device replacement

Using SICK Smart Sensor Solutions, the automation systems can display the exact location of a failure on the human-machine interface. Once the device has been replaced, the automation system automatically recognizes that a new sensor has been connected. The application-specific parameters, such as basic configuration settings, are written to the sensor quickly and reliably. The result is an efficient and documented sensor replacement process.

#### Fields of application:

- Systems and machines with high numbers of sensors and which are operated by untrained personnel
- Manufacturers who provide your machines with maintenance contracts and a spare parts service

# C

### Machine reports a failure

- The failure is reported on the operating terminal of the control system
- The failure and its assessment can be viewed on the terminal
- · The sensor type and its location are displayed
- Easy integration thanks to IO-Link technology and flexible machines and system adaptations
- Precise localization of the sensor within the machine and system



### Sensor is replaced

- · Operating personnel replace the sensor
- No manual settings, such as sensing range, need to be made on the sensor
- Even personnel who have not been trained can replace the sensors without the need for additional tools or instructions
- Automatic configuration prevents incorrect settings



### Machine is put into operation

- The automation system checks whether the new sensor is working correctly
- Settings are automatically taken from the automation system, and a record of the replacement process can be created
- The production process is restarted after minimal downtime by means of an acknowledgment on the operating terminal
- Sensor replacement precisely documented
- ♣ Reduced service work costs
- Minimized downtime periods
- Guaranteed machine throughput





### Flexible sensor adjustment



The flexibility of today's machines and systems aid in the development of a wide range of different product types. This is largely due to different order-specific requirements and configurations. As a result, products can differ significantly in terms of their shape and surface properties.

Although sensors are able to reliably detect various product shapes and surfaces, in many cases they require manual configuration for the sensing range or threshold settings to ensure they can offer the best possible performance. This can result in the loss of valuable production time.

#### The solution: Flexible sensor adjustment

Now, parameters for specific formats and configurations can be stored in the sensors or automation system without manual intervention. They can be activated quickly

and automatically when a product change occurs – with full repeatability. The automation system provides the sensor with optimum application-specific parameters for the manufacturing process or the product being manufactured, such as the sensing range, hysteresis, or threshold.

These production parameters are managed by a server, for example. They are activated by the operating personnel and transferred to the sensor quickly and reliably.

#### Fields of application:

- Systems and machines with high numbers of format changes, configurations, and product variants
- Machine manufacturers that only want sensor settings to be made by the PLC

# Operating personnel receive a new production order

- The machine has to produce a new product
- The operator activates the new machine settings by pressing a button
- The application-specific sensor parameters are automatically loaded to the sensors
- Automatic configuration prevents incorrect settings



## Product-specific parameter settings

### A number of factors determine what the best settings for the sensors are:

#### Shape and size



Sensing range and hysteresis

#### **Color and contrast**



Color and contrast threshold

#### Surface




ON and OFF delay

## Machine is put into operation

- The system performs a self-test to ensure that the sensors are working correctly.
- The production process is restarted after a very short downtime by means of an acknowledgement on the operating terminal.
- Less downtime when product changes take place
- More machine flexibility
- Increase in the variety of products a machine can handle





## Condition monitoring and diagnostics



Sensors are often mounted in the most active production areas and are therefore highly exposed to the effects of their surroundings.

Dust, water, vibrations, and other harsh environmental conditions require cleaning and maintenance to be carried out to keep sensors performing reliably and to ensure the system or machine stays up and running. Environment-related sensor failures – as well as the downtime associated with them – are particularly unwelcome when systems are working at a high level of production capacity.

#### The solution: Condition monitoring and diagnostics

Thanks to integrated diagnostics and self-test options, sensors are able to provide information regarding the presence of contamination. The self-monitoring capabilities of the sensors enables preventive maintenance to

be carried out using a precise maintenance plan. This ability to predict machine status even extends across area boundaries.

One example of these functions is remote maintenance, which provides a continuous way of identifying the areas requiring maintenance and allows maintenance work to be performed during a scheduled machine downtime, such as over the weekend.

### Fields of application:

- Systems and machines that require frequent cleaning, use large numbers of concealed sensors, or operate in harsh environments
- Manufacturers who provide your machines with maintenance contracts and a spare parts service, and guarantee machine throughput

#### Preventive maintenance

- The staff member in charge of production creates a tailored maintenance plan using the condition monitoring data that is available, and hands this over to the service technician
- Reduced risk of failure
- **①** Optimized maintenance and servicing periods
- Service technician can prepare for maintenance using remote diagnostics



# Maintenance is carried out on the system

- When a contract has been arranged, the service technician performs maintenance on the sensors at specified intervals
- 1 Trained personnel perform maintenance work
- The service technician can identify critical sensor statuses and rectify any potential problems before a failure happens
- Enhanced maintenance contracts that include process monitoring are available




### System is put into operation

- The system performs a self-test to ensure that the sensors are working correctly.
- The operating personnel begin production as scheduled, without any delays
- The maintenance work is accepted by the operating personnel
- Optimized production times
- Verification that the sensors are working correctly




C

By using state-of-the-art sensor technology and integrating it into an automation network, it is possible to take advantage of innovative functions that have a direct impact on a system's or machine's productivity.



Boosting the productivity of systems and machines requires ever more powerful automation networks and control systems.




One option for improving the performance of automation networks is to place intelligent functions in remote locations. The various ways in which sensors and control systems can work together open up new possibilities for enhancing productivity.



# **Advanced functions**







Function 2	C-72
Timers	



Function 3	C-74
False Tripping Suppression (Debouncing)	



Function 4	C-76
Profile recognition and verification	



Function 5 C-78

Product tracking via timestamp



### High-speed counters



Some systems and machines have to know how fast conveying equipment is moving in order to carry out control tasks, or they need to ensure that the speed of a roller stays within defined limits.

Embedding a counting function in the sensor makes it possible to carry out these automation tasks and others with maximum efficiency. The microcontroller of a sensor can use its maximum clock frequency to optimize the detection process. This makes high-speed counting in the sensor an alternative to the central counter module.

#### Fields of application:

- Systems and machines that require a mechanically rugged, yet inexpensive method of counting, value detection or speed measurement
- Systems and machines that would benefit from monitoring the direction of rotation in the sensor

W4S-3F-	-260
W4S-3 GlassF-	-272
W12-3	-528
W12G	-520

### Speed monitor

- The sensor detects the teeth of a gearwheel and monitors the speed of the roller
- Any deviations that extend beyond the speed tolerances are communicated to the PLC
- High-speed counting in the sensor provides an alternative to the central counter module
- Cost reduction





### Speed measuring

- The optical sensor detects and counts the holes of a perforated disk
- Parameters specified by the control system are used to convert the counter value into a speed
- The speed per minute is transferred to the control system cyclically
- **1** Easy and precise speed measuring
- Option of linking a sensor to an additional sensor in order to determine the direction of rotation. The sensor then sends information on the direction of rotation and speed cyclically to the PLC.

## Precise detection and counting

- The optical sensor detects and processes a parameter-specific counting function
- The counting results are transferred to the control system cyclically
- The counting value is reset via the control system or an optional sensor input
- Reliable detection and counting within the sensor instead of the PLC







# **Timers**



Sometimes it is necessary to check whether an object is in the correct position on the belt or whether it is too large or too small.

If the conveying equipment is moving at high speeds, however, conventional detection methods that use a sensor as well as time evaluation in the control system often cannot provide the level of accuracy required. These systems are often limited by the control system's computing capacity and the speed of the network. Innovative sensors, however, measure the time window directly and with high precision, as well as provide the control system with the measurement result in the required format so that this information can undergo further processing.

#### Fields of application:

- Systems and machines that require more precise time detection for object lengths; for example, as a means of enhancing production quality or increasing the number of cycles
- Systems and machines that involve precise product distance monitoring
- · Systems and machines that involve slip monitoring

W4S-3
W4S-3 GlassF-272
W12-3
W12G

### Product length measurement


- Using a high-precision method, the sensor detects the product passing by on the conveyor
- The time between the rising and falling edges is determined using the maximum internal clock frequency
- The product length is calculated in the PLC based on the time value determined in the sensor and the belt speed
- If the belt speed is constant, the length can also be calculated in the sensor. The sensor receives the parameters it needs from the PLC.
- Simple and extremely precise time measurement provides the basis for calculating length


# Distance measurement between two products


- Using a high-precision method, the sensor detects the gap between two products passing by on the conveyor
- The time between the falling and rising edges is determined using the maximum internal clock frequency
- The distance between the two products is calculated in the PLC based on the time value determined in the sensor and the belt speed
- If the belt speed is constant, the distance can also be calculated in the sensor. The sensor receives the parameters it needs from the PLC.
- Simple and extremely precise time measurement provides the basis for calculating distance


# Speed measuring

- Linking a sensor to an additional sensor makes it possible to determine the speed of the product on the belt without a PLC
- The time between the rising edge for "sensor 1" and the rising edge for "sensor 2" is determined using the maximum internal clock frequency of the sensor and converted into a speed
- Since belt speed information is not required to calculate the speed, it does not matter if there is any slip between the belt and product
- The sensor cyclically sends product speed information to the PLC
- Easy and precise speed measuring
- Slip-free speed measuring









# False Tripping Suppression (Debouncing)



In order to maintain productivity in some systems and machines, it is important for a sensor to be able to identify which detection signals are disturbances. It can then suppress such disturbances using additional detection information. In the wood processing industry, for example, it is possible for sensors to identify any signal change of less than 5 ms as irrelevant and reliably suppress it. This prevents the control system from being burdened with information that will disrupt the process. The automation system manages the disturbance suppression parameters in a way that is specific to the application concerned.

#### Fields of application:

- Systems and machines affected by large numbers of disturbance signals, resulting from either the process or the environment
- · Systems and machines with lean control technology


W4S-3 F-260	W12-3 G-528
W4S-3 GlassF-272	W12G G-520

# Application possibilities for decentralized debouncing

Undefined leading edges on objects



Unexpected gaps and holes in PCBs




Chips, dust, dirt particles



# False Tripping Suppression (Debouncing)

- Every object that enters a sensor's field of view causes the sensor signal to switch on (0/1 signal switch).
- As soon as the sensor can no longer see the object, it switches
  off (1/0 signal switch) Because of the time delay involved in
  switching the signal (debouncing), brief disturbance variables
  do not cause the sensor to switch. Signal switching will not take
  place if the delay time (debounce time) is longer than the disturbance variable. The debounce time can be configured for rising
  and falling edges.
- If a time stamp is also being used, the time delay can be corrected as the sensor internally "identifies" the time until each rising or falling edge
- Reliable detection of objects in harsh environments




# C


### Debouncing in the sensor instead of the PLC


- Debouncing takes place where the signal is picked up
- Debounce times can be implemented independently of cycle times, bus runtimes, and input delays
- Debouncing uses the speed of the sensor's microcontroller (e.g., 5 kHz)
- Precise leading edge and/or trailing edge detection for objects, as disturbance variables bouncing off an object are detected in even the smallest of gaps and do not extend the switching signal
- The sensor is provided with a production-specific debounce value (e.g., 3 ms)
- The sensor debounces interference effects and detection errors, and sends a clean signal back to the PLC
- Sensor debounces what it really "sees", not the switching signal
- 1 Increased machine speed
- More precise detection

#### Linking sensors

- To improve reliability, a second signal can be read in on the sensor (IO-Link sensor) as an addition to debouncing
- The two raw signals are compared and only the signal that is cleaned by means of the logic is output to the PLC
- The two raw signals can be debounced independently of one another
- Maximum signal quality combined with reliable detection in harsh environments







# Profile recognition and verification



Sometimes it is necessary to check whether an object is in the correct position on the belt or whether it is the right shape. If the conveying equipment is moving at high speeds, however, conventional detection methods that use a distance sensor and contour analysis in the control system require complex technology for this type of application.

These systems are often limited by the control system's computing capacity and the speed of the network. Smart sensors, however, measure the actual profile directly and with high precision. They then evaluate the result by comparing the shape and measured values with a desired profile that has been configured or taught in. The control system simply receives a binary signal to enable further action to be taken.

#### Fields of application:

- Systems and machines that require profile recognition; for example, as a means of enhancing production quality or increasing the number of cycles
- Profile measurement for position detection in systems and machines
- Sorting by means of product features in systems and machines
- High-speed profile verification in systems and machines, without significant demands being placed on the PLC

# Object position detection


- The sensor receives the corner points of the object's profile by means of a teach-in process
- The tolerances are defined using configuration settings (e.g., ± 5 mm)
- While the machine is operating, the sensor simply tells the control system whether the position of the object is right or wrong
- Use of standard sensors in a way that provides an alternative to high-precision sensors (with analog output and an analog PLC input card)


# Differentiation between types of packaging


- The sensor receives multiple corner points of the profile for the types of packaging by means of a teach-in process or configuration settings
- The tolerances for the relevant profiles are defined using configuration settings
- While the machine is operating, the sensor tells the PLC which profile has been recognized
- Increased machine flexibility


# Detecting deviations in shapes and product errors

- Profile corner points on the packaging or box are entered using the PLC's configuration tool
- The tolerances are defined using configuration settings (e.g.,  $\pm$  1 mm)
- While the machine is operating, the sensor simply detects the deviation in shape and reports the packaging error to the control system
- 1 Optimized allocation of PLC resources









# Product track and trace using timestamps



The fast, precise process of product detection during production can be linked to a time value. The result is a highly accurate method of specifying a position based on timestamping.

The time at which the product is detected is precisely synchronized with the automation system's real time. This synchronization typically takes place in the PLC. Areas of inaccuracy (jitter) that occur when the switching signal is being transmitted to the PLC (e.g., on the bus) and when a program is being executed are added together.

Synchronization with real time takes place in the sensor, not in the PLC.


#### Fields of application:

- Production lines with high productivity levels and high production speeds
- · Precise production systems and machines
- Functional synchronization with sensor/actuator units

W4S-3F-260	W12-3 G-528
W4S-3 GlassF-272	W12G G-520


#### Fast detection

- Every object that enters a sensor's field of view generates a rising/falling edge and timestamps that are set internally
- If the signal proves to be the result of correct detection (after debouncing, for example), then the relevant time stamp is transmitted to the control system for signal change purposes
- Increase in machine speed thanks to more precise detection




#### PLC calculations

- The PLC receives the sensor time stamp and calculates
  the actuator time stamp based on this information. The
  distance between the sensor and actuator corresponds
  to the difference between the sensor and actuator time.
  The PLC cycle time that is affected by jitter and the bus
  runtime are not taken into account when the actuator
  time stamp is calculated.
- Optimized signal processing reduces strain on the network structure



# Precise reaction of actuators

- The actuator is informed early on about the time at which
  it has to execute a desired action. For this purpose, a rising
  edge for controlling a valve, for example, plus the associated
  timestamp are transmitted to the actuator. Another timestamp and the "falling edge" signal are used to reset the
  valve.
- In the case of a pneumatic cylinder, an analog positioning sensor (e.g., MPA) continually monitors the throughput time, for example. If the environmental conditions change and the throughput time slows down, the actuator can automatically correct the start time so that the action can be performed at the right point.
- Functional synchronization with sensor/actuator units
- Guaranteed machine performance





# **Typical applications**



# **Typical applications**

This chapter describes typical applications for photoelectric sensors. Arranged according to industry, you will find application examples with a brief description of the typical application as well as a direct product recommendation from our varied product portfolio.

# **Typical applications**

Selection guide							
Automotive and parts supplier D-86	Retail and warehousing D-95						
Print	Food						
Electronics D-90	Tire D-97						
Beverage D-91	Solar						
Wood	Traffic D-99						
Rubber and plastics D-93	Machine tools						
Courier, express, postal and cargo D-94							

# **Application overview**

	MultiTa	ask pho	otoelecti	ric sens	ors	Miniat	ture pho	otoelect	ric sens	ors				
	MultiLine Sensor	MultiPac	Reflex Array	TranspaTect	ZoneControl	95	W2 Flat	W2S-2	W4-3	W4-3 Glass	W4S-3	W4S-3 Inox	W100 Laser	
Automotive and parts supplier														
Presence and type checking for seat underframe parts														
Part detection														
Part detection in a crossbar robot														
Vehicle protrusion monitoring														
Collision prevention at robot grippers														
Quality check using photoelectric sensors														
Robot guidance for installation of windshields														
Skid detection at the lift station entry														
Type check for car body parts														
Monitoring the feeder clips														
Print									_					
Presence monitoring and counting process														
Sheet presence and position monitoring														
Detection of paper edges														
Paper tear monitor														
Electronics														
Detecting circuit boards														
Device detection in gripper														
Object detection and intelligent identification														
Wire bonder automation solutions														
Beverage														
Detection of single trays														
Detecting PET cases W4S-3 Inox in a bottling plant		-												
Wine bottling plant: WLL180T determines the filling level														
Wood														
Board detection (application 1)														
Board detection (application 2)														
End of material detection														
Accurate and reliable leading edge detection of profile wood and pallets			•											
Rubber and plastics														
Checking presence and fill level in the singulation system														
Checking the presence and position of trays														
Controlling the conveying line														
Detecting parts in the gripper and the injection molding tool														



Small pho	toelectric se	ensors				Compact photoelect sensors	ric	Cylindrical	photoelect	ric sensors		Fiber- optic sensors and fibers	Page
W9-3	W9L-3	W12-2 Laser	W12-3	W14-2	W18-3	W27-3	W280L-2 Long Range	GR18S	V18V	V180-2	W15	WLL180T and LL3	
													D-86
													D-86
		-				_							D-86 D-86
						•							D-86 D-87
			-										D-87
													D-87
													D-87
													D-88
													D-88
													D-89
													D-89
													D-89
													D-89
													D-90
												_	D-90
													D-90
													D-90
													D-91
													D-91
													D-91
													D-91
													D-92
													D-92
													D-92
													D-92
													D-93
													D-93
													D-93
													D-93



		_	_	_	_		_	_	_	_	_	_	_	
	MultiT	ask pho	toelecti	ric sens	ors	Miniat	ure pho	toelecti	ric sens	ors				
			ray	ect	trol					SS		XO	ser	
	MultiLine Sensor	MultiPac	Reflex Array	TranspaTect	ZoneControl		W2 Flat	2-5	က္	W4-3 Glass	W4S-3	W4S-3 Inox	W100 Laser	
	Mul	Σ	Refl	Trar	Zon	95	W2	W2S-2	W4-3	W4	W4	W4	W1(	
Courier, express, postal and cargo														
Level control for slides/chutes														
Speed measurement with laser sensors														
Empty detection														
Leading edge detection														
Retail and warehousing														
Tilt-tray sorter off load detection														
Detection of inhomogeneous containers														
Pallet detection														
Accumulation conveyor/retrofits														
Food														
Detection of highly reflective coffee packages														
V18V on a conveyor belt														
WTB4-3 for securing apertures														
Tire														
Automatic wheel separating on conveyor belts														
Tire detection														
Loop control: loop measurement														
Tire separating														
Solar														
Detection in harsh environment														
Smart wafer presence detection														
Glass panel overhang detection														
Double wafer detection														
Traffic														
Detection of persons for automatic door opening														
Detection of the direction of travel														
Separation in security gates														
Machine tools														
Automated parts infeed and outfeed														
Component detection in a crossbar robot														
Tracking the sheet roll														
Detection of assigned tool locations														
End of material detection														
Stamp breakage monitoring														
Optical inline quality checking														
Positioning of the sheet pallet														



Small phot	toelectric se	ensors				Compact photoelect sensors	ric	Cylindrica	l photoelecti	ic sensors		Fiber- optic sensors and fibers	Page
W9-3	W9L-3	W12-2 Laser	W12-3	W14-2	W18-3	W27-3	W280L-2 Long Range	GR18S	V18V	V180-2	W15	WLL180T and LL3	
													D-94
				_									D-94
													D-94
													D-94
													D-95
			_										D-95
													D-95
													D-95
													D-96
													D-96
													D-96
													D-97
													D-97
													D-97
													D-97
													D-98
													D-98
													D-98
													D-98
													D-99
													D-99
													D-99
													2 33
													D-100
													D-100
													D-100
						•							D-100
													D-101
													D-101
		-											D-101
													D-101



# Presence and type checking for seat underframe parts



Besides the presence of parts, additional features such as holes, boreholes and cutouts must be detected at the turntable for type testing. The WTB12-3 small photoelectric sensor is used for quality

assurance and type testing. The pin-point technology produces a highly visible light spot, which simplifies alignment and enables precise detection.

#### **Recommended products**

W12-3......G-528

# **Part detection**



Two redundant receiver arrays are used to check that the side panels are present. The MultiPac compact photoelectric sensor has been developed specially to

detect complex objects such as bright metal parts. The powerful LED produces a highly visible light spot and makes for easy alignment.

#### **Recommended products**



#### Part detection in a crossbar robot



The WT12L-2 small photoelectric sensor checks whether the part is located in the gripper of the robot and whether the part

has been removed from the press tool. This prevents mechanical damage to the press

#### Recommended products



# Vehicle protrusion monitoring



When lifting the vehicle, it is essential to rule out contact that could cause damage to the body. The WTB27-3 compact

photoelectric sensor detects the position of the skid and recognizes any protrusion of the vehicle.

#### **Recommended products**

W27-3......H-616

# **Collision prevention at robot grippers**



The WTB12 small photoelectric sensor checks whether the seat is at the correct position so that the robot can grip it

accurately. This prevents any collision between the robot and the seat.

#### **Recommended products**

# Quality check using photoelectric sensors



The MultiPac MultiTask photoelectric sensors were developed specially for use with a reflective, bright surfaces. Two independent receiver arrays provide

redundant detection, which enables even the most complex applications to be solved reliably and ensures high system availability.

#### **Recommended products**



# Robot guidance for installation of windshields




The robot takes the windshield from the turntable. Four W12-3 small photoelectric sensors ensure that the gripper is positioned precisely and that the windshield is picked up without tension. The robot then travels to the approximate

position over the windshield cutout in the body. It moves its gripper over the installation point until the OD short range distance sensors (displacement) register the exact distance. The windshield is then inserted precisely.

#### Recommended products

# Skid detection at the lift station entry



The skid with the body is detected prior to entering the lift using the Reflex Array MultiTask photoelectric sensor. The photoelectric sensor produces a line, which

is used to detect the different skids. As a result, the position tolerances are compensated by up and down movement of the skid on the roller conveyor.

#### Recommended products



# Type check for car body parts



Besides the presence of parts, additional features such as holes, boreholes or cutouts must be detected for type testing. The Inspector vision sensor detects several parts simultaneously. Several features can be taught and a variety of testing tasks defined. W12-3 small pho-

toelectric sensors with pin-point technology use a small light spot to detect even the smallest gaps without the limiting laser class. When all parts are inserted correctly and completely, the turntable is enabled for further processing.

## **Recommended products**

W12-3......G-528

# Monitoring the feeder clips




Fast and reliable monitoring of closed feeder clips at feeders is possible with only one Reflex Array MultiTask photoelectric sensor. The 50-mm line detects any deviation from the correct position, thus preventing damage to the placement head and enhancing machine availability.

#### **Recommended products**



# Presence monitoring and counting process



WTB4-3 and WTB9-3 miniature and small photoelectric sensors detect the "shoulders" of the copies and check

that they are present. Noncontact and wear-free copy counting takes place at the same time.

#### **Recommended products**

W4-3	W9-3
W4S-3	

# Sheet presence and position monitoring



WTB4-3, WTB9-3, WTB12-3 or WT18-3 miniature or small photoelectric sensors reliably detect the presence of a print sheet or paper sheet regardless of their colors. They forward this information to

the controller of the printing machine in the form of a control signal. This allows detection of a non-synchronous paper feed and monitors the correct paper flow.

#### **Recommended products**

W4-3 F-238	W9-3 G-448	W18-3 G-556
W4S-3 F-260	W12-3 G-528	

# **Detection of paper edges**



WTB4-3, WTB9-3 or WTB12-3 fast miniature and small photoelectric sensors use a precise light spot to detect the positions of the paper front and back edges,

regardless of the color of the paper. This determines the length of the paper sheet precisely and eliminates any background disturbances.

#### Recommended products

W4-3	W9-3
W4S-3	W12-3

# Paper tear monitor




The WTB4-3, WTB9-3 or WTB12-3 miniature and small photoelectric sensors detect paper tears fast and reliably. Equally important is the absolutely reliable detection of the paper web, even

with varying surface reflections. This prevents unnecessary machine downtime. Background suppression ensures that the rear web has no impact on the paper tear check of the front web.

#### **Recommended products**

W4-3	W9-3
W4S-3	W12-3

# **Detecting circuit boards**



Circuit boards must be reliably detected at many different points along a production line. Standard photoelectric proximity sensors that rely on a punctiform light spot do not always detect circuit boards reliably because any openings in the circuit board will result


in signal interruptions. With its two lineshaped light spots, the MultiLine sensor compensates for the openings or other factors (reflective surface). As a result, the circuit boards are detected reliably without any signal interruptions.

#### **Recommended products**





# **Device detection in gripper**



Grippers often make large movements to grab their objects. The ideal sensors to mount on the gripper must be small

and light-weight. The sub-miniature (7.7 x 21.8 x 13.5 mm) WT2S-2 photoelectric proximity sensor is the answer.

#### Recommended products

W2S-2......F-216

# Object detection and intelligent identification



An elegant solution comprised of the WLL180T-2 fiber-optic sensor with the LL3-TS40 fiber-optic cable creates the light array which provides real-time position data. The DFS60 incremental encoder reports the belt position. At the same time, the CLV620, featuring


SMART620 code reconstruction, reads even damaged bar codes on the PCB, with the highest read rates in its class. It comes complete with Serial, Ethernet TCP/IP, and CAN network support. An optional expansion interface is available for OEMs requiring custom solutions.

#### **Recommended products**

WLL180T and LL3 ...... J-798



#### Wire bonder automation solutions



Here, the fiber-optic solution works best. The area near the bonding head is hot. The WLL180 fiber-optic sensor with a 16µs response time together with the precise light array of the LL3-DH fiber cable provide a precise edge detection signal to the controller. The grippers must move fragile substrates at very high speeds with high precision to minimize bonding

head idle time. The dual TTK70 linear encoder read heads operate at speeds up to 10 m/s with µm accuracy, contributing substantially to machine throughput. The W2S photoelectric proximity sensor with diffused light spot ensures the absence of substrate before allowing the cassette to move to the next slot.

#### **Recommended products**

W2S-2 . . . . . . . . . . . . F-216 WLL180T and LL3. . . . . J-798



# **Detection of single trays**



The new MultiTask sensor TranspaTect needs no reflector to detect transparent object – it uses the machine background as a reference surface instead. This

results in a new freedom in machine design. At the same time AutoAdapt function ensures a smooth production process.

#### **Recommended products**

TranspaTect ...... E-142



# **Detecting PET cases**



The transport of the cases is monitored and controlled with photoelectric sensor. Therefore the transport speed is increased or decreased – depending on the accumulated packages on the conveyor line. When a case is not detected, the controller receives no signal, and the


speed of the conveyor belt is maintained or increased. Are still cases present, damage to the container and eventually stops can be the result. The MultiTask sensor MultiPac with its redundant detection system detects the different cases without signal interruptions.

#### **Recommended products**





# W4S-3 Inox in a bottling plant




Recognition of PET and glass bottles under very harsh ambient conditions. The all around solution – reliable recognition of all packaging in the food and

beverages market. Simple setting via Metal Membrane Teach. High reliability due to automatically tracking switching threshold.

#### **Recommended products**



# Wine bottling plant: WLL180T determines the filling level



The filling tube, which is fitted with a filling level fiber-optic cable, is inserted down into the bottle neck, and filling

begins. Once the desired level has been reached, the WLL180T switches and the filling process stops immediately.

#### **Recommended products**



# **Board detection**




VTB180-2 photoelectric proximity sensors can be used for versatile detection tasks in automation technology. The small transition zone from the sensing

distance to the background allows objects to be precisely detected. Interferences outside of the working area will be reliably ignored.

#### **Recommended products**

# **Board detection**




The compact photoelectric sensor W280L-2 Long Range recognizes boards thanks to the extremely high sensing range of up to 4 m without a reflector from a distance. In addition, a protection system prevents the W280L-2 Long

Range impairments caused by reflections from the background, such as by shiny metal surfaces, windows or safety vests and allows the opposing mounting of the sensors without any interference.

#### Recommended products

#### **End of material detection**




The end of the material is reliably detected with the compact and versatile W9-3 photoelectric proximity sensors. The sensing distance ranges from 30 to 250

mm. Precise background suppression makes the WTB9-3 immune to ambient light sources and is easy to adjust.

#### **Recommended products**

# Accurate and reliable leading edge detection of profile wood and pallets



Due to the high conveying speed and the length of the profile wood, the wood does often not lie evenly on the conveyor belt. Thanks to its broad light band the Multi-

Task sensor Reflex Array reliably detects profile wood and pallets - regardless of their position.

#### **Recommended products**

Reflex Array......E-134



# Checking presence and fill level in the singulation system



To ensure that the vibration drives of a bowl feeder and the linear conveyors connected to it are not continually in operation, the presence of the material to be conveyed must be checked at various points in the singulation system. To ensure this occurs, all the material placed on the linear conveyor is detected using

the rugged and easily adjustable WFL fork sensor. The WLL180 fiber-optic sensor is even able to monitor the presence of parts on the loading pallet when the space available is severely limited. The UP56 ultrasonic level sensor is used to check how full the bowl feeder is.

#### **Recommended products**

# Checking the presence and position of trays



To control the conveying line, it is necessary to check whether the trays to be transported are present and whether they are in the correct position. The WTB12-3 small photoelectric sensor

is used for this purpose. In addition to detecting the trays, this photoelectric sensor can also detect the position of the trays using the background suppression function.

#### **Recommended products**

# Controlling the conveying line



The WL15 small photoelectric sensor reliably detects the presence of the foamed block in order to control the downstream conveying line. The WL15 or GL18S are designed for highly flexible mounting using M18 front mounting

plastic nuts and a snap ring or side attachment. When it comes to mounting on an aluminum profile, the WL12-3 small photoelectric sensor is the perfect choice.

#### **Recommended products**


# Detecting parts in the gripper and the injection molding tool



There is very limited room available for sensors in the robot gripper and the injection molding tool. For this reason, the W2 Flat miniature photoelectric sensor is the ideal choice for detecting inserts and finished parts so that they can then be placed in the gripper. The WLL180T fiber-optic sensor, featuring high temperature-resistant LL3-DH03 fibers, is perfect for use in injection molding tools.

#### **Recommended products**


# Level control for slides/chutes



Cost-effective photoelectric red light sensors are used to monitor the filling level of slides. While the PLC knows the exact volume of the individual parcels in a slide, it has no information on the actual space still available in the slide since the parcels occupy it in an irregular way. Several sensors installed along the edge of the slide provide the PLC with the pre-alarm and alarm signals required to manage and prioritize the subsequent loading activities. PinPoint LEDs generate an extremely bright, precise light spot.

#### **Recommended products**

# Speed measurement with laser sensors




Laser sensors are used to measure speed on sorters without rotating axes. Robust, high-performance photoelectric laser sensors create light barriers and

detect a part of a cross belt or tilt-tray belt as it passes through the laser beam to provide the controller with a reliable signal.

#### Recommended products


# **Empty detection**



Empty detection is essential in avoiding double occupation of cells. If undetected, this condition inevitably results in incorrect deliveries and additional costs. A cost-effective W14-2 photoelectric sensor is used to check whether the cell

#### **Recommended products**

# Leading edge detection



Leading edge detection with MultiTask photoelectric sensors is required to merge items, to detect the handover status to or off the sorter cells, or for other types of simple belt control tasks. MultiTask photoelectric sensors detect the leading edge of an item. The speed

of individual belt segments is then controlled to create the gaps between the items. The Reflex Array multi-task photoelectric sensor with its light band is then used when objects with no clearly defined leading edge have to be detected reliably.

#### **Recommended products**

Reflex Array......E-134



# **Tilt-tray sorter off load detection**



On automatic tilt-tray sorting systems, WL12-3 sensors are mounted at the divert lane entry point to verify the

lane and count items that are diverted through it.

#### **Recommended products**

W12-3......G-528

# **Detection of inhomogeneous containers**



Inhomogeneous containers such as lattice boxes must also be detected reliably - there should be no multiple switchings. The 50-mm light band of the MultiTask

photoelectric sensor Reflex Array allows precise leading edge detection even of inhomogeneous objects.


#### **Recommended products**

Reflex Array..... E-134





# **Pallet detection**



Reliable pallet detection is ensured with the MultiTask photoelectric sensor Reflex

Array. Its 50 mm light band can compensate for different pallet heights.

#### **Recommended products**

Reflex Array..... E-134





# Accumulation conveyor/retrofits



Parcels are more efficiently accumulated along conveyor lines to reduce backpressure, jams and product damage using ZoneControl sensors and logic modules.

The sensors are mounted between the rollers of multiple conveyor zones where they are protected from damage.

#### Recommended products



# **Detection of highly reflective coffee packages**



In the production line, the reflecting coffee packages have to be detected reliably in different positions. The multi-line


sensor reliably detects the leading edge of the coffee packaging without signal interruption.

#### **Recommended products**

MultiLine Sensor ..... E-124



# V18V on a conveyor belt



The VL18V retro-reflective photoelectric sensor for clear material detection triggers the portioning belt for synchronizing

the feed belt (packaging/transparent belts).

#### **Recommended products**



# WTB4-3 for securing apertures



Task: to ensure that the aperture is sealed by the boxes. Solution: A WTB4-3 sensor with self monitoring function. If

the aperture is not sealed or if there is a sensor error, a message is sent to the control sytem.

#### **Recommended products**

W4-3 ..... F-238 W4S-3 ..... F-260

# Automatic wheel separating on conveyor belts




The ZoneControl sensor controls the wheel feed to the assembly station. The sensor is designed for so-called "Accumulating roller conveyors". It is equipped with solenoids. The conveyor is divided into segments with a ZoneControl sensor

with adjacent reflectors at the end of each section. The internal logic of the sensors ensures a controlled material flow to start or stop wheel feeding to the defined segments.

#### **Recommended products**



# **Tire detection**



The tires must be detected at the handover point in order to be handled by the linear robot. This is done using a Multitask photoelectric sensor MultiPac. It detects the tires reliably.

#### **Recommended products**

# Loop control: loop measurement



Loop measurement enables decoupling of processes such as calendering and material infeed and out-feed when replacing the bobbin. Retro-reflective sensors (e.g., WL12, WL18 or WL27) installed on the top or bottom enable loop measurement.

#### Recommended products

W12-3	.G-528	W27-3
W18-3	.G-556	

# Tire separating



MultiTask photoelectric sensors MultiPac detect tires in the individual sections of the roller conveyor. The switching signal


serves to control the roller conveyor. This ensures that the tires are separated and forwarded at identical intervals.

#### **Recommended products**

MultiPac . . . . . . . . . E-130 ZoneControl . . . . . . . . . . . . E-148



# **Detection in harsh environment**



After wire sawing, the wafers are covered with abrasive coolant that will damage any unprotected device, and can obscure sensor windows. The WTB4S-3V photoelectric sensor is imperious to

contamination. With the optional IO-Link interface, sensor window contamination can be continuously monitored, reducing machine downtime.

#### **Recommended products**



# **Smart wafer presence detection**




Sometimes the machine operator needs an unobstructed view. The ideal location for presence sensors in this instance is beneath the wafers, looking up into ambient light. Thanks to SICK's unmatched

background suppression algorithms, both the operator and the W2S-2 photoelectric sensor can work without interference.

#### **Recommended products**

W2S-2......F-216

# Glass panel overhang detection



The WTV4-3 photoelectric proximity sensor monitors the often difficult to detect glass as the buffer loads/unloads. After the process, the glass may not reload


into the magazine correctly, breaking the glass in transport. A WLG4 photoelectric retro-reflective sensor guards against overhanging panels.

#### Recommended products





# **Double wafer detection**



Wafers are light and thin, and stick easily, especially during the cleaning process. Stuck wafers must be detected quickly, as they will likely break and damage others. SICK's WLL180T fiber-optic sen-

sor coupled with wide bandwidth fibers LL3-TW01, use a 1450 nm infrared beam to penetrate the wafer, instantly detecting stacked wafers.


#### **Recommended products**

WLL180T and LL3 . . . . . . . . . . . . . . . . . J-798





# **Detection of persons for automatic door opening**



The position of pushbuttons for doors in public transportation vehicles are often not designed for the needs of wheelchair users. To accommodate individuals in wheelchairs, the WTB27-3 compact photoelectric sensor is mounted above the door to accurately detect when a

wheelchair user approaches the door. The sensing range can be adjusted to reliably detect objects close to the ground (e.g., footrest). The door then opens on time and the wheelchair user can pass unhindered.

#### **Recommended products**

W27-3......H-616

#### **Detection of the direction of travel**



Toll stations must be able to reliably detect when a vehicle reverses out of the single lane. Acquiring this data ensures the proper toll amount has been paid. Two series-mounted GSE6 photoelectric

sensors with a switching frequency of 1 kHz and an infrared light identify the contours of the vehicle very quickly. Even the travel direction of vehicles moving at high speeds is reliably measured.

#### **Recommended products**

# **Separation in security gates**



At public transportation stations, automatic access systems ensure that only people with valid tickets are transported. Multiple WL15 cylindrical photoelectric sensors are mounted on an access system. Combined with a downstream con-

troller, the system ensures that only one person passes the turnstile per opening process. The WL15 uses the reflection principle and therefore, only has to be wired on one side of the turnstile, which saves time and money.

#### Recommended products

W15......I-766

# **Automated parts infeed and outfeed**



The conveyor feeds in new workpieces and discharges machined ones simultaneously. The individual workpieces and empty workpiece carriers are made available. The IME inductive proximity sensor detects the position of the workpiece

carrier. The WL12-3 small photoelectric sensor monitors whether a workpiece is placed on the carrier. Both signals are used to control the process.

#### **Recommended products**

W12-3......G-528

# Component detection in a crossbar robot



The WT12L-2 small photoelectric sensor checks whether the component is located in the gripper of the robot and whether the component has therefore

been removed from the press tool. This prevents mechanical damage to the press.

#### **Recommended products**



### Tracking the sheet roll



The WTB27-3 photoelectric proximity sensor monitors the presence of the sheet roll at various points throughout the industrial manufacturing process. It

is immune to ambient light and optical reflections. The continuous flow of material while the plate shears are operating is monitored reliably.

#### Recommended products

W27-3......H-616

# **Detection of assigned tool locations**




The machining process on a punching machine requires different tools, which are provided by a tool magazine. The assignment of the tool magazine location

and the correct positioning of a tool holder are reliably detected using the W27-3 compact photoelectric sensor.

#### **Recommended products**

W27-3......H-616

# **End of material detection**



A VSE180-2 cylindrical photoelectric sensor detects the presence of the raw material in the saw. Its digital signal is

used to control the machine in harsh environments.

#### **Recommended products**

# Stamp breakage monitoring



In press or stamping tools, the inductive proximity sensor IQ Flat detects whether the metal workpiece is correctly positioned. The small photoelectric sensor WTB9L-3 – mounted outside of the tool –

precisely detects workpiece characteristics. The stamp breakage monitoring works for shiny surfaces too: with the MultiTask photoelectric sensor MultiPac.

#### **Recommended products**

W9L-3 . . . . . . . . . G-470 MultiPac . . . . . . . E-130





# Optical inline quality checking



For full quality checking, correct processing of the motor block must be checked. The Inspector vision sensor checks that the holes and cutouts are present and

correct. The precise light spot of the WT12L-2 reflection photoelectric sensor detects even the smallest holes on the motor block.

#### Recommended products



# Positioning of the sheet pallet



A WSE12-3 small photoelectric throughbeam sensor or a WTB12-3 photoelectric proximity sensor precisely detect the presence of the sheet pallet or the position of the pallet edge thanks to a fast switching frequency. They ensure that the vacuum nozzle or the transfer carriage of the material infeed can place the sheets correctly and that there is always a gap between the material lift and the interim shelf. This eliminates collisions and reduces downtime.

#### **Recommended products**





# Detecting, verifying, positioning, counting - photoelectric sensors from SICK

SICK's vast range of photoelectric sensors offer precise optics and advanced technology, creating market-leading solutions with sensor intelligence. By using the latest ASIC and LED technologies, these sensors offer the highest level of operational reliability regardless of any interference factors. Additional sensor information can be used to simplify modern production processes.

This extensive range of photoelectric sensors is used in many automation applications around the world.





# MultiTask photoelectric sensors

ZoneControl	E-104 E-106 E-108 E-110
<b>DeltaPac </b>	TranspaTect
MultiLine Sensor E-124 Two is better than one	ZoneControl
MultiPac	WLR E-160
Reflex Array E-134  The sensor with the light band: multifaceted and economical	









# Focusing on efficiency: SICK MultiTask photoelectric sensors offer optimum performance at low investment costs

# Reliable gapless sensing: DeltaPac from SICK perfects production



Products can be counted and detected on the belt in a way that was not possible before. Without gaps. Without delays. DeltaPac accurately detects the transition between successive packaging items or workpieces. This ensures faster, smarter, more economical, and more reliable production. In other words: DeltaPac is a patented technological world first, implemented in a unique way. DeltaPac closes every gap. It eliminates product separation on the belt and reduces downtime caused by collisions. DeltaPac is an energy-efficient solution that increases production and requires less hardware, opening up new applications for systems engineering. Its control systems ensures users are always aware of what is happening in the system. DeltaPac: The new, uniquely efficient photoelectric sensor from SICK.




DeltaPac . . . . . . . E-114

· Zero gap detection



# MultiLine Sensor: The detection of complex, textured objects made easy



The MultiLine sensor meets customer requirements in ways that optical sensors were previously incapable of handling. With an unprecedented level of detection reliability, this sensor can reliably detect objects with an extraordinarily wide range of holes, cutouts, reflective or transparent areas, or contours. This is made possible thanks to an innovative multi-sensor principle, which evaluates two visible light lines independently of one another. The sensor output remains switched on even when a section of or an entire light line of the sensor leaves the object.

A further benefit is the fact that it is not necessary to keep resetting the sensor to handle different detection tasks. If you need to detect coffee packaging, soup packets, or chocolate bars from above – the MultiLine sensor is the optimum solution.



MultiLine Sensor . . . E-124

- · Detecting perforated objects
- · Detecting uneven, shiny objects
- Detecting objects wrapped in film







# MultiPac: For extreme detection




When it comes to optical sensors, detecting very shiny, highly reflective, and uneven surfaces, such as metal, presents just as much of a challenge as detecting packaging units wrapped in film. The optimum solution is the MultiPac sensor from SICK. Its secret is based around three key features: Two completely separate receiver systems double the sensor's detection capability, a high-performance LED generates an extremely high light intensity, and the detection algorithm controls the complex evaluation process. So simple, yet so impressive. The sensor can be mounted up to 500 mm above the conveying line, enabling an extremely wide range of packaging unit types and heights to be detected with only one fixed sensor position. With different packaging unit heights, the mechanical position adjustment that was often required becomes unnecessary, significantly reducing effort and expense for users.

- Detecting uneven, shiny objects
- · Detecting objects wrapped in film





# Reflex Array: The photoelectric sensor with the light array - multifaceted and economical



The detection of misshapen or uneven objects, or objects of varying height presents a particular challenge. Reliably detecting the leading edge in such cases generally requires the installation of two photoelectric sensors positioned one on top of the other or the use of a light grid. This of course results in high installation costs. With the Reflex Array sensor, however, SICK offers a cost-effective alternative: A housing and a connecting cable, while also ensuring reliable detection, regardless of position, of all objects within its innovative light array. Other features include the capability to detect transparent objects and the prevention of multiple switching when detecting perforated objects. Four variants of the Reflex Array photoelectric sensor are available for a wide range of requirements with regard to detection height and minimum object size.



Reflex Array..... E-134

- · Detecting transparent objects
- · Detecting perforated objects
- · Detecting objects with position tolerances







# TranspaTect: Detecting transparent objects in a new dimension



Need to detect transparent objects? Only possible with a reflector.

This response is now a thing of the past. New technology allows the TranspaTect photoelectric proximity sensor to detect transparent trays and bottles without any reflectors, instead using the system itself as a reference surface. All you need is a stable, matte background, such as a machine element. The TranspaTect can also reliably detect very shiny, highly reflective, and uneven surfaces. This not only saves time and costs, it also opens up new machine design possibilities. In addition, continuous threshold adaptation guarantees optimum operational safety with respect to industrial contamination, e.g., for packaging processes in the food, beverage, and pharmaceutical industries. TranspaTect clearly and reliably identifies transparent objects.



TranspaTect ..... E-142

- Detecting uneven, shiny objects
- Detecting transparent objects







# The green light for accumulation conveyors

# SICK ZoneControl solutions control product flow



The three key features of a ZoneControl solution

In towns and cities, traffic lights are mainly responsible for controlling the flow of vehicles on the roads. ZoneControl solutions from SICK fulfill a very similar role when it comes to controlling the flow of products on accumulation conveyors – and all without the need for a programmable logic controller (PLC) or another type of external control system. Accumulation conveyors briefly hold a product before re-releasing it for the next phase in the production process. This must involve zero pressure accumulation (ZPA) in order to prevent damage or products falling from the belt.

Three product families ensure that everything runs smoothly during the ZPA process. ZoneControl solutions are commissioned via plug-and-play and are extremely straightforward: Simply connect the ZoneControl products in a series, install the sensor, and then connect it to the pneumatic line or motorized rollers. There is no need to configure a PLC, use a laptop, or carry out expensive field wiring.

#### Sensor

- Reliably detects the conveyed product

#### Integrated logic

- No PLC, no laptop
- Sensors are connected in series

# Direct transmission to the conveying equipment

- Pneumatic drive or
  - Motorized rollers

#### **Variants**

Each of these ZoneControl products are connected in a series and operate according to one of two feed logics, depending on the application in question: **Single feed** (with or without sleep function) or **block feed** (slug).

Whether the accumulation conveyor is powered **pneumatically** or by **motorized rollers**, ZPA is incredibly simple with ZoneControl solutions from SICK.

In order to satisfy various installation situations, four different sensor variants are available:

- Between the rollers of the conveyor, R/IR from page E-148
- Over the conveyor, WLR from E-160
- On the side frame of the conveyor, **ZLM** from page E-164 Special options are also available for mounting each sensor on the accumulation conveyor.


R/IR WLR ZLM








# Conveying logic



In the case of **single feed** (with or without sleep function), the conveyed product that has been detected is stopped and prevented from being transported further until the next zone is free.

If there are two successive zones, the downstream section is brought to a halt in sleep mode if no products are detected for nine seconds.

**Block feed** (slug) allows a larger quantity of products to travel downstream, typically to the picking zone. In this case, no zone is stopped in the accumulation conveyor until the conveyed product has reached the last downstream section.



#### Overview

				Mounting			Single feed logic		Type of release		Product features					Page
	Sensor	Logic unit	Valve <sup>1)</sup>	Between the rollers	On the side frame	Over the conveyor	Single feed	Block feed	Single release	Slug release	Max. sensing range (mm)	Enclosure rating	AC (alternating current)	Compatible with motorized rollers	Connection to external valve	
R											900	IP 67				E-148
IR		•					•		•	-	900	IP 65		•	•	E-148
WLR		•									9,000	IP 67	•			E-160
ZLM		•			•		•			•	1)	IP 65				E-164


<sup>1)</sup> Connection to all discrete DC sensors.

#### Overview of MultiTask photoelectric sensors

	Housing properties			Senso	Sensor properties										
	Materi	al	Enclos rating												
	Plastic	Metal	IP 66	IP 67	Photoelectric proximity sensor	Multi-background suppression	Background suppression	Foreground suppression	Photoelectric retro- reflective sensor	Reflex Array	MultiLine	MultiPac	IO-Link	AutoAdapt 🔭	
DeltaPac NEW															
WTD20				•	•								•		
MultiLine Sensor															
MultiLine			•		•	•					•				
MultiPac															
WTB27-3 MultiPac			•	•	•										
Reflex Array															
WL27-3 Reflex Array	•			•						•					
TranspaTect NEW															
WTF12G-3		•		•				•							
ZoneControl NEW															
R	•			•											
IR				•											
WLR210															
ZLM															

#### Photoelectric proximity sensors


	<b>-</b>	•	
	Maximum sensing range	Dimensions (W x H x D)	Page
DeltaPac	30 mm 40 mm	42 mm x 42 mm x 45 mm	E-114
MultiLine Sensor	5 mm 120 mm	16 mm x 39.5 mm x 12 mm	E-124
MultiPac	30 mm 500 mm	24.6 mm x 80.6 mm x 54.8 mm	E-130
TranspaTect	150 mm 700 mm	15.6 mm x 48.5 mm x 42 mm	E-142
R	60 mm 900 mm	20.6 mm x 99.2 mm x 48.9 mm	E-148
IR	60 mm 900 mm	59.9 mm x 151.9 mm x 48.9 mm	E-148
Reflex Array	0 m 4.5 m	24.6 mm x 80 mm x 54.2 mm	E-134



#### Photoelectric retro-reflective sensors




#### **Product family overview**




→ E-114


**Detailed information** 

→ E-124



#### **Product family overview**





#### **Bridging the Gap**







#### **Additional information**

Detailed technical data E-115
Ordering informationE-116
Dimensional drawingsE-117
Sensing range in detailE-118
Productivity key figures E-119
Connection diagram
Recommended accessories E-122



#### **Product description**

For higher efficiency and quality in the packaging industry, the DeltaPac MultiTask photoelectric sensor utilizes Delta-S-Technology®, which combines four PinPoint emitters and two receivers with SIRIC® and distance measurement technology. The photoelectric sensor detects object contours with radii between 1 and 20 mm – independent of the direction and irrespective of the object's surface color –with the highest level of immunity to active and passive interference. The operating distance is between

30 and 40 mm to the front edge of the object. This means that packages do not need to be manually separated. Collisions are avoided. For better space and time utilization. The DeltaPac provides information about how many packages are present in the process for full production monitoring. The photoelectric sensor is available as a pre-configured device for fast and error-free commissioning. IO-Link, which is also available, enables tailored configuration and adaptation to match the desired application.

#### At a glance

- Delta-S-Technology®: four PinPoint emitters and two energy scales combined with SIRIC® and distance measurement technology
- Direction-independent object contours with radius up to 20 mm
- For conveyor speeds up to 3 m/s or production capacities up to 200.000 packages per hour
- Pre-configured sensors and individual setting via IO-Link
- Compact housing (42 mm x 42 mm x 45 mm) with an IP 67 enclosure rating

#### Your benefits

- Selective process optimization: information about the number of packages in the process enables better production monitoring
- Better space utilization: no mechanical devices are required to isolate packages, reducing the width of packaging systems and saving space
- Better time management: packages run in push-push mode, which prevents collisions and toppling, and reduces machine downtime
- Stable production for enhanced energy consumption
- Fast and intuitive commissioning due to pre-configuration
- Configuration via the IO-Link enables users to customize features based on the applications
- Space-saving mounting due to compact housing

#### → www.mysick.com/en/DeltaPac

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



#### **Detailed technical data**

#### **Features**

Sensor principle	Delta-S-Technology®
Dimensions (W x H x D)	42 mm x 42 mm x 45 mm
Housing design (light emission)	Rectangular
Sensing range max.	30 mm 40 mm <sup>1)</sup> (depending on type)
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	4 x Ø 1 mm (30 mm)
Wave length	635 nm
Optimized parameterization for the following objects	Folding box or stacked empty packages / rounded, rounded out and prism shaped packaging, such as beverage cartons and soft packaging (depending on type)

<sup>1)</sup> The sensing range max, refers to the object leading edge. The individual object leading edges must be within the operating range.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>
Power consumption	$\leq$ 70 mA $^{3}$ / $\leq$ 160 mA (depending on type)
Output type	NPN/PNP (depending on type)
Output current I <sub>max.</sub>	≤ 2 x 100 mA
Connection type	Cable, 2 m <sup>4</sup> /Male connector, M12 (depending on type)
Circuit protection	A <sup>5)</sup> , B <sup>6)</sup> , C <sup>7)</sup>
Protection class	III
Weight	130 g
IO-Link	-/✔ (COM2) (depending on type)
Housing material	Bayblend
Enclosure rating	IP 67
Ambient operating temperature	-40 °C +55 °C
Ambient storage temperature	-40 °C +75 °C
Productivity max.	$\leq 40,\!000$ Stk./h/ $\leq 200,\!000$ Stk./h/ $\leq 54,\!000$ Stk./h (depending on type)
Object speed max.	0.6 m/s/1.2 m/s/3 m/s (depending on type)
Radius of the object contour	1 mm 20 mm (depending on type)
Switching accuracy	≤ 2 x radius
Repeatability (T <sub>a</sub> not constant)	Typ. < 1 mm
Object width min.	≥ 10 mm/≥ 30 mm/≥ 20 mm (depending on type)
Object height min.	30 mm /50 mm (depending on type)

 $<sup>^{</sup> ext{1}}$  Limit values, reverse-polarity protected, operation in short-circuit protected network: max. 8 A.

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> At 24 V.

<sup>&</sup>lt;sup>4)</sup> Do not bend below 0 °C.

 $<sup>^{5)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{\</sup>rm 6)}$  B = inputs and output reverse-polarity protected.

 $<sup>^{7)}</sup>$  C = interference suppression.

#### WTD20E, for folded boxes

• Object speed max.: 0.6 m/s

• Productivity max.: ≤ 40,000 Stk./h

• Switch on delay Q₁ & Q₂: ≤ 80 ms

• Time delay off Q₁: ≤ 80 ms

• **Pulse length (Q2)**: ≤ 20 ms

• Background suppression: ≥ 60 mm

• Object height min.: 30 mm (The object heigh min. is relevant only for the installation of DeltaPac above the conveyor belt.)

• Current consumption: ≤ 70 mA

Object width min.	Radius of the object contour	Key fea- ture of the object		Output type	Connection	Con- nection diagram	Model name	Part no.
≥ 10 mm	1 mm	Edgo	20 1 / 2 mm	NPN	Cable, 4-wire, 2 m, PVC	Cd-242	WTD20E-W1145	1065773
2 10 111111	2 mm	Edge	30 +/- 2 mm	PNP	Connector M12, 4-pin	Cd-243	WTD20E-V2445	1065772

#### WTD20E, IO-Link for folded boxes

• Object speed max.: 0.6 m/s

• Productivity max.: ≤ 200,000 Stk./h

• Switch on delay  $\mathbf{Q}_1$  &  $\mathbf{Q}_2$ : 0 ms ... 255 ms

• Time delay off Q<sub>1</sub>: 0 ms ... 255 ms

• Pulse length (Q2): 0 ms ... 63 ms

• Background suppression: ≥ 60 mm

. Object height min.: 30 mm (The object heigh min. is relevant only for the installation of DeltaPac above the conveyor belt.)

• Current consumption: ≤ 70 mA

Object width min.	Radius of the object contour		Sensing range	Output type	Connection	Con- nection diagram	Model name	Part no.
≥ 10 mm	1 mm 2 mm	Edge	30 +/- 2 mm	PNP, IO-Link	Connector M12, 4-pin	Cd-244	WTD20EC-V2449	1064783

#### WTD20E, rounded, rounded out and prism shaped packaging

• Object speed max.: 1.2 m/s

• Productivity max.: ≤ 54,000 Stk./h

• Switch on delay  $Q_1 \& Q_2 \le 60 \text{ ms}$ 

• Time delay off Q<sub>1</sub>: ≤ 60 ms

• **Pulse length (Q2)**: ≤ 20 ms

• Background suppression: ≥ 80 mm

. Object height min.: 50 mm (The object heigh min. is relevant only for the installation of DeltaPac above the conveyor belt.)

Object width min.	Radius of the object contour	Key fea- ture of the object	Sensing range	Output type	Current consump- tion	Connection	Con- nection diagram	Model name	Part no.
≥ 30 mm	5 mm 20 mm	Rounded edges,	30 mm 40 mm	NPN	≤ 70 mA	Cable, 4-wire, 2 m, PVC	Cd-242	WTD20E-W1114	1064779
≥ 20 mm	2 mm 5 mm	rounded out body and prism shaped	30 mm 40 mm	PNP	≤ 160 mA	Connector M12, 4-pin	Cd-243	WTD20E-V2414	1064778

#### WTD20E, IO-Link for rounded, rounded out and prism shaped packaging


- Object speed max.: 3 m/s
- Productivity max.: ≤ 200,000 Stk./h
- Switch on delay Q<sub>1</sub> & Q<sub>2</sub>: 0 ms ... 255 ms
- Time delay off Q<sub>1</sub>: 0 ms ... 255 ms
- Pulse length (Q2): 0 ms ... 63 ms
- Background suppression: ≥ 80 mm
- Object height min.: 50 mm (The object heigh min. is relevant only for the installation of DeltaPac above the conveyor belt.)
- Current consumption: ≤ 70 mA

Object width min.	Radius of the object contour	Key fea- ture of the object	Sensing range	Output type	Connection	Con- nection diagram	Model name	Part no.
≥ 20 mm	2 mm 20 mm	Rounded out body and prism shaped	30 mm 40 mm	PNP, IO-Link	Connector M12, 4-pin	Cd-244	WTD20EC-V2419	1064782


#### **Dimensional drawings**

Dimensions in mm (inch)

#### WTD20E-V, cable




6 7




- ① Standard direction
- 2 Center of optical axis, sender
- $\ensuremath{\mathfrak{3}} \ensuremath{\text{ Center of optical axis, receiver (first energy scale)}}$
- ④ Center of optical axis, receiver (second energy scale)
- 3 Optical axis, receiver
- © LED indicator orange: status of received light beam, presence signal Q1
- 7 Status indicator LED green: power on
- 8 Mounting hole

43.4 (1.71)

#### WTD20E-V/W11xx, connector




6 7



- ${\bf \textcircled{1}} \ {\bf Standard} \ {\bf direction}$
- 2 Center of optical axis, sender
- 3 Center of optical axis, receiver (first energy scale)
- ④ Center of optical axis, receiver (second energy scale)
- ⑤ Optical axis, receiver
- © LED indicator orange: status of received light beam, presence signal Q1
- 7 Status indicator LED green: power on
- 8 Mounting hole
- 9 Connection (rotatable)


#### Sensing range in detail


43.4 (1.71)



#### **Productivity key figures**

#### WTD20E-V/Wxx4x, edge, productivity





#### Parameter example, dimensions in mm (inch)

Object width	Object radii	Productivity min.	Productivity max.
25 (0.98)	1 (0.04)	7,500 pc/h	38,000 pc/h
75 (2.95)	2 (0.08)	3,500 pc/h	28,500 pc/h


= R1, Radii of 1 mm


= R2, Radii of 2 mm

= Working range

= Maximal working range

#### WTD20E-V/Wxx4x, edge, speed






#### Parameter example, dimensions in mm (inch)


Object width	Object radii	Object speed min.	Object speed max.
25 (0.98)	1 (0.04)	0.05 m/s	0.26 m/s
75 (2.95)	2 (0.08)	0.08 m/s	0.6 m/s

= R1, Radii of 1 mm
= R2, Radii of 2 mm
= Working range

= Maximal working range

#### WTD20E-V/Wxx1x, rounded edges, productivity







#### Parameter example, dimensions in mm (inch)

Object width	Object radii	Productivity min.	Productivity max.
75 (2.95)	2 (0.08)	7,000 pc/h	53,000 pc/h
125 (4.92)	5 (0.20)	7,000 pc/h	34,500 pc/h

### = R2, Radii of 2 mm = R5, Radii of 5 mm = Working range = Maximal working range

#### WTD20E-V/Wxx1x, rounded edges, speed







#### Parameter example, dimensions in mm (inch)

Object width	Object radii	Object speed min.	Object speed max.
75 (2.95)	2 (0.08)	0.15 m/s	1.1 m/s
125 (4.92)	5 (0.20)	0.25 m/s	1.2 m/s

#### WTD20E-V/Wxx1x, rounded out body and prism shaped, productivity







#### Parameter example, dimensions in mm (inch)

Object width	Object radii	Productivity min.	Productivity max.
200 (7.87)	5 (0.20)	4,500 pc/h	53,500 pc/h
250 (9.84)	20 (0.79)	11,000 pc/h	43,000 pc/h

= R5, Radii of 5 mm • = R20, Radii of 20 mm = Working range = Maximal working range

#### WTD20E-V/Wxx1x, rounded out body and prism shaped, productivity, speed





#### Parameter example, dimensions in mm (inch)

Object width	Object radii	Object speed min.	Object speed max.
200 (7.87)	5 (0.20)	0.25 m/s	3.0 m/s
250 (9.84)	20 (0.79)	0.75 m/s	3.0 m/s

= R5, Radii of 5 mm •• = R20, Radii of 20 mm

= Working range

= Maximal working range

#### **Connection diagram**

Cd-242	Cd-243	Cd-244
$ \begin{array}{ccc}  & & & \\  & & & &$	$ \begin{array}{c c}  & \text{bin} & 1 \\  & \text{blk} & 4 \\  & \text{wht} & 2 \\  & & 2 \end{array} $	$\begin{array}{c c} & & \\ & & \\ \hline & \\ \hline & & \\ \hline & \\ \hline & \\$
— blu M	— blu <u>3</u> M	— blu 3 M

#### **Recommended accessories**

Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866	
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
		ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

#### Connection cable (male-female connector)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Male connector,	2 m, 4-wire	IP 67	DSL-1204-G02M	6022567
100	M12, 4-pin, straight	M12, 4-pin, straight	5 m, 4-wire	IP 67	DSL-1204-G05M	6022569

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

#### F

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N10 for universal clamp bracket	BEF-KHS-N11N	2071081

#### Test and monitoring tools

Dimensions	Model name	Part no.
1.0 – 7.0 mm	Radius gauge	5328155
7.0 – 15.0 mm	Radius gauge	5328157
15.5 – 25.0 mm	Radius gauge	5328158

#### Reference materials

Dimensions	Material	Model name	Part no.
10 mm x 55 mm x 40 mm	ABS	Demonstration target	4077622

#### Cleaning agent

Figure	Description	Model name	Part no.
	Plastic cleaner and care product, anti-static	Plastic cleaner	5600006
	35 cm x 35 cm	Lens cloth	4003553

→ For additional accessories, please see page L-861

#### Two is better than one







#### **Additional information**

Detailed technical dataE-125
Ordering informationE-126
Dimensional drawings E-126
AdjustmentsE-126
Light spot diameter
Connection diagram E-127
Recommended accessories E-128





#### **Product description**

The MultiLine sensor: two sensors in one housing with an intelligent logical linking. The MultiLine sensor proves itself in

challenging situations as a rugged detector of flat and structured objects with an availability not achieved until now.

#### At a glance

- Two logical and intelligently linked sensors with background suppression in one miniature housing offer the highest ruggedness for object detection
- Consistent, reliable detection of structures and perforated objects such as e-cards
- Consistent, reliable detection of reflective and irregular objects such as blister packs and soup sachets on conveyor belts
- Maximum sensing range 120 mm
- Simple adjustment via teach-in button

#### Your benefits

- The MultiLine sensor facilitates faster production sequences since the distances between objects can be reduced
- The sensor position no longer needs to be modified for format changes since the sensor is able to detect objects independently of their position.
   This saves time and money
- The reliable signal of the sensor from the arriving to the departing edge places less demands on the control software since it no longer needs to be debounced or evaluated
- The MultiLine sensor offers high process reliability because all objects are detected independently of their structure, geometry and surface properties
- And placing the sensor into operation is as easy as pressing a button. A fast and reliable commissioning without complicated operating algorithms is thus given

#### → www.mysick.com/en/MultiLine\_Sensor

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Multi-background suppression
Dimensions (W x H x D)	16 mm x 39.5 mm x 12 mm
Housing design (light emission)	Rectangular
Sensing range max.	5 mm 120 mm
Sensing range	15 mm 120 mm
Type of light	Visible red light
Light source 1)	PinPoint LED
Light spot size (distance)	5 mm x 22 mm (40 mm)/3 mm x 25 mm (40 mm)/(depending on type)
Wave length	650 nm
Adjustment	Single teach-in button
Special feature	Detection of transparent objects

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Average service life of 100,000 h at  $\mbox{T}_{\mbox{\tiny A}}$  = +25 °C.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>
Power consumption 3)	≤ 30 mA
Output type	PNP/NPN (depending on type)
Output function	Complementary
Switching mode	Light switching /Light/dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	< 1.2 ms
Switching frequency 5)	400 Hz
Connection type	Male connector <sup>6)</sup> /Cable, 2 m <sup>6)</sup> (depending on type)
Circuit protection	A <sup>7)</sup> , C <sup>8)</sup> , D <sup>9)</sup>
Protection class	III
Weight	30 g
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 66, IP 67
Ambient operating temperature	-40 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

<sup>9)</sup> D = outputs overcurrent and short-circuit protected.

#### **Ordering information**


Other models available at www.mysick.com/en/MultiLine\_Sensor

- Sensor principle: photoelectric proximity sensor
- Detection principle: multi-background suppression
- Sensing range max.: 5 mm ... 120 mm
- Adjustment: single teach-in button


Sensing range max.	Light spot size (dis- tance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
	5 mm x 22 mm (40 mm)	PNP	Light switching	Connector M8, 3-pin	Cd-043	WTB4-3P2192	1058268
5 mm 120 m		PNP	Light/dark-switching	Connector M8, 4-pin	Cd-084	WTB4-3P2292	1062850
	3 mm x 25 mm (40 mm)	NPN	Light/dark-switching	Cable, 4-wire, 2 m	Cd-094	WTB4-3N1192	1059272

#### **Dimensional drawings**

Dimensions in mm (inch)




#### **Adjustments**




① Teach-in button


- ① Standard direction of the material being detected
- 2 Optical axis sender
- 3 Optical axis receiver
- ④ Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- Teach-in button
- 7 Threaded mounting hole M3
- ® Connection

#### Light spot diameter





#### **Connection diagram**



#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W4-A	2051628
4	1.4571	Mounting bracket for floor mounting	BEF-W4-B	2051630

#### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

• Description: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Model name	Part no.
//	Female connector,	Cable, open	2 m, 3-wire	TPU	DOL-0803-G02M	6010785
	M8, 3-pin, straight	conductor heads	5 m, 3-wire	TPU	DOL-0803-G05M	6022009
	Female connector,	Cable, open	2 m, 3-wire	TPU	DOL-0803-W02M	6008489
	M8, 3-pin, angled	conductor heads	5 m, 3-wire	TPU	DOL-0803-W05M	6022010
11	Female connector,	Cable, open	2 m, 4-wire	PVC	DOL-0804-G02M	6009870
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	PVC	DOL-0804-G05M	6009872
	Female connector,	Cable, open	2 m, 4-wire	PVC	DOL-0804-W02M	6009871
	M8, 4-pin, angled	conductor heads	5 m, 4-wire	PVC	DOL-0804-W05M	6009873

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

#### Ē

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	STE-0804-G	6037323

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel	Plate N05 for universal clamp bracket	BEF-KHS-N05	2051611
	(sheet), Diecast zinc (clamp)	Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

#### Terminal and alignment brackets

#### **Alignment brackets**

Figure	Material	Description	Model name	Part no.
	Plastic	Ball clamp bracket	BEF-GH-MINI01	2023160

→ For additional accessories, please see page L-861

# MultiPac - for extreme detection











#### **Additional information**

Detailed technical dataE-131
Ordering informationE-132
Dimensional drawingsE-132
AdjustmentsE-132
Characteristic curves E-132
Connection diagram E-133
Recommended accessories E-133

#### **Product description**

The MultiPac photoelectric sensor is designed for challenging applications which require detection of very shiny and irregular targets. Some examples are PET Bottles, food & beverage packets, glass or metal surfaces. These surfaces redirect the emitted light away from the sensor causing signal interruption. Using two independent receivers coupled with the newest chip technology, the MultiPac delivers reliable detection of these targets. Additionally, film wrapped pallets and other targets in the logistics branch can be detected using a higher angle of incidence. This removes the typical mounting restrictions associated with detecting these products. Thanks to its twin detection technology and flexible mounting, the MultiPac eliminates machine downtime due to loss of detection.

#### At a glance

- · Two redundant receiver arrays from
- The newest SICK chip technology
- Intense, visible red HighPower LED
- Sensing distance up to 500 mm
- · Fast and precise commissioning thanks to the highly visible light spot

#### Your benefits

- · Redundant receiver arrays provide reliable detection of shiny, gloss, dark, or irregular shaped objects without signal interruptions
- Products can be detected using a higher angle of incidence. This removes the typical mounting restrictions associated with detecting these products.
- In applications involving plastic wrapped bottles, the MultiPac replaces current solutions which require expensive mechanical height adjustment
- Allows overhead detection of product that is transported on a single conveyor belt but seperated into multiple lanes

#### → www.mysick.com/en/MultiPac

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Background suppression
Dimensions (W x H x D)	24.6 mm x 80.6 mm x 54.8 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	30 mm 500 mm
Sensing range	100 mm 500 mm
Type of light	Visible red light
Light source	PinPoint LED 2)
Light spot size (distance)	Ø 12 mm (500 mm)
Wave length	625 nm
Adjustment	Double teach-in button

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>
Power consumption <sup>3)</sup>	≤ 55 mA
Output type	PNP/NPN (depending on type)
Output function	Complementary
Switching mode	Light/dark-switching
Signal voltage PNP HIGH/LOW	Approx. $V_S - 2.5 V / 0 V$
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.5 V
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	≤ 5 ms
Switching frequency 5)	100 Hz
Connection type	Male connector
Circuit protection	A <sup>6)</sup> , B <sup>7)</sup> , C <sup>8)</sup>
Protection class 9)	II
Weight	150 g
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 66, IP 67
Ambient operating temperature	-30 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

 $<sup>^{5)}</sup>$  With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

 $<sup>^{7)}\,\</sup>mathrm{B}$  = inputs and output reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

<sup>9)</sup> Reference voltage: 50 V DC.

#### **Ordering information**

Other models available at www.mysick.com/en/MultiPac

#### WTB27-3 MultiPac

• Connection: connector M12, 4-pin


Sensing range max. 1)	Output type	Connection diagram	Туре	Part no.
20 mm = E00 mm	PNP	Cd-083	WTB27-3P2483	1056384
30 mm 500 mm	NPN	Cd-083	WTB27-3N2483	1056385


 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### **Dimensional drawings**

Dimensions in mm (inch)


- ① Optical axis, sender
- 2 Optical axis, receiver 1
- 3 Optical axis, receiver 2
- 4 Mounting hole ø 5.2 mm
- ⑤ Status indicator LED green: power on
- ⑤ Status indicator LED yellow: Status of received light beam
- 7 Sensing range adjustment: double teach button





#### **Adjustments**


#### **Double teach-in button**



① Double teach-in button

#### **Characteristic curves**

% of sensing distance



#### **Connection diagram**

#### Cd-083

#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W27	2009122

#### Terminal and alignment brackets

Figure	Material	Delivery	Model name	Part no.
4	Steel, galvanised (plate) Zinc, die-cast (clamp)	Incl. universal bar clamp and mounting material	BEF-KHS-A01	2022458

#### Plug connectors and cables

#### Connecting cable (female connector-open)

Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

#### Device protection (mechanical)

#### Protective housing/pipes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601

→ For additional accessories, please see page L-861











#### **Additional information**

Detailed technical data	.E-135
Ordering information	.E-136
Dimensional drawings	.E-137
Adjustments	.E-139
Connection diagram	.E-139
Recommended accessories	F-139

#### **Product description**

The Reflex Array is unique. The Multi-Task photoelectric sensor detects the leading edge of small, flat, transparent, or uneven objects within its light band, regardless of position. Perforated objects are reliably detected without multiple adjustments. This considerably reduces installation costs and speeds up commissioning. The Reflex Array therefore offers major cost benefits over conventional solutions, which use several individual photoelectric sensors or a small light grid. The Reflex Array is available in four variants with varying detection heights and minimum object sizes.

#### At a glance

- Detects objects > 12 mm within a 50 mm light array, regardless of posi-
- Sensing range for detection from 0 m to max. 4.5 m
- Minimum distance of 0.5 m between sensor and reflector for all variants
- PinPoint technology for intense red
- · Automatic adjustment of the switching threshold when there is contamination

#### Your benefits

- · Reduces the installation work required by up to 50% compared to light grids or multiple photoelectric sensors
- Detects objects > 12 mm within a 50 mm light array, regardless of position Three other variants are available for other objects.
- · PinPoint technology and optical alignment procedure enables simple and quick commissioning
- Continuous Threshold Adjustment (AutoAdapt) ensures less downtime

#### → www.mysick.com/en/Reflex\_Array

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



#### **Detailed technical data**

#### **Features**

Sensor principle	Reflex Array
Dimensions (W x H x D)	24.6 mm x 80 mm x 54.2 mm
Housing design (light emission)	Rectangular
Sensing range max.	0 m 2 m $^{1}$ /0 m 4.5 m $^{2}$ (depending on type)
Sensing range	0 m 2 m $^{1}$ /0 m 4.5 m $^{2}$ (depending on type)
Type of light	Visible red light
Light source 3)	PinPoint LED
Distance sensor to reflector	0.5 m 4.5 m
Adjustment	Single teach-in button
Continuous threshold adaption	V
Special feature	Light band

<sup>1)</sup> PL40A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>		
Power consumption 3)	≤ 35 mA		
Output type	PNP		
Output function	Complementary		
Switching mode	Light/dark-switching		
Signal voltage PNP HIGH/LOW	Approx. $V_S - 2.5 V / 0 V$		
Output current I <sub>max.</sub>	≤ 100 mA		
Response time 4)	≤ 2.5 ms		
Switching frequency 5)	200 Hz		
Connection type	Cable with connector, M12, 270 mm $^6$ /Cable, 2 m $^6$ /Male connector, M12 (depending on type)		
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , C <sup>9)</sup>		
Protection class <sup>10)</sup>	II		
Weight	130 g		
Housing material	ABS		
Optics material	PMMA		
Enclosure rating	IP 67		
Ambient operating temperature	-30 °C +60 °C		
Ambient storage temperature	-40 °C +75 °C		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\!_{A}}$  = +25  $^{\circ}$  C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

 $<sup>^{\</sup>mbox{\tiny 5)}}$  With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{9)}</sup>$  C = interference suppression.

 $<sup>^{\</sup>rm 10)}$  Reference voltage: 50 V DC.

#### **Ordering information**

Other models available at www.mysick.com/en/Reflex\_Array

Detection height: 24 mm

• Output type: PNP

• Minimum distance sensor - Reflector: 0.5 m

Sensing range max. <sup>1)</sup>	Minimum object size	Connection	Connection diagram	Туре	Part no.
0 m 1.5 m	≥ 5 mm	Cable with connector M12, 4-pin 270 mm PVC	Cd-083	WL27-3P3402S17	1051529

<sup>1)</sup> PL40A.

Detection height: 30 mm

• Output type: PNP

• Minimum distance sensor - Reflector: 0.5 m

Sensing range max.	Minimum object size	Connection	Connection diagram	Туре	Part no.
0 m 4.5 m <sup>1)</sup>	≥ 8 mm	Cable with connector M12, 4-pin 270 mm PVC	Cd-083	WL27-3P3402S20	1060755

<sup>1)</sup> PL80A.

Detection height: 45 mm

• Output type: PNP

• Minimum distance sensor - Reflector: 0.5 m

Sensing range max. <sup>1)</sup>	Minimum object size	Connection	Connection diagram	Туре	Part no.
0 m 3.5 m	≥ 10 mm	Cable with connector M12, 4-pin 270 mm PVC	Cd-083	WL27-3P3402S19	1056382

<sup>1)</sup> PL80A.

Detection height: 50 mm

• Output type: PNP

• Minimum distance sensor - Reflector: 0.5 m

Sensing range max.	Minimum object size	Connection	Connection diagram	Туре	Part no.
		Cable, 4-wire 2 m PVC	Cd-094	WL27-3P1102S16	1050825
0 m 4.5 m <sup>1)</sup>	≥ 12 mm	Connector M12, 4-pin	Cd-083	WL27-3P2402S18	1051577
0 m 2 m <sup>2)</sup>		Cable with connector M12, 4-pin 270 mm PVC	Cd-083	WL27-3P3402S13	1046538
	≥ 16 mm	Cable with connector M12, 4-pin 270 mm PVC	Cd-083	WL27-3P3402S15	1048230


<sup>1)</sup> PL80A.


<sup>&</sup>lt;sup>2)</sup> PL40A.


#### **Dimensional drawings**

Dimensions in mm (inch)

#### Detection height: 24 mm










- ① Opening of light band
- ② Mounting hole ø 5.2 mm
- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- (5) Sensitivity setting; single teach button

#### E

#### Detection height: 30 mm









- ① Opening of light band
- ② Mounting hole ø 5.2 mm
- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam


#### Detection height: 45 mm







- ① Opening of light band
- 2 Mounting hole ø 5.2 mm
- 3 Status indicator LED green: power on
- Status indicator LED, yellow:
   Status of received light beam
- ⑤ Sensitivity setting; single teach button

#### Detection height: 50 mm, cable










- ① Opening of light band
- ② Mounting hole ø 5.2 mm
- $\ensuremath{\mathfrak{B}}$  Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Sensitivity setting; single teach button

#### Detection height: 50 mm, connector








- ① Opening of light band
- ② Mounting hole ø 5.2 mm
- $\ensuremath{\mathfrak{G}}$  Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Sensitivity setting; single teach button

#### **Adjustments**



- ③ Status indicator LED green: power on
- ④ Status indicator LED, yellow: Status of received light beam
- ⑤ Sensitivity setting; single teach button

#### **Connection diagram**

## Cd-083 Cd-094 → brn; 1 / (L+) → brn; + (L-) → whti 2 Q → whti Q → blu! 3 / (M) → blu! - (M) → blk; 4 Q → blk; Q

#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
6	Steel zine conted	Mounting bracket with hinged arm for W11-2, W27, Dx50	BEF-WN-MULTI	2064469
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W27	2009122

#### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	10 m, 4-wire	IP 67	DOL-1204-G10M	6010543
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-L02M	6027945
1 2	M12, 4-pin, angled, with 3 LEDs	ductor heads	10 m, 4-wire	IP 67	DOL-1204-L10M	6027946
	Female connector,		2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled		10 m, 4-wire	IP 67	DOL-1204-W10M	6010541

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
M/s	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
ð	Zinc plated steel	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610
6	(sheet), Diecast zinc (clamp)	Plate N07 with threat and screws (P250, PL40A)	BEF-KHS-N07	2051613

#### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
	PMMA/ABS	Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
	FIVIIVIA/ ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865
		Rectangular, screw connection, 175 mm x 34 mm	PL180E01	1013289

<sup>→</sup> For additional accessories, please see page L-861

E

#### One thing is clear - no reflector needed







#### **Additional information**

Detailed technical dataE-143
Ordering informationE-144
Dimensional drawingsE-144
AdjustmentsE-144
Characteristic curvesE-145
Connection diagram E-145
Recommended accessories E-146

#### **Product description**

Thanks to new technologies from SICK, TranspaTect MultiTask photoelectric sensors are now able to detect transparent and semitransparent trays and bottles without the need for reflectors, a frequent source of errors. In these applications, the reference surface is provided by a stable matte background. Sensitivity is taught in simply by pressing the teachin button. Even high-gloss, reflective, or uneven surfaces can be detected reliably. Combined with AutoAdapt, SICK's function for continuous threshold adaptation, TranspaTect sensors provide a cost-effective and reliable detection solution in packaging processes in the food and beverage, and pharmaceuticals industries.

#### At a glance

- High-performance SICK technology
- · No reflectors required
- Existing machine parts are used as reference target
- · AutoAdapt for continuous threshold adaptation in contaminated conditions
- PinPoint LED with bright and precise light spot
- Easy-to-use teach-in button
- · Status LEDs visible from all sides
- · Rugged metal housing (PTFE coating available on request)

#### Your benefits

- Reliable detection of transparent and semitransparent objects without a reflector
- Reliable detection of objects regardless of color or surface qualities
- Freedom of machine design: no mounting system for the installation of a reflector required
- Quick commissioning: there is no need to mount a reflector or precisely adjust the sensor
- · High operational safety: if the background becomes contaminated, object detection will continue uninter-
- · Machine downtime is minimized: the integrated AutoAdapt function extends the time between cleanings
- · Heightened productivity: mechanical and chemical ruggedness due to the metal housing

#### → www.mysick.com/en/TranspaTect

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Foreground suppression
Dimensions (W x H x D)	15.6 mm x 48.5 mm x 42 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	150 mm 700 mm (adjustment range background)
Sensing range 1)	0 mm 400 mm (detection range transparent objects) <sup>2)</sup>
Type of light	Visible red light
Light source 3)	PinPoint LED
Light spot size (distance)	Ø 8 mm (300 mm)
Wave length	660 nm
Adjustment	Single teach-in button
Continuous threshold adaption	V

<sup>1)</sup> Referring to the background with 90 % remission (based on glass-bead blasted stainless steel, equivalent to standard white DIN 5033)

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>
Power consumption 3)	≤ 55 mA
Output type	PNP/NPN (depending on type)
Output function	Complementary
Switching mode	Light/dark-switching
Signal voltage PNP HIGH/LOW	> Uv - 2,5 V / ca. 0 V
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.5 V
Output current I <sub>max.</sub>	100 mA
Response time 4)	2 ms
Switching frequency 5)	250 Hz
Connection type	Male connector, M12
Circuit protection	A <sup>6)</sup> , C <sup>7)</sup> , D <sup>8)</sup>
Protection class	II .
Weight	120 g
Enclosure rating	IP 66/IP 67
Ambient operating temperature	-40 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

 $<sup>^{\</sup>rm 2)}\,0$  mm ... 550 mm detection range non-transparent objects.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25 °C.

<sup>&</sup>lt;sup>2)</sup> May not exceed or fall short of V<sub>S</sub> tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/TranspaTect

#### WTF12G-3, clear material detection

• Switching mode: light/dark-switching

• Adjustment: single teach-in button

• Light spot size (distance): Ø 8 mm (300 mm)


Sensing range max. 1)	Sensing range 1)	Output type	Connection	Connection diagram	Model name	Part no.
150 mm 700 mm <sup>2)</sup>	0 mm 400 mm <sup>3)</sup>	PNP	Connector M12, 4-pin	Cd-084	WTF12G-3P2432	1065719
	0 mm 550 mm <sup>4)</sup>	NPN	Connector M12, 4-pin	Cd-084	WTF12G-3N2432	1066279

<sup>1)</sup> Referring to the background with 90 % remission (based on glass-bead blasted stainless steel, equivalent to standard white DIN 5033)

## **Dimensional drawings**

Dimensions in mm (inch)


10 (0.39)



24 (0.94)

- ① Recommended installation for the detection of transparent trays
- 2 Recommended installation for the detection of transparent bottles
- $\begin{tabular}{ll} \end{tabular} \begin{tabular}{ll} \end{tabular} \beg$
- ④ Optical axis, sender
- ⑤ Status indicator LED green: power on
- **6** Status indicator LED, yellow: Status of received light beam
- 7 M4 threaded mounting hole, 4 mm deep
- ® Mounting hole, Ø 4.2 mm
- $\ensuremath{\mathfrak{9}} \ensuremath{ \mbox{Adjustment sensing range: single teach button}$
- 10 Connection

## **Adjustments**




- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- ® Adjustment sensing range: single teach button

<sup>&</sup>lt;sup>2)</sup> Adjustment range background

<sup>3)</sup> Detection range transparent objects

<sup>4)</sup> Detection range non-transparent objects

## **Characteristic curves**



#### Legend:

x: Sensing range max. in mm (adjustment range background)

= Distance sensor / background

y: Sensing range in mm (detection range object)

= Maximum distance sensor / front edge of the object

Minimum distance sensor / background: 150 mm\*

\*) Referring to the background with 90 % remission equivalent to standard white DIN 5033 (i.e. glass-bead blasted stainless steel). The use of a shiny background can increase the minimum distance to the background (i.e. brushed and pickled stainless steel, minimum distance sensor to background: 300 mm).

#### How to use this diagram:

Measure the distance from the sensor to the metal surface in the background.

This is the value for x (adjustment range background). If this is 500 mm for example,

the maximum distance between the sensor and the leading edge of a transparent object is 300 mm.

## **Connection diagram**

#### Cd-084

## **Recommended accessories**

## Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
10_	Stainless steel	Mounting bracket, large	BEF-WG-W12	2013942
3	Starriess steer	Mounting bracket, small	BEF-WK-W12	2012938

## Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867	

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	(sheet), Diecast zinc (clamp)	Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609

## Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W12-3	2045175

## Terminal and alignment brackets

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Clamping block for dovetail mounting	BEF-KH-W12	2013285

→ For additional accessories, please see page L-861

Ε









# Additional information

Additional information
Detailed technical dataE-149
Ordering informationE-151
Dimensional drawingsE-153
Bar diagramsE-156
Connection diagram E-157
Recommended accessories E-158

## **Product description**

Just as traffic lights handle the flow of cars in big cities, SICK ZoneControl solutions control product traffic on a conveyor without any other PLC or other external control. SICK ZoneControl is made up of three product families designed to control this traffic, known as Zero Pressure Accumulation (ZPA). Installation of ZoneControl solutions - via plug and play - is incredibly simple: daisy chain the ZoneControl products to one another, install the sensor, and connect the pneumatic line or connection to motor rollers.

No programming of a PLC, no laptop, and no expensive wiring is required. Each of these products creates one of two types of accumulation logic: Single Accumulation (with/without sleep) and Block (Slug) Accumulation, depending on what the application requires. To accomodate various mounting requirements, there are three different versions with different mounting configurations: between the rollers (R/IR), side frame mount (ZLM) and over the conveyor (WLR).

## At a glance

- Three mounting versions: betweeen the rollers (IR/R), side frame mount (ZLM) and over the conveyor (WLR)
- · Three types of logic: single accumulation, single accumulation with sleep, block (slug) accumulation
- Up to 50 ZoneControl solutions can be cascaded in one string
- · Fully animated simulation to ease selection and implementation
- Standard zone lengths of 1m (3ft) or 2m (6 ft)

#### Your benefits

- · Largest Zero Pressure Accumulation portfolio on the market gives users a wide variety of choices for their application
- SICK ZoneControl solutions control the flow of packages a on conveyor without a PLC or other external control.
- · Quick setup since no programming, no laptop, and no PLC interfacing are required
- · With 20 years of ZoneControl experience and personal support from SICK experts, all application and product issues are quickly addressed
- Quick expansion or modification of the conveyor due to the modular design

#### → www.mysick.com/en/ZoneControl

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	R DC	R AC/DC	IR DC
Sensor principle	Photoelectric proximity sensor		
Detection principle	Background suppression		
Actuator	-		Pneumatic, valve on board Pneumatic, valve supplied separately Electrical (depending on type)
Max. number of sensors	Approx. 30 $^{1)}$ /Approx. 50 $^{2)}$		
Logical principle of operation	-		Single accumulation/single accumulation with sleep (depending on type)
Type of Release	-		Single release/block (slug) release/single release (depending on type)
Dimensions (W x H x D)	20.6 mm x 99.2 mm x 48.9 mm	n	50 mm x 147.4 mm x 48.9 mm 59.9 mm x 151.9 mm x 48.9 mm 20.6 mm x 99.2 mm x 48.9 mm (depending on type)
Housing design (light emission)	Fitting roller spacings		
Sensing range	60 mm 900 mm		
Type of light	Infrared light		
Light source 3)	LED		
Light spot size (distance)	Ø 20 mm (500 mm)		
Angle of dispersion	7°		
Adjustment	Potentiometer, 9 turns		
Time type	Switch on delay/time delay off (depending on type)	Time delay off/switch on delay (depending on type)	-
Delay time	0 s 5 s		-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  When powerd from the end of the IR daisy chain.

## Mechanics/electronics

	R DC	R AC/DC	IR DC
Supply voltage 1)	10 V DC 30 V DC	≤ 250 V AC/DC	10 V DC 30 V DC
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>		
Power consumption 3)	< 20 mA	< 100 mA	< 20 mA
Output type	NPN, PNP	FET switch	Valve/PNP
Switching mode	Light switching Dark-switching Light/dark-switching 4) (depending on type)	Light switching Dark-switching (depending on type)	Dark-switching
Signal voltage PNP HIGH/LOW	Approx. $V_S - 0.5 V / 0 V$	-	Approx. $V_S - 0.5 V / 0 V$
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.0 V		-
Output current I <sub>max.</sub>	≤ 100 mA		
Response time	2 ms		
Switching frequency	± 250 Hz		

 $<sup>^{\</sup>rm 2)}$  When powerd from center of the IR daisy chain.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25 °C.

	R DC	R AC/DC	IR DC
Connection type	Male connector, M12 <sup>5)</sup> Cable, 2 m <sup>5)</sup> (depending on type)	Cable, 2 m <sup>5)</sup>	Male connector, M12 <sup>5)</sup>
Connection type for daisy chain	-		Cable with connector M12, 4-pin
Circuit protection	A $^{6)}$ , C $^{7)}$ , D $^{8)}$		
Protection class	III		
Weight	175 g	-	175 g
Housing material	ABS		
Enclosure rating	IP 67		IP 65
Shock/vibration	According to IEC 68		
Ambient operating temperature	-40 °C +60 °C (depending on type)	+10 °C +55 °C	-40 °C +60 °C (depending on type)
Ambient storage temperature	-40 °C +75 °C		

<sup>1)</sup> Limit values.

#### Pneumatic

	R DC	R AC/DC	IR DC
Coil ratings			
Valve, metric	-		24 V DC 1 W
Valve, imperial	-		24 V DC 1 W
Medium for valves	-		Compressed air or neutral gases filtered, non-lubricated or lubricated
Design solenoid valve	-		3/2-way valve
Connection type solenoid valve			
Valve, metric	-		Compressed air 2 x 8 mm diameter, output line 4 mm diameter
Valve, imperial	-		Control line 1/4 " diameter, compressed air 2x 3/8 " diameter: output line 2 x 1/4 " diameter, compressed air 2x 3/8 " diameter (depending on type)
Without magnetic valve	-		Cable with 9.4 mm DIN valve connector
Air flow rate			
Valve, metric	-		Approx. 20 NI/min
Valve, imperial	-		Approx. 1.4 SCFM
Ventilation capacity			
Valve, metric	-		Approx. 130 NI/min
Valve, imperial	-		Approx. 1.4 SCFM
Operating pressure range			
Valve, metric	-		2 bar 8 bar
Valve, imperial	-		0 psi 65 psi

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Without load and valve deenergized.

<sup>&</sup>lt;sup>4)</sup> Selectable via light/dark rotary switch.

 $<sup>^{5)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/ZoneControl

## R DC

Switching mode	Output type	Time type	Connection	Connection diagram	Туре	Part no.
Light quitching	PNP, NPN	-	Connector M12, 4-pin	Cd-256	RT-B1221	1063174
Light switching	Light Switching Five, INFIV		Cable, 4-wire, 2 m	Cd-251	RT-B1117	1063153
Dark-switching	PNP, NPN		Connector M12, 4-pin	Cd-261	RT-B2221	1063175
Dark-Switching	PINP, INPIN	_	Cable, 4-wire, 2 m	Cd-252	RT-B2117	1063178
			Cable, 4-wire, 2 m	Cd-249	RT-P3117	1063179
	PNP	_	Connector M12, 4-pin	Cd-255	RT-P3221	1063129
		Switch on delay	Connector M12, 4-pin	Cd-255	RTN-P3221	1063172
Light (dark awitahing			Cable, 4-wire, 2 m	Cd-249	RTN-P3117	1063182
Light/dark-switching		Time delay off	Cable, 4-wire, 2 m	Cd-249	RTF-P3117	1063181
			Connector M12, 4-pin	Cd-255	RTF-P3221	1063171
	NPN	-	Connector M12, 4-pin	Cd-255	RT-N3221	1063162
			Cable, 4-wire, 2 m	Cd-249	RT-N3117	1063180
	PNP		Connector M12, 4-pin	Cd-258	RTQ-P4221	1063173
1 : (-1	PINP	_	Cable, 4-wire, 2 m	Cd-250	RTQ-P4117	1063183
Light/dark-switching 1)	PNP, NPN		Connector M12, 4-pin	Cd-256	RTQ-B1221	1063177
	FINE, INFIN	_	Cable, 4-wire, 2 m	Cd-251	RTQ-B1117	1063184

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Selectable via light/dark rotary switch.

# R AC/DC

Switching mode	Output type	Time type	Connection	Connection diagram	Туре	Part no.
	FET switch	-	Cable, 4-wire, 2 m	Cd-247	RT-M1117	1063194
Light switching		Time delay off	Cable, 4-wire, 2 m	Cd-247	RTF-M1117	1063195
		Switch on delay	Cable, 4-wire, 2 m	Cd-247	RTN-M1117	1063196
		-	Cable, 4-wire, 2 m	Cd-248	RT-M2117	1063197
Dark-switching		Time delay off	Cable, 4-wire, 2 m	Cd-248	RTF-M2117	1063198
		Switch on delay	Cable, 4-wire, 2 m	Cd-248	RTN-M2117	1063199

## IR DC Air to Drive (NC)

Actuator: pneumatic, valve on board

Switching mode: dark-switching

• Output type: valve

• Connection: Connector M12, 4-pin

Type of output	Connection type solenoid valve	Connection type for daisy chain	Connection diagram	Туре	Part no.
Valve, metric	Compressed air 2 x 8 mm diameter, output line 4 mm diameter	Cable with connector M12, 4-pin 2 m	Cd-265	IRT-P212E40	1063108
Valve,	Control line 1/4 " diameter, compressed	Cable with connector M12, 4-pin 1.2 m	Cd-265	IRT-P211A10	1063117
imperial	air 2x 3/8 " diameter	Cable with connector M12, 4-pin 2 m	Cd-265	IRT-P212A10	1063123

# IR DC Air to Brake (NO)

• Actuator: pneumatic, valve on board

• Switching mode: dark-switching

• Output type: valve

• Connection: Connector M12, 4-pin

Type of output	Connection type solenoid valve	Connection type for daisy chain	Connection diagram	Туре	Part no.
Valve,	Compressed air 2 x 8 mm diameter,	Cable with connector M12, 4-pin 1.2 m	Cd-265	IRT-P211E41	1063107
metric	metric output line 4 mm diameter	Cable with connector M12, 4-pin 2 m	Cd-265	IRT-P212E41	1063109
Valve,	Output line 2 x 1/4 " diameter, compressed air 2x 3/8 " diameter	Cable with connector M12, 4-pin 1.2 m	Cd-265	IRT-P211A11	1063118
/	Control line 1/4 " diameter, compressed air 2x 3/8 " diameter	Cable with connector M12, 4-pin 2 m	Cd-265	IRT-P212A11	1063124

#### IR DC HIGH to Drive

• Switching mode: dark-switching Output type: valve / PNP


• Connection: connector M12, 4-pin


Type of output	Actuator	Connection type solenoid valve	Connection type for daisy chain	Connection diagram	Туре	Part no.
Without	Pneumatic, valve	Cable with 9.4 mm	Cable with connector M12, 4-pin 1.2 m	Cd-265	IRT-P211C63	1063127
magnetic valve	supplied separately	DIN valve connector	Cable with connector M12, 4-pin 2 m	Cd-265	IRT-P212C63	1063116
For Motor Driven Roll-	Electrical		Cable with connector M12, 4-pin 1.2 m	Cd-266	IRT-P231C83	1063101
ers (MDR)	Electrical	-	Cable with connector M12, 4-pin 2 m	Cd-266	IRT-P232C83	1063100


# **Dimensional drawings**


Dimensions in mm (inch)

#### R / IR without valve













- ① LED
- 2 Potentiometer
- 3 Mounting hole
- 4 Center of optical axis, sender
- ⑤ Center of optical axis, receiver
- 6 Connector M12, 4-pin

#### R cable










- ① LED
- 2 Potentiometer
- 3 Mounting hole
- 4 Cable
- ⑤ Center of optical axis, sender
- 6 Center of optical axis, receiver

#### IR, valve metric/imperial



ш

<u>|</u>100

20.6

D

**11** 

8

① Potentiometer

4.0

(.16)

② LED

4.0 (.16)

⋖

- 3 Mounting hole
- 4 Center of optical axis, sender

В

40.0 (1.57)


48.0 (1.89)


- ⑤ Center of optical axis, receiver
- 6 Connector M12, 4-pin
- 7 Daisy chain, cable with female connector


الان الان

23.0 (.91)

#### IR, for Motor Driven Rollers (MDR)








- ① LED
- ② Potentiometer
- 3 Mounting hole
- 4 Center of optical axis, sender
- ⑤ Daisy chain, cable with female connector
- **6** Connection for motor
- 7 Center of optical axis, receiver
- 8 Connector M12, 4-pin

# **Bar diagrams**




- Sensing range max.
- ① Sensing range on black, 5 % remission
- $\ensuremath{\text{@}}$  Sensing range on white, 90 % remission

## **Connection diagram**

# Cd-247

#### Cd-248



#### Cd-249



#### Cd-250

#### Cd-251



#### Cd-252




#### Cd-255

#### Cd-256


#### Cd-258



#### Cd-265



#### Cd-266



# **Recommended accessories**

# Adapters/distributors

## **T-junctions**

Figure	Connecting cable	Connector material	Locking nut material	Description	Model name	Part no.
	0.3 m	TPU	CuZn, nickel-	Signal interrogation and logic interrupt	DSL-1104-T0M3	6011683
	0.5 111	IPU	plated brass	Signal interrogation	DSL-1204-T0M4	6011682

## Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
0 0	Steel, zinc coated	Mounting bracket	BEF-WK-WTR	2051786

→ For additional accessories, please see page L-861

E







## **Product description**

Just as traffic lights handle the flow of cars in big cities, SICK ZoneControl solutions control product traffic on a conveyor without any other PLC or other external control. SICK ZoneControl is made up of three product families designed to control this traffic, known as Zero Pressure Accumulation (ZPA). Installation of ZoneControl solutions - via plug and play - is incredibly simple: daisy chain the ZoneControl products to one another, install the sensor, and connect the pneumatic line or connection to motor rollers.

No programming of a PLC, no laptop, and no expensive wiring is required. Each of these products creates one of two types of accumulation logic: Single Accumulation (with/without sleep) and Block (Slug) Accumulation, depending on what the application requires. To accomodate various mounting requirements, there are three different versions with different mounting configurations: between the rollers (R/IR), side frame mount (ZLM) and over the conveyor (WLR).

## At a glance

- Connects to any 9.4 mm DIN valve
- Single or slug accumulation
- Ideal for pneumatic actuators or motor-driven rollers
- · Daisy chain connection cables included for zone lengths of 1m (3 ft) and 2 m (6 ft)
- · AC power options

#### Your benefits

- Attach your choice of actuator to complete the ZoneControl Solution
- Linear polarized retro-reflective sensing technology eliminates false detection of shiny or plastic-wrapped objects
- The Daisy Chain means that last minute changes or adding a zone is a matter of minutes
- · A sealed IP67 housing to withstand harsh environments and washdown
- Single or Block (slug) Accumulation Logic to maximize product throughput
- · Output cable for connection to electric motor control or pneumatic valve



#### **Additional information**

Detailed technical data. . . . . . . . E-161 Ordering information.....E-162 Dimensional drawings .....E-162 Connection diagram . . . . . . . . . E-163

#### → www.mysick.com/en/WLR

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	Single accumulation	Block (slug) accumulation
Sensor principle	Photoelectric retro-reflective sensor	
Logical principle of operation	Single accumulation	Block (slug) accumulation
Type of Release	Single release, block (slug) release	Block (slug) release
Dimensions (W x H x D)	45 mm x 73.7 mm x 48.6 mm	
Housing design (light emission)	Rectangular	
Sensing range 1)	0 m 9 m	
Type of light	Visible red light	
Light source 2)	LED	
Light spot size (distance)	Ø 205 mm (9 m)	

<sup>&</sup>lt;sup>1)</sup> PL80A.

## Mechanics/electronics

<b></b>	
Ripple 1)	< 5 V <sub>pp</sub>
Power consumption <sup>2)</sup>	≤ 40 mA
Switching mode	Light switching
Response time	1 ms
Switching frequency	500 Hz
Connection type	Cable with connector, M12, 300 mm
Connection type for daisy chain	Cable with receptacle, M12, 4-pin
Circuit protection	A <sup>3)</sup> , C <sup>4)</sup> , D <sup>5)</sup>
Protection class	II
Housing material	ABS
Enclosure rating	IP 67
Shock/vibration	According to IEC 68
Ambient operating temperature	-25 °C +55 °C
Ambient storage temperature	-40 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Of  $\mbox{V}_{\mbox{\scriptsize S}}.$ 

## Pneumatic

	Single accumulation	Block (slug) accumulation
Connection type solenoid valve	Spade, 1 m: spade, 2 m cable, 1 m, with 9.4 mm DIN valve connector cable, 2m, with 9.4 mm DIN valve connector (depending on type)	Cable, 1 m, with 9.4 mm DIN valve connector: cable, 2m, with 9.4 mm DIN valve connector (depending on type)

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>mbox{\tiny 2)}}$  Without load and valve deenergized.

 $<sup>^{\</sup>rm 3)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>4)</sup> C = interference suppression.

 $<sup>^{5)}</sup>$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/WLR

## Single accumulation

• Switching mode: light switching

• Connection to sensor: cable with connector M12, 4-pin 300 mm

Connection type for daisy chain	Connection type solenoid valve	Connection diagram	Model name	Part no.
Cable with receptacle, M12, 4-pin, 1 m	Spade, 1 m	Cd-246	WLR2100-D1311	7027185
Cable with receptacie, M12, 4-pm, 1 m	Cable, 1 m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D2311	7027808
Cable with receptacle, M12, 4-pin, 2 m	Spade, 2 m	Cd-246	WLR2100-D1312	7027753
Cable with receptacle, M12, 4-pin, 2 m	Cable, 2m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D2312	7027811

#### Block (slug) accumulation


• Switching mode: light switching

• Connection to sensor: cable with connector M12, 4-pin 300 mm

Connection type for daisy chain	Connection type solenoid valve	Connection diagram	Model name	Part no.
Cable with receptacle, M12, 4-pin, 1 m	Cable, 1 m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D1321	7027754
Cable with receptacle, M12, 4-pin, 1 m	Cable, 1 m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D2321	7027809
Cable with receptacle, M12, 4-pin, 2 m	Cable, 2m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D1322	7027755
Cable with receptable, M12, 4-pin, 2 m	Cable, 2m, with 9.4 mm DIN valve connector	Cd-246	WLR2100-D2322	7027810

# **Dimensional drawings**


Dimensions in mm (inch)



- ① Sender
- 2 Receiver
- 3 Fastening threads
- $\ensuremath{\textcircled{4}}$  Threaded mounting hole
- ⑤ Daisy chain, cable with female connector
- 6 Cable
- 7 Daisy chain connector, male
- Status indicator: LED

# **Connection diagram**

#### Cd-246











## **Product description**

Just as traffic lights handle the flow of cars in big cities, SICK ZoneControl solutions control product traffic on a conveyor without any other PLC or other external control. SICK ZoneControl is made up of three product families designed to control this traffic, known as Zero Pressure Accumulation (ZPA). Installation of ZoneControl solutions - via plug and play - is incredibly simple: daisy chain the ZoneControl products to one another, install the sensor, and connect the pneumatic line or connection to motor rollers.

No programming of a PLC, no laptop, and no expensive wiring is required. Each of these products creates one of two types of accumulation logic: Single Accumulation (with/without sleep) and Block (Slug) Accumulation, depending on what the application requires. To accomodate various mounting requirements, there are three different versions with different mounting configurations: between the rollers (R/IR), side frame mount (ZLM) and over the conveyor (WLR).

# At a glance

- · Connects to any discrete DC voltage sensor
- Single or slug accumulation
- · Ideal for pneumatic actuators
- · Daisy chain connection cable included for zone lengths of 1m (3ft) or 2m (6 ft)
- · Bolt-on or clip-on installation into the conveyor's side frame

#### Your benefits

- · Sensor cable integrated for you to attach nearly any sensor
- SICK's most compact ZoneControl solution, you won't even know it's there
- Single or Block (slug) Accumulation Logic to maximize product throughput
- . The Daisy Chain means that last minute changes or adding a zone is a matter of minutes



#### **Additional information**

Detailed technical data.....E-165 Ordering information.....E-166 Dimensional drawings .....E-168 Connection diagram . . . . . . . . E-168

#### www.mysick.com/en/ZLM

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

#### **Features**

	ZLM-B	ZLM-C	
Actuator	Pneumatic, valve on board		
Max. number of sensors	Approx. 30 <sup>1</sup> /Approx. 50 <sup>2</sup>		
Logical principle of operation	Single accumulation / block (slug) accumulation (depending on type)		
Type of Release	Single release / block (slug) release / block (slug) release (depending on type)		
Dimensions (W x H x D)	31 mm x 110 mm x 83 mm 31 mm x 93 mm x 74 mm 31 mm x 105 mm x 74 mm (depending on type)	30 mm x 110 mm x 70 mm	
Housing design (light emission)	Bolt-on mounting	Clip-on mounting	
Time type	Time delay off	-	
Delay time	0 s 2 s	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  When powerd from the end of the IR daisy chain.

#### Mechanics/electronics

	ZLM-B	ZLM-C
Supply voltage	≥ 21.6 V DC <sup>1)</sup>	≥ 21.6 V DC <sup>2)</sup>
Ripple	< 5 V <sub>pp</sub>	
Power consumption 3)	< 60 mA	
Output type	PNP	
Signal voltage PNP HIGH/LOW	Approx. $V_S - 0.5 V / 0 V$	
Output current I <sub>max.</sub>	100 mA	
Response time	2.5 ms	
Switching frequency	200 Hz	
Connection type	Cable with receptacle 4)	
Connection type for daisy chain	Cable with connector M12, 4-pin / Cable with push-on connector M12, 4-pin (depending on type)	Cable with push-on connector M12, 4-pin / Cable with connector M12, 4-pin (depending on type)
Circuit protection	A <sup>5)</sup> , C <sup>6)</sup> , D <sup>7)</sup>	
Protection class	III <sup>8)</sup>	
Housing material	ABS	
Enclosure rating	IP 40	
Shock/vibration	According to IEC 68	
Ambient operating temperature	-10 °C +55 °C	
Ambient storage temperature	-40 °C +75 °C (depending on type)	-40 °C +75 °C
Mounting system type	Side-Frame-Mount	

<sup>1)</sup> Limit values.

 $<sup>^{\</sup>rm 2)}\,\mbox{When powerd from center of the IR daisy chain.}$ 

 $<sup>^{\</sup>mbox{\tiny 2)}}$  Limit values, the device may connect only to protected extra low voltage.

<sup>&</sup>lt;sup>3)</sup> Without load and valve deenergized.

 $<sup>^{\</sup>text{\tiny 4)}}$  Do not bend below 0 °C.

 $<sup>^{5)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>6)</sup> C = interference suppression.

 $<sup>^{7)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>rm 8)}$  Reference voltage: 50 V DC.

#### Pneumatic

	ZLM-B	ZLM-C
Coil ratings		
Valve, imperial	24 V DC 1 W	
Valve, metric	24 V DC 2 W 24 V DC 1 W	-
	(depending on type)	
Medium for valves	Compressed air or neutral gases filtered, non-lu	bricated or lubricated
Design solenoid valve 1)	3/2-way valve	
Connection type solenoid valve		
Valve, imperial	Compressed air 3/8 " diameter, control line 1/4	1 " diameter
Valve, metric	Compressed air 2 x 8 mm diameter, output line 4 mm diameter	-
Air flow rate		
Valve, imperial	40 NI/min	
Valve, metric <sup>2)</sup>	Approx. 20 NI/min	-
Ventilation capacity		
Valve, imperial	40 NI/min	
Valve, metric	Approx. 100 NI/min / approx. 130 NI/min (depending on type)	-
Operating pressure range		
Valve, imperial	0 bar 4.5 bar	
Valve, metric	0.5 bar 8 bar <sup>3)</sup> (depending on type)	-
Response time solenoid valve	Partially open 10 ms Open 23 ms Close 21 ms	

<sup>1)</sup> Other valve types available on request.

# **Ordering information**

Other models available at www.mysick.com/en/ZLM

## Bolt-on mounting, Air to Drive (NC)

• Connection diagram: Cd-263

Type of output	Logical principle of operation	Ventilation capacity	Operating pres- sure range	Connection to sensor	Connection type for daisy chain	Model name	Part no.
				Cable with receptacle,	Cable with connector M12, 4-pin 1.2 m	ZLM1-B1111A10	7027768
	Single accumulation 40 NI/mi Valve, imperial	40 NI/min	0 bar 4.5 bar	M12, 4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-B1211A10	7027784
				Cable with receptacle, M12 push-on, 4-pin 0.5 m	Cable with push-on connector M12, 4-pin 1.2 m	ZLM1-B1451A10	1052126
	Block (slug)	40 NI/min	0 bar 4.5 bar	Cable with receptacle,	Cable with connector M12, 4-pin 1.2 m	ZLM1-B2111A10	7027770
	accumulation		0 bar 4.5 bar	M12, 4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-B2211A10	7027786
Valve, metric	Single accumulation	Approx. 130 NI/min	2 bar 8 bar 1)	Cable with receptacle, M12, 4-pin 1.1 m PVC	Cable with connector M12, 4-pin 1.2 m	ZLM1-B1612E42	7028842

 $<sup>^{\</sup>mbox{\tiny 1)}}$  In combination with cylinders with small air volume we recommend tests.

<sup>&</sup>lt;sup>3)</sup> In combination with cylinders with small air volume we recommend tests.

## Bolt-on mounting, Air to Brake (NO)

• Connection diagram: Cd-263

Type of output	Logical principle of operation	Ventilation capacity	Operating pres- sure range	Connection to sensor	Connection type for daisy chain	Model name	Part no.
	Single	40 NI/min	0 bar 4.5 bar	Cable with receptacle,	Cable with connector M12, 4-pin 1.2 m	ZLM1-B1111A11	7027769
Valve,	accumulation '	40 NI/IIIIII	0 bar 4.5 bar	M12, 4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-B1211A11	7027785
imperial	· .	40 NI/min	0 bar 4.5 bar	Cable with receptacle,	Cable with connector M12, 4-pin 2 m	ZLM1-B2211A11	7027787
	accumulation	40 NI/IIIIII	0 bar 4.5 bar	M12, 4-pin 0.5 m	Cable with connector M12, 4-pin 1.2 m	ZLM1-B2111A11	7027771
Valve,	Single	Approx. 100 NI/min	0.5 bar 8 bar <sup>1)</sup>	Cable with receptacle, M12, 4-pin 1.1 m PVC	Cable with connector M12, 4-pin	ZLM1-B5612E41	7028428
metric	accumulation	Approx. 130 NI/min	2 bar 8 bar 1)	Cable with receptacle, M12, 4-pin 1.1 m PVC	Cable with connector M12, 4-pin	ZLM1-B1612E43	7028843

 $<sup>^{\</sup>mbox{\tiny 1)}}$  In combination with cylinders with small air volume we recommend tests.

## Clip-on mounting, Air to Drive (NC)

Type of output: valve, imperialVentilation capacity: 40 NI/min

• Operating pressure range: 0 bar ... 4.5 bar

• Connection diagram: Cd-263

Logical principle of operation	Connection to sensor	Connection type for daisy chain	Model name	Part no.
	Cable with receptacle, M12 push-on, 4-pin 0.5 m	Cable with push-on connector M12, 4-pin 1.2 m	ZLM1-C1451A10	7029987
Single accumulation	Cable with receptacle, M12,	Cable with connector M12, 4-pin 1.2 m	ZLM1-C1111A10	7027764
	4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-C1211A10	7027780
Block (slug) accumulation	Cable with receptacle, M12, 4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-C2211A10	7027782

## Clip-on mounting, Air to Brake (NO)

Type of output: valve, imperialVentilation capacity: 40 NI/min

• Operating pressure range: 0 bar ... 4.5 bar


• Connection diagram: Cd-263

Logical principle of operation	Connection to sensor	Connection type for daisy chain	Model name	Part no.
	Cable with receptacle, M12,	Cable with connector M12, 4-pin 2 m	ZLM1-C1211A11	7027781
Single accumulation	4-pin 0.5 m	Cable with connector M12, 4-pin 1.2 m	ZLM1-C1111A11	7027765
S	Cable with receptacle, M12 push-on, 4-pin 0.5 m	Cable with push-on connector M12, 4-pin 1.2 m	ZLM1-C1451A11	7029988
Block (slug)	Cable with receptacle, M12,	Cable with connector M12, 4-pin 1.2 m	ZLM1-C2111A11	7027767
accumulation	4-pin 0.5 m	Cable with connector M12, 4-pin 2 m	ZLM1-C2211A11	7027783

# **Dimensional drawings**


Dimensions in mm (inch)

#### ZLM-B



- ① Daisy chain connector, male
- ② Exhaust
- 3 Output port (x1)
- 4 Media connector (x2)
- (5) Manual override switch
- 7 Daisy chain connector, male or female
- 8 Sensor connection cable, female
- Mounting stud
- 10 Anti-rotation stud
- 1 Mounting clip

#### ZLM-C



- ① Daisy chain connector, male
- ② Exhaust

15 (0.59)


(3.15)

8

- 3 Output port (x1)
- 4 Media connector (x2)
- (5) Manual override switch
- Mounting slots (x2)
- 7 Daisy chain connector, male or female

## **Connection diagram**

#### Cd-263



E



# Best-in-class – minimum size for the toughest requirements

Providing maximum performance in minimum space requirements is no problem for SICK's miniature sensor technology. Tiny machines, intricate and complicated systems, the toughest ambient conditions, and targets of any kind – SICK can provide the solution for a combination of requirements. The latest PinPoint LEDs, SIRIC® and IO-Link technologies are packed into rugged, ultra compact housings and supplemented with practical accessories. These sensors are ideal for nearly all applications and installation conditions.

#### Your benefits

- The widest range in automation technology we stock miniature photoelectric sensors for all requirements
- We meet the needs of all industries from the world's smallest background suppression sensor to the most rugged stainless steel sensor for extreme applications in the food and beverage industry
- Virtually our entire miniature line comes with PinPoint technology, enabling the fast and safe alignment of photoelectric sensors. Even jet-black objects like car tires, textiles and carpets are reliably detected
- Flexible operation every time, whether preset at the factory, via a potentiometer, teach-in button or external teach via cable and IO-Link





# Miniature photoelectric sensors

	Product selection
	G2S
<b>I</b>	G6
( )	W2 Flat F-208  One of the smallest photoelectric sensor families in the world
	<b>W2S-2</b>
	<b>W4-3</b>
P	<b>W4S-3</b>

<b>W4SL-3</b>
W4S-3 Inox             F-298         W4S-3 Inox          W4S-3 Inox       Hygiene
W4SL-3V/H
W8
W100-2
W100 Laser

# Overview of miniature photoelectric sensors

	Housing properties						Sensor properties												
	Mate	erial		Encle	osure i	rating													
	Stainless steel	Plastic	PTFE coating	IP 66	IP 67	IP 68	<b>★</b>	Photoelectric proximity sensor	Energetic	Background suppression	Foreground suppression	Photoelectric retro- reflective sensor	Autocollimation	Standard optics	Through-beam photoelectric sensor	IO-Link	AutoAdapt 🔭	Switching frequency ≥ 2 kHz	
G2S														_					
G2S NEW																			
<b>G6</b>																			
W2																			
W2 Flat																			
W2S-2																			
W2SG-2																			
W4																			
W4-3																			
W4-3 PTFE																			
W4-3 Glass																			
W4S-3		•		•											•				
W4S-3 Glass		•																	
W4SL-3																			
W4SLG-3				•															
W4 Inox																			
W4S-3 Inox																			
W4S-3 Inox Glass							•												
W4S-3 Inox Hygiene				•	•	•	•								•				
W4S-3 Inox Hyg. Glass				•		•													
W4SL-3V NEW	•			•	•	•	•	•		•					•				
W4SLG-3V NEW				•	•	•													
W4SL-3H NEW						•													
W4SLG-3H NEW							_												

Optica	l proper	ties						Specia	l applica	ations						Page
	f light/L		der	Light spot geom- etry	Techno	ology										3
LED infrared light	LED red light	Red laser light	PinPoint LED red light 🛪	Line-shaped light spot 🖈	Focused optics	SIRIC®	V-optics	Hygienic and washdown zones	Detecting transparent objects	Detecting perforated objects	Detecting small objects	Detecting uneven, shiny objects	Detecting objects wrapped in film	Detecting objects with position tolerances	Detecting high-speed objects	
																F-186
																L-T00
									•							F-196
	•															F-208
				•	•		•			•	-		•	•		F-216
			•			•			•							F-232
•	-		-	•			•	_		•	•	•	•	•		F-238
	-								_							F-250
									•							F-254
									_							F-260 F-272
	•		•						•							F-272
											÷					F-278
		_							_							1-250
									•							F-298
									•							F-312
																F-320
									•							F-334
		-						•			•					F-342
									•		•					F-350
											•					F-358
																F-364

	Housing properties							Sensor properties											
	Hous	ilig þi	opera					Sensor properties											
	Mate	Material			Enclosure rating														
			*				*	>		on	Ľ						*	*	
								Photoelectric proximity sensor		Background suppression	Foreground suppression	٥			sor			ر کر	
	<u> </u>							pro)		ddns	uppr	Photoelectric retro- reflective sensor	on	ics	Through-beam photoelectric sensor			Switching frequency ≥ 2 kHz	
	Stainless steel		PTFE coating					ectric	O	nnd (	s pui	ectric e ser	Autocollimation	Standard optics	bear		pt	g fre	
	nles	itic	E CO	ဖွ	7	œ	Α	toele	Energetic	kgro	grou	toele	ocolli	ndarc	ough toele	ž	AutoAdapt	tchin KHz	
	Stai	Plastic	PTF	IP 66	IP 67	IP 68	IP 69K	Pho	Ene	Bac	Fore	Phor	Autc	Star	Thro	IO-Link	Aut	Swit ≥ 2	
W8																			
W8		•								•		•	•						
W8G		•			•							•	•						
W8 Inox								•											
W8 Laser																			
W100																			
W100-2																			
W100 Laser																			

_	
	_
	_

Optical properties							Special applications						Page			
Type of light/Light sender				Light spot geom- etry	Tookhoology											
		*	*	*	*		*	_			"	>				
LED infrared light	LED red light	Red laser light	PinPoint LED red light	Line-shaped light spot	Focused optics	SIRIC®	V-optics	Hygienic and washdown zones	Detecting transparent objects	Detecting perforated objects	Detecting small objects	Detecting uneven, shiny objects	Detecting objects wrapped in film	Detecting objects with position tolerances	Detecting high-speed objects	
	•															F-372
	•															F-380
	•							•								F-386
		•													•	F-398
	•															F-404
																F-412

# Photoelectric proximity sensors

	Maximum sensing range	Dimensions (W x H x D)	Page
W2 Flat	1 mm 115 mm	12 mm x 20 mm x 3.5 mm	F-208
G2S	1 mm 120 mm	7.7 mm x 27.5 mm x 13.5 mm	F-186
W4-3 PTFE	4 mm 120 mm	22 mm x 42 mm x 21.8 mm	F-250
W2S-2	1 mm 150 mm	7.7 mm x 21.8 mm x 13.5 mm	F-216
W4-3	3 mm 150 mm	16 mm x 39.5 mm x 12 mm	F-238
W4S-3	4 mm 180 mm	12.2 mm x 41.8 mm x 17.3 mm	F-260
G6	5 mm 300 mm	12 mm x 31.5 mm x 21 mm	F-196
W8	5 mm 300 mm	11 mm x 31 mm x 20 mm	F-372
W8 Laser	5 mm 300 mm	11 mm x 31 mm x 20 mm	F-398
W4SL-3	25 mm 300 mm	12.2 mm x 41.8 mm x 17.3 mm	F-278
W4SL-3H	25 mm 300 mm	15.3 mm x 63.2 mm x 22.2 mm	F-358
W4SL-3V	25 mm 300 mm	15.3 mm x 55.4 mm x 22.2 mm	F-342
W100 Laser	0 mm 450 mm	11 mm x 31 mm x 20 mm	F-412
W4S-3 Inox	4 mm 500 mm	15.3 mm x 55.4 mm x 22.2 mm	F-298
W4S-3 Inox Hygiene	4 mm 500 mm	15.3 mm x 63.2 mm x 22.15 mm	F-320
W8 Inox	0 mm 950 mm	11 mm x 21 mm x 33.3 mm	F-386
W100-2	0 mm 1,000 mm	11 mm x 31 mm x 20 mm	F-404

# F


# Photoelectric retro-reflective sensors

	■ Maximum sensing range	Dimensions (W x H x D)	Page
W2S-2	0 m 1.2 m	7.7 mm x 21.8 mm x 13.5 mm	F-216
W2SG-2	0 m 1.2 m	7.7 mm x 21.8 mm x 13.5 mm	F-232
G2S	0.02 m 3 m	7.7 mm x 21.8 mm x 13.5 mm	F-186
W8G	0 m 3 m	11 mm x 31 mm x 20 mm	F-380
W8	0 m 4 m	11 mm x 31 mm x 20 mm	F-372
W4-3	0.01 m 4.5 m	16 mm x 39.5 mm x 12 mm	F-238
W4-3 Glass	0.01 m 4.5 m	16 mm x 39.5 mm x 12 mm	F-254
W4SLG-3	0 m 4.5 m	12.2 mm x 41.8 mm x 17.3 mm	F-290
W4SLG-3H	0 m 4.5 m	15.3 mm x 63.2 mm x 22.2 mm	F-364
W4SLG-3V	0 m 4.5 m	15.3 mm x 55.4 mm x 22.2 mm	F-350
W4S-3	0 m 5 m	12.2 mm x 41.8 mm x 17.3 mm	F-260
W4S-3 Glass	0.01 m 5 m	12.2 mm x 41.8 mm x 17.3 mm	F-272
W4S-3 Inox	0 m 5 m	15.3 mm x 55.4 mm x 22.2 mm	F-298
W4S-3 Inox Glass	0 m 5 m	15.3 mm x 55.4 mm x 22.2 mm	F-312
W4S-3 Inox Hygiene	0 m 5 m	15.3 mm x 63.2 mm x 22.15 mm	F-320
W4S-3 Inox Hygiene Glass	0 m 5 m	15.3 mm x 63.2 mm x 22.15 mm	F-334
G6	0 m 6 m	12 mm x 31.5 mm x 21 mm	F-196
W8 Inox	0.01 m 6.5 m	11 mm x 21 mm x 33.3 mm	F-386
W100-2	0.01 m 7.5 m	11 mm x 31 mm x 20 mm	F-404
W4SL-3	0 m 12 m	12.2 mm x 41.8 mm x 17.3 mm	F-278
W100 Laser	0.08 m 12 m	11 mm x 31 mm x 20 mm	F-412

# Through-beam photoelectric sensors

	■ Maximum sensing range	Dimensions (W x H x D)	Page
W2 Flat	0 m 0.5 m	12 mm x 20 mm x 3.5 mm	F-208
G2S	0 m 2 m	7.7 mm x 21.8 mm x 13.5 mm	F-186
W2S-2	0 m 2.5 m	7.7 mm x 21.8 mm x 13.5 mm	F-216
W4-3 PTFE	0 m 3 m	22 mm x 42 mm x 21.8 mm	F-250
W4-3	0 m 4 m	16 mm x 39.5 mm x 12 mm	F-238
W4S-3	0 m 5 m	12.2 mm x 41.8 mm x 17.3 mm	F-260
W4S-3 Inox	0 m 5 m	15.3 mm x 55.4 mm x 22.2 mm	F-298
W4S-3 Inox Hygiene	0 m 5 m	15.3 mm x 63.2 mm x 22.15 mm	F-320
G6	0 m 15 m	12 mm x 31.5 mm x 21 mm	F-196
W100-2	0 m 30 m	11 mm x 31 mm x 20 mm	F-404
W100 Laser	0 m 35 m	11 mm x 31 mm x 20 mm	F-412
W8 Inox	0 m 45 m	11 mm x 21 mm x 33.3 mm	F-386
W4SL-3	0 m 60 m	12.2 mm x 41.8 mm x 17.3 mm	F-278
W4SL-3V	0 m 60 m	15.3 mm x 55.4 mm x 22.2 mm	F-342

## **Product family overview**





W25-



**W2SG-2** 



W4-3



W4-3 PTF

Incredibly small, yet powerful Powerful clear material detection in an ultra-compact housing

Best-in-class sensing performance in a miniature housing

Teflon-coated photoelectric sensors withstand the harshest environments

7.7 mm x 21.8 mm x 13.5 mm	7.7 mm x 21.8 mm x 13.5 mm	16 mm x 39.5 mm x 12 mm	22 mm x 42 mm x 21.8 mm	
1 mm 150 mm	-	3 mm 150 mm	4 mm 120 mm	
0 m 1.2 m	0 m 1.2 m	0.01 m 4.5 m	-	
0 m 2.5 m	-	0 m 4 m	0 m 3 m	
PinPoint LED	PinPoint LED	PinPoint LED	PinPoint LED	
Visible red light	Visible red light	Visible red light / Infrared light	Visible red light	
IP 67	IP 67	IP 66, IP 67	IP 68, IP 69K	
Plastic	Plastic	Plastic	PTFE	

- All variants with M8, 3and 4-pin pigtail
- Proximity sensor with precise background suppression and fixed focusing
- IP 67 enclosure rating
- Two sensing ranges with either a 15 mm or a 30 mm range are available
- All variants with M8, 3and 4-pin pigtail
- Proximity sensor with precise background suppression and fixed focusing
- IP 67 enclosure rating
- Two sensing ranges with either a 15 mm or a 30 mm range are available
- Best-in-class background suppression, reliable detection of critical objects and a high immunity to ambient light
- Quick and easy setup using a precise 5-turn potentiometer, control wire or teach function
- Best background suppression in its class
- PinPoint LED for brightest light spot in its class

- Sensor and cable have a rugged Teflon coating for use in the most aggressive environments
- Suitable for use in the food and beverage industry
- Sensing range adjustment via teach wire
- Background suppression and through-beam types available

→ F-216

→ F-232

→ F-238

→ F-250

### **Product family overview**





W4-3 Glass

Reliable detection of transparent objects



Photoelectric sensor family with best-in-class performance



W4S-3 Glass

Slim photoelectric sensors reliably detect transparent objects

#### Technical data overview

Dimensions (W x H x D)	16 mm x 39.5 mm x 12 mm	12.2 mm x 41.8 mm x 17.3 mm	12.2 mm x 41.8 mm x 17.3 mm	
Housing design	<del>-</del>	-	_	
Sensing range max.				
Photoelectric proximity sensor	-	4 mm 180 mm	-	
Photoelectric retro-reflective sensor	0.01 m 4.5 m	0 m 5 m	0.01 m 5 m	
Through-beam photoelectric sensor	-	0 m 5 m	-	
Light source	PinPoint LED	PinPoint LED	PinPoint LED	
Type of light	Visible red light	Visible red light	Visible red light	
Enclosure rating	IP 66, IP 67	IP 66, IP 67	IP 66, IP 67	
Housing material	Plastic	Plastic	Plastic	
At a glance				

- At a giance
- Fast and reliable setup via teach-in pushbutton
- · Continuous threshold adaptation (AutoAdapt) technology to detect objects in changing conditions such as temperature, contamination and reflector wear
- · Versions without polarizing filters to better detect depolarizing objects such as PET bottles, CD sleeves and shrink-wrapped, glossy objects
- · Best background suppression sensor in its class
- Universal use of PinPoint LED technology in all models
- · BGS proximity sensor with laser-like light spot for precise detection tasks
- Reliable setting via 5-turn potentiometer, teach-in pushbutton, teach-in via cable or IO-Link
- · Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

- · Continuous threshold adaption (AutoAdapt) of the switching threshold compensates for environmental changes
- Single-lens autocollimation optics
- · Simple setting either via teach-in pushbutton, cable or IO-Link
- · PinPoint LED technology with a small, highly visible, well-defined light spot enables high reserve levels when using small reflectors
- · Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

**Detailed information** → F-254 → F-260 → F-272



W4SL-

Laser precision for very small or transparent objects



W4SI G-3

Detect all objects with one device – Change mode via teach button



W4S-3 Inox

Highest reliability, maximum resistance and endless possibilities



W4S-3 Inox Glass

Reliable detection of transparent objects

12.2 mm x 41.8 mm x 17.3 mm	12.2 mm x 41.8 mm x 17.3 mm	15.3 mm x 55.4 mm x 22.2 mm	15.3 mm x 55.4 mm x 22.2 mm
-	-	Washdown	Washdown
25 mm 300 mm	-	4 mm 500 mm	-
0 m 12 m	0 m 4.5 m	0 m 5 m	0 m 5 m
0 m 60 m	-	0 m 5 m	-
Laser	Laser	PinPoint LED	PinPoint LED
Visible red light	Visible red light	Visible red light	Visible red light
IP 66, IP 67	IP 66, IP 67	IP 66, IP 67, IP 68, IP 69K	IP 66, IP 67, IP 68, IP 69K
Plastic	Plastic	Stainless steel	Stainless steel

- Precise laser light spot, laser class 1
- Teach-in pushbutton can be switched between detection of transparent and non-transparent objects
- Sensing ranges between 25 mm and 60 m
- Latest SIRIC® and laser technologies with second emitter LED to provide outstanding background suppression and ambient light immunity
- Choice of adjustment via teach-in button, potentiometer, cable, or IO-Link

- Precise laser light spot, laser class 1
- Teach-in button can be switched between detection of transparent and smallest non-transparent objects
- Continuous threshold adaptation (AutoAdapt) provides automatic adjustment to changes in light conditions
- Sensing ranges up to 4.5 m
- Autocollimation optics prevent blind spots
- Choice of adjustment via teach-in button, potentiometer, cable, or IO-Link

- WashDown rated for fluid tightness (IP 66, IP 67, IP 68 and IP 69K) and Ecolab certified
- Tough stainless steel housing (316L/1.4404)
- Resistant to a variety of common cleaning and disinfection agents
- Highly visible laser-like light spot due to PinPoint LFD
- Teach-in via stainless steel pushbutton with a metal membrane

- IP 66, IP 67, IP 68 and IP 69K enclosure rating and Ecolab certified
- Tough stainless steel housing (316L/1.4404)
- Resistant to a variety of common cleaning and disinfection agents
- Modern electrical connection available M12 connector with pin casting
- PinPoint LED technology provides a highly visible laser-like light spot
- Teach-in via stainless steel pushbutton with a metal membrane
- Continuous threshold adaptation (AutoAdapt) technology reliably detects objects in changing conditions


→ F-278

→ F-290

→ F-298

→ F-312

### **Product family overview**





- Change mode via teach button

Detect all transparent objects with one device



Laser technology and stainless steel hygienically combined



Detect all transparent objects with one device - Change mode via teach button

15.3 mm x 55.4 mm x 22.2 mm	15.3 mm x 63.2 mm x 22.2 mm	15.3 mm x 63.2 mm x 22.2 mm
Washdown	Hygiene	Hygiene
-	25 mm 300 mm	-
0 m 4.5 m	-	0 m 4.5 m
-	-	-
Laser	Laser	Laser
Visible red light	Visible red light	Visible red light
IP 66, IP 67, IP 68, IP 69K	IP 66, IP 67, IP 68, IP 69K	IP 66, IP 67, IP 68, IP 69K
Stainless steel	Stainless steel	Stainless steel

- Precise laser light spot, laser class 1, no blind spots
- · Stainless steel housing with washdown design
- Latest SIRIC<sup>®</sup> and laser technologies for very good background suppression and ambient light immunity
- ECOLAB certified, tested to IP66, IP67, IP68 and IP69K enclosure rating
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- IO-Link (optional)

- Precise laser light spot, laser class 1
- Stainless steel housing with wash down design
- Latest SIRIC<sup>®</sup> and laser technologies for outstanding background suppression and ambient light immunity
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- · ECOLAB certified, tested to IP 66, IP 67, IP 68 and IP 69K enclosure rating
- IO-Link (optional)

- Precise laser light spot, laser class 1
- Stainless steel housing with hygienic
- Latest SIRIC<sup>®</sup> and laser technologies for outstanding background suppression and ambient light immunity
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- · ECOLAB certified, tested to IP 66, IP 67, IP 68 and IP 69K enclosure rating
- IO-Link (optional)

→ F-350

→ F-358

→ F-364

**Product family overview** 





High-performance object detection at close range



Photoelectric sensor detects transparent objects at close range



Compact, high-performance INOX sensors for harsh wash down environments

Techn	บเกลโ	data	OVER	/IEW/

Dimensions (W x H x D)	11 mm x 31 mm x 20 mm	11 mm x 31 mm x 20 mm	11 mm x 21 mm x 33.3 mm	
Sensing range max.				
Photoelectric proximity sensor	5 mm 300 mm	-	0 mm 950 mm	
Photoelectric retro-reflective sensor	0 m 4 m	0 m 3 m	0.01 m 6.5 m	
Through-beam photoelectric sensor	-	-	0 m 45 m	
Light source	LED	LED	LED	
Type of light	Visible red light	Visible red light	Visible red light	
Enclosure rating	IP 67	IP 67	IP 69K	
Housing material	Plastic	Plastic	Stainless steel	
At a glance				

- · Miniature housing with M3 threaded mounting holes
- Switching frequency up to 2 kHz
- · Stainless steel mounting bracket (1.4301/304) BEF-W100-A included with delivery
- Autocollimation
- Standard miniature housing with M3 threaded mounting holes
- · Light/dark switching selectable via rotary switch
- · Adjustable sensing range
- · All necessary accessories (BEF-W100-A and P250) are included with delivery
- Rugged IP 69K stainless steel housing 1.4404/316L
- · Front screen made of highperformance PPSU plastic that is resistant to heat and chemicals
- · Potentiometer made of mechanically stable high-performance PEEK (polyether ketone) plastic
- Constructed with FDAapproved materials
- Well-defined, highly visible light spot
- · M3 threaded mounting holes and stainless steel mounting bracket (1.4301/304) included with delivery

**Detailed information** → F-386 → F-372 → F-380



WRIase

Laser photoelectric proximity sensor with background suppression for close-range applications



W100-2

Miniature photoelectric sensors for standard applications



W100 Laser

Miniature photoelectric laser sensor provides precise detection of objects in standard applications

applications		plications
11 mm x 31 mm x 20 mm	11 m x 31 m x 20 m	11 mm x 31 mm x 20 mm
5 mm 300 mm	0 mm 1,000 mm	0 mm 450 mm
-	0.01 m 7.5 m	0.08 m 12 m
-	0 m 30 m	0 m 35 m
Laser	LED	Laser
Visible red light	Visible red light	Visible red light
IP 67	IP 67	IP 65
Plastic	Plastic	Plastic
· ·		
<ul> <li>Laser class 1</li> <li>Background suppression</li> <li>Standard miniature housing with M3 threaded mounting holes</li> <li>Switching frequency up to 2 kHz</li> <li>Light/dark switching via rotary switch</li> <li>Mounting bracket BEF-W100-A is included with delivery</li> </ul>	<ul> <li>Reliable detection behavior, rugged housing and immunity to ambient light</li> <li>WT100-2 photoelectric proximity sensor (energetic or with background blanking)</li> <li>WL100-2 photoelectric retro-reflective sensor; variant available for detecting transparent objects</li> <li>WS/WE100-2 through-beam photoelectric sensor</li> <li>Various connection types available (standard: 2 m cable; M8 male connector, 3-pin; M8 male connector, 4-pin; male cable connector available on request)</li> <li>Light/dark switching and sensitivity adjustment possible</li> <li>Wide range of accessories</li> </ul>	<ul> <li>Standard miniature housing with M3 threaded mounting holes</li> <li>Long sensing range</li> <li>Light/dark switching and sensitivity adjustment via rotary switch possible</li> <li>Various versions are available, including through-beam, retro-reflective and energetic</li> <li>Wide variety of accessories available</li> <li>Laser emitter LED, class 1</li> </ul>
→ F-398	→ F-404	→ F-412

### No space is too small









### **Additional information**

/ taditional information
Detailed technical dataF-187
Ordering informationF-188
Dimensional drawingsF-189
Characteristic curvesF-191
Bar diagramsF-192
Light spot diameter F-193
Connection diagram F-193
Recommended accessories F-194



### **Product description**

Machines and systems are becoming more compact while the space available for sensors is shrinking. Sub-miniature sensors in the G2S product family feature a rugged, compact housing that

can be integrated into various applications with limited space. These sensors feature a long sensing range with reliable object detection.

#### At a glance

- · Complete product family of photoelectric sensors in a tried-and-tested sensor design
- · Adjustable BGS photoelectric proximity sensor with an sensing range up to 120 mm
- · Optical performance data that exceeds market standards for sensing range and housing design
- · Reliable detection of jet-black, poorly reflective and highly reflective objects
- · PinPoint LED ensures high sensing ranges and reliable object detection

#### Your benefits

- · Reliable object detection in confined environments helps cut costs and save space
- · Sub-miniature housing enables seamless integration and creates opportunities for new machine designs
- Tried-and-tested, rugged housing design can be easily integrated into compact machines and systems
- Complete, ultra-small product family with operating functions for every application
- The 45-degree tilted cable entry offers maximum installation flexibility with additional soft rubber bearings to absorb vibrations and tensile loads

#### → www.mysick.com/en/G2S

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



#### **Features**

	GTB2S ,fix	GTB2S, adjustable	GL2S	GSE2S	
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor	
Detection principle	Background suppression	on	Standard optics	-	
Dimensions (W x H x D)	7.7 mm x 21.8 mm x 13.5 mm	7.7 mm x 27.5 mm x 13.5 mm	7.7 mm x 21.8 mm x 13.5 mm		
Housing design (light emission)	Rectangular				
Sensing range max.	1 mm 36 mm <sup>1)</sup> (depending on type)	2 mm 120 mm <sup>1)</sup>	0.02 m 3 m <sup>2)</sup>	0 m 2 m	
Sensing range	4 mm 30 mm <sup>3)</sup> (depending on type)	25 mm 90 mm <sup>3)</sup>	0.03 m 2.5 m <sup>2)</sup>	0 m 1.5 m	
Background suppression typ. from	20 mm / 38 mm (depending on type)	-			
Type of light	Visible red light				
Light source 4)	PinPoint LED				
Wave length	640 nm				
Adjustment	-	Potentiometer, 3 turns	-		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	GTB2S, fix	GTB2S, adjustable	GL2S	GSE2S		
Supply voltage 1)	10 V DC 30 V DC					
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>					
Power consumption 3)	≤ 20 mA					
Output type	PNP / NPN (depending	g on type)				
Switching mode	Light switching / Dark-s	switching (depending on	type)			
Output current I <sub>max.</sub>	< 50 mA	< 50 mA				
Response time 4)	< 0.6 ms					
Switching frequency 5)	800 Hz					
Connection type	Cable, 2 m 6) / Cable wi	th connector, M8, 200 n	nm <sup>6)</sup> (depending on type	)		
Circuit protection	A $^{7)}$ , C $^{8)}$ , D $^{9)}$					
Polarisation filter	-		<b>✓</b>	-		
Housing material	ABS					
Optics material	PMMA					
Enclosure rating	IP 67					
Ambient operating temperature	-20 °C +50 °C					
Ambient storage temperature	-40 °C +75 °C					

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

F

<sup>2)</sup> PL40A

<sup>&</sup>lt;sup>3)</sup> Object with 6 % remission.

 $<sup>^{\</sup>rm 4)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

### **Ordering information**

Other models available at www.mysick.com/en/G2S

#### GTB2S

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			Light assistable of	Cable, 3-wire 2 m	Cd-043	GTB2S-P1311	1064345
		PNP	Light switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-P5311	1062872
		PNP	Dayle awitahing	Cable, 3-wire 2 m	Cd-043	GTB2S-F1311	1064346
1 mm 18 mm	Ø 2 mm (8 mm)		Dark-switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-F5311	1064347
20			Light quitabing	Cable, 3-wire 2 m	Cd-043	GTB2S-N1311	1062840
		NPN	Light switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-N5311	1064349
			Dark-switching	Cable, 3-wire 2 m	Cd-043	GTB2S-E1311	1064348
			Light switching	Cable, 3-wire 2 m	Cd-043	GTB2S-P1331	1064351
		PNP	Light Switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-P5331	1062930
1 mm 36 mm	Ø 3 mm (15 mm)		Dark-switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-F5331	1064353
33	(10)		Light switching	Cable, 3-wire 2 m	Cd-043	GTB2S-N1331	1062929
		INPIN	Dark-switching	Cable, 3-wire 2 m	Cd-043	GTB2S-E1331	1064354
			Light quitabing	Cable, 3-wire 2 m	Cd-043	GTB2S-P1451	1060205
		PNP	Light switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-P5451	1060204
			Dark-switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-F5451	1064341
2 mm 120 mm	Ø 3.5 mm (50 mm)		Limbs avvisabing	Cable, 3-wire 2 m	Cd-043	GTB2S-N1451	1060203
120 11111	(00 11111)		Light switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-N5451	1064343
		NPN	Dork quitobing	Cable, 3-wire 2 m	Cd-043	GTB2S-E1451	1064342
			Dark-switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GTB2S-E5451	1064344

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### GL2S

- Sensor principle: Photoelectric retro-reflective sensor
- Detection principle: Standard optics

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0.02 m 3 m Ø 11 mm (250 mm)			Light switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GL2S-P5311	1064359
	PNP	Dark-switching	Cable, 3-wire 2 m	Cd-043	GL2S-F1311	1064358	
		Dark-Switching	Cable with connector M8, 3-pin 200 mm	Cd-045	GL2S-F5311	1063008	
	~	NPN	Light switching	Cable, 3-wire 2 m	Cd-043	GL2S-N1311	1064360
	(200)					GL2S-N1312	1064423
			Dark-switching	Cable, 3-wire 2 m	Cd-043	GL2S-E1311	1063009
						GL2S-E1312	1064424

<sup>1)</sup> PL40A.

#### GSE2S


• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0 m 2 m Ø 23 mm (500 mm)	PNP	Light switching	Cable with connector M8, 3-pin 200 mm	Cd-051	GSE2S-P5311	1064364	
		Dark-switching	Cable, 3-wire 2 m	Cd-049	GSE2S-F1311	1064363	
			Cable with connector M8, 3-pin 200 mm	Cd-051	GSE2S-F5311	1063072	
	(000)	NIDNI	Light switching	Cable, 3-wire 2 m	Cd-049	GSE2S-N1311	1064365
		NPN	Dark-switching	Cable, 3-wire 2 m	Cd-049	GSE2S-E1311	1063070

### **Dimensional drawings**

Dimensions in mm (inch)

#### GTB2S, 15 mm, 30 mm




- ① Optical axis receiver
- ② Optical axis sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Status indicator LED green: power on
- Status indicator LED, yellow: Status of received light beam
- 6 Connection

F

- ${f @}$  Optical axis receiver
- 2 Optical axis sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: status of received light beam
- 6 Potentiometer
- 7 Connection


F

#### GL2S



- ① Optical axis receiver
- ② Optical axis sender
- 4 Status indicator LED green: power on
- Status indicator LED, yellow: status of received light beam
- Connection

#### GSE2S




- ① Optical axis receiver
- 2 Optical axis sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Status indicator LED green: power on
- Status indicator LED, yellow: status of received light beam
- **6** Connection

### **Characteristic curves**

#### Black-white shift

### GTB2S, 120 mm

% of sensing range




- 1 Sensing range on white, 90 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission

F

## r


#### Operating reserve

#### GL2S




- ① PL40A
- ② PL20A
- ③ PL10F
- 4 IREF6000 (REF-IRF-56)

#### GSE2S




### **Bar diagrams**

#### **GTB2S**, 15 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

## GTB2S, 30 mm



- ① Sensing range on white, 90 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

### GTB2S, 120 mm



- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### GL2S



Sensing range Sensing range typ. max.


- ① PL40A
- ② PL20A
- ③ PL10F
- ④ IREF6000 (REF-IRF-56)

#### GSE2S




### **Light spot diameter**







#### GTB2S, 30 mm




GTB2S, 120 mm



#### GL2S




#### GSE2S




### **Connection diagram**


#### Cd-043

#### Cd-045






#### Cd-049



- ① Sender
- 2 Receiver

#### Cd-051



- ① Sender
- 2 Receiver

## F

### **Recommended accessories**

### Plug connectors and cables

#### Connecting cable (female connector-open), PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Cable, open con- ductor heads	2 m, 3-wire	IP 65, IP 68, IP 69K	DOL-0803-G02MC	6025888
1	Female connector, M8, 3-pin, angled	Cable, open con- ductor heads	2 m, 3-wire	IP 65, IP 68, IP 69K	DOL-0803-W02MC	6025891
	Female connector, M8, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 65, IP 68, IP 69K	DOL-0804-G02MC	6025894
	Female connector, M8, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 65, IP 68, IP 69K	DOL-0804-W02MC	6025897

#### Connecting cable (female connector-open), PVC

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Cable, open con- ductor heads	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	Female connector, M8, 3-pin, angled	Cable, open con- ductor heads	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	Female connector, M8, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	Female connector, M8, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871

#### Female connector (ready to assemble) M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
<b>%</b>	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
OW.	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078

#### Male connector (ready to assemble) M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	F	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	·	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
)	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210

### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861







#### **Additional information**

Detailed technical dataF-197
Ordering informationF-198
Dimensional drawings F-202
AdjustmentsF-202
Characteristic curvesF-203
Bar diagramsF-204
Light spot diameterF-204
Connection diagram F-205
Recommended accessories F-205

### **Product description**

The G6 Global photoelectric sensor is enclosed in a miniature housing and provides an optimal price-performance ratio. This sensor provides outstanding sensing performance using a standard 1-inch hole distance. With PinPoint LEDs, metal inserts for mounting, large indicator LEDs, large user-friendly adjustment potentiometers, an IP 67 enclosure rating and the very latest SICK ASIC technology, this is truly a high performance sensor in a small package.

#### At a glance

- PinPoint LED for a bright, precise light spot
- · Durable metal threaded inserts
- · SICK ASIC technology the result of decades of experience in photoelectric sensors
- Large, user-friendly potentiometer
- Large, bright indicator LEDs
- IP 67 enclosure rating

#### Your benefits

- · Easy alignment and precise object detection due to a highly visible PinPoint
- Quick and easy mounting and high durability due to threaded metal
- · SICK ASIC technology provides high performance and excellent reliability
- · Easy to adjust due to large, userfriendly potentiometers
- · Easy to monitor due to large, bright indicator LEDs
- · Easy installation with SICK accessories

#### → www.mysick.com/en/G6

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



### **Detailed technical data**

### **Features**

	GTE6	GTB6	GL6	GL6G	GSE6
Sensor principle	Photoelectric proximity sensor		Photoelectric retro	Photoelectric retro-reflective sensor	
Detection principle	Energetic	Background sup- pression	Standard optics		-
Dimensions (W x H x D)	12 mm x 31.5 mm	x 21 mm			
Housing design (light emission)	Rectangular				
Sensing range max.	≤ 300 mm ¹)	5 mm 250 mm <sup>1)</sup>	≤ 6 m <sup>2)</sup>		0 m 15 m
Sensing range	≤ 250 mm	35 mm 140 mm	≤ 5 m <sup>2)</sup>		0 m 10 m
Type of light	Visible red light				
Light source 3)	PinPoint LED				
Wave length	650 nm				
Adjustment	Mechanical spindle, 5 turns		Potentiometer, 270 °		
Special feature	-			Detection of transparent objects	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	GTE6	GTB6	GL6	GL6G	GSE6
Supply voltage 1)	10 V DC 30 V D	C			
Ripple <sup>2)</sup>	± 10 %				
Power consumption <sup>3)</sup>	≤ 30 mA				
Output type	PNP, open collecto	or / NPN, open colle	ctor		
Switching mode	Light/dark-switchi	ng (selectable via lig	ght/dark selector)		
Signal voltage PNP HIGH/LOW	V <sub>S</sub> - (<=3 V) / app	rox. 0 V			
Signal voltage NPN HIGH/LOW	Approx. $V_S / \le 3$	V			
Output current I <sub>max.</sub> 4)	≤ 100 mA				
Response time <sup>5)</sup>	< 1,250 ms	< 625 µs			< 500 µs
Switching frequency 6)	500 Hz	1,000 Hz			
Attenuation along light beam	-			> 20 %	-
Connection type	Cable, 2 m <sup>7)</sup> Male connector, M8 Cable with connector, M8, 300 mm <sup>7)</sup> Cable with connector, M12, 300 mm <sup>7)</sup> (depending on type)				
Circuit protection	A $^{8)}$ , B $^{9)}$ , D $^{10)}$				
Protection class	III				
Weight					
Connector	20 g				40 g
Cable/Cable with connector	60 g				170 g
Polarisation filter	-		<b>✓</b>		-
Housing material	ABS/PC				

F

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $T_A$  = +25 °C.

	GTE6	GTB6	GL6	GL6G	GSE6
Optics material	PMMA				
Enclosure rating	IP 67				
Items supplied		Stainless steel mounting bracket (1.4301/304) BEF-W100-A		unting bracket -W100-A,	Stainless steel mounting bracket (1.4301/304) BEF-W100-A
Ambient operating temperature 11)	-25 °C +55 °C				
Ambient storage temperature	-40 °C +70 °C				

 $<sup>^{\</sup>scriptsize 1)}$  Limit values, operation in short-circuit protected network max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/G6

#### GTE6

- Sensor principle: photoelectric proximity sensor
- Detection principle: energetic
- Light spot size (distance): Ø 7 mm (90 mm)
- Switching mode: light/dark-switching

Sensing range max. 1)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
					-	GTE6-P1211	1050712
			Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A	GTE6-P1212	1051783
PNP		Mechani-	Connector M8, 4-pin Cd-066 S	-	GTE6-P4211	1050710	
	PNP	P cal spindle, 5 turns		Cd-066	Stainless steel mounting bracket BEF-W100-A	GTE6-P4212	1051781
			Cable with connector M12, 4-pin, 300 mm, PVC	Cd-066	-	GTE6-P7211	1053589
≤ 300 mm					Stainless steel mounting bracket BEF-W100-A	GTE6-P7212	1053628
					-	GTE6-N1211	1050713
NPN	NDN	Mechani-	Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A	GTE6-N1212	1051784
	INFIN	cal spindle, 5 turns			-	GTE6-N4211	1050711
		3 turno	Connector M8, 4-pin	Cd-066	Stainless steel mounting bracket BEF-W100-A	GTE6-N4212	1051782

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>scriptscriptstyle (4)}$  At Vs > 24 V, I<sub>A</sub> max = 50 mA.

 $<sup>^{\</sup>rm 5)}$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>6)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>7)</sup> Do not bend below 0 °C.

 $<sup>^{8)}</sup>$  A =  $V_{\rm S}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>9)</sup> B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> D = outputs overcurrent and short-circuit protected.

 $<sup>^{11)}</sup>$  Temperature stability after adjustment +/-10  $^{\circ}\text{C}.$ 

### GTB6

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Light spot size (distance): Ø 6 mm (100 mm)
- Switching mode: light/dark-switching

Sensing range max. 1)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.			
					-	GTB6-P1211	1052440			
			Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A	GTB6-P1212	1052444			
			Connector M8, 4-pin	Cd-066	-	GTB6-P4211	1052438			
	PNP				Stainless steel mounting bracket BEF-W100-A	GTB6-P4212	1052442			
		Mechani- cal spindle, 5 turns	Cable with connector M8, 3-pin, 300 mm	Cd-043	-	GTB6-P5211	1059333			
			Cable with connector M8, 4-pin, 300 mm	Cd-066	-	GTB6-P6211	1059320			
5 mm 250 mm			Cable with connector M12, 4-pin, 300 mm	Cd-066	-	GTB6-P7211	1057705			
					-	GTB6-N1211	1052441			
							Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A	GTB6-N1212
					-	GTB6-N4211	1052439			
N	NPN		Connector M8, 4-pin	Cd-066	Stainless steel mounting bracket BEF-W100-A	GTB6-N4212	1052443			
			Cable with connector M8.		-	GTB6-N6211	1058774			
			4-pin, 300 mm	Cd-066	Stainless steel mounting bracket BEF-W100-A	GTB6-N6212	1058769			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



G6

#### GL6

- Sensor principle: photoelectric retro-reflective sensor
- Light spot size (distance): Ø 8 mm (350 mm)
- Switching mode: light/dark-switching

Sensing range max. 1)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.					
					-	GL6-P1111	1050708					
			Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P1112	1051779					
					-	GL6-P4111	1050706					
			Connector M8, 4-pin	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P4112	1051777					
		_	Cable with connector M8,		-	GL6-P6111	1060234					
	PNP		4-pin, 300 mm, PVC	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P6112	1060235					
	FINE		Connector M12, 4-pin,		-	GL6-P7111	1052966					
							300 mm, PVC	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P7112	1053590	
≤ 6 m		Potentiometer, 270 °			Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P1212	1060815			
≥ 0 111				Connector M8, 4-pin	Cd-066	-	GL6-P4211	1059241				
				270 °	270 °	270 °	270 °	Cable with connector M8,		-	GL6-P6211	1058851
				4-pin, 300 mm, PVC	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-P6212	1062753				
					-	GL6-N1111	1050709					
		-	Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-N1112	1051780					
	NPN		Connector M8, 4-pin	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-N4112	1051778					
	INFIN		Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-N1212	1060814					
		Potentiometer, 270 °	Connector M8, 4-pin	Cd-066	-	GL6-N4211	1059631					
				210	Cable with connector M8, 4-pin, 300 mm, PVC	Cd-066	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6-N6212	1062588			

<sup>&</sup>lt;sup>1)</sup> PL80A.

### GL6G, clear material detection

- Sensor principle: photoelectric retro-reflective sensor
- Light spot size (distance): Ø 8 mm (350 mm)
- Switching mode: light/dark-switching

Sensing range max. 1)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
					-	GL6G-P1211	1059924
PNP	DNID	Potentiometer,	Cable, 3-wire, 2 m, PVC	Cd-043	Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6G-P1212	1060812
	FINE	270°	Connector M8, 4-pin	Cd-066	-	GL6G-P4211	1059632
≤ 6 m					Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6G-P4212	1060810
> 0 III		Potentiometer, 270 °	Cable, 3-wire, 2 m, PVC	Cd-043	-	GL6G-N1211	1059925
	NDN				Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6G-N1212	1060811
	NPN			Cd-066	-	GL6G-N4211	1059633
			Connector M8, 4-pin		Stainless steel mounting bracket BEF-W100-A, Reflector P250	GL6G-N4212	1060809

<sup>1)</sup> PL80A.

### GSE6


- Sensor principle: through-beam photoelectric sensor
- Light spot size (distance): Ø 375 mm (12 m)
- Switching mode: light/dark-switching

Sensing range max.	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.				
					-	GSE6-P1111	1052448				
			Cable, 3-wire, 2 m, PVC	Cd-049	Stainless steel mounting bracket BEF-W100-A	GSE6-P1112	1052452				
					-	GSE6-P4111	1052446				
		_	Connector M8, 4-pin	Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-P4112	1052450				
		_	Cable with connector M12, 4-pin, 300 mm, PVC		-	GSE6-P7111	1054830				
0 m 15 m	PNP			Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-P7112	1054831				
0111 10111	1 141		Cable with connector M8, 4-pin, 300 mm, PVC		-	GSE6-P6111	1054848				
				Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-P6112	1054850				
		Potentiometer, 270 °		Cd-049	-	GSE6-P1211	1060792				
					Stainless steel mounting bracket BEF-W100-A	GSE6-P1212	1061398				
					-	GSE6-P4211	1061394				
			Connector M8, 4-pin, PVC	Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-P4212	1061396				
					-	GSE6-N1111	1052449				
							Cable, 3-wire, 2 m, PVC	Cd-049	Stainless steel mounting bracket BEF-W100-A	GSE6-N1112	1052453
					-	GSE6-N4111	1052447				
		_	Connector M8, 4-pin	Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-N4112	1052451				
0 m 15 m NP	NPN	_	Cable with connector		-	GSE6-N7111	1054833				
			M12, 4-pin, 300 mm, PVC	Cd-057	Stainless steel mounting bracket BEF-W100-A	GSE6-N7112	1054835				
			Cable with connector M8,	Cd-057	-	GSE6-N6111	1054849				
			4-pin, 300 mm, PVC		Stainless steel mounting bracket BEF-W100-A	GSE6-N6112	1054852				
		Potentiometer, 270 °	Cable, 3-wire, 2 m, PVC	Cd-049	-	GSE6-N1211	1060791				

F

### **Dimensional drawings**


Dimensions in mm (inch)



- ① Optical axis, receiver
- 2 Optical axis, sender
- 3 Mounting holes M3
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- © Light/ dark rotary switch:
  - L = light switching, D = dark switching


### **Adjustments**

#### **Adjustment possibility**



- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: status of received light beam
- $\ensuremath{\mathfrak{D}}$  Sensitivity adjustment: poti

#### No adjustment possibility




- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: status of received light beam



#### **Characteristic curves**

#### Black-white shift


#### GTE6



- $\ensuremath{\textcircled{1}}$  Object with 90% remission (referred to standard white DIN 5033)
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission


### Operating reserve

### GL6




- ① PL80A
- ② PL40A
- ③ P250
- ④ PL20A
- ⑤ REF-IRF-56

#### GTB6




- ① Object with 90% remission (referred to standard white DIN 5033)
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### GSE6




### **Bar diagrams**

#### GTE6



- ① Object with 90% remission (referred to standard white DIN 5033)
- 2 Sensing range on gray, 18 % remission

#### GL6, GL6G




Sensing range

Sensing range max.

- ① PL80A
- ② PL40A
- ③ P250
- ④ PL20A
- ⑤ REF-IRF-56

#### GTB6




Sensing range max.

Sensing range


- ① Object with 90% remission (referred to standard white DIN 5033)
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on black, 6 % remission

#### GSE6




### Light spot diameter


#### GTE6



### GL6, GL6G




#### GTB6



All dimensions in mm (inch)

### GSE6




### **Connection diagram**

#### Cd-043




#### Cd-049




- ① Sender
- 2 Receiver

#### Cd-057



Cd-066



- ① Sender
- ② Receiver

### **Recommended accessories**

### Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
2	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled	conductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873
	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled	' '	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

### G6

### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
J.	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
3	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	DMMMA /ADS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
	DMMMA /ADS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
1	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244



#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861

F









### **Additional information**

Detailed technical data F-209
Ordering informationF-210
Dimensional drawings F-211
Characteristic curves F-212
Bar diagramsF-213
Connection diagram F-214
Recommended accessories F-214

### **Product description**

The W2 Flat photoelectric sensor family is enclosed in a housing only 3.5 mm high, enabling it to fit in nearly all machine parts for reliable object detection. These sensors, which are one of the smallest photoelectric sensor families in the world, enable thin and compact

machine designs. Their rugged housing includes metal-reinforced fixing holes that simplify machine integration. This flat design enables even a milling recess to be used to integrate the sensor safely in the machine.

### At a glance

- · One of the smallest photoelectric sensors in the world
- No external amplifier required
- · Variant designed to detect transparent and glossy objects
- · Rugged housing with metal-reinforced fixing holes

#### Your benefits

- High-performance solutions for very tight spaces provide increased application flexibility
- Fast response times with a high level of accuracy and precise switching points
- The high enclosure rating and the rugged housing offer a long service life that withstands harsh environmental conditions
- · Quick and easy installation since sensors can be mounted directly on machine parts

#### → www.mysick.com/en/W2\_Flat

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



### **Detailed technical data**

#### **Features**

	WT2 Flat	WS/WE2 Flat
Sensor principle	Photoelectric proximity sensor	Through-beam photoelectric sensor
Detection principle	Energetic	-
Dimensions (W x H x D)	14 mm x 19.5 mm x 3.5 mm	12 mm x 20 mm x 3.5 mm
Housing design (light emission)	Rectangular	
Sensing range max.	1 mm 115 mm $^{1)}$ (depending on type)	0 m 0.5 m
Sensing range	1 mm 115 mm $^{1)}$ (depending on type)	0 m 0.4 m
Type of light	Visible red light	
Light source 2)	LED	
Light spot size (distance)	-	Ø 10 mm (100 mm)
Wave length	660 nm	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

Supply voltage 1)	12 V DC 24 V DC
Ripple 2)	≤ 5 V <sub>pp</sub>
Output type	PNP / NPN (depending on type)
Switching mode	Light switching / Dark-switching (depending on type)
Signal voltage PNP HIGH/LOW	Approx. $V_S - 1.8 V / 0 V$
Signal voltage NPN HIGH/LOW	Approx. $V_S / < 1.8 V$
Output current I <sub>max.</sub>	≤ 50 mA
Response time 3)	≤ 0.5 ms
Switching frequency 4)	1,000 Hz
Connection type	Cable, 2 m $^{5)}$ / Cable with connector, M8, 200 mm $^{5)}$ (depending on type)
Circuit protection	A <sup>6)</sup> , C <sup>7)</sup> , D <sup>8)</sup>
Weight	20 g
Reverse polarity protection	V
Short-circuit protection	<b>✓</b>
Housing material	PC
Optics material	PC
Enclosure rating	IP 67
Ambient operating temperature	-20 °C +55 °C
Ambient storage temperature	-40 °C +75 °C

<sup>1) +- 10 %</sup> 

F

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

 $<sup>^{\</sup>scriptsize{\rm 3)}}$  Signal transit time with resistive load.

<sup>4)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>5)</sup> Do not bend below 0 °C.

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

### **Ordering information**

Other models available at www.mysick.com/en/W2\_Flat

#### WT2 Flat

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

Sensing range max. <sup>1)</sup>	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-P170	6030588
	PNP		Cable with connector M8, 3-pin, 200 mm, PVC	Cd-045	WT2F-P270	6030589
1 mm 9 mm			Cable with connector M8, 4-pin, 200 mm, PVC	Cd-066	WT2F-P470	6030590
	NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-N170	6030587
			Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-P140	6030584
2 mm 18 mm	PNP	Light switching	Cable with connector M8, 3-pin, 200 mm, PVC	Cd-045	WT2F-P240	6030585
2 111111 10 111111			Cable with connector M8, 4-pin, 200 mm, PVC	Cd-066	WT2F-P440	6030586
	NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-N140	6030583
	PNP	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-P150	6030580
			Cable with connector M8, 3-pin, 200 mm, PVC	Cd-045	WT2F-P250	6030581
2 mm 34 mm			Cable with connector M8, 4-pin, 200 mm, PVC	Cd-066	WT2F-P450	6030582
	NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-N150	6030576
		Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-E150	6043902
	PNP	NP Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-P180	6030573
4 mm 115 mm			Cable with connector M8, 3-pin, 200 mm, PVC	Cd-045	WT2F-P280	6030574
			Cable with connector M8, 4-pin, 200 mm, PVC	Cd-066	WT2F-P480	6030575
	NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WT2F-N180	6030572

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WS/WE2 Flat


• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0 m 0.5 m		مر درا داد داد المار در المارات ا	Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE2F-P110	6049355
		Light switching	Cable with connector M8, 3-pin, 200 mm, PVC	Cd-051	WS/WE2F-P210	6030566
	PNP	P Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE2F-F110	6030569
			Dark-switching Cable with connector M8, 3-pin, 200 mm, PVC		WS/WE2F-F210	6030570
			Cable with connector M8, 4-pin, 200 mm, PVC	Cd-057	WS/WE2F-F410	6030571
	NPN	NPN Light switching Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE2F-N110	6030540
			Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE2F-E110	6030554

### **Dimensional drawings**


Dimensions in mm (inch)

#### WT2F



- ① Mounting holes, Ø 2.1 mm
- 2 Optical axis, sender
- 3 Optical axis, receiver
- ④ LED indicator orange: switching output active
- ⑤ LED indicator green: strength indicator
- **6** Connection

#### WS/WE2F




- $\ensuremath{\textcircled{1}}$  Mounting holes, Ø 2.1 mm
- ② Optical axis, receiver
- 3 Optical axis, sender
- 4 LED indicator green
- ⑤ LED indicator orange
- 6 LED indicator green
- 7 Connection

#### **Characteristic curves**


#### Black-white shift

#### **WT2F, 9 mm**




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WT2F, 34 mm




- 1 Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WT2F, 18 mm



- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### WT2F, 115 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


#### Operating reserve

#### WS/WE2F




### **Bar diagrams**

#### **WT2F, 9 mm**




- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WT2F, 34 mm



- Sensing range
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


#### WS/WE2F



Sensing range


Sensing range typ. max.

#### WT2F, 18 mm




- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WT2F, 115 mm




- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission


### Cd-043



#### Cd-045




#### Cd-049




- ① Sender
- 2 Receiver

#### Cd-051




- ① Sender
- 2 Receiver

#### Cd-066



#### Cd-057



- ① Sender
- 2 Receiver

# **Recommended accessories**

Plug connectors and cables

Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	nnector, Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,		2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled		5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
11	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	3, 4-pin, straight ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled	' ' ' '	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
			5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
OR.	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0804-G	6037323

<sup>→</sup> For additional accessories, please see page L-861

Ē








#### **Additional information**

Detailed technical dataF-217
Ordering informationF-218
Dimensional drawings F-221
Characteristic curvesF-224
Bar diagramsF-225
Light spot diameterF-227
Connection diagram F-229
Light spot size F-230
Recommended accessories F-231



## **Product description**

Developing lighter, more compact and more intelligent machines. The incredibly small, new-generation W2S-2 miniature photoelectric sensor offers completely new machine design possibilities. Intelligent features: the sensors feature background suppression that enables detection of black objects with a degree of reflection of 1%. The W2S-2 also offers world-class sensing distances in this housing size.

Whether it is used in machines in the pharmaceutical industry, in logistics handling applications or in automatic assembly equipment, the ultra-compact W2S-2 offers optimal performance and high reliability in industrial environments. The latest automation innovation is already on board: both the sensing range as well as continuous monitoring are set via the controller. The W2S-2 reduces the load on the machine control by using a counter, timestamp and false tripping suppression functions.

Programmable sensors, adjustable via a 3-turn potentiometer, and sensors with fixed sensing distances of 15 mm, 30 mm, 45 mm and 60 mm are also available.

## At a glance

- Sensor with background suppression and without any significant black/ white shift
- PinPoint 2.0 LED with extended sensing distances and high operating reserves
- · Clearly-defined laser-like or lineshaped light spots
- · Detection of highly-transparent and reflective objects using sensors with V-optics
- · Photoelectric retro-reflective sensor with autocollimation

#### Your benefits

- Machine design flexibility: the ultracompact sensors offer above-average sensing distances and provide spacesaving installation
- Remote setup: sensors installed in confined spaces can be set and monitored remotely via IO-Link.
- High operational reliability: black objects are detected with a degree of reflection of 1%
- Maximum reliability during object detection
- Quick and easy commissioning: the photoelectric retro-reflective sensor with autocollimation provides a clearly visible light spot for high process reliability
- Universal application options: wide range of models enclosed in a rugged housing

#### www.mysick.com/en/W2S-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	WTB2S-2	WTV2S-2	WL2S-2	WSE2S-2	
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor	
Detection principle	Background suppression	on	Autocollimation	-	
Dimensions (W x H x D)	13.5 mm	7.7 mm x 21.8 mm x 13.5 mm			
	7.7 mm x 27.5 mm x 13.5 mm				
	(depending on type)				
Housing design (light emission)	Rectangular				
Sensing range max.	1 mm 150 mm <sup>1)</sup> (depending on type)	1 mm 36 mm <sup>1)</sup>	0 m 1.2 m <sup>2)</sup>	0 m 2.5 m	
Sensing range	3 mm 110 mm <sup>1)</sup> (depending on type)	4 mm 30 mm <sup>1)</sup>	0 m 0.55 m <sup>2)</sup>	0 m 2 m	
Type of light	Visible red light				
Light source 3)	PinPoint LED				
Wave length	640 nm				
Adjustment	Cable / potentiometer, 3 turns (depending on type)	-			
Special feature	Line-shaped light spot (depending on type)	-			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	WTB2S-2	WTV2S-2	WL2S-2	WSE2S-2			
Supply voltage 1)	10 V DC 30 V DC						
Ripple 2)	≤ 5 V <sub>pp</sub>						
Power consumption 3)	≤ 20 mA						
Output type	PNP / NPN 4) (dependi	PNP / NPN <sup>4)</sup> (depending on type)					
Switching mode	Light switching / Dark-s	Light switching / Dark-switching / Light/dark-switching 4) (depending on type)					
Output current I <sub>max.</sub>	< 50 mA						
Response time <sup>5)</sup>	< 0.4 ms / < 0.5 ms (depending on type)	< 0.4 ms	< 0.5 ms	< 0.4 ms			
Switching frequency <sup>6) 7)</sup>	1,000 Hz / 1,200 Hz (depending on type)	1,200 Hz	1,000 Hz	1,200 Hz			
Connection type	Cable, 2 m 8) / Cable wi	ith connector, M8, 200 n	nm <sup>8)</sup> (depending on type)				
Circuit protection	A $^{9)}$ , B $^{10)}$ , D $^{11)}$						
Polarisation filter	-		<b>~</b>	-			
IO-Link	<ul><li>- / ✔ (COM2)</li><li>(depending on type)</li></ul>	-	-				
Housing material	ABS/PC						

F

<sup>2)</sup> P250I

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WTB2S-2	WTV2S-2	WL2S-2	WSE2S-2
Optics material	PMMA			
Enclosure rating	IP 67			
Ambient operating temperature	-20 °C +50 °C			
Ambient storage temperature	-40 °C +75 °C			

<sup>1)</sup> Limit values.

## **Ordering information**

Other models available at www.mysick.com/en/W2S-2

#### WTB2S-2

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

Sensing range max.1)	Light spot size (distance)	Adjust- ment	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
					Cable, 3-wire, 2 m	Cd-044	WTB2S-2P1310	1064393
				Light switching	Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2P3110	1064395
			PNP		Cable, 3-wire, 2 m	Cd-044	WTB2S-2F1310	1064394
1 mm 18 mm Ø 2 mm (8 mm)	Ø 2 mm (8 mm)	-		Dark-switching	Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2F3110	1064396
				Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2P3210	1063314
			NPN	Light switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2N1310	1064249
				Dark-switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2E1310	1064397
				Light switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2P1330	1064573
					Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2P3130	1064575
			PNP		Cable, 3-wire, 2 m	Cd-044	WTB2S-2F1330	1064574
				Dark-switching	Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2F3130	1064576
1 mm 36 mm	Ø 3 mm (15 mm)	-		Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2P3230	1063517
				Light switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2N1330	1064578
			NPN	Dark-switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2E1330	1064580
					Cable, 4-wire, 2 m	Cd-095	WTB2S-2N1130	1063321
				Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2N3230	1064581

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Parametrisable via IO-Link.

<sup>&</sup>lt;sup>5)</sup> Signal transit time with resistive load.

<sup>6)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>7)</sup> With light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.

 $<sup>^{8)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{\</sup>rm 9)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = output reverse-polarity protected.

 $<sup>^{\</sup>mbox{\scriptsize 11)}}$  D = outputs overcurrent and short-circuit protected.

Sensing range max.1)	Light spot size (distance)	Adjust- ment	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.	
				Light switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2P1360	1064605	
1 mm Ø 4.5 mm 66 mm (40 mm)					Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2P3160	1064607	
	Ø 4 5 mm		PNP		Cable, 3-wire, 2 m	Cd-044	WTB2S-2F1360	1064606	
	,	-		Dark-switching	Cable with connector M8, 3-pin, 200 mm	Cd-045	WTB2S-2F3160	1064608	
					Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2P3260	1063545
			NPN	Light switching	Cable, 3-wire, 2 m	Cd-044	WTB2S-2N1360	1064609	
		Cable	PNP	Light switching	Cable, 4-wire, 2 m	Cd-093	WTB2S-2P1145	1064614	
4 mm 110 mm	Ø 4.4 mm (100 mm)				Cable with connector M8, 4-pin, 200 mm	Cd-092	WTB2S-2P3245	1064615	
			NPN	Light switching	Cable, 4-wire, 2 m	Cd-093	WTB2S-2N1145	1063552	
					Cable, 4-wire, 2 m	Cd-095	WTB2S-2P1151	1066110	
1 mm	Ø 3.5 mm	Potenti- ometer, 3 turns	PNP	Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2P3251	1066111	
150 mm	(50 mm)		NPN		Cable, 4-wire, 2 m	Cd-095	WTB2S-2N1151	1066113	
				Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTB2S-2N3251	1066114	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

## WTB2S-2, line-shaped light spot

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching frequency: 1,000 Hz (with light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.)

Sensing range max.1)	Light spot size (distance)	Adjust- ment	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
4 mm 2.2 mm x 9 mm 90 mm (45 mm)	Cable	NPN	Light switching	Cable, 4-wire, 2 m	Cd-093	WTB2S-2P1175	1064621	
		PNP	Light switching	Cable with connector M8, 4-pin, 200 mm	Cd-092	WTB2S-2P3275	1064620	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

#### WTB2S-2, IO-Link

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching mode: light switching (Parametrisable via IO-Link.)
- Switching frequency: 1,000 Hz (with light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.)

Sensing range max.1)	Light spot size (distance)	Adjust- ment	Output type	IO-Link	Connection	Connection diagram	Model name	Part no.
4 mm 110 mm	Ø 4.4 mm (60 mm)	Cable	PNP	Standard functions	Cable with connector M8, 4-pin, 200 mm	Cd-098	WTB2SC-2P3244	1063550

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

## WTB2S-2, IO-Link, line-shaped light spot

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching mode: light switching (Parametrisable via IO-Link.)
- Switching frequency: 1,000 Hz (with light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.)

Sensing range max.1)	Light spot size (distance)	Adjust- ment	Output type	IO-Link	Connection	Connection diagram	Model name	Part no.
4 mm 90 mm	2.2 mm x 9 mm (45 mm)	Cable	PNP	Standard functions	Cable with connector M8, 4-pin, 200 mm	Cd-098	WTB2SC-2P3274	1063646

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

## WTV2S-2, V-optics

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Switching frequency: 1,200 Hz (With light/dark ratio 1:1.)

Sensing range max.1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		5 mm) PNP	Light switching	Cable, 3-wire, 2 m	Cd-044	WTV2S-2P1320	1064660
1 mm 36 mm	Ø 2 mm (15 mm)			Cable with connector M8, 3-pin, 200 mm	Cd-045	WTV2S-2P3120	1064662
36 mm			Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WTV2S-2P3220	1064661

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

## WL2S-2

• Sensor principle: photoelectric retro-reflective sensor

Detection principle: autocollimation

• Switching frequency: 1,000 Hz (With light/dark ratio 1:1.)

Sensing range max.1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP	Light switching	Cable, 3-wire, 2 m	Cd-044	WL2S-2P1330	1064590
				Cable with connector M8, 3-pin, 200 mm	Cd-045	WL2S-2P3130	1064592
			Dark-switching	Cable, 3-wire, 2 m	Cd-044	WL2S-2F1330	1064591
				Cable with connector M8, 3-pin, 200 mm	Cd-045	WL2S-2F3130	1064593
0 m 1.2 m	Ø 12 mm (250 mm)		Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-084	WL2S-2P3230	1063572
				Cable with connector M8, 4-pin, 200 mm	Cd-110	WL2S-2K3230 2)	1064594
			Light switching	Cable, 3-wire, 2 m	Cd-044	WL2S-2N1330	1064595
		NPN	Dark-switching	Cable, 3-wire, 2 m	Cd-044	WL2S-2E1330	1064596
			Light/dark-switching	Cable, 4-wire, 2 m	Cd-095	WL2S-2N1130	1063571

<sup>&</sup>lt;sup>1)</sup> P250F.

<sup>2)</sup> Pin 2 and 4 swapped.

## WSE2S-2


- Sensor principle: through-beam photoelectric sensor
- Switching frequency: 1,200 Hz (With light/dark ratio 1:1.)

Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP		Cable, 3-wire, 2 m	Cd-049	WSE2S-2P1330	1065940
			Light switching	Cable with connector M8, 3-pin, 200 mm	Cd-051	WSE2S-2P3130	1063521
			Dark-switching	Cable, 3-wire, 2 m	Cd-049	WSE2S-2F1330	1965941
				Cable with connector M8, 3-pin, 200 mm	Cd-051	WSE2S-2F3130	1063523
0 m 2.5 m	Ø 65 mm (1,500 mm)		Light/dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-085	WSE2S-2P3230	1063650
			Light switching	Cable, 3-wire, 2 m	Cd-049	WSE2S-2N1330	1064584
				Cable, 3-wire, 2 m	Cd-049	WSE2S-2E1330	1064586
		NPN	Dark-switching	Cable with connector M8, 3-pin, 200 mm	Cd-051	WSE2S-2E3130	1064588
			Light/dark-switching	Cable, 4-wire, 2 m	Cd-085	WSE2S-2N1130	1063660

# **Dimensional drawings**

Dimensions in mm (inch)


## WTB2S-2, 15 mm, 30 mm, WTV2S-2



- ① Optical axis receiver
- ② Optical axis sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Connection

F


#### WTB2S-2, 60 mm, 80 mm



- ① Optical axis, receiver
- 2 Optical axis, sender
- 3 Middle axis fixing hole Ø 3.2 mm
- $\ensuremath{\textcircled{4}}$  Status indicator LED green: power on
- Status indicator LED, yellow: Status of received light beam
- 6 Connection


F

#### WTB2S-2, 150 mm




- ① Optical axis, receiver (sensing range min.)
- $\ensuremath{\mathfrak{D}}$  Optical axis, receiver (sensing range max.)
- 3 Optical axis, sender
- 4 Fixing hole ø 3.2 mm
- ⑤ Status indicator LED green: power on
- Status indicator LED, yellow:
   Status of received light beam
- ② Sensing range adjustment: potentiometer, 3 turns
- ® Connection

#### WL2S-2



- ① Optical axis, receiver
- 2 Optical axis, sender
- $\ensuremath{\mathfrak{G}}$  Middle axis fixing hole Ø 3.2 mm
- 4 Status indicator LED green: power on
- Status indicator LED, yellow: Status of received light beam
- **6** Connection

#### **WSE2S-2**




- ① Optical axis, receiver
- 2 Optical axis, sender
- $\ensuremath{\mathfrak{G}}$  Middle axis fixing hole  $\emptyset$  3.2 mm
- $\ensuremath{\textcircled{4}}$  LED indicator green: power on
- Status indicator LED, yellow: Status of received light beam
- **6** Connection

F

## **Characteristic curves**


#### Black-white shift

#### WTB2S-2, 110 mm




- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission

#### WTB2S-2, 150 mm




- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### WTB2S-2, 90 mm, line-shaped light spot



- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission


#### **WL2S-2**



- ① P250F
- ② PL20A
- ③ REF-AC1000
- 4 PL10F


## Operating reserve

#### **WL2S-2**



- ① P250F
- ② PL20A


#### **WSE2S-2**



- ③ REF-AC1000
- 4 PL10F


## **Bar diagrams**

## WTB2S-2, 15 mm




- Sensing range
- Sensing range max.
- ① Sensing range on white, 90 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### WTB2S-2, 30 mm




- Sensing range
- Sensing range max.
- ① Sensing range on white, 90 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### WTB2S-2, 60 mm




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### WTB2S-2, 90 mm, line-shaped light spot




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### **WL2S-2**




- Sensing range
- Sensing range max.
- ① P250F
- ② PL20A
- ③ REF-AC1000
- 4 PL10F

#### WTB2S-2, 110 mm




- Sensing range
- Sensing range max.
- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### WTB2S-2, 150 mm



- Sensing range
- Sensing range max.
- $\ensuremath{\textcircled{1}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission
- 4 Sensing range on ultrablack, 1 % remission

#### **WSE2S-2**




# WTB2S-2, 30 mm


## WTB2S-2, 15 mm

Spot diameter in mm (inch)

**Light spot diameter** 




#### Spot diameter in mm (inch)




#### WTB2S-2, 60 mm

Spot diameter in mm (inch)




#### WTB2S-2, 110 mm

Spot diameter in mm (inch)



#### WTB2S-2, 90 mm, line-shaped light spot


Spot diameter in mm (inch)



Vertical
Horizontal


#### **WTV2S-2**

Spot diameter in mm (inch)




#### WTB2S-2, 150 mm

Spot diameter in mm (inch)




#### **WL2S-2**

Spot diameter in mm (inch)



#### **WSE2S-2**


Spot diameter in mm (inch)




# **Connection diagram**

#### Cd-044

#### Cd-045




#### Cd-049



- ① Sender
- ② Receiver

#### Cd-051

$$\begin{array}{c|c}
\hline
 & bin & 1 \\
\hline
 & blu & 3 \\
\hline
 & blk & 4 \\
\hline
 & l & not connected
\end{array}$$



- ① Sender
- 2 Receiver

#### Cd-084

#### Cd-085

Cd-092


$$\begin{array}{c|c} & & \\ \hline & \text{bin} & 1 \\ \hline & \text{wht} & 2 \\ \hline & & \text{leach} \\ \hline & & \text{blu} & 3 \\ \hline & & \text{c} & \text{(M)} \\ \hline & & \text{blk} & 4 \\ \hline & & \text{Q} \\ \hline \end{array}$$

Cd-093



- ① Sender
- 2 Receiver

#### Cd-095




Cd-098

Cd-110

$$\begin{array}{c|c} & bm & 1 \\ \hline & bm & 2 \\ \hline & blu & 3 \\ \hline & blk & 4 \\ \hline & \overline{Q} \\ \end{array}$$

## Light spot size

#### WTB2S-2, 90 mm, line-shaped light spot



## **Recommended accessories**

## Plug connectors and cables

## Connecting cable (female connector-open)M8, 3-pin, PVC

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,		2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled		5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector, M8, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
			5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled		5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

## Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

→ For additional accessories, please see page L-861

# Powerful clear material detection in an ultra-compact housing













## Additional information

🚷 IO-Link

Additional information
Detailed technical dataF-233
Ordering informationF-234
Dimensional drawingsF-234
Characteristic curvesF-235
Bar diagramsF-235
Light spot diameterF-235
Connection diagram F-235
Recommended accessories F-236



## **Product description**

New possibilities in machine construction: the ultra-compact WL2SG-2 miniature photoelectric sensor for detecting transparent objects offers features that were previously only available with much larger sensors. Ampules, foil and glass are reliably detected in the most confined of spaces.

The WL2SG-2 is adaptable: dust on the reflector or wear is compensated for in the same way as temperature changes and changes in light intensity. The WL2SG-2 is not only adaptable with regard to harsh industrial environments

- settings for the respective application can also be selected via IO-Link.

Special operating modes for gaps in the bottle flow or for foil tear monitoring are available for extreme operating conditions. The W2S-2 offers optimal performance with an ultra-compact design for use in both pharmaceutical and automatic assembly machines.

The newest automation innovation is already on board. Configuration and diagnostics are set via the control in the same way as continuous monitoring.

## At a glance

- Extremely high sensor size to sensing distance ratio
- · High switching point accuracy
- Teach-in functions enable reliable settings
- Continuous threshold adaption (AutoAdapt)
- Single-lens autocollimation for visibility through apertures and drill holes
- · Flexible sensor settings, monitoring, advanced diagnostics, and display thanks to IO-Link

#### Your benefits

- Machine design flexibility: the ultracompact sensors offer above-average sensing distances and provide spacesaving installation
- Remote setup: sensors installed in confined spaces can be set and monitored remotely via IO-Link.
- High operational reliability and system throughput: all familiar, highly-transparent objects are reliably detected
- Reliable object detection: precise switching characteristics and a high detection quality
- · Universal use: conventional mounting and housing design
- The precise light spot of the Pin-Point<sup>2.0</sup> LED enables the use of very small reflectors and reflector surfaces

#### → www.mysick.com/en/W2SG-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



**Detailed technical data** 

# Features

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	7.7 mm x 21.8 mm x 13.5 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 1.2 m
Sensing range 1)	0 m 0.55 m
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	Ø 12 mm (250 mm)
Wave length	640 nm
Adjustment	Cable
Continuous threshold adaption (AutoAdapt)	V
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> P250F.

## Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple 2)	≤ 5 V <sub>pp</sub>
Power consumption 3)	≤ 20 mA
Output type	PNP / NPN (depending on type)
Switching mode	Light switching / Dark-switching / Light/dark-switching (depending on type)
Output current I <sub>max.</sub>	< 50 mA
Response time 4)	< 0.5 ms
Switching frequency 5)	1,000 Hz
Connection type	Cable with connector, 200 mm $^{\rm 6)}/$ Cable, 2 m $^{\rm 6)}($ depending on type $)$
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , D <sup>9)</sup>
Polarisation filter	V
IO-Link	-/✔ (COM2) (depending on type)
Housing material	ABS/PC
Optics material	PMMA
Enclosure rating	IP 67
Ambient operating temperature	-20 °C +50 °C
Ambient storage temperature	-40 °C +75 °C

<sup>1)</sup> Limit values

F

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at T  $_{\!\scriptscriptstyle \Delta}$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = output reverse-polarity protected.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/W2SG-2

#### WL2SG-2, clear material detection

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

Sensing range max.1)	Adjustment	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP	Light switching	Cable with connector M8, 4-pin, 200 mm	Cd-093	WL2SG-2P3235	1065929
0 m 1.2 m	Cable		Dark-switching	Cable with connector M8, 4-pin, 200 mm	Cd-093	WL2SG-2F3235	1063647
0 111 1.2 111		NIDNI	Light switching	Cable, 4-wire, 2 m	Cd-093	WL2SG-2N1135	1065934
		NPN	Dark-switching	Cable, 4-wire, 2 m	Cd-093	WL2SG-2E1135	1065930

<sup>&</sup>lt;sup>1)</sup> P250F.

#### WL2SG-2, IO-Link

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

• Switching mode: light/dark-switching

Sensing range max. 1)	Adjustment	Output type	IO-Link	Connection	Connection diagram	Model name	Part no.
0 m 1.2 m	Cable	PNP	Standard func- tions	Cable with connector M8, 4-pin, 200 mm	Cd-098	WL2SGC-2P3234	1063648

<sup>1)</sup> P250F.

# **Dimensional drawings**

Dimensions in mm (inch)




② Optical axis, sender

③ Middle axis fixing hole Ø 3.2 mm

④ Status indicator LED green: power on

⑤ Status indicator LED, yellow: Status of received light beam


6 Connection





## **Characteristic curves**


#### WL2SG-2



- ① P250F
- ② PL20A
- ③ REF-AC1000
- 4 PL10F

# **Bar diagrams**

#### WL2SG-2




- Sensing range
- Sensing range max.
- ① P250F
- ② PL20A
- ③ REF-AC1000
- 4 PL10F

# **Light spot diameter**

#### WL2SG-2

Spot diameter in mm (inch)



# **Connection diagram**

#### Cd-093

#### Cd-098

## **Recommended accessories**

## Plug connectors and cables

#### Connecting cable (female connector-open), PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled	· •	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
			5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
-	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure Material Description Model name Part no. Fine triple, screw connection, suitable for laser sensors, P250F 5308843 47 mm x 47 mm PMMA/ABS Fine triple, screw connection, suitable for laser sensors, 5311210 PL10F 18 mm x 18 mm Fine triple, chemically resistant, screw connection, Plastic PL10F CHEM 5321636 18 mm x 18 mm Fine triple, screw connection, suitable for laser sensors, PMMA/ABS PL20F 5308844 38 mm x 16 mm Fine triple, chemically resistant, screw connection, suitable for Plastic PL20F-CHEM 5326089 laser sensors, 16 mm x 38 mm Fine triple, screw connection, suitable for laser sensors, PL30F 5326523 56 mm x 28 mm PMMA/ABS Fine triple, screw connection, suitable for laser sensors, PL81-1F 5325060 76 mm x 45 mm

#### Reflective tape

Figure	Description	Model name	Part no.
1	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030



## **Special reflectors**

Figure	Material	Description	Model name	Part no.
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

F











## **Additional information**

Detailed technical dataF-239
Ordering informationF-240
Dimensional drawings F-243
Characteristic curves F-244
Bar diagramsF-245
Light spot diameter
Minimum detectable object F-246
Connection diagram F-247
Recommended accessories F-248



The W4-3 family of photoelectric sensors offers best-in-class performance in a miniature housing design. Using the latest SIRIC® and PinPoint LED technologies, these sensors provide reliable object detection of transparent and

glossy objects like blisters, e-cards and aluminum cans. Optical axes on the flat side enable simple, space-saving integration in machine environments - even without mounting brackets.

## At a glance

- · Best-in-class background suppression, reliable detection of critical objects and a high immunity to ambient light
- Quick and easy setup using a precise 5-turn potentiometer, control wire or teach function
- Best background suppression in its
- · PinPoint LED for brightest light spot in its class

#### Your benefits

- · Low-cost integration due to optimal machine integration in areas with limited space
- Application versatility due to reliable detection of shiny or jet-black objects
- · Rugged mounting system with M3 threaded metal inserts reduces maintenance costs due to a long service life
- · High immunity to ambient light reduces downtime caused by false trips
- Clearly visible light spot simplifies alignment

#### → www.mysick.com/en/W4-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	WTB4-3	WTV4-3	WL4-3	WSE4-3
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor
Detection principle	Background suppression	on	Standard optics	-
Dimensions (W x H x D)	16 mm x 39.5 mm x 12	2 mm		
Housing design (light emission)	Rectangular			
Sensing range max.	4 mm 150 mm <sup>1)</sup>	3 mm 50 mm <sup>1)</sup> (depending on type)	0.01 m 4.5 m <sup>2)</sup>	0 m 4 m
Sensing range	15 mm 150 mm <sup>1)</sup>	5 mm 50 mm <sup>1)</sup> (depending on type)	0.02 m 3.5 m <sup>2)</sup>	0 m 3.5 m
Type of light	Visible red light	Visible red light / Infrared light (depending on type)	Visible red light	
Light source 3)	PinPoint LED <sup>2.0</sup>			
Wave length				
Visible red light	650 nm / 660 nm (depending on type)	650 nm		
Infrared light	-	880 nm	-	
Adjustment	Potentiometer, 5 turns Cable Single teach-in button (depending on type)	Potentiometer, 5 turns	-	
Special feature	Line-shaped light spot	V-optics / line-shaped light spot (depending on type)	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTB4-3	WTV4-3	WL4-3	WSE4-3
Supply voltage	10 V DC 30 V DC <sup>1)</sup>			
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>			
Power consumption	≤ 20 mA <sup>3)</sup>			≤ 20 mA <sup>4)</sup>
Output type	PNP / NPN (depending	g on type)		
Switching mode	Light switching / Dark-s	switching / Light/dark-sw	ritching (depending on ty	/pe)
Output current I <sub>max.</sub>	≤ 100 mA			
Response time 5)	< 0.5 ms			
With IO-Link light 7)	< 0.65 ms	-		
Switching frequency 6)	1,000 Hz			
Connection type	Cable, 2 m 8) / Male con (depending on type)	nnector, M8 / Cable with	connector, M12, 150 m	ım <sup>8)</sup>
Circuit protection	A $^{9)}$ , C $^{10)}$ , D $^{11)}$			
Protection class	III			
Weight	30 g			60 g
Polarisation filter	-		<b>✓</b>	-
Housing material	ABS			
Optics material	PMMA			
Enclosure rating	IP 66 / IP 67			

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WTB4-3	WTV4-3	WL4-3	WSE4-3
Test input sender off	-			"Test" to 0 V
Ambient operating temperature	-40 °C +60 °C			
Ambient storage temperature	-40 °C +75 °C			

<sup>1)</sup> Limit values.

# **Ordering information**

Other models available at www.mysick.com/en/W4-3

## WTB4-3

Sensor principle: photoelectric proximity sensor
 Detection principle: background suppression

• Type of light: visible red light

• Light spot size (distance): Ø 7 mm (50 mm)

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
			Potentiometer,	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3P1361	1028094
			5 turns	Connector M8, 3-pin	Cd-045	WTB4-3P2161	1028099
		Light switching	Single teach-in	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3P1362	1028081
			button	Connector M8, 3-pin	Cd-045	WTB4-3P2162	1028084
	PNP		Cable, Single teach-in button 2)	Cable, 4-wire, 5 m, PVC	Cd-093	WTB4-3P1264	1041890
	FINE	Dark-switching	Potentiometer,	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3F1361	1028105
		Dark-switching	5 turns	Connector M8, 3-pin	Cd-045	WTB4-3F2161	1028107
		Light/dark- switching	Potentiometer, 5 turns	Connector M8, 4-pin	Cd-083	WTB4-3P2261	1028100
				Cable, 4-wire, 2 m, PVC	Cd-094	WTB4-3P1161	1028096
4 mm 150 mm			Single teach-in button	Connector M8, 4-pin	Cd-083	WTB4-3P2262	1028085
			Potentiometer,	Cable, 3-wire, 5 m, PVC	Cd-043	WTB4-3N1461	1057301
			5 turns	Connector M8, 3-pin	Cd-045	WTB4-3N2161	1028104
		Light switching	Single teach-in	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3N1362	1028087
			button	Connector M8, 3-pin	Cd-045	WTB4-3N2162	1028088
	NPN		Cable, Single teach-in button 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WTB4-3N1164	1028090
		Dark-switching	Potentiometer,	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3E1361	1028108
		Dark-Switching	5 turns	Connector M8, 3-pin	Cd-045	WTB4-3E2161	1028110
		Light/dark- switching	Potentiometer, 5 turns	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4-3N1161	1028102

<sup>1)</sup> Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Sender.

<sup>&</sup>lt;sup>5)</sup> Signal transit time with resistive load.

<sup>6)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>7)</sup> With light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $V_{c}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> C = interference suppression.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>rm 2)}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

#### WTB4-3, line-shaped light spot

- Supply voltage: 10 V DC ... 30 V DC (Limit values.)
- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Type of light: visible red light
- Light spot size (distance): 5 mm x 28 mm (50 mm)

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
		Light avvitable of	Potentiometer, 5 turns	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3P1371	1028121
	PNP	Light switching		Connector M8, 3-pin	Cd-045	WTB4-3P2171	1028123
4 mm 150 mm		Light/dark- switching		Connector M8, 4-pin	Cd-083	WTB4-3P2271	1042190
		Light switching	Potentiometer, 5 turns	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4-3N1371	1028125
				Connector M8, 3-pin	Cd-045	WTB4-3N2171	1028126

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WTV4-3, V-optics, line-shaped light spot

- Supply voltage: 10 V DC ... 30 V DC (Limit values.)
- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Type of light: visible red light
- Light spot size (distance): 3 mm x 20 mm (40 mm)

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
3 mm 50 mm	PNP	Light switching	Potentiometer, 5 turns	Connector M8, 4-pin	Cd-083	WTV4-3P2271	1046644
	NPN	Light switching	Potentiometer, 5 turns	Cable, 4-wire, 2 m, PVC	Cd-083	WTV4-3N1171	1046898

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WTV4-3, V-optics

- Supply voltage: 10 V DC ... 30 V DC (Limit values.)
- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Light spot size (distance): Ø 10 mm (40 mm)
- Adjustment: potentiometer, 5 turns

Type of light	Sensing range max. <sup>1)</sup>	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			Liefak assiikalainee	Cable, 3-wire, 2 m, PVC	Cd-043	WTV4-3P1341	1028111
		PNP	Light switching	Connector M8, 3-pin	Cd-045	WTV4-3P2141	1028113
Visible red light	Visible 4 mm 50 mm		Light/dark-switching	Connector M8, 4-pin	Cd-083	WTV4-3P2241	1028114
		NPN		Cable, 3-wire, 2 m, PVC	Cd-043	WTV4-3N1341	1028115
			Light switching	Connector M8, 3-pin	Cd-045	WTV4-3N2141	1028116
		PNP	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTV4-3P1321	1029888
Infrared 4 mm 50 mm	4 mm 50 mm	NIDNI	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTV4-3N1321	1029885
	NPN	Light/dark-switching	Connector M8, 4-pin	Cd-083	WTV4-3N2221	1048995	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

• Type of light: visible red light

• Light spot size (distance): Ø 75 mm (1.5 m)

Sensing range max. 1)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		Light awitching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4-3P1330	1028143
		Light switching	Connector M8, 3-pin	Cd-045	WL4-3P2130	1028146
	PNP	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4-3F1330	1028152
			Connector M8, 3-pin	Cd-045	WL4-3F2130	1028155
0.01 m 4.5 m		Light/dark-switching	Connector M8, 4-pin	Cd-083	WL4-3P2230	1028147
		Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4-3N1330	1028148
	NPN		Connector M8, 3-pin	Cd-045	WL4-3N2130	1028151
	INFIN		Cable, 3-wire, 2 m, PVC	Cd-043	WL4-3E1330	1028156
		Dark-switching	Connector M8, 3-pin	Cd-045	WL4-3E2130	1028158

<sup>1)</sup> PL80A.

## WSE4-3

Supply voltage: 10 V DC ... 30 V DC (Limit values.)
 Sensor principle: through-beam photoelectric sensor

• Type of light: visible red light


• Light spot size (distance): Ø 210 mm (2 m)

Sensing range max.	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			Cable, 3-wire, 2 m, PVC	Cd-061	WSE4-3P1330	1028159
		Light switching	Cable, 3-wire, 5 m, PVC	Cd-061	WSE4-3P1430	1029645
	PNP		Connector M8, 3-pin	Cd-069	WSE4-3P2130	1028163
	FINE	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4-3F1330	1028168
0 m 4 m			Connector M8, 3-pin	Cd-069	WSE4-3F2130	1028171
0 111 4 111		Light/dark-switching	Connector M8, 4-pin	Cd-072	WSE4-3P2230	1028160
		Light switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4-3N1330	1028164
	NPN	Light Switching	Connector M8, 3-pin	Cd-069	WSE4-3N2130	1028167
	INFIN	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4-3E1330	1028172
		Dain-Switching	Connector M8, 3-pin	Cd-069	WSE4-3E2130	1028175

# **Dimensional drawings**


Dimensions in mm (inch)

#### WTB4-3, WTV4-3, potentiometer




- ① Standard direction of the material being detected
- 2 Optical axis, sender
- 3 Optical axis, receiver
- ④ Status indicator LED, yellow: Status of received light beam
- $\ensuremath{\mathfrak{D}}$  Status indicator LED green: power on
- 6 Potentiometer
- 7 Threaded mounting hole M3
- 8 Connection

#### WTB4-3, WTV4-3, single teach button




- ① Standard direction of the material being detected
- 2 Optical axis sender
- 3 Optical axis receiver
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- Teach-in button
- 7 Threaded mounting hole M3
- 8 Connection

#### WL4-3



- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 LED indicator orange: status of received light beam
- 4 Status indicator LED green: power on
- **6** Connection

#### **WSE4-3**




- ① Center of optical axis
- 2 LED indicator orange: status of received light beam
- 3 Status indicator LED green: power on
- Threaded mounting hole M3
- ⑤ Connection

## **Characteristic curves**

#### Black-white shift


#### WTB4-3

% of sensing distance



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission


#### WTV4-3, V-optics



- ① Black-white shift 90% / 6%
- ② Distance to the background with transparent objects

WL4-3


Operating reserve in %



- ① REF-IRF-56
- ② PL10F
- ③ PL20A
- 4 PL40A
- ⑤ PL80A


#### **WSE4-3**

Operating reserve




## **Bar diagrams**

## **WTB4-3**




- Sensing range max.
- Sensing range
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission

## WLG4-3 with polarisation filter




- Sensing range
- Sensing range max.
- ① REF-IRF-56
- ② PL10F
- ③ PL20A
- 4 PL40A
- ⑤ PL80A

## WTB4-3, line-shaped light spot



- ① Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on black, 6 % remission


#### **WSE4-3**




## **Light spot diameter**


## WTB4-3, line-shaped light spot

Lightspot: line width



#### WTV4-3, V-optics, line-shaped light spot






## Minimum detectable object


## WTB4-3, line-shaped light spot

Width of object



## WTB4-3, line-shaped light spot

Width of object




#### Cd-043

# 


## Cd-045

#### Cd-061



- ① Sender
- 2 Receiver

#### Cd-069




- ① Sender
- 2 Receiver


#### Cd-083



## Cd-093



#### Cd-072



- ① Sender
- ② Receiver

#### Cd-094



# **Recommended accessories**

## Plug connectors and cables

## Connecting cable (female connector-open), PVC

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled	ductor heads	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	3, 4-pin, straight ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled		2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
			5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

## Male connector (ready to assemble)M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0804-G	6037323

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

## Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
*	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861

F

PTFE-coated photoelectric sensors withstand the harshest environments















## **Additional information**

Detailed technical dataF-251
Ordering informationF-252
Dimensional drawings F-252
Characteristic curves F-252
Bar diagramsF-253
Connection diagram F-253
Recommended accessories F-253



The W4-3 photoelectric sensors in a Teflon® shell coating are resistant to harsh chemicals. Both the housing and cable

are Teflon coated, making them ideal for wet, harsh environments in the food and beverage industry.

## At a glance

- · Sensor and cable have a rugged Teflon coating for use in the most aggressive environments
- · Suitable for use in the food and beverage industry
- Sensing range adjustment via teach
- Background suppression and through-beam types available

## Your benefits

- High cost savings since neither the sensor nor the cable requires a protective barrier
- · Less machine downtime due to a long sensor life that withstands all cleaning and process agents

#### → www.mysick.com/en/W4-3\_PTFE

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

#### **Features**

	WT4-3 PTFE	WSE4-3 PTFE
Sensor principle	Photoelectric proximity sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	-
Dimensions (W x H x D)	22 mm x 42 mm x 21.8 mm	
Housing design (light emission)	Rectangular	
Sensing range max.	4 mm 120 mm <sup>1)</sup>	0 m 3 m
Sensing range	15 mm 120 mm <sup>1)</sup>	0 m 2.5 m
Type of light	Visible red light	
Light source 2)	PinPoint LED	
Light spot size (distance)	Ø 7 mm (50 mm)	Ø 210 mm (2 m)
Wave length	650 nm	
Adjustment	Cable, Single teach-in button	-

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	WT4-3 PTFE	WSE4-3 PTFE
Supply voltage 1)	10 V DC 30 V DC	
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>	
Power consumption	≤ 20 mA <sup>3)</sup>	≤ 20 mA <sup>4) 5)</sup>
Output type	PNP / NPN (depending on type)	
Switching mode	Light switching	Light switching / Dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA	
Response time 6)	< 0.5 ms	
Switching frequency 7)	1,000 Hz	
Connection type 8)	Cable, 4-wire, 5 m, PVC/PTFE coating	
Circuit protection	A <sup>9)</sup> , C <sup>10)</sup> , D <sup>11)</sup>	
Protection class	III	
Weight	30 g	
Housing material	PTFE	
Optics material	PMMA	
Enclosure rating	IP 68 / IP 69K	
Test input sender off	-	"TEST" to 0 V
Ambient operating temperature	-40 °C +60 °C	
Ambient storage temperature	-40 °C +75 °C	

<sup>1)</sup> Limit values.

F

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Sender.

<sup>5)</sup> Receiver.

 $<sup>^{\</sup>rm 6)}$  Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> C = interference suppression.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

#### **Ordering information**

Other models available at www.mysick.com/en/W4-3\_PTFE

#### WT4-3 PTFE

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Adjustment: cable, single teach-in button
- Connection: cable, 4-wire, 5 m, PVC/PTFE coating

Sensing range max. 1)	Output type	Switching mode	Connection diagram	Model name	Part no.
4 mm 120 mm	PNP	Light switching	Cd-093	WTB4T-3P1264	1028091
	NPN	Light switching	Cd-093	WTB4T-3N1264	1028092

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WSE4-3 PTFE


- Sensor principle: through-beam photoelectric sensor
- Connection: cable, 3-wire, 5 m, PVC/PTFE coating

	Sensing range max.	Output type	Switching mode	Connection diagram	Model name	Part no.
	0 m 3 m	PNP	Light switching	Cd-061	WSE4T-3P1430	1029646
			Dark-switching	Cd-061	WSE4T-3F1430	1029647
		NPN	Dark-switching	Cd-061	WSE4T-3E1430	1029648

#### **Dimensional drawings**

Dimensions in mm (inch)

#### WTB4T-3, PTFE




- ${\bf 1\!\!\!\! D} \; {\rm LED} \; {\rm signal} \;$
- 2 Mounting hole, Ø 4.3 mm
- ④ Optical axis, receiver
- ⑤ Optical axis, sender

#### **Characteristic curves**


#### **WSE4T-3 PTFE**






#### **Bar diagrams**

#### **WSE4T-3 PTFE**



#### **Connection diagram**

#### Cd-061



- ① Sender
- 2 Receiver

#### **Recommended accessories**

Plug connectors and cables

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

Cd-093

Teach

#### Male connector (ready to assemble)M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0804-G	6037323

→ For additional accessories, please see page L-861



Reliable detection of transparent objects



#### **Additional information**

Detailed technical dataF-255
Ordering informationF-256
Dimensional drawingsF-256
Characteristic curvesF-256
Bar diagramsF-257
Connection diagram F-257
Recommended accessories F-257

#### **Product description**

The WLG4-3 photoelectric retro-reflective sensor reliably detects transparent objects such as glass. Its small size is ideal for applications with limited mounting space. Adjusting these sensors can

be done with the click of an easy-to-use teach-in pushbutton. Plus, these sensors don't require any brackets, making them easy to mount directly to the machine even in tight spaces.

#### At a glance

- Fast and reliable setup via teach-in pushbutton
- Continuous threshold adaptation (AutoAdapt) technology to detect objects in changing conditions such as temperature, contamination and reflector wear
- Versions without polarizing filters to better detect depolarizing objects such as PET bottles, CD sleeves and shrink-wrapped, glossy objects

#### Your benefits

- · Reliable and quick setting via the push of a button
- · Flat housing design eliminates alignment or mounting brackets, which saves time and money
- · Low-cost machine integration due to small dimensions that enable mounting in areas with space restrictions
- · Quick and easy setup due to highly visible intensive light spot
- · The PinPoint LED's well-defined, intense light spot simplifies alignment
- Nearly all transparent objects can be reliably detected

#### → www.mysick.com/en/W4-3\_Glass

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## F

#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Dimensions (W x H x D)	16 mm x 39.5 mm x 12 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0.01 m 4.5 m
Sensing range <sup>1)</sup>	0.02 m 3.5 m
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	Ø 75 mm (1.5 m)
Wave length	650 nm
Adjustment	Cable, Single teach-in button / Single teach-in button (depending on type)
Continuous threshold adaption (AutoAdapt)	
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple 2)	< 5 V <sub>pp</sub>
Power consumption 3)	≤ 20 mA
Output type	PNP / NPN (depending on type)
Switching mode	Light switching / Dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	< 0.5 ms
Switching frequency 5)	1,000 Hz
Angle of reception	Approx. 30°
Attenuation along light beam	> 8 %
Connection type	Cable, 2 m $^{\rm 6)}$ / Male connector, M8 / Cable with connector, M12, 150 mm $^{\rm 6)}$ (depending on type)
Circuit protection	A <sup>7)</sup> , C <sup>8)</sup> , D <sup>9)</sup>
Protection class	III
Weight	30 g
Polarisation filter	V
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 66, IP 67
Ambient operating temperature	-40 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

<sup>1)</sup> Limit values.

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{2)}\,\</sup>mbox{May}$  not exceed or fall short of  $\mbox{V}_{\mbox{\scriptsize S}}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

#### **Ordering information**

Other models available at www.mysick.com/en/W4-3\_Glass

#### WLG4-3 with polarisation filter

#### Polarisation filter:


Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
		Light switching	Cingle teach in hutten	Cable, 3-wire, 2 m, PVC	Cd-043	WLG4-3P1332	1042844
			Single teach-in button	Connector M8, 3-pin	Cd-045	WLG4-3P2132	1029567
	PNP	PNP	Single teach-in button	Connector M8, 3-pin	Cd-045	WLG4-3F2132	1028127
0.01 m 4.5 m		Dark-switching	Cable, Single teach-in button	Connector M8, 4-pin	Cd-092	WLG4-3F2234	1028130
				Cable with connector M12, 4-pin, 150 mm, PVC	Cd-092	WLG4-3F3434	1043683
	NIDNI	I Dark-switching	Single teach-in button	Cable, 3-wire, 2 m, PVC	Cd-043	WLG4-3E1332	1028131
	NPN			Connector M8, 3-pin	Cd-045	WLG4-3E2132	1028132

<sup>1)</sup> PL80A.

#### **Dimensional drawings**

Dimensions in mm (inch)

#### WLG4-3




- ① Center of optical axis, sender
- ② Center of optical axis, receiver
- $\ensuremath{\mathfrak{B}}$  LED indicator orange: status of received light beam
- 4 Status indicator LED green: power on
- 6 Connection
- 7 Teach-in button

#### **Characteristic curves**

#### Operating reserve

#### WLG4-3


Operating reserve in %



- ① REF-IRF-56
- ② PL10F
- ③ PL20A
- 4 PL40A
- ⑤ PL80A

#### **Bar diagrams**

#### WLG4-3



Sensing range

Sensing range max.

- ① REF-IRF-56
- ② PL10F
- ③ PL20A
- 4 PL40A
- ⑤ PL80A

#### **Connection diagram**

# Cd-043 Cd-045 Cd-092 $\begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \begin{array}{c} \\ \end{array}\\ \end{array} \end{array} \end{array} \begin{array}{c} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \begin{array}{c} \\ \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c} \end{array} \begin{array}{c} \\ \end{array} \begin{array}{c}$

#### **Recommended accessories**

Plug connectors and cables

#### Connecting cable (female connector-open), PVC

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled	ductor heads	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
100	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
O.	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1204-W	6007303

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0804-G	6037323
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N08N for universal clamp bracket	BEF-KHS-N08N	2051616

#### Reflectors

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861

F











#### Additional information

Additional information
Detailed technical dataF-261
Ordering informationF-262
Dimensional drawingsF-266
Characteristic curvesF-267
Bar diagramsF-268
Connection diagram F-269
Recommended accessories F-270

#### **Product description**

The W4S-3 family of photoelectric sensors offers best-in-class performance in a slim housing design. Universal use of the latest SIRIC® and PinPoint LED technologies provide maximum reliability in the detection of all objects, including

transparent and shiny objects like blisters, e-cards and aluminum cans. Optical axes on the flat side enable simple, space-saving integration in the machine environment - even without separate mounting brackets.

#### At a glance

- Best background suppression sensor in its class
- Universal use of PinPoint LED technology in all models
- · BGS proximity sensor with laser-like light spot for precise detection tasks
- Reliable setting via 5-turn potentiometer, teach-in pushbutton, teach-in via cable or IO-Link
- · Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

#### **Your benefits**

- Application versatility due to reliable detection of shiny, transparent or jetblack objects
- · Very quick and easy alignment due to the highly visible, intense PinPoint LED light spot
- Rugged mounting system with M3 threaded metal inserts reduces maintenance costs due to a long service life
- · Background suppression sensors with a laser-like light spot reduce costs and installation of additional protective measures by replacing laser sensors
- IO-Link provides easy data access from the PLC
- Quick and easy configuration
- Quick and easy integration using function blocks

#### → www.mysick.com/en/W4S-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



#### **Detailed technical data**

#### **Features**

	WTB4S-3	WL4S-3	WSE4S-3
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Autocollimation	-
Dimensions (W x H x D)	12.2 mm x 41.8 mm x 17.3 mr	n	
Housing design (light emission)	Rectangular		
Sensing range max.	4 mm 180 mm <sup>1)</sup> (depending on type)	0 m 5 m <sup>2)</sup> (depending on type)	0 m 5 m
Sensing range	10 mm 180 mm <sup>1)</sup> (depending on type)	0 m 3 m <sup>2)</sup> (depending on type)	0 m 4.5 m
Type of light	Visible red light		
Light source 3)	PinPoint LED <sup>2.0</sup>		
Wave length	650 nm / 660 nm (depending on type)	650 nm	
Adjustment	Potentiometer, 5 turns, Cable, Single teach-in button (depending on type)	Single teach-in button	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

	WTB4S-3	WL4S-3	WSE4S-3
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>		
Power consumption	≤ 20 mA <sup>3)</sup>		≤ 20 mA <sup>4) 5)</sup>
Output type	PNP / NPN (depending on type	)	
Output function	Complementary		-
Switching mode	Light switching / Dark-switching	g/Light/dark-switching (dependi	ng on type)
Output current I <sub>max.</sub>	≤ 100 mA		
Response time 6)	< 0.5 ms		
With IO-Link 8)	< 0.65 ms	-	
Switching frequency 7)	1,000 Hz		
Connection type	Cable, 2 m <sup>9)</sup> / Male connector, (depending on type)	M8 / Cable with connector, M12	, 150 mm <sup>9)</sup>
Circuit protection	A $^{10)}$ , C $^{11)}$ , D $^{12)}$		
Protection class	III		
Weight	30 g		40 g
Polarisation filter	-	V	-
IO-Link	-/ <b>✔</b> (COM2)	-	
Housing material	ABS		
Optics material	PMMA		

F

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $T_{_{A}}$  = +25 °C.

	WTB4S-3	WL4S-3	WSE4S-3
Enclosure rating	IP 66, IP 67		
Test input sender off	-		"Test" to 0 V
Ambient operating temperature	-40 °C +60 °C		
Ambient storage temperature	-40 °C +75 °C		

<sup>1)</sup> Limit values.

#### **Ordering information**

Other models available at www.mysick.com/en/W4S-3

#### **WTB4S-3**

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

Sensing range max. 1)	Light spot size (distance)	Output type	Adjustment	Switching mode	Connection	Con- nection diagram	Model name	Part no.
				Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3P1331	1042059
			Potentiometer,	Light Switching	Connector M8, 3-pin	Cd-045	WTB4S-3P2131	1042056
			5 turns	Dark-switching	Connector M8, 3-pin	Cd-045	WTB4S-3F2131	1042060
				Light/dark- switching	Connector M8, 4-pin	Cd-083	WTB4S-3P2231	1042057
		PNP		Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3P1332	1052284
			Single teach-in	Light Switching	Connector M8, 3-pin	Cd-045	WTB4S-3P2132	1042053
	Ø 2.5 mm		button	Light/dark- switching	Connector M8, 4-pin	Cd-083	WTB4S-3P2232	1054282
4 mm			Cable, Single teach-in button $^{2)}$	Light switching	Connector M8, 4-pin	Cd-092	WTB4S-3P2234	1042050
120 mm	(50 mm)			Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3N1331	1042062
			Potentiometer,	Light Switching	Connector M8, 3-pin	Cd-045	WTB4S-3N2131	1042061
			5 turns	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3E1331	1042064
				Light/dark- switching	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3N1131	1042063
		NPN	Single teach-in	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3N1332	1042055
			button	Light Switching	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3N1132	1051563
			Cable, Single teach-in button <sup>2)</sup>	Light switching	Cable, 4-wire, 2 m, PVC	Cd-093	WTB4S-3N1134	1042052
			Single teach-in button	Light/dark- switching	Connector M8, 4-pin	Cd-083	WTB4S-3N2232	1051872

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Sender.

<sup>5)</sup> Receiver.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 8)}$  With light/dark ratio 1:1 in switching mode. Different values possible in COM2 mode.

 $<sup>^{9)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{10)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.

<sup>&</sup>lt;sup>12)</sup> D = outputs overcurrent and short-circuit protected.

 $<sup>^{2)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

Sensing range max. 1)	Light spot size (distance)	type	Adjustment	Switching mode	Connection	Con- nection diagram	Model name	Part no.
				Light awitching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3P1361	1042043
			Potentiometer, 5 turns	Light switching	Connector M8, 3-pin	Cd-045	WTB4S-3P2161	1042040
		PNP		Dark-switching	Connector M8, 3-pin	Cd-045	WTB4S-3F2161	1042044
4 mm 180 mm	Ø 6.5 mm (150 mm)			Light/dark- switching	Connector M8, 4-pin	Cd-083	WTB4S-3P2261	1042041
				Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3N1361	1042046
		NPN Pot	Potentiometer, 5 turns		Connector M8, 3-pin	Cd-045	WTB4S-3N2161	1042045
			o tarrio	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3E1361	1042047

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WTB4S-3 health output

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

range	Light spot size (distance)	type	Adjustment	Switching mode	Connection	Con- nection diagram	Model name	Part no.
4 mm 120 mm	Ø 2.5 mm (50 mm)	NPN	Potentiometer, 5 turns	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WTB4S-3W1331	1050573

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



#### WTB4SC-3 IO-Link

- Sensor principle: photoelectric proximity sensor
- **Detection principle:** background suppression
- Light spot size (distance): Ø 6.5 mm (150 mm)
- Output type): PNP
- Switching mode: light/dark-switching (parametrisable via IO-Link)

Sensing range max. <sup>1)</sup>	Adjust- ment	IO-Link	Advanced functions	Connection	Con- nection diagram	Model name	Part no.
		Standard functions	-	Connector M8, 4-pin	Cd-098	WTB4SC-3P2262	1042033
	Cable, Single teach-in button	Standard functions, advanced function	Timer, False Tripping Suppression (Debouncing)			WTB4SC-3P2262A70	1067756
4 mm 180 mm			High-Speed Counter, False Tripping Suppression (Debouncing)			WTB4SC-3P2262A71	1067757
			Time Stamp, False Tripping Suppression (Debouncing)			WTB4SC-3P2262A91	1067758

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

F

 $<sup>^{\</sup>rm 2)}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

#### **WL4S-3**

• Sensor principle: photoelectric retro-reflective sensor

• **Detection principle:** autocollimation

Sensing range max. 1)	Light spot size (distance)	Output type	Adjustment	Switching mode	Connection	Con- nection diagram	Model name	Part no.
				Light switching	Connector M8, 3-pin	Cd-045	WL4S-3P2130	1042069
				Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3F1330	1042068
		PNP	-	Dark-Switching	Connector M8, 3-pin	Cd-045	WL4S-3F2130	1042065
0 m 4 m	Ø 45 mm (1.5 m)			Light/dark- switching	Connector M8, 4-pin	Cd-083	WL4S-3P2230	1042066
		NPN	-	Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3N1330	1042073
				Doulcouitabing	Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3E1330	1042072
				Dark-switching	Connector M8, 3-pin	Cd-045	WL4S-3E2130	1042071
			Single teach-in	Light switching	Connector M8, 3-pin	Cd-045	WL4S-3P2132	1042077
				Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3F1332	1042076
		PNP	button	Dark-Switching	Connector M8, 3-pin	Cd-045	WL4S-3F2132	1042074
0 m	Ø 45 mm			Light/dark- switching	Connector M8, 4-pin	Cd-083	WL4S-3P2232	1042078
5 m	(1.5 m)			Light switching	Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3N1332	1042082
		NPN	Single teach-in button		Cable, 3-wire, 2 m, PVC	Cd-043	WL4S-3E1332	1042081
				Dark-switching	Connector M8, 3-pin	Cd-045	WL4S-3E2132	1042080
					Cable, 4-wire, 2 m, PVC	Cd-107	WL4S-3W1132	1042083

1) PL80A.



• Sensor principle: photoelectric retro-reflective sensor

Detection principle: autocollimation
 Light spot size: Ø 2 mm (20 mm)

• Output type: PNP

Switching mode: light/dark-switching
 Switching frequency: 2,000 Hz

• Response time: 0.25 ms

Sensing range max. <sup>1)</sup>	Adjust- ment	IO-Link	Advanced functions	Connection	Con- nection diagram	Model name	Part no.
		Standard functions	-			WL4SC-3P2232	1065315
	Cable,		Timer, False Tripping Suppression (Debouncing)		Cd-098	WL4SC-3P2232A70	1067760
0 mm 70 mm	- 0 -	Standard functions, Advanced functions	High-Speed Counter, False Tripping Suppression (Debouncing)	Connector M8, 4-pin		WL4SC-3P2232A71	1067761
			Time Stamp, False Tripping Suppression (Debouncing)			WL4SC-3P2232A91	1067762

<sup>1)</sup> PL80A.

#### WL4S-3 health output

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation

range	Light spot size (distance)	type	Adjustment	Switching mode	Connection	Con- nection diagram	Model name	Part no.
0 m 5 m	Ø 45 mm (1.5 m)	PNP	Single teach-in button	Dark-switching	Connector M8, 4-pin	Cd-107	WL4S-3V2232	1042079

<sup>1)</sup> PL80A.

#### WSE4S-3

• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (distance)	type	Switching mode	Connection	Con- nection diagram	Model name	Part no.	
			Light switching	Connector M8, 3-pin	Cd-069	WSE4S-3P2130	1052892	
		PNP	PNP	Dark awitahing	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3F1330	1052879
0 m	Ø 50 mm				Dark-switching	Connector M8, 3-pin	Cd-069	WSE4S-3F2130
5 m	(2 m)	(2 m)		Light switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3N1330	1052872
		NPN	Danis authoriza	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3E1330	1052867	
			Dark-switching	Connector M8, 3-pin	Cd-069	WSE4S-3E2130	1052876	



WSE4S-3, IO-Link
 Sensor principle: through-beam photoelectric sensor

• Light spot size: Ø 50 mm (2 m)

Output type: PNP


• Switching mode: light/dark-switching

•	Connection:	connector	M8, 4-pin

Sensing range max.	IO-Link	Advanced functions	Connection	Con- nection diagram	Model name	Part no.
	Standard functions	-			WSE4SC-3P2230	1067767
	Standard functions, Advanced functions	Timer, False Tripping Suppression (Debouncing)	Connector M8, 4-pin	Cd-268	WSE4SC-3P2230A70	1067768
0 m 5 m		High-Speed Counter, False Tripping Suppression (Debouncing)			WSE4SC-3P2230A71	1067769
		Time Stamp, False Tripping Suppression (Debouncing)			WSE4SC-3P2230A91	1067770


F

#### WTB4S-3, potentiometer




- $\ensuremath{\mbox{\scriptsize $0$}}$  Standard direction of the material being detected
- 2 Optical axis receiver
- 3 Optical axis sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Potentiometer
- 7 Threaded mounting hole M3
- 8 Connection

#### WTB4S-3, Single teach-in button




- ① Standard direction of the material being detected
- 2 Optical axis receiver
- 3 Optical axis sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Teach-in button
- Threaded mounting hole M3
- 8 Connection

#### WL4S-3, WSE4S-3, potentiometer



- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam

#### WL4S-3, WLG4S-3, single teach-in button



- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- 4 Status indicator LED green: power on
- ⑤ LED indicator orange: status of received light beam
- 6 Teach-in button


## F

#### **Characteristic curves**

#### Black-white shift

#### WTB4S-3, 120 mm


% of sensing distance



- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WTB4S-3, 180 mm

% of sensing distance




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### Operating reserve

#### **WL4S-3**


#### Operating reserve



- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20F
- ⑤ PL10F
- 6 REF-IRF-56


#### **WSE4S-3**

#### Operating reserve




#### **Bar diagrams**

#### WTB4S-3, 120 mm




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB4S-3, 180 mm



- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WL4S-3, 4 m




- Sensing range
- Sensing range max.
- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20F
- ⑤ PL10F
- @ REF-IRF-56

#### **WSE4S-3**



- Sensing range typ. max
- Sensing range

#### WL4S-3, 5 m



- Sensing range
- Sensing range max.
- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ③ REF-IRF-56

## F

## Connection diagram


#### Cd-043

## → blu - (M) → blk Q

#### Cd-045




#### Cd-061



- ① Sender
- ② Receiver

#### Cd-069



- ②

  | bin 1 + (L+
  | blu 3 (M)
  | blk 4 Q
- ① Sender
- ② Receiver

#### Cd-083

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
 & \text{wht} & 2 \\
\hline
 & \text{blu} & 3 \\
\hline
 & \text{-(M)}
\end{array}$$

#### Cd-093


## 

#### Cd-094

#### Cd-098

#### Cd-107

#### Cd-268



$$\begin{array}{c|c}
\hline
2 \\
\hline
brin 1 \\
\hline
wht 2 \overline{Q} \\
\hline
blu 3 \\
\hline
blk 4 Q/C
\end{array}$$

- ${\small \textcircled{1}} \ \mathsf{Sender}$
- 2 Receiver

#### **Recommended accessories**

#### Plug connectors and cables

#### Connecting cable (female connector-open), PVC

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled	ductor heads	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
//	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled		5 m, 4-wire	IP 67	DOL-0804-W05M	6009873
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	· ·	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	· · ·	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
13	M12, 4-pin, angled		5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

#### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm $$	PL10F	5311210

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861



transparent objects





Slim photoelectric sensors reliably detect







#### Additional information

Additional information
Detailed technical dataF-273
Ordering informationF-274
Dimensional drawingsF-275
Characteristic curvesF-275
Bar diagramsF-275
Connection diagram F-276
Recommended accessories F-276



The WLG4S-3 is a retro-reflective sensor enclosed in a slim housing that reliably detects transparent objects. Even small gaps between objects, highly transparent thin films, and vials with flow marks and severe lens defects can be reliably detected. Setting the sensor requires a single press of the teach-in pushbutton. The sensor reliably adjusts for any changes to environmental conditions such as temperature, dust or dirt. The single-lens autocollimation system "sees" through even the smallest of openings. The Pin-Point LED's small but intense light spot enables quick and easy alignment even when using the smallest reflectors. Plus, variants with IO-Link provide continuous diagnostics data.

#### At a glance

- Continuous threshold adaption (AutoAdapt) of the switching threshold compensates for environmental changes
- Single-lens autocollimation optics
- Simple setting either via teach-in pushbutton, cable or IO-Link
- PinPoint LED technology with a small, highly visible, well-defined light spot enables high reserve levels when using small reflectors
- · Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

#### Your benefits

- · Optimal detection of any kind of transparent object
- Quick and easy operation via the push of a button - automatic setting of the correct switching threshold
- Less downtime due to a Continuous threshold adaption (AutoAdapt) which compensates for changing environmental conditions, including temperature, dust and drift effects
- The well-defined, highly visible intense light spot provides quick and reliable alignment
- · IO-Link provides easy data access from the PLC
- · Quick and easy configuration
- · Quick and easy integration using function blocks
- · Easy device replacement and identification

#### www.mysick.com/en/W4S-3\_Glass

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## F

#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	12.2 mm x 41.8 mm x 17.3 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0.01 m 5 m
Sensing range 1)	0 m 3 m
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	Ø 45 mm (1.5 m)
Wave length	650 nm
Adjustment	Cable, Single teach-in button / Single teach-in button (depending on type)
Continuous threshold adaption (AutoAdapt)	V
Special feature	Detection of transparent objects

<sup>1)</sup> PL80A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>
Power consumption	≤ 20 mA <sup>3)</sup>
With IO-Link	≤ 30 mA <sup>3)</sup>
Output type	PNP / NPN (depending on type)
Switching mode	Light switching / Dark-switching / Light/dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	< 0.5 ms
Switching frequency 5)	1,000 Hz
Angle of reception	30°
Attenuation along light beam	> 8 %
Connection type	Male connector, M8 / Cable, 2 m <sup>6)</sup> (depending on type)
Circuit protection	A 7, C 8, D 9
Protection class	III
Weight	30 g
Polarisation filter	<i>v</i>
IO-Link	V
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 66, IP 67
Ambient operating temperature	-40 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

<sup>1)</sup> Limit values.

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at T  $_{\!\scriptscriptstyle \Delta}$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>8)</sup> C = interference suppression.

 $<sup>^{\</sup>rm 9)}$  D = outputs overcurrent and short-circuit protected.

#### **Ordering information**

Other models available at www.mysick.com/en/W4S-3\_Glass

#### WLG4S-3

• Detection principle: autocollimation

• Polarisation filter: ✓

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0.01 m 5 m		Light switching	Cable, Single teach-in button	Connector M8, 4-pin	Cd-092	WLG4S-3P2234	1052999
	PNP	Dark-switching	Cable, Single teach-in button	Connector M8, 4-pin	Cd-092	WLG4S-3F2234	1042084
		Light/dark- switching	Single teach-in button	Connector M8, 4-pin	Cd-083	WLG4S-3P2232	1044186
	NPN	Light switching	Single teach-in button	Cable, 3-wire, 2 m, PVC	Cd-044	WLG4S-3N1332	1046111
		Dark-switching	Cable, Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-044	WLG4S-3E1134	1042085

<sup>1)</sup> PL80A.

#### WLG4S-3 Alarm output

• Detection principle: autocollimation

• Polarisation filter: ✓

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0.01 m 5 m	PNP Dark-switching	Dork quitabing	Cingle to only in booth on	Cable, 4-wire, 2 m, PVC	Cd-107	WLG4S-3V1132	1055895
		Single teach-in button	Connector M8, 4-pin	Cd-107	WLG4S-3V2232	1042087	
	NPN	Dark-switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-107	WLG4S-3W1132	1042086

<sup>&</sup>lt;sup>1)</sup> PL80A.



## WLG4S-3 IO-Link

• Detection principle: autocollimation

• Output type: PNP

• Switching mode: light/dark-switching


Polarisation filter:

Sensing range max. 1)	Adjust- ment	IO-Link	Advanced functions	Connection	Connection diagram	Model name	Part no.
		Standard functions	=			WLG4SC-3P2232	1057177
Single 0.01 m 5 m teach-in button		Timer, False Tripping Suppression (Debouncing)			WLG4SC-3P2232A70	1067763	
	teach-in	-in Standard functions,	High-Speed Counter, False Tripping Suppression (Debouncing)	Connector M8, 4-pin	Cd-098	WLG4SC-3P2232A71	1067765
			Time Stamp, False Tripping Suppression (Debouncing)			WLG4SC-3P2232A91	1067766

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### Dimensions in mm (inch)

#### WLG4S-3, single teach-in button




- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- 4 Status indicator LED green: power on
- ⑤ LED indicator orange: status of received light beam
- Teach-in button

## F

#### **Characteristic curves**

#### WLG4S-3, 5 m

## Operating reserve



- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- 6 REF-IRF-56

#### Bar diagrams

#### WLG4S-3, 5 m

						_			_
1	0				3.0	0		5.0	
2	0			2.0			4.0		]
3	0		1.3	2	.2				
4	0	1.	2	1.6					1
<b>(5)</b>	0 0.5	0.8							1
	)	1		2	2	3		1	5
							Distance	e in m (fe	et

- Sensing range
- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F

Sensing range max.

#### **Connection diagram**

Cd-044	Cd-083	Cd-092	Cd-098
— bin + (L+) — blu - (M)	$ \begin{array}{c c}  & \text{brn} & 1 \\  & \text{wht} & 2 \\ \hline \end{array} $	$\frac{\text{brn}}{\downarrow} \frac{1}{\downarrow} + (\text{L+})$ $\frac{\text{whtl}}{\downarrow} \frac{2}{\downarrow} \text{ Teach}$	$\frac{1}{\frac{\text{brn}}{2}} + (\text{L+})$
→ blk! Q		blu! 3 - (M) blk! 4 0	$\frac{\text{blu} \cdot 3}{1} - (M)$ $\frac{\text{blk} \cdot 4}{1} = O/C$
i			

#### Cd-107

#### **Recommended accessories**

#### Plug connectors and cables

#### Connecting cable (female connector-open)M8, 4-pin, PVC

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873	

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N02 for universal clamp bracket	BEF-KHS-N02	2051608
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607
(6)	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N08N for universal clamp bracket	BEF-KHS-N08N	2051616

#### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm $$	P250F	5308843
2	FIVIIVIA/ ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Plastic Fine triple, chemically resistant, screw connection, 18 mm x 18 mm		5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm		5308844
	Plastic	Plastic Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm		5326089
e	DMMA /ADC	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape


Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861

W4















#### **Additional information**

7 total till till till till till till till t
Detailed technical dataF-279
Ordering informationF-280
Dimensional drawingsF-281
Characteristic curvesF-282
Bar diagramsF-283
Light spot diameterF-284
Connection diagram F-286
Recommended accessories F-287

#### **Product description**

Maximum performance for handling demanding detection tasks involving tiny objects. With its precise laser light spot, the W4SL-3 miniature product family sets new standards by providing high optical light immunity from undesired background reflections and immunity to ambient light - even from modern energy-saving lamps. The combination of SICK's proprietary laser and SIRIC®

technologies reduces incorrect switching to minimize machine downtime, reducing the variety of devices and saving on storage costs. The photoelectric sensors also provide an IO-Link interface for initial system performance diagnostics. Furthermore, IO-Link permits the integration of additional functions such as meters directly into the sensor. There is no need for complex control programming.

#### At a glance

- Precise laser light spot, laser class 1
- Teach-in pushbutton can be switched between detection of transparent and non-transparent objects
- Sensing ranges between 25 mm and 60 m
- Latest SIRIC® and laser technologies with second emitter LED to provide outstanding background suppression and ambient light immunity
- · Choice of adjustment via teach-in button, potentiometer, cable, or IO-Link

#### Your benefits

- Precise laser light spot for highly accurate switching behavior
- High optical ambient light immunity reduces incorrect switching and thus machine downtime, even when modern energy-saving lamps are used
- The highest degree of machine design flexibility BGS (background suppression) eliminates the effect of undesired background reflections. In addition, autocollimation allows detection through small drilled holes
- · One device for detecting both transparent objects and the smallest nontransparent objects, thus reducing the variety of sensors and saving on storage costs
- · IO-Link facilitates initial system performance diagnostics and uses additional sensor functions (optional) to reduce complex control programming

#### www.mysick.com/en/W4SL-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



#### **Detailed technical data**

#### **Features**

	WTB4SL-3	WL4SL-3	WSE4SL-3
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Autocollimation	-
Dimensions (W x H x D)	12.2 mm x 41.8 mm x 17.3 mm	n	
Housing design (light emission)	Rectangular		
Mounting hole	M3		
Sensing range max.	25 mm 300 mm <sup>1)</sup>	0 m 12 m <sup>2)</sup>	0 m 60 m
Sensing range	25 mm 300 mm <sup>1)</sup>	0 m 8 m $^{2)}$	0 m 50 m
Type of light	Visible red light		
Light source 3)	Laser		
Light spot size (distance)	Ø 1 mm (170 mm)	Ø 1 mm (500 mm)	
Wave length	650 nm		
Laser class 4)	1		
Adjustment	Potentiometer, 5 turns	Single teach-in button / Cable, Single teach-in button <sup>5)</sup> (depending on type)	Single teach-in button
Special feature	-	IO-Link	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

	WTB4SL-3	WL4SL-3	WSE4SL-3		
Supply voltage 1)	10 V DC 30 V DC				
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>				
Power consumption 3)	≤ 30 mA				
Output type	PNP / NPN (depending on type)				
Output function	Complementary				
Switching mode	Light/dark-switching 4) / Dark-switching 5) (depending on type)				
Output current I <sub>max.</sub>	≤ 100 mA				
Response time 6)	≤ 0.5 ms				
Switching frequency 7)	1,000 Hz				
Connection type	Cable, 2 m <sup>8)</sup> / Male connector,	M8 / Cable with connector, M8,	120 mm <sup>8)</sup> (depending on type)		
Circuit protection	A $^{9)}$ , B $^{10)}$ , C $^{11)}$				
Protection class	III				
Weight	100 g				
Polarisation filter	-	<b>✓</b>	-		
IO-Link	-	-/✔ (COM2) (depending on type)	-		
Housing material	Bayblend				
Optics material	PMMA				

F

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life 50,000 h at  $T_A$  = +25 °C.

 $<sup>^{\</sup>rm 4)}\,{\rm EN60825\text{-}1\text{:}2008\text{-}05}$  & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11

<sup>5)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

	WTB4SL-3	WL4SL-3	WSE4SL-3
Enclosure rating	IP 66, IP 67		
Ambient operating temperature	-10 °C +50 °C		
Ambient operating temperature extended <sup>12)</sup> <sup>13)</sup>	-30 °C +55 °C		
Ambient storage temperature	-30 °C +70 °C		

<sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

#### **Ordering information**

Other models available at www.mysick.com/en/W4SL-3

#### WTB4SL-3

• Sensor principle: photoelectric proximity sensor

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
		NP Light/dark-switching <sup>2)</sup>	Potentiometer, 5 turns	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4SL-3P1161	1058239
	PNP			Connector M8, 4-pin	Cd-083	WTB4SL-3P2261	1058237
25 mm				Cable with connector M8, 4-pin, 120 mm, PVC	Cd-083	WTB4SL-3P3261	1058238
300 mm	300 mm	NPN Light/dark-switching <sup>2)</sup>	Potentiometer, 5 turns	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4SL-3N1161	1058242
NPN	NPN			Connector M8, 4-pin	Cd-083	WTB4SL-3N2261	1058240
				Cable with connector M8, 4-pin, 120 mm, PVC	Cd-083	WTB4SL-3N3261	1058241

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL4SL-3

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
			Single teach-in button	Connector M8, 4-pin	Cd-083	WL4SL-3P2232	1061561
	PNP	Light/dark-switching <sup>2)</sup>		Cable with connector M8, 4-pin, 120 mm, PVC	Cd-083	WL4SL-3P3232	1061563
0 m 12 m	Dark-switching <sup>3)</sup>	Cable, Single teach-in button 4)	Connector M8, 4-pin	Cd-195	WL4SL-3F2234	1061562	
			Cable with connector M8, 4-pin, 120 mm, PVC	Cd-195	WL4SL-3F3234	1061564	
	Light/dark-switching 2)	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WL4SL-3N1132	1061565	
	NPN	Dark-switching 3)	Cable, Single teach-in button 4)	Cable, 4-wire, 2 m, PVC	Cd-212	WL4SL-3E1134	1061566

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

<sup>&</sup>lt;sup>5)</sup> Q = dark-switching.

<sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{\</sup>mbox{\scriptsize 11)}}$  C = interference suppression.

 $<sup>^{12)}</sup>$  As of T<sub>a</sub> = 50 °C, a max. supply voltage V<sub>max.</sub> = 24 V and a max. load current I<sub>max.</sub> = 50 mA is permitted.

<sup>&</sup>lt;sup>13)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

<sup>2)</sup> Q = light-switching.

<sup>&</sup>lt;sup>2)</sup> Q = light-switching.

 $<sup>^{3)}</sup>$  Q = dark-switching.

<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

#### WL4SL-3, IO-Link

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max. 1)		Switching mode	Adjustment	IO-Link	Connection	Connection diagram	Model name	Part no.
0 m 12 m	PNP	Light/dark-switching 2)	Single teach-in button	~	Connector M8, 4-pin	Cd-083	WL4SLC-3P2232	1061569

<sup>1)</sup> PL80A.

#### WSE4SL-3

• Sensor principle: through-beam photoelectric sensor


Sensing range max.	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0 00	PNP	Light (doub out to bing 1)	Cingle teach in button	Connector M8, 4-pin	Cd-232	WSE4SL-3P2237	1058249
0 m 60 m	NPN	Light/dark-switching 1)	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-231	WSE4SL-3N1137	1058250

<sup>1)</sup> Q = light-switching.

#### **Dimensional drawings**


Dimensions in mm (inch)

#### WTB4SL-3, cable



- ① Standard direction of the material being detected
- 2 Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Status indicator LED green: power on
- $\ensuremath{\mathfrak{D}}$  Status indicator LED, yellow: Status of received light beam
- 6 Potentiometer
- Threaded mounting hole M3
- 8 Connection

#### WTB4SL-3, plug



- ① Standard direction of the material being detected
- ② Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Potentiometer
- 7 Threaded mounting hole M3
- Connection


<sup>2)</sup> Q = light-switching.

#### WL4SL-3, WL4SLG-3, WSE4SL-3, plug

## 12.2 (0.48) (0.48) (0.11) (0.47) (0.48) (0.11) (0.47) (0.47) (0.47)

- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Single teach-in button

#### WL4SL-3, WL4SLG-3, WSE4SL-3, cable




- ① Center of optical axis
- 2 Threaded mounting hole M3
- 3 Connection
- 4 Status indicator LED green: power on
- § Status indicator LED, yellow: Status of received light beam
- 6 Single teach-in button

#### **Characteristic curves**

#### Black-white shift

#### WTB4SL-3, laser class 1


% of sensing range



- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- 3 Sensing range on white, 90 % remission


#### Operating reserve

#### WL4SL-3




- ① PL20A
- ② PL40A
- ③ PL80A
- 4 PL10F
- ⑤ PL20F
- @ P250F
- ⑦ REF-AC1000

#### WSE4SL-3




#### **Bar diagrams**


#### WTB4SL-3, laser class 1



- Sensing range typ. max.
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission




#### WSE4SL-3



Sensing range

Sensing range typ. max.


#### WL4SL-3



#### **Light spot diameter**

#### WTB4SL-3, laser class 1

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
50 mm	1.2	1.0
(1.97)	(0.05)	(0.04)
100 mm	1.1	1.0
(3.94)	(0.04)	(0.04)
200 mm	0.9	0.9
(7.87)	(0.04)	(0.04)
300 mm	0.8	0.8
(11.81)	(0.03)	(0.03)

Vertical
Horizontal

#### WL4SL-3, Overview

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
6 m	15.2	7.6
(19.69 feet)	(0.60)	(0.30)
12 m	32.4	16.4
(39.37 feet)	(1.28)	(0.65)

Vertical
Horizontal

#### WL4SL-3, detailed view, close up






Vertical
Horizontal

#### WSE4SL-3, overview

#### Radius in mm (inch)



#### Dimensions in mm (inch)


Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
5 m	15	11
(16.40 feet)	(0.59)	(0.43)
10 m	45	28
(32.81 feet)	(1.77)	(1.10)
60 m	336	200
(196.85 feet)	(13.23)	(7.87)

Vertical
Horizontal

F

#### WSE4SL-3, detailed view, close up

Radius in mm (inch)



Vertical
Horizontal

#### **Connection diagram**

Cd-083

$$\begin{array}{c|c}
 & brn & 1 \\
 & brn & 2 \\
\hline
 & blu & 3 \\
\hline
 & blk & 4 \\
\hline
 & Q
\end{array}$$

Cd-094



Cd-195

Cd-212

Cd-231

Sender
 Receiver

② → bik Q → wht Q

wht! Q
blu - (M)

Cd-232

Sender
 Receiver

$$\begin{array}{c|c}
\hline
2 \\
\hline
 & \text{brin} & 1 \\
\hline
 & \text{blk} & 4 \\
\hline
 & \text{wht} & 2 \\
\hline
 & \text{blu} & 3 \\
\hline
 & \text{c}(M)
\end{array}$$

#### **Recommended accessories**

#### Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	or, Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873	

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

#### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
6	(sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

#### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
Je.	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, Ø 23 mm	P25F-1	5319385
	PMMA/ABS	Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm	P41F	5315128
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
*		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# F

### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

→ For additional accessories, please see page L-861

Detect all objects with one device - Change mode via teach button


















# **Product description**

The WL4SLG-3 detects all types of objects, including transparent vials, PET bottles, metallic needles, and wires, thus reducing the variety of sensors and their storage costs. The precise, highly visible laser light spot ensures a high level of detection quality and facilitates sensor alignment. Autocollimation technology ensures that the sensor reliably detects objects at close range and through small drilled holes. The sensor uses continuous threshold adaptation (AutoAdapt) to adjust automatically to changing light conditions, helping ensure maintenancefree system operation. The photoelectric sensors also provide an IO-Link interface to allow performing initial system performance diagnostics. Furthermore, IO-Link permits the integration of additional functions such as meters directly into the sensor. There is no need for complex control programming.

### At a glance

- Precise laser light spot, laser class 1
- Teach-in button can be switched between detection of transparent and smallest non-transparent objects
- · Continuous threshold adaptation (AutoAdapt) provides automatic adjustment to changes in light conditions
- Sensing ranges up to 4.5 m
- · Autocollimation optics prevent blind
- · Choice of adjustment via teach-in button, potentiometer, cable, or IO-Link

### Your benefits



- · Highly visible, even laser light spot with a sharp contour to facilitate alignment
- The highest degree of machine design flexibility. Autocollimation permits detection even through small drilled holes
- · High-quality sensor manufacturing and testing reduce maintenance
- · Established and proven housing design for easy installation
- IO-Link facilitates initial system performance diagnostics and uses additional sensor functions to reduce complex control programming

#### Additional information

 $C \in \mathbb{A}$ 

Additional information
Detailed technical dataF-291
Ordering informationF-292
Dimensional drawingsF-293
Characteristic curvesF-293
Light spot diameterF-294
Connection diagram F-294
Recommended accessories F-295



For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	12.2 mm x 41.8 mm x 17.3 mm
Housing design (light emission)	Rectangular
Mounting hole	M3
Sensing range max. 1)	0 m 4.5 m
Sensing range 1)	0 m 2 m
Type of light	Visible red light
Light source 2)	Laser
Light spot size (distance)	Ø 1 mm (500 mm)
Wave length	650 nm
Laser class 3)	1
Adjustment	Single teach-in button / Cable, Single teach-in button 4) (depending on type)
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> REF-AC1000.

# Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple 2)	< 5 V <sub>pp</sub>
Power consumption 3)	≤ 30 mA
Output type	PNP / NPN (depending on type)
Output function	Complementary
Switching mode	Light/dark-switching 4) / Dark-switching 5) (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 6)	≤ 0.5 ms
Switching frequency 7)	1,000 Hz
Connection type	Male connector, M8 Cable, 2 m <sup>8)</sup> Cable with connector, M8, 120 mm <sup>8)</sup> (depending on type)
Circuit protection	A <sup>9)</sup> , B <sup>10)</sup> , C <sup>11)</sup>
Protection class	III
Weight	100 g
Polarisation filter	V
Housing material	Bayblend
Optics material	PMMA

 $<sup>^{2)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 3)}\,{\rm EN60825\text{-}1:2008\text{-}05}$  & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11

<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

Enclosure rating	IP 66, IP 67
Ambient operating temperature	-10 °C +50 °C
Ambient operating temperature extended <sup>12)</sup> <sup>13)</sup>	-30 °C +55 °C
Ambient storage temperature	-30 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/W4SLG-3

#### WL4SLG-3

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
	PNP		Single teach-in button	Connector M8, 4-pin	Cd-083	WL4SLG-3P2232	1058243
		Light/dark-switching <sup>2)</sup>		Cable with connector M8, 4-pin, 120 mm, PVC	Cd-083	WL4SLG-3P3232	1058245
		Dark-switching <sup>3)</sup> Cable, Single teach-in button <sup>4)</sup>	Cable Single teach in	Connector M8, 4-pin	Cd-195	WL4SLG-3F2234	1058244
0 m 4.5 m			Cable with connector M8, 4-pin, 120 mm, PVC	Cd-195	WL4SLG-3F3234	1058246	
	NPN	Light/dark-switching 2)	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WL4SLG-3N1132	1058247
		Dark-switching 3)	Cable, Single teach-in button 4)	Cable, 4-wire, 2 m, PVC	Cd-212	WL4SLG-3E1134	1058248

<sup>&</sup>lt;sup>1)</sup> REF-AC1000.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{4)}</sup>$  Q = light-switching.

<sup>&</sup>lt;sup>5)</sup> Q = dark-switching.

<sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{\</sup>rm 9)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.

 $<sup>^{12)}</sup>$  As of T  $_{\!a}$  = 50 °C, a max. supply voltage V  $_{\!max.}$  = 24 V and a max. load current I  $_{\!max.}$  = 50 mA is permitted.


<sup>&</sup>lt;sup>13)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

<sup>&</sup>lt;sup>2)</sup> Q = light-switching.

<sup>3)</sup> Q = dark-switching.


<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

#### WL4SLG-3, plug



- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- $\ensuremath{\textcircled{4}}$  Status indicator LED green: power on
- $\ensuremath{\mathfrak{D}}$  Status indicator LED, yellow: Status of received light beam
- 6 Single teach-in button


#### WL4SLG-3, cable



- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Connection
- ④ Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Single teach-in button

### **Characteristic curves**

#### WL4SLG-3




- ① PLV14-A / PLH25-M12 / PLH25-D12
- ② P41F / REF-AC1000

# **Light spot diameter**

#### WL4SLG-3, Overview

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
2 m	4.3	2.6
(6.56 feet)	(0.17)	(0.10)
4.5 m	11.3	5.6
(14.76 feet)	(0.44)	(0.22)

Vertical
Horizontal

#### WL4SLG-3, detail, close up


Radius in mm (inch)




Vertical
Horizontal

# **Connection diagram**

Cd-083	
brn 1 + (	(L+)
$\rightarrow$ wht $\frac{2}{\overline{Q}}$ $\overline{Q}$	
blu! 3 - (I	M)
$\rightarrow blk \frac{4}{} Q$	,



Cd-195



### Plug connectors and cables

### Connecting cable (female connector-open), PVC

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
100	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled	conductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

### Female connector (ready to assemble)M8, 4-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO8N for universal clamp bracket	BEF-KHS-N08N	2051616

### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

### Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	FIVINIA/ ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
	DMMA /ADC	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

### Reflective tape


Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861

Highest reliability, maximum resistance and endless possibilities



















series in WashDown-Design combines a rugged and water tight IP 69K stainless steel housing with "best-in-class" optical functionality. This product family features a compact design that saves space and ensures high plant availability due to

water tight teach-in pushbutton with a metal membrane and pin casting M12connector. The stainless steel housing withstands stringent cleaning procedures in food and beverage, pharmaceutical, solar and semiconductor industries.

### At a glance

- · WashDown rated for fluid tightness (IP 66, IP 67, IP 68 and IP 69K) and Ecolab certified
- · Tough stainless steel housing (316L/1.4404)
- · Resistant to a variety of common cleaning and disinfection agents
- · Highly visible laser-like light spot due to PinPoint LED
- Teach-in via stainless steel pushbutton with a metal membrane

#### Your benefits

- Long service life in harsh conditions ensures less downtime and fewer replacement costs
- · Quick and easy alignment due to highly visible PinPoint emitter LED
- Easy adjustment via a stainless steel metal membrane teach-in pushbutton



### **Additional information**

Detailed technical dataF-299
Ordering informationF-300
Dimensional drawings F-303
Characteristic curvesF-305
Bar diagramsF-307
Connection diagram F-308
Recommended accessories F-309

#### → www.mysick.com/en/W4S-3\_Inox

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

#### **Features**

	WTB4S-3V	WTF4S-3V	WL4S-3V	WSE4S-3V
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor
Detection principle	Background suppression	Foreground suppression	Autocollimation	-
Dimensions (W x H x D)	15.25 mm x 49.2 mm x (depending on type)	x 22.2 mm		15.25 mm x 48.6 mm x 22.2 mm(depending on type)
Housing design	Washdown			
Housing design (light emission)	Rectangular			
Sensing range max.	4 mm 500 mm <sup>1)</sup> (depending on type)	20 mm 200 mm <sup>1)</sup>	0 m 5 m <sup>2)</sup> (depending on type)	0 m 5 m
Sensing range	10 mm 350 mm <sup>1)</sup> (depending on type)	-	0 m 3 m <sup>2)</sup> (depending on type)	0 m 4.5 m
Type of light	Visible red light			
Light source 3)	PinPoint LED			
Wave length	650 nm			
Adjustment	Cable <sup>4)</sup> / Single teach-in button (depending on type)		Single teach-in button	-
Alarm output	-		✓ (depending on type)	-
Special feature	-	Detection of transparent objects	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTB4S-3V	WTF4S-3V	WL4S-3V	WSE4S-3V		
Supply voltage 1)	10 V DC 30 V DC					
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>					
Power consumption 3)	≤ 30 mA					
Power consumption, sender	-			≤ 20 mA <sup>3)</sup>		
Power consumption, receiver	-			≤ 20 mA <sup>3)</sup>		
Output type	PNP / NPN (depending on type)	PNP	PNP / NPN (depending	g on type)		
Output function	Complementary			-		
Switching mode	Light switching / Dark-switching / Light/dark-switching (depending on type)					
Output current I <sub>max.</sub>	≤ 100 mA					
Response time 4)	< 0.5 ms					
Switching frequency 5)	1,000 Hz					
Connection type	Cable, 2 m $^{7)}$ / Male connector, M8 $^{6)}$ / Male connector, M12 $^{7)}$ 8) (depending on type)					
Circuit protection	A $^{9)}$ , B $^{10)}$ , C $^{11)}$					
Protection class	III					
Weight						
Cable, 4-wire	80 g	-	80 g			
Connector M8	40 g					
Connector M8, 4-pin	45 g	-	60 g			

<sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>scriptscriptstyle{(4)}}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

	WTB4S-3V	WTF4S-3V	WL4S-3V	WSE4S-3V
Polarisation filter	-		•	-
Housing material	Stainless steel 316L			
Enclosure rating	IP 66, IP 67, IP 68, IP 6	9K <sup>12)</sup>		
Test input sender off	-			"Test" to 0 V
Ambient operating temperature	-30 °C +70 °C <sup>13)</sup> -30 °C +60 °C			-30 °C +70 °C <sup>13)</sup>
Ambient storage temperature	-30 °C +75 °C			

<sup>&</sup>lt;sup>1)</sup> Limit values, reverse-polarity protected, operation in short-circuit protected network: max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/W4S-3\_Inox



#### WTB4S-3V

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.						
				Single teach-in	Connector M8, 3-pin	Cd-045	WTB4S-3P2132V	1046397						
			Light switching	button	Connector M12, 4-pin	Cd-083	WTB4S-3P2432V	1054672						
		PNP		Cable 2)	Connector M8, 4-pin	Cd-092	WTB4S-3P2235V	1045093						
4 mm	Ø 2.5 mm	FINE	Dark-switching	Single teach-in button	Connector M8, 3-pin	Cd-045	WTB4S-3F2132V	1046404						
120 mm	(50 mm)		Light/dark-switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3P1132V	1046402						
		NPN	Light switching NPN	Single teach-in	Connector M8, 3-pin	Cd-045	WTB4S-3N2132V	1046405						
				button	Cable, 3-wire, 2 m, PVC	Cd-044	WTB4S-3N1332V	1046406						
			Light/dark-switching	Single teach-in button	Connector M12, 4-pin	Cd-083	WTB4S-3N2432V	1054674						
										Cable, Single	Connector M8, 4-pin	Cd-092	WTB4S-3P2204VS02	1047652
				teach-in button 2)	Connector M8, 4-pin	Cd-092	WTB4S-3F2234VS08	1053075						
4	Ø 2.5 mm		Light switching	Cable 2)	Connector M8, 4-pin	Cd-092	WTB4S-3P2205VS01	1046214						
4 mm 280 mm	(100 mm)	PNP		Single teach-in button 2)	Connector M8, 4-pin	Cd-092	WTB4S-3P2234VS05	1050833						
			Light/dark-switching	Cable Single teach-in button	Connector M12, 4-pin	Cd-098	WTB4S-3P2402VS09	1054706						

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>6)</sup> Tightening torque, max.: 0.6 Nm.

 $<sup>^{\</sup>scriptscriptstyle{7)}}$  Do not bend below 0 °C.

<sup>8)</sup> Tightening torque, max.: 0.7 Nm.

 $<sup>^{\</sup>rm 9)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{11)}</sup>$  C = interference suppression.

 $<sup>^{\</sup>rm 12)}$  Only in case of correctly mounted IP 69K connecting cable.

 $<sup>^{13)}</sup>$  At UV  $\leq 24$  V and IA  $\leq 30$  mA.

 $<sup>^{\</sup>rm 2)}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
		PNP 6.5 mm 50 mm)	Light switching	Single teach-in button	Connector M8, 3-pin	Cd-045	WTB4S-3P2162V	1046384
			Dark-switching	Single teach-in button	Connector M8, 3-pin	Cd-045	WTB4S-3F2162V	1046389
4 mm 500 mm	Ø 6.5 mm (150 mm)		Light/dark-switching	Single teach-in	Connector M8, 4-pin	Cd-083	WTB4S-3P2262V	1046383
• • • • • • • • • • • • • • • • • • • •	(200)			button	Connector M12, 4-pin	Cd-083	WTB4S-3P2462V	1054675
		NIDNI	Light/dark-switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3N1162V	1046391
		NPN			Connector M12, 4-pin	Cd-083	WTB4S-3N2462V	1054703

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WTF4S-3V, Detection of transparent objects

Sensor principle: photoelectric proximity sensor

• Detection principle: foreground suppression

Sensing range max. 1)	Light spot size (dis- tance)	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
20 mm	20 mm	6.5 mm	Light switching	Cable 2)	Connector M8, 4-pin	Cd-083	WTF4S-3P2265V	1045094
20 mm Ø 6.5 mm 200 mm (150 mm)	PNP	Light/dark-switching	Single teach-in button	Connector M8, 4-pin	Cd-083	WTF4S-3P2262V	1046410	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WL4S-3V

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
			Light switching	-	Cable, 3-wire, 2 m, PVC	Cd-044	WL4S-3P1330V	1048044
_		PNP	Dark-switching	-	Connector M8, 3-pin	Cd-045	WL4S-3F2130V	1045096
0 m 4 m	Ø 45 mm (1.5 m)		Light/dark-switching	-	Connector M8, 4-pin	Cd-083	WL4S-3P2230V	1045095
	(=:= :)	NPN	Dark switching		Cable, 3-wire, 2 m, PVC	Cd-044	WL4S-3E1330V	1046420
		INPIN	Dark-switching	_	Connector M8, 3-pin	Cd-045	WL4S-3E2130V	1045097
			Light switching	Single teach-in button	Cable, 3-wire, 2 m, PVC	Cd-044	WL4S-3P1332V	1046427
					Connector M8, 3-pin	Cd-045	WL4S-3P2132V	1046424
			Dark-switching	Single teach-in	Cable, 3-wire, 2 m, PVC	Cd-044	WL4S-3F1332V	1046430
				button	Connector M8, 3-pin	Cd-045	WL4S-3F2132V	1046428
	~ 4=			Single teach-in	Connector M8, 4-pin	Cd-083	WL4S-3P2232V	1046421
0 m 5 m	Ø 45 mm (1.5 m)			Light/dark-switching	button	Connector M12, 4-pin, PVC	Cd-083	WL4S-3P2432V
			Light switching	Single teach-in button	Connector M8, 3-pin	Cd-045	WL4S-3N2132V	1046432
		NPN	Dark-switching	Single teach-in button	Connector M8, 3-pin	Cd-045	WL4S-3E2132V	1046435
			Light/dark-switching	Single teach-in button	Connector M12, 4-pin, PVC	Cd-083	WL4S-3N2432V	1054722

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{\</sup>rm 2)}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

 $<sup>^{2)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

# WL4S-3V, Alarm output

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation

Sens ran max	ge s	ight spot size (dis- tance)	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m		Ø 45 mm (1.5 m)	PNP	Dark-switching	Single teach-in button	Connector M8, 4-pin	Cd-107	WL4S-3V2232V	1046422


<sup>1)</sup> PL80A.

### WSE4S-3V

• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (dis- tance)	Output type	Switching mode	Connection	Con- nection diagram	Model name	Part no.
			Light switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3P1330V	1052887
		PNP		Connector M8, 3-pin	Cd-069	WSE4S-3P2130V	1052893
			Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3F1330V	1052880
0 m	Ø 40 mm			Connector M8, 3-pin	Cd-069	WSE4S-3F2130V	1052891
5 m	(2 m)		Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3E1330V	1052869
				Connector M8, 3-pin	Cd-069	WSE4S-3E2130V	1052877
			l delega constantes de	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3N1330V	1052874
			Light switching	Connector M8, 3-pin	Cd-069	WSE4S-3N2130V	1052878


#### WTB4S-3V, WTF4S-3V, Single teach-in button



- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Threaded mounting hole M3

- 4 Status indicator LED, yellow: Status of received light beam
- Status indicator LED green: power on
  - 6 Teach-in button


#### WTB4S-3V, WTF4S-3V, without single teach-in button



- $\ensuremath{\text{\textcircled{1}}}$  Center of receiver's optical axis
- ② Center of optical axis, sender
- $\ensuremath{\mathfrak{G}}$  Threaded mounting hole M3


- $\ensuremath{\textcircled{4}}$  Status indicator LED, yellow: Status of received light beam
- Status indicator LED green: power on

#### WL4S-3V, WSE4S-2V, without single teach-in button



- F
- ① Center of optical axis
- ② Threaded mounting hole M3
- ③ Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on

### WL4S-3V, with single teach-in button




- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- ⑤ Teach-in button

### **Characteristic curves**


#### Black-white shift

#### WTB4S-3, 120 mm



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


### WTB4S-3, 500 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\begin{tabular}{ll} \hline \end{tabular}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


### WTB4S-3, 280 mm

% of sensing distance




### Operating reserve

#### WL4S-3, 4 m




- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- **6** P250 CHEM
- ⑦ REF-IRF-56

#### **WSE4S-3V, WSE4S-3H**



#### WL4S-3, 5 m






- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- @ REF-IRF-56


### **Bar diagrams**

#### WTB4S-3, 120 mm




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WTB4S-3, 500 mm




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WTB4S-3, 280 mm



- Operating distance
- Sensing distance typ. max.
- (1) Sensing distance on black, 6 % remission
- 2 Sensing distance on grey, 18 % remission
- 3 Sensing distance on whitw, 90 % remission


#### WL4S-3, 4 m



- Sensing range
- Sensing range max.
- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- @ P250 CHEM
- ⑦ REF-IRF-56

<sup>1)</sup> Due to the focus of the light spot at 100 mm (3.94 inch)

#### WL4S-3, 5 m




Sensing range

Sensing range max.

- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F5 P250 CHEM
- 6 REF-IRF-56

#### **WSE4S-3**




# **Connection diagram**


#### Cd-044




#### Cd-045




#### Cd-061






- ① Sender
- ② Receiver

#### Cd-069





Cd-083

$$\begin{array}{c|c} & & & 1 \\ \hline & & & 1 \\ \hline & & & & 1 \\ \hline$$

$$\begin{array}{c|c} - & & \\ \hline & \text{brn} & 1 \\ \hline & \text{wht} & 2 \\ \hline & \text{blu} & 3 \\ \hline & & - & (M) \\ \end{array}$$

Cd-092

- ${\bf 1}\!\!{\rm Sender}$
- 2 Receiver

#### Cd-094

# **Recommended accessories**

### Plug connectors and cables

### Connecting cable (female connector-open), hygienic systems

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open	2 m, 3-wire	IP 67, IP 69K	DOL-0803-G02MN	6033664
	M8, 3-pin, straight	conductor heads	5 m, 3-wire	IP 67, IP 69K	DOL-0803-G05MN	6033665
	Female connector,	Cable, open	2 m, 3-wire	IP 67, IP 69K	DOL-0803-W02MN	6033667
	M8, 3-pin, angled	conductor heads	5 m, 3-wire	IP 67, IP 69K	DOL-0803-W05MN	6033668
00	Female connector, M8, 4-pin, straight	Cable, open conductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
			5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
	Female connector, M8, 4-pin, angled	Cable, open conductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
			5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
1 100	M12, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
	Female connector,	Cable, open conductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
1/2	M12, 4-pin, angled		5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
500	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-GN	6028357

### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-0804-G	6037323
	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-GN	6028359

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618

### Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Diactic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### **Special reflectors**

Figure	Material	Description	Model name	Part no.
8	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861





















### **Additional information**

Detailed technical dataF-313
Ordering informationF-314
Dimensional drawingsF-315
Characteristic curvesF-316
Bar diagramsF-316
Connection diagram F-316
Recommended accessories F-317

### **Product description**

The WLG4S-3 Inox is a photoelectric retro-reflective sensor designed to detect transparent objects. The WashDown-Design combines a rugged and water tight IP 69K stainless steel housing with "best-in-class" optical functionality. The continuous threshold adaptation (AutoAdapt) of the switching threshold enables reliable transparent object detection and reduces the frequency that the sensor or reflector needs. This product family features a compact design that saves space and ensures high plant availability due to water tight teach-in pushbutton with a metal membrane and pin casting M12-connector. The stainless steel housing withstands stringent cleaning procedures in food and beverage, pharmaceutical, solar and semiconductor industries. Especially for this harsh environment chemically resistant reflectors are available as accessories.

### At a glance

- IP 66, IP 67, IP 68 and IP 69K enclosure rating and Ecolab certified
- · Tough stainless steel housing (316L/1.4404)
- Resistant to a variety of common cleaning and disinfection agents
- Modern electrical connection available - M12 connector with pin casting
- · PinPoint LED technology provides a highly visible laser-like light spot
- · Teach-in via stainless steel pushbutton with a metal membrane
- · Continuous threshold adaptation (AutoAdapt) technology reliably detects objects in changing conditions

#### Your benefits

- Long service life in harsh conditions ensures less downtime and fewer replacement costs
- Reliable detection of all materials, including transparent objects in the pharmaceutical, packaging, and food and beverage industries
- Easy adjustment via a stainless steel metal membrane teach-in pushbutton
- · Quick and easy alignment due to highly visible PinPoint emitter LED
- · Remote monitoring and quick diagnostics via IO-Link (optional)

#### → www.mysick.com/en/W4S-3\_Inox\_Glass

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	15.25 mm x 49.2 mm x 22.2 mm
Housing design	Washdown
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 5 m
Sensing range 1)	0 m 3 m
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	Ø 45 mm (1.5 m)
Wave length	650 nm
Adjustment	Cable <sup>3</sup> / Cable, Single teach-in button <sup>3</sup> / Single teach-in button (depending on type)
Continuous threshold adaption (AutoAdapt)	V
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> PL80A.

### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	$<$ 5 $V_{pp}$
Power consumption 3)	≤ 30 mA
Output type	PNP / NPN (depending on type)
Output function	Complementary
Switching mode	Dark-switching / Light/dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	< 0.5 ms
Switching frequency 5)	1,000 Hz
Connection type	Male connector, M8 $^{\rm 6)}$ / Male connector, M12 $^{\rm 7)~8)}$ / Cable, 2 m $^{\rm 7)}$ (depending on type)
Circuit protection	A <sup>9)</sup> , B <sup>10)</sup> , C <sup>11)</sup>
Protection class	III
Weight	
Connector M8, 4-pin	40 g
Connector M12, 4-pin	45 g
Cable, 4-wire	80 g
Polarisation filter	V

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{3)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

Housing material	Stainless steel 316L
Enclosure rating	IP 66, IP 67, IP 68, IP 69K <sup>12)</sup>
Ambient operating temperature	-30 °C +60 °C / -30 °C +70 °C <sup>13)</sup>
Ambient storage temperature	-30 °C +75 °C

<sup>&</sup>lt;sup>1)</sup> Limit values, reverse-polarity protected, operation in short-circuit protected network: max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W4S-3\_Inox\_Glass

#### WLG4S-3V

Sensing range max. 1)	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
F			Cable 2)	Connector M8, 4-pin	Cd-092	WLG4S-3F2235V	1045098
		Dark-switching	Cable, Single teach-in	Connector M8, 4-pin	Cd-092	WLG4S-3F2234V	1047653
	PNP		button <sup>2)</sup>	Connector M12, 4-pin, PVC	Cd-092	WLG4S-3F2434V	1054727
	FINE	Light/dark-switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3P1132V	1055044
				Connector M8, 4-pin	Cd-083	WLG4S-3P2232V	1046446
0 m 5 m				Connector M12, 4-pin, PVC	Cd-083	WLG4S-3P2432V	1054725
		Dark-switching	Cable 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3E1135V	1046438
	NPN		Cable, Single teach-in button <sup>2)</sup>	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3E1134V	1048027
		Light/dark switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3N1132V	1046450
		Light/dark-switching	Single teach-in button	Connector M12, 4-pin, PVC	Cd-083	WLG4S-3N2432V	1054728

<sup>1)</sup> PL80A.

### WLG4S-3V Alarm output

Sensing range max. 1)	•	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0 m 5 m	PNP	Dark-switching	Single teach-in button	Connector M8, 4-pin	Cd-107	WLG4S-3V2232V	1046447

<sup>1)</sup> PL80A.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Tightening torque, max.: 0.6 Nm.

<sup>&</sup>lt;sup>7)</sup> Do not bend below 0 °C.

<sup>8)</sup> Tightening torque, max.: 0.7 Nm.

 $<sup>^{9)}</sup>$  A =  $\rm V_{S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{11)}</sup>$  C = interference suppression.

 $<sup>^{\</sup>rm 12)}$  Only in case of correctly mounted IP 69K connecting cable.


 $<sup>^{13)}</sup>$  At UV  $\leq$  24 V and IA  $\leq$  30 mA.

 $<sup>^{2)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

# **Dimensional drawings**

Dimensions in mm (inch)


#### WLG4S-3V, without single teach-in button



- ① Center of optical axis
- ② Threaded mounting hole M3

- 3 Status indicator LED, yellow: Status of received light beam
- $\ensuremath{\mathfrak{A}}$  Status indicator LED green: power on

#### WLG4S-3V, with single teach-in button




- ① Center of optical axis
- ② Threaded mounting hole M3
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- ⑤ Teach-in button

### **Characteristic curves**

#### WLG4S-3, 5 m


Operating reserve



- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- 6 REF-IRF-56

### **Bar diagrams**

#### WLG4S-3, 5 m



Sensing range

Sensing range max.

- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- **⑤** P250 CHEM
- @ REF-IRF-56

# F

# **Connection diagram**

### Cd-083

$$\begin{array}{c|c}
 & brn; 1 \\
 & wht 2 \overline{Q} \\
 & blu! 3 \\
 & blk; 4 Q
\end{array}$$

### Cd-092

#### Cd-093

#### Cd-107

### **Recommended accessories**

### Plug connectors and cables

### Connecting cable (female connector-open), hygienic systems

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
			5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
Ties and	Female connector,	· '	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
Ø @	M8, 4-pin, angled		5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674
	Female connector,		2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
1	M12, 4-pin, straight		5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
1 3	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618

### Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	Plactic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

Ė

Ī				
	г	ī	ī	
	۰			i

Figure	Material	Description	Model name	Part no.
0	DMAMA (ADC	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x $45 \text{ mm}$	PL81-1F	5325060

### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

















#### Additional information

/taaitional illionilati	011
Detailed technical data	F-321
Ordering information	F-322
Dimensional drawings	F-324
Characteristic curves	F-327
Bar diagrams	F-329
Connection diagram	F-330
Recommended accessories	F-331

## **Product description**

The W4S-3 Inox Hygiene series of photoelectric sensors combines hygienic requirements based on EHEDG with best-in-class performance. These sensors are completely enclosed in a stainless steel housing and can be taught via a stainless steel teach button with a metal membrane. With built in protec-

tion for the sensor cable, no additional mounting brackets or mounting holes are required for in-process machine integration. These sensors are designed for a completely hygienic sensor solution that is a necessity for the most hygienic machines.

### At a glance

- Smooth stainless steel housing (316L/1.4404)
- Hygienic mounting using M12-adapter thread or D12-adapter shaft
- IP 66, IP 67, IP 68 and IP 69K enclosure rating and Ecolab certified
- Resistant to a variety of common cleaning and disinfection agents
- Highly visible laser-like light spot due to PinPoint LED
- Teach-in via stainless steel pushbutton with a metal membrane

#### Your benefits

- Smooth hygienic housing and accessories with no grooves or crevices
  eliminates the potential for bacteria
  to grow, providing a more hygienic
  solution.
- Long service life in harsh conditions ensures less downtime and fewer replacement costs
- Easy adjustment via a stainless steel metal membrane teach-in pushbutton
- Quick and easy alignment due to highly visible PinPoint emitter LED

#### → www.mysick.com/en/W4S-3\_Inox\_Hygiene

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

### **Features**

	WTB4S-3H	WTF4S-3H	WL4S-3H	WSE4S-3H
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Foreground suppression	Autocollimation	-
Dimensions (W x H x D)	15.25 mm x 48.6 mm	x 22.15 mm / 15.25 mm	n x 63.2 mm x 22.15 mm	n (depending on type)
Housing design	Hygiene			
Housing design (light emission)	Rectangular			
Sensing range max.	4 mm 500 mm <sup>1)</sup> (depending on type)	20 mm 200 mm <sup>1)</sup>	0 m 5 m <sup>2)</sup> (depending on type)	0 m 5 m
Sensing range	10 mm 350 mm <sup>1)</sup> (depending on type)	-	0 m 3 m <sup>2)</sup> (depending on type)	0 m 4.5 m
Type of light	Visible red light			
Light source 3)	PinPoint LED			
Wave length	650 nm			
Adjustment	Cable <sup>4)</sup> / Single teach-in button / Cable, Single teach-in button <sup>4)</sup> (depending on type)	Cable, Single teach-in button <sup>4)</sup>	Single teach-in button	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	WTB4S-3H	WTF4S-3H	WL4S-3H	WSE4S-3H			
Supply voltage 1)	10 V DC 30 V DC	•	"				
Ripple 2)	< 5 V <sub>pp</sub>						
Power consumption	≤ 30 mA <sup>3)</sup>			≤ 20 mA <sup>4)</sup>			
Output type	PNP / NPN (depending	g on type)					
Output function	Complementary	-	Complementary				
Switching mode	Light switching / Light/dark-switching (depending on type)	Light switching	Light/dark-switching	Light switching Dark-switching Light/dark-switching (depending on type)			
Output current I <sub>max.</sub>	≤ 100 mA						
Response time 5)	< 0.5 ms						
Switching frequency <sup>6)</sup>	1,000 Hz						
Connection type	Cable, 2 m $^{7)}$ / Male connector, M8 $^{8)}$ /Cable with connector, M8, 150 mm $^{7)}$ $^{8)}$ (depending on type)						
Mechanical connection	M12 adapter thread / D12 adapter shaft (depending on type)	M12 adapter thread	M12 adapter thread / D12 adapter shaft (depending on type)				
Circuit protection	A $^{9)}$ , B $^{10)}$ , C $^{11)}$						
Protection class	III						
Weight							
Cable 7)	80 g	-	80 g	-			
Connector 8)	140 g	50 g	40 g	140 g			
Cable with connector 7) 8	50 g						

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>scriptscriptstyle (4)}$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

	WTB4S-3H	WTF4S-3H	WL4S-3H	WSE4S-3H
Polarisation filter	-		V	-
Housing material	Stainless steel 316L			
Enclosure rating	IP 66, IP 67, IP 68, IP 6			
Test input sender off	-		"Test" to 0 V	
Ambient operating temperature	-30 °C +60 °C / -3			
Ambient storage temperature	-30 °C +75 °C			

 $<sup>^{1)}</sup>$  Limit values, reverse-polarity protected, operation in short-circuit protected network: max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W4S-3\_Inox\_Hygiene

### WTB4S-3H

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression

Sensing range max. 1)	Light spot size (distance)	Mechani- cal con- nection	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.						
				Light switching	Cable 2)	Cable with con-	Cd-092	WTB4S-3P3235H	1048100						
		M12	PNP	Light/dark- switching	Single teach-in button	nector M8, 4-pin, 150 mm, PVC	Cd-083	WTB4S-3P3232H	1048096						
4 mm	Ø 2.5 mm	adapter thread	NPN	Light switching	Cable 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WTB4S-3N1135H	1048101						
120 mm	(50 mm)		INPIN	Light/dark- switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3N1132H	1048098						
		D12 adapter shaft	adapter PNP	Light/dark- switching	Single teach-in button	Connector M8, 4-pin	Cd-083	WTB4S-3P5232H	1054864						
				Light switching	Cable, Single teach-in button 2)	Connector M8, 4-pin	Cd-083	WTB4S-3P5204HS02	1054865						
			DAID	DND			Light switching	Cable, Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3P1162H	1051983			
		M12	PNP		Cable 2)	Cable with con-	Cd-092	WTB4S-3P3265H	1048102						
4 mm 500 mm	Ø 6.5 mm (150 mm)	nm adapter	adapter	adapter	ter					Light/dark- switching	Single teach-in button	nector M8, 4-pin, 150 mm, PVC	Cd-083	WTB4S-3P3262H	1048094
				Light switching	Cable 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WTB4S-3N1165H	1048107						
			NPN	Light/dark- switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WTB4S-3N1162H	1048095						

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Sender.

 $<sup>^{\</sup>rm 5)}$  Signal transit time with resistive load.

<sup>6)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>7)</sup> Do not bend below 0 °C.

<sup>8)</sup> Tightening torque, max.: 0.6 Nm.

 $<sup>^{9)}</sup>$  A =  $V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{11)}</sup>$  C = interference suppression.

 $<sup>^{12)}</sup>$  At UV  $\leq 24$  V and IA  $\leq 30$  mA.

<sup>&</sup>lt;sup>2)</sup> External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

### WTF4S-3H

- Sensor principle: photoelectric proximity sensor
- Detection principle: foreground suppression

Sensing range max. 1)	Light spot size (distance)	cal con-	Output type	Switching mode	Adjustment <sup>2)</sup>	Connection	Con- nection diagram	Model name	Part no.
20 mm 200 mm	Ø 6.5 mm (150 mm)	M12 adapter thread	PNP	Light switching	Cable, Single teach-in button	Cable with con- nector M8, 4-pin, 150 mm, PVC	Cd-092	WTF4S-3P3264H	1048109

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WL4S-3H

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

Sensing range max. 1)	Light spot size (distance)	Mechani- cal con- nection	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
	M12 adapter	PNP	Light/dark- switching	-	Cable with con- nector M8, 4-pin, 150 mm, PVC	Cd-083	WL4S-3P3230H	1048115	
0 m 4 m	Ø 45 mm (1,5 mm)		NPN	Light/dark- switching	-	Cable, 4-wire, 2 m, PVC	Cd-094	WL4S-3N1130H	1048116
		D12 adapter shaft	PNP	Light/dark- switching	-	Connector M8, 4-pin	Cd-083	WL4S-3P5230H	1057052
0 m 5 m	Ø 45 mm (1,5 mm)	adanter	PNP	Light/dark- switching	Single teach-in button	Cable with con- nector M8, 4-pin, 150 mm, PVC	Cd-083	WL4S-3P3232H	1048117
			NPN	Light/dark- switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WL4S-3N1132H	1048119

<sup>1)</sup> PL80A.

### WL4S-3H, Alarm output

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation

Sensing range max. 1)	Light spot size (distance)	cal con-	type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m 5 m	Ø 45 mm (1,5 mm)	M12 adapter thread	PNP	Light/dark- switching	Single teach-in button	Cable with con- nector M8, 4-pin, 150 mm, PVC	Cd-107	WL4S-3V3232H	1048118

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{2)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

#### WSE4S-3H

• Sensor principle: through-beam photoelectric sensor


Sensing range max.	Light spot size (distance)	Mechani- cal con- nection	Output type	Switching mode	Connection	Con- nection diagram	Model name	Part no.
			PNP	Light switching	Cable with connector M8, 3-pin,	Cd-069	WSE4S-3P3130H	1052888
			PNP	Dark-switching	150 mm, PVC	Cd-069	WSE4S-3F3130H	1052882
		1440		Light quitabing	Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3N1330H	1052873
		M12 adapter		Light switching	Cable, 3-wire, 2 m, PVC	Cd-055	WSE4S-3N1330H	1048129
0 m 5 m	Ø 50 mm (2 mm)	thread	NPN		Cable, 3-wire, 2 m, PVC	Cd-055	WSE4S-3E1330H	1048130
<b>5</b>	(=)			Dark-switching	Cable with connector M8, 3-pin, 150 mm, PVC	Cd-069	WSE4S-3E3130H	1052870
					Cable, 3-wire, 2 m, PVC	Cd-061	WSE4S-3E1330H	1052868
		D12ada- pter shaft	PNP	Light/dark- switching	Cable with connector M8, 4-pin, 150 mm, PVC	Cd-072	WSE4S-3P5230H	1054896


# **Dimensional drawings**

#### WTB4S-3H, WTF4S-3H, without single teach-in button


WTB4S-3H, WTF4S-3H, with single teach-in button, D12 adapter shaft, L-adaption

Dimensions in mm (inch)






- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- ③ Gasket (tightening torque 6Nm)
- 4 Connector M12
- ⑤ Status indicator LED, yellow: Status of received light beam
- **6** Status indicator LED green: power on



- ① Center of receiver's optical axis
- 2 Center of optical axis, sender
- ③ Status indicator LED, yellow: Status of received light beam
- ④ Status indicator LED green: power on
- Single teach-in button


#### WTB4S-3H, WTF4S-3H, with single teach-in button



- ① Center of optical axis, receiver
- ② Center of optical axis, sender
- ③ Gasket (tightening torque 6Nm)
- 4 Connector M12
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Status indicator LED green: power on
- 7 Teach-in button



#### WL4S-3H, without single teach-in button




- ① Center of optical axis
- ② Gasket (tightening torque 6Nm)
- 3 Connector M12

48.6 (1.91)

- Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on


#### WL4S-3H, with single teach-in button, D12 adapter shaft, I-adaption



- ① Center of optical axis
- ② Status indicator LED green: power on
- ③ Status indicator LED, yellow: Status of received light beam


F


#### WL4S-3H, with single teach-in button



- ① Center of optical axis
- ② Gasket (tightening torque 6Nm)
- 3 Connector M12
- $\ensuremath{\textcircled{4}}$  Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- 6 Teach-in button

#### WSE4S-3H






- $\ensuremath{\boxdot}$  Center of optical axis, sender (WS) and receiver (WE)
- ② Gasket (tightening torque 6Nm)
- 3 Connector M12
- ④ Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on

# F

#### **Characteristic curves**


#### Black-white shift

#### WTB4S-3, 120 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


#### WTB4S-3, 500 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### Operating reserve

#### WL4S-3, 4 m




- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- © P250 CHEM⑦ REF-IRF-56

#### WSE4S-3V, WSE4S-3H



#### WL4S-3, 5 m






- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- **⑤** P250 CHEM
- 6 REF-IRF-56

#### **Bar diagrams**

#### WTB4S-3, 120 mm




Sensing range max.

- $\begin{tabular}{ll} \hline \end{tabular}$  Sensing range on black, 6 % remission  $\begin{tabular}{ll} \hline \end{tabular}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### WL4S-3, 4 m

Sensing range




- Sensing range
- Sensing range max.
- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- **6** P250 CHEM
- 7 REF-IRF-56

#### **WSE4S-3**




#### WTB4S-3, 500 mm



- Sensing range
- Sensing range max.
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WL4S-3, 5 m



- Sensing range
- Sensing range max.
- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- 6 REF-IRF-56


F

# **Connection diagram**

#### Cd-055




# Cd-069




① Sender

2 Receiver

#### Cd-061





① Sender 2 Receiver

#### Cd-072

① Sender

② Receiver

#### Cd-083

#### Cd-092

$$\begin{array}{c|c} - & & 1 \\ \hline & \text{brn} & 1 \\ \hline & \text{wht} & 2 \\ \hline & & \text{blu} & 3 \\ \hline & & \text{-} & \text{(M)} \\ \hline & & \text{blk} & 4 \\ \hline & & \text{Q} \\ \end{array}$$

#### Cd-093

#### Cd-094



#### Cd-107

#### **Recommended accessories**

#### Plug connectors and cables

#### Connecting cable (female connector-open)M8, 4-pin, PP, hygienic systems

- Cable material: PP
- Connector material: PP

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
00	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
	M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674

#### Universal bar clamp systems

• For product family: Hygienic Design BeftecHD for sensors with D12 adapter shaft

Figure	Material	Description	Model name	Part no.
	Hygienic Design, Stainless steel V4A (1.4404, 316L), Silicone (seal)	Hygienic design mounting tube with bayonet lock, 14.4 mm x 85.5 mm x 14.4 mm	BEF-HDSBR	4074403
		Hygienic design flange with seal, 40 mm x 12 mm x 40 mm	BEF-HDSF	4072880
		Hygienic design telescopic tube, straight, with bayonet lock without flange, $23\;\text{mm}\;x\;153\;\text{mm}\;x\;23\;\text{mm}$	BEF-HDSTRG	2067780
		Hygienic design telescopic tube, straight, with bayonet lock with flange, $40\ \text{mm}\ x\ 165\ \text{mm}\ x\ 40\ \text{mm}$	BEF-HDSTRGF	2067779
		Hygienic design telescopic tube, angled, with bayonet lock without flange, $23\;\text{mm}\;x\;125\;\text{mm}\;x\;73\;\text{mm}$	BEF-HDSTRW	2067778
		Hygienic design telescopic tube, angled, with bayonet lock with flange, $40\ mm\ x\ 125\ mm\ x\ 76\ mm$	BEF-HDSTRWF	2067777

#### Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
==	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

Ē

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
		Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

F

**SIRIC®** 



# **Product description**

The WLG4S-3 Inox Hygiene photoelectric retro-reflective sensors combine strict hygiene requirements based on EHEDG with best-in-class optical performance. The continuous threshold adaptation (AutoAdapt) of the switching threshold enables reliable transparent object detection and reduces the frequency that the sensor or reflector needs. Enclosed in an IP 69K stainless steel housing, these sensors can be adjusted

via a stainless steel pushbutton with a metal membrane. With built-in protection for the sensor cable, no additional mounting brackets or mounting holes are required for in-process machine integration. These sensors as well as additional hygienic reflectors are designed for a completely hygienic sensor solution that is a necessity for the most hygienic machines.



- · Hygienic designed stainless steel housing and accessories (316L/1.4404)
- · Hygienic mounting using M12-adapter thread or D12-adapter shaft
- IP 66, IP 67, IP 68 and IP 69K enclosure rating and Ecolab certified
- · Resistant to a variety of common cleaning and disinfection agents
- · PinPoint LED technology provides a highly visible laser-like light spot
- · Teach-in stainless steel metal membrane or external teach-in



- Smooth hygienic housing and accessories with no grooves or crevices eliminates the potential for bacteria to grow, providing a more hygienic solution.
- Long service life in harsh conditions ensures less downtime and fewer replacement costs
- Reliable detection of all transparent objects in the pharmaceutical and food and beverage industries
- · Quick and easy adjustment via a stainless steel metal membrane teach-in pushbutton
- · Quick and easy alignment due to highly visible PinPoint emitter LED
- Remote monitoring and fast diagnostics via IO-Link (optional)





### Additional information

Additional information
Detailed technical data F-335
Ordering informationF-336
Dimensional drawingsF-337
Characteristic curvesF-338
Bar diagramsF-338
Connection diagram F-338
Recommended accessories F-339

→ www.mysick.com/en/W4S-3\_Inox\_Hygiene\_Glass

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	15.25 mm x 63.2 mm x 22.15 mm
Housing design	Hygiene
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 5 m
Sensing range 1)	0 m 3 m
Type of light	Visible red light
Light source 2)	PinPoint LED
Light spot size (distance)	Ø 45 mm (1.5 m)
Wave length	650 nm
Adjustment	Single teach-in button / Cable, Single teach-in button $^{3)}$ / Cable $^{3)}$ (depending on type)
Continuous threshold adaption (AutoAdapt)	
Special feature	Detection of transparent objects

<sup>1)</sup> PL80A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple 2)	$<$ 5 $V_{pp}$
Power consumption 3)	≤ 30 mA
Output type	PNP / NPN (depending on type)
Output function	Complementary
Switching mode	Light/dark-switching / Dark-switching (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	< 0.5 ms
Switching frequency 5)	1,000 Hz
Connection type	Cable, 2 m $^{6)}$ / Male connector, M8 $^{7)}$ / Cable with connector, M8, 150 mm $^{6)}$ $^{7)}$ (depending on type)
Mechanical connection	M12 adapter thread / D12 adapter shaft (depending on type)
Circuit protection	A 8), B 9), C 10)
Protection class	III
Weight	
Cable <sup>6)</sup>	80 g
Connector 7)	140 g
Cable with connector 6) 7)	50 g
Polarisation filter	V

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{3)}</sup>$  External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

Housing material	Stainless steel 316L
Enclosure rating	IP 66, IP 67, IP 68, IP 69K
Ambient operating temperature	-30 °C +60 °C / -30 °C +70 °C <sup>11)</sup>
Ambient storage temperature	-30 °C +75 °C

<sup>&</sup>lt;sup>1)</sup> Limit values, reverse-polarity protected, operation in short-circuit protected network: max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/W4S-3\_Inox\_Hygiene\_Glass

#### WLG4S-3H

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation

Sensing range max. 1)	Mechanical connection	Output type	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
		PNP	Light/dark- switching	Single teach-in button	Cable with connector M8, 4-pin, 150 mm, PVC	Cd-083	WLG4S-3P3232H	1048120
		PINP	Dark- switching	Cable, Single teach-in button 2)		Cd-092	WLG4S-3F3234H	1048121
0 m 5 m	M12 adapt- er thread	•	Light/dark- switching	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WLG4S-3N1132H	1048123
			NPN	Dark-	Cable, Single teach-in button 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3E1134H
			switching	Cable 2)	Cable, 4-wire, 2 m, PVC	Cd-093	WLG4S-3E1135H	1048126
	D12 adapter shaft	PNP	Light/dark- switching	Single teach-in button	Connector M8, 4-pin	Cd-083	WLG4S-3P5232H	1057053

<sup>1)</sup> PL80A.

#### WLG4S-3H Alarm output

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation

Sensing range max. 1)	Mechanical connection		Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0 m 5 m	M12 adapt- er thread	PNP	Dark- switching	Single teach-in button	Cable with connector M8, 4-pin, 150 mm, PVC	Cd-107	WLG4S-3V3232H	1048122

<sup>1)</sup> PL80A.

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

<sup>&</sup>lt;sup>7)</sup> Tightening torque, max.: 0.6 Nm.

 $<sup>^{8)}</sup>$  A =  $\rm V_{_{\rm S}}$  connections reverse-polarity protected.

 $<sup>^{9)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{10)}</sup>$  C = interference suppression.


 $<sup>^{11)}</sup>$  At UV  $\leq 24$  V and IA  $\leq 30$  mA.

<sup>&</sup>lt;sup>2)</sup> External teach-in: pulse > 2 s with voltage Uv with PNP and M with NPN.

# **Dimensional drawings**

Dimensions in mm (inch)


#### WLG4S-3H, with single teach-in button



- ${f @}$  Center of optical axis
- ② Gasket (tightening torque 6Nm)
- 3 Connector M12
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- 6 Teach-in button



#### WLG4S-3H, without single teach-in button, D12 adapter shaft, I-adaption




- ① Center of optical axis
- ② Status indicator LED green: power on
- $\ensuremath{\mathfrak{B}}$  Status indicator LED, yellow: Status of received light beam

### **Characteristic curves**

#### WLG4S-3, 5 m


Operating reserve



- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- 6 REF-IRF-56

## **Bar diagrams**

#### WLG4S-3, 5 m



Sensing range

- Sensing range max.
- ① PL80A
- ② PL40A
- ③ PL20A
- 4 PL10F
- ⑤ P250 CHEM
- @ REF-IRF-56

# F

# **Connection diagram**

#### Cd-083

brn 1 + (L+

wht 2 Q

blu 3 - (M)

#### Cd-092



#### Cd-093



#### Cd-094



#### Cd-107

# Recommended accessories

#### Plug connectors and cables

#### Connecting cable (female connector-open), hygienic systems

- Cable material: PP
- Connector material: PP

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
	Female connector, M8, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
			5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674

#### Universal bar clamp systems

• For product family: Hygienic Design BeftecHD for sensors with D12 adapter shaft

Figure	Material	Description	Model name	Part no.
	Hygienic Design, Stainless steel V4A (1.4404, 316L), Silicone (seal)	Hygienic design mounting tube with bayonet lock, 14.4 mm x 85.5 mm x 14.4 mm	BEF-HDSBR	4074403
		Hygienic design flange with seal, 40 mm x 12 mm x 40 mm	BEF-HDSF	4072880
		Hygienic design telescopic tube, straight, with bayonet lock without flange, $23\;\text{mm}\;x\;23\;\text{mm}$	BEF-HDSTRG	2067780
		Hygienic design telescopic tube, straight, with bayonet lock with flange, $40\ \text{mm}\ x\ 165\ \text{mm}\ x\ 40\ \text{mm}$	BEF-HDSTRGF	2067779
		Hygienic design telescopic tube, angled, with bayonet lock without flange, $23\;\text{mm}\;x\;125\;\text{mm}\;x\;73\;\text{mm}$	BEF-HDSTRW	2067778
		Hygienic design telescopic tube, angled, with bayonet lock with flange, $40\ mm\ x\ 125\ mm\ x\ 76\ mm$	BEF-HDSTRWF	2067777

#### Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
==	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

Ē

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

F

The new standard for optical and mechanical ruggedness







#### **Additional information**

/ taditional information
Detailed technical dataF-343
Ordering informationF-344
Dimensional drawingsF-345
Characteristic curvesF-346
Bar diagramsF-346
Light spot diameterF-347
Connection diagram F-348
Recommended accessories F-349



For the best possible performance in a wet environment: thanks to high light immunity, the new W4SL-3 Inox miniature photoelectric sensors from SICK with precise laser light spot set new standards when it comes to preventing undesired background reflections and to ambient light immunity, even in modern energy-saving lights. The combination of SICK's latest proprietary laser and SIRIC® technologies reduces incorrect switching. The photoelectric sensors complete this product family. One device can reliably

detect all transparent objects as well as tiny non-transparent objects. This reduces the variety of devices and saves on storage costs. The photoelectric sensors also feature an IO-Link function, so that initial system performance diagnostics can be done independently. The W4SL-3 Inox is certified in accordance with ECOLAB. The membrane teach-in pushbutton and the pin-cast electrical connections make it reliable even in critical ambient conditions.

#### At a glance

- Precise laser light spot, laser class 1
- Stainless steel housing with washdown design
- Latest SIRIC® and laser technologies for outstanding background suppression and ambient light immunity
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- · ECOLAB certified, tested to IP 66, IP 67, IP 68 and IP 69K enclosure
- · IO-Link (optional)

#### Your benefits

- · Precise laser light spot for highly accurate switching
- Washable stainless steel housing reduces bacterial contamination
- · Innovative washdown design with sealed connections and unique patented membrane teach-in pushbutton
- · High ambient light immunity reduces incorrect switching and ultimately machine downtime, even when modern energy-saving lights are used
- · The highest degree of machine design flexibility. Outstanding BGS (background suppression) eliminates the effect of undesired background reflections. Autocollimation permits detection through very small drilled
- · IO-Link provides effortless initial diagnostics of system performance

#### www.mysick.com/en/W4SL-3V

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	WTB4SL-3V	WSE4SL-3V
Sensor principle	Photoelectric proximity sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	-
Dimensions (W x H x D)	15.3 mm x 55.4 mm x 22.2 mm	
Housing design	Washdown	
Housing design (light emission)	Rectangular, Slim	
Mounting hole	M3	
Sensing range max.	25 mm 300 mm <sup>1)</sup>	0 m 60 m
Sensing range	25 mm 300 mm <sup>1)</sup>	0 m 50 m
Type of light	Visible red light	
Light source 2)	Laser	
Light spot size (distance)	Ø 1 mm (170 mm)	Ø 1 mm (500 mm)
Wave length	650 nm	
Laser class 3)	1	
Adjustment	Single teach-in button	

 $<sup>^{1)}\,\</sup>mbox{Object}$  with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

	WTB4SL-3V	WSE4SL-3V
Supply voltage 1)	10 V DC 30 V DC	
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>	
Power consumption 3)	≤ 30 mA	
Output type	PNP $^{4)}$ / NPN $^{4)}$ (depending on type)	
Output function	Complementary	
Switching mode 4)	Light/dark-switching	
Output current I <sub>max.</sub>	≤ 100 mA	
Response time 5)	≤ 0.5 ms	
Switching frequency 6)	1,000 Hz	
Connection type	Male connector, M8 $^{7)}/$ Male connector, M12 $^{9)}$	/ Cable, 2 m <sup>8)</sup> (depending on type)
Circuit protection	A $^{10)}$ , B $^{11)}$ , C $^{12)}$	
Protection class	III	
Weight		
Cable <sup>8</sup>	80 g	
Connector M8 7	40 g	
Connector M12 9)	45 g	
Housing material	Stainless steel V4A (1.4404, 316L)	
Optics material	PMMA	

F

 $<sup>^{2)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

<sup>&</sup>lt;sup>3)</sup> EN60825-1:2008-05 & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11

	WTB4SL-3V	WSE4SL-3V
Enclosure rating	IP 66, IP 67, IP 68, IP 69K 13)	
Ambient operating temperature	-10 °C +50 °C	
Ambient operating temperature extended <sup>14) 15)</sup>	-30 °C +55 °C	
Ambient storage temperature	-30 °C +70 °C	

<sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

#### **Ordering information**

Other models available at www.mysick.com/en/W4SL-3V

#### WTB4SL-3V

• Sensor principle: photoelectric proximity sensor

• **Switching mode:** light/dark-switching (Q = light-switching.)

• Adjustment: single teach-in button

Sensing range max. 1)	Output type	Connection	Connection diagram	Model name	Part no.
		Connector M8, 4-pin	Cd-083	WTB4SL-3P2262V	1058251
	PNP	Connector M12, 4-pin	Cd-083	WTB4SL-3P2462V	1058253
25 mm 300 mm		Cable, 4-wire, 2 m, PVC	Cd-094	WTB4SL-3P1162V	1058256
25 11111 300 111111		Connector M8, 4-pin	Cd-083	WTB4SL-3N2262V	1058252
	NPN	Connector M12, 4-pin	Cd-083	WTB4SL-3N2462V	1058254
		Cable, 4-wire, 2 m, PVC	Cd-094	WTB4SL-3N1162V	1058257

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WSE4SL-3V

• Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching (Q = light-switching.)

• Adjustment: single teach-in button

Sensing range max.	Output type	Connection	Connection diagram	Model name	Part no.
	PNP	Connector M8, 4-pin	Cd-232	WSE4SL-3P2237V	1058267
0 m 60 m		Connector M12, 4-pin	Cd-232	WSE4SL-3P2437V	1058269
	NPN	Cable, 4-wire, 2 m, PVC	Cd-231	WSE4SL-3N1137V	1058270

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

<sup>5)</sup> Signal transit time with resistive load.

<sup>6)</sup> With light/dark ratio 1:1.

<sup>7)</sup> Tightening torque, max.: 0.6 Nm.

<sup>&</sup>lt;sup>8)</sup> Do not bend below 0 °C.

<sup>9)</sup> Tightening torque, max.: 0.7 Nm.

 $<sup>^{10)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

 $<sup>^{11)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{12)}</sup>$  C = interference suppression.

 $<sup>^{\</sup>mbox{\scriptsize 13)}}$  Only in case of correctly mounted IP 69K connecting cable.


 $<sup>^{14)}</sup>$  As of T<sub>a</sub> = 50 °C, a max. supply voltage V<sub>max.</sub> = 24 V and a max. load current I<sub>max.</sub> = 50 mA is permitted.

<sup>&</sup>lt;sup>15)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

# **Dimensional drawings**

Dimensions in mm (inch)


#### WTB4SL-3



- ${\scriptsize \textcircled{\scriptsize 1}}$  Center of optical axis, sender
- ② Center of optical axis, receiver
- 3 Threaded mounting hole M3

- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- 6 Single teach-in button

#### WSE4SL-3




- $\ensuremath{\ensuremath{\mathbb{T}}}$  Center of optical axis
- ② Threaded mounting hole M3
- ③ Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- ⑤ Single teach-in button

#### **Characteristic curves**

#### Black-white shift


#### WTB4SL-3

% of sensing range



#### Operating reserve

#### WSE4SL-3




# Ē

- 1 Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

# **Bar diagrams**


#### WTB4SL-3



Sensing range typ. max.

- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission


#### WSE4SL-3



# **Light spot diameter**

#### WTB4SL-3

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
50 mm	1.2	1.0
(1.97)	(0.05)	(0.04)
100 mm	1.1	1.0
(3.94)	(0.04)	(0.04)
200 mm	0.9	0.9
(7.87)	(0.04)	(0.04)
300 mm	0.8	0.8
(11.81)	(0.03)	(0.03)

Vertical
Horizontal

#### WSE4SL-3

Radius in mm (inch)



#### Dimensions in mm (inch)


Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
5 m	15	11
(16.40 feet)	(0.59)	(0.43)
10 m	45	28
(32.81 feet)	(1.77)	(1.10)
60 m	336	200
(196.85 feet)	(13.23)	(7.87)

Vertical
Horizontal

F

#### WSE4SL-3, close up, near range

Radius in mm (inch)



Vertical
Horizontal

# **Connection diagram**


Cd-083

$$\begin{array}{c|c}
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 & 1 \\
 &$$

Cd-094



Cd-231



① Sender

2 Receiver

Cd-232

① Sender

2 Receiver

#### **Recommended accessories**

#### Plug connectors and cables


#### Connecting cable (female connector-open), PVC, hygienic systems

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
00	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
	M8, 4-pin, angled conductor heads	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
1	M12, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129	
1 3	M12, 4-pin, angled	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618





Detect all transparent objects with one device – Change mode via teach button





**SIRIC®** 









#### Additional information

Additional information
Detailed technical dataF-351
Ordering informationF-352
Dimensional drawings F-353
Characteristic curvesF-353
Bar diagramsF-353
Light spot diameter F-354
Connection diagram F-355
Recommended accessories F-355

# **Product description**

A single press of a button on the WL4SLG-3 Inox allows operation in the detection mode for transparent and/ or non-transparent objects. This means that one device can be used to detect transparent vials and PET bottles, but also metallic needles and wires, for example. The precise, highly visible laser light spot with sharp contour ensures a high level of detection quality and facilitates alignment. Autocollimation technology ensures that the sensor

reliably detects objects at close range as well as through narrow gaps or small drilled holes. The photoelectric sensors also feature an IO-Link function, so that initial system performance diagnostics can be done independently. Furthermore, IO-Link permits the integration of additional functions such as meters or profile recognition directly into the sensor. There is no need for complex control programming.

#### At a glance

- Precise laser light spot, laser class 1, no blind spots
- Stainless steel housing with washdown design
- Latest SIRIC® and laser technologies for very good background suppression and ambient light immunity
- ECOLAB certified, tested to IP66, IP67, IP68 and IP69K enclosure rating
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- IO-Link (optional)

#### **Your benefits**

- Precise laser light spot for highly accurate switching
- Washable stainless steel housing reduces bacterial contamination
- Innovative washdown design with sealed connections and unique patented membrane teach-in pushbutton
- High ambient light immunity reduces incorrect switching and ultimately machine downtime, even when modern energy-saving lights are used
- The highest degree of machine design flexibility. Outstanding BGS (background suppression) eliminates the effect of undesired background reflections. Autocollimation permits detection through very small drilled holes
- IO-Link provides effortless initial diagnostics of system performance

#### → www.mysick.com/en/W4SLG-3V

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

Autocollimation
15.3 mm x 55.4 mm x 22.2 mm
Washdown
Rectangular, Slim
M3
0 m 4.5 m
0 m 2 m
Visible red light
Laser
Ø 1 mm (500 mm)
650 nm
1
Single teach-in button / Cable, Single teach-in button 4) (depending on type)
Detection of transparent objects
1 N C C N L Q 6 1 5

<sup>&</sup>lt;sup>1)</sup> REF-AC1000.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	$< 5 V_{pp}$
Power consumption 3)	≤ 30 mA
Output type	PNP 4) 5)
Output function	Complementary
Switching mode	Light/dark-switching 4) 5)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 6)	≤ 0.5 ms
Switching frequency 7)	1,000 Hz
Connection type	Male connector, M8 $^{8)}$ / Male connector, M12 $^{9)}$ / Cable, 2 m $^{10)}$ (depending on type)
Circuit protection	A <sup>11)</sup> , B <sup>12)</sup> , C <sup>13)</sup>
Protection class	III
Weight	
Cable <sup>10)</sup>	80 g
Connector M8 8)	40 g
Connector M12 9)	45 g
Polarisation filter	<b>√</b>
Housing material	Stainless steel V4A (1.4404, 316L)
Optics material	PMMA

Ē

 $<sup>^{2)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 3)}$  EN60825-1:2008-05 & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11.

<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

Enclosure rating	IP 66, IP 67, IP 68, IP 69K <sup>14)</sup>		
Ambient operating temperature	-10 °C +50 °C		
Ambient operating temperature extended <sup>15)</sup> <sup>16)</sup>	-30 °C +55 °C		
Ambient storage temperature	-30 °C +70 °C		
1) Limit values, operation in short-circuit protected network max, 8 A			

### **Ordering information**

Other models available at www.mysick.com/en/W4SLG-3V

#### WL4SLG-3V

• Sensor principle: photoelectric retro-reflective sensor

Output type: PNP

Sensing range max. 1)	Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
			Connector M8, 4-pin	Cd-083	WL4SLG-3P2232V	1058258
	Light/dark-switching 2)	Single teach-in button	le teach-in button Connector M12, 4-pin	Cd-083	WL4SLG-3P2432V	1058261
0 m 4.5 m		Cable, Single teach-in button <sup>4)</sup>	Cable, 4-wire, 2 m, PVC	Cd-094	WL4SLG-3P1132V	1058266
	1 :		Connector M8, 4-pin	Cd-195	WL4SLG-3F2234V	1058260
	Light/dark-switching 3)		Connector M12, 4-pin	Cd-195	WL4SLG-3F2434V	1058263

<sup>1)</sup> REF-AC1000.

#### WL4SLG-3V, IO-Link

• Sensor principle: photoelectric retro-reflective sensor

• Output type: PNP

• IO-Link: standard functions

Sensing range max. 1)	Switching mode <sup>2)</sup>	Adjustment	Connection	Connection diagram	Model name	Part no.
0 m 4.5 m	Light/dark-switching	Single teach-in button	Connector M12, 4-pin	Cd-083	WL4SLGC- 3P2432V	1058262

<sup>1)</sup> REF-AC1000.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

<sup>&</sup>lt;sup>5)</sup> Q = dark-switching.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Tightening torque, max.: 0.6 Nm.

<sup>9)</sup> Tightening torque, max.: 0.7 Nm.

<sup>&</sup>lt;sup>10)</sup> Do not bend below 0 °C.

 $<sup>^{11)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>12)</sup> B = inputs and output reverse-polarity protected.

<sup>13)</sup> C = interference suppression.

<sup>&</sup>lt;sup>14)</sup> Only in case of correctly mounted IP 69K connecting cable.

 $<sup>^{15)}</sup>$  As of  $T_a$  = 50 °C, a max. supply voltage  $V_{max.}$  = 24 V and a max. load current  $I_{max.}$  = 50 mA is permitted.

<sup>&</sup>lt;sup>16)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

<sup>&</sup>lt;sup>2)</sup> Q = light-switching.

<sup>3)</sup> Q = dark-switching.


<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

<sup>2)</sup> Q = light-switching.

# **Dimensional drawings**

Dimensions in mm (inch)

#### WL4SLG-3V




- $\ensuremath{\ensuremath{\mathbb{O}}}$  Center of optical axis
- ② Threaded mounting hole M3
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- . Single teach-in button

#### **Characteristic curves**

#### Operating reserve

#### WL4SLG-3




① PLV14-A / PLH25-M12 / PLH25-D12

② P41F / REF-AC1000

### **Bar diagrams**

#### WL4SLG-3




② P41F / REF-AC1000

# **Light spot diameter**

#### WL4SLG-3, overview






#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
2 m	4.3	2.6
(6.56 feet)	(0.17)	(0.10)
4.5 m	11.3	5.6
(14.76 feet)	(0.44)	(0.22)

Vertical
Horizontal

#### WL4SLG-3, detailed view

Radius in mm (inch)



Vertical
Horizontal

# **Connection diagram**

Cd-083	Cd-094	Cd-195
brn: 1 + (L+)	→ brn: + (L+)	brn: 1 + (L+)
$\rightarrow$ wht $\frac{2}{\overline{Q}}$ $\overline{Q}$	→ wht   Q	$\rightarrow$ blk $\frac{4}{}$ Q
blu! 3 - (M)	— blu! - (M)	→ wht! 2 Teach
$\rightarrow \frac{\text{blk}}{4}$ Q	→ blk Q	<u>blu 3</u> - (M)
_ · _ · J	_ · _ · ¬	

#### **Recommended accessories**

Plug connectors and cables

## Connecting cable (female connector-open), PVC, hygienic systems

• Cable material: PVC

• Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
00	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
	M8, 4-pin, angled	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
M12, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130	
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
M12, 4-pin, angled	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131	

### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
2	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861

Laser technology and stainless steel hygienically combined



















#### **Additional information**

/ total to little little to little t
Detailed technical dataF-359
Ordering informationF-360
Dimensional drawings F-361
Characteristic curvesF-362
Bar diagramsF-362
Light spot diameterF-362
Connection diagram F-363
Recommended accessories F-363

# **Product description**

For the best possible hygienic performance: thanks to high immunity to ambient light, the new W4SL-3 Inox Hygiene miniature photoelectric sensors with precise laser light spot set new standards when it comes to preventing undesired background reflections and to ambient light immunity, even with modern energy-saving lights. The combination of SICK's latest proprietary laser and SIRIC® technologies reduces incorrect switching to minimize machine downtime. The photoelectric sensors complete this product

family. One device can reliably detect all transparent objects as well as tiny non-transparent objects, thus reducing the variety of devices. The photoelectric sensors also feature an IO-Link function, so that initial system performance diagnostics can be done independently. The W4SL-3 Inox Hygiene is certified in accordance with ECOLAB. In addition to an innovative leak-tight design, the sensors also have an impressive smooth housing design, which follows current hygiene guidelines.

### At a glance

- Precise laser light spot, laser class 1
- Stainless steel housing with wash down design
- Latest SIRIC® and laser technologies for outstanding background suppression and ambient light immunity
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- · ECOLAB certified, tested to IP 66, IP 67, IP 68 and IP 69K enclosure
- · IO-Link (optional)

#### Your benefits

- · Precise laser light spot for highly accurate switching
- Washable stainless steel housing reduces bacterial contamination
- · Innovative wash down design with sealed connections and unique patented membrane teach-in pushbutton
- · High ambient light immunity reduces incorrect switching and ultimately machine downtime, even when modern energy-saving lights are used
- · The highest degree of machine design flexibility. Outstanding BGS (background suppression) eliminates the effect of undesired background reflections. Autocollimation permits detection through very small drilled
- · IO-Link provides effortless initial diagnostics of system performance

#### → www.mysick.com/en/W4SL-3H

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Background suppression
Dimensions (W x H x D)	15.3 mm x 63.2 mm x 22.2 mm
Housing design	Hygiene
Housing design (light emission)	Rectangular, Slim
Mounting hole	M3
Sensing range max. 1)	25 mm 300 mm
Sensing range 1)	25 mm 300 mm
Type of light	Visible red light
Light source 2)	Laser
Light spot size (distance)	Ø 1 mm (170 mm)
Wave length	650 nm
Laser class 3)	1
Adjustment	Single teach-in button

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>
Power consumption 3)	≤ 30 mA
Output type	PNP <sup>4)</sup> / NPN <sup>4)</sup> (depending on type)
Output function	Complementary
Switching mode 4)	Light/dark-switching
Output current I <sub>max.</sub>	≤ 100 mA
Response time 5)	≤ 0.5 ms
Switching frequency 6)	± 1,000 Hz
Connection type	Male connector, M8 $^{7)}$ / Cable, 2 m $^{8)}$ (depending on type)
Mechanical connection	D12 adapter shaft
Circuit protection	A <sup>9)</sup> , B <sup>10)</sup> , C <sup>11)</sup>
Protection class	III
Weight	
Connector M8 7)	140 g
Cable <sup>8)</sup>	180 g
Housing material	Stainless steel V4A (1.4404, 316L)
Optics material	PMMA

 $<sup>^{2)}</sup>$  Average service life 50,000 h at T  $_{\!A}$  = +25 °C.

<sup>&</sup>lt;sup>3)</sup> EN60825-1:2008-05 & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11.

Enclosure rating	IP 66, IP 67, IP 68, IP 69K <sup>12)</sup>				
Ambient operating temperature	-10 °C +50 °C				
Ambient operating temperature extended <sup>13)</sup> <sup>14)</sup>	-30 °C +55 °C				
Ambient storage temperature	-30 °C +70 °C				
Ulimit values, operation in short-circuit protected network max. 8 A					

## **Ordering information**

Other models available at www.mysick.com/en/W4SL-3H

#### WTB4SL-3H

- · Sensor principle: photoelectric proximity sensor
- Switching mode: light/dark-switching (Q = light-switching.)
- Adjustment: single teach-in button

Sensing range max. 1)	Mechanical connection	Output type	Connection	Connection diagram	Model name	Part no.
		PNP	Connector M8, 4-pin	Cd-094	WTB4SL-3P5262H	1058271
25 mm 300 mm	D12 adapter shaft	PINP	Cable, 4-wire, 2 m, PVC	Cd-083	WTB4SL-3P4162H	1058274
		NPN	Cable, 4-wire, 2 m, PVC	Cd-083	WTB4SL-3N4162H	1058275

<sup>1)</sup> Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{4)}</sup>$  Q = light-switching.

 $<sup>^{\</sup>rm 5)}$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>6)</sup> With light/dark ratio 1:1.

 $<sup>^{7)}</sup>$  Tightening torque, max.: 0.6 Nm.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{\</sup>rm 9)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.

<sup>12)</sup> Only in case of correctly mounted IP 69K connecting cable.

 $<sup>^{13)}</sup>$  As of T  $_{\!a}$  = 50 °C, a max. supply voltage V  $_{\!max.}$  = 24 V and a max. load current I  $_{\!max.}$  = 50 mA is permitted.

 $<sup>^{14)}</sup>$  Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

## **Dimensional drawings**


Dimensions in mm (inch)


#### WTB4SL-3H, connector

# 15.3 (0.60) (0.30) (0.30) (0.47) (0.30) (0.47) (0.30) (0.47) (0.30) (0.47)

- ① Center of receiver's optical axis
- ② Center of optical axis, sender
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- 3 Single teach-in button

#### WTB4SL-3H, cable





- $\ensuremath{\textcircled{1}}$  Center of optical axis, sender
- 2 Center of optical axis, receiver
- $\ensuremath{\mathfrak{J}}$  Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- ⑤ Single teach-in button




### **Characteristic curves**

#### Black-white shift

#### WTB4SL-3H


% of sensing range



- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

## **Bar diagrams**

#### WTB4SL-3H




- Sensing range typ. max.
- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

## Г

## Light spot diameter

#### WTB4SL-3H

Radius in mm (inch)



#### **Dimensions in mm (inch)**

Sensing range	Vertical	Horizontal
50 mm	1.2	1.0
(1.97)	(0.05)	(0.04)
100 mm	1.1	1.0
(3.94)	(0.04)	(0.04)
200 mm	0.9	0.9
(7.87)	(0.04)	(0.04)
300 mm	0.8	0.8
(11.81)	(0.03)	(0.03)




## **Connection diagram**

#### Cd-083

#### Cd-094





## **Recommended accessories**

Plug connectors and cables

Connecting cable (female connector-open), PVC, hygienic systems

• Cable material: PVC

• Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
00	Female connector, M8, 4-pin, angled	nector, Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
		conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674

### Universal bar clamp systems

• For product family: Hygienic Design BeftecHD for sensors with D12 adapter shaft

Figure	Material	Description	Model name	Part no.
	Hygienic Design, Stainless steel V4A (1.4404, 316L), Silicone (seal)	Hygienic design mounting tube with bayonet lock, 14.4 mm x 85.5 mm x 14.4 mm	BEF-HDSBR	4074403
		Hygienic design flange with seal, 40 mm x 12 mm x 40 mm	BEF-HDSF	4072880
		Hygienic design telescopic tube, straight, with bayonet lock without flange, 23 mm x 153 mm x 23 mm	BEF-HDSTRG	2067780
		Hygienic design telescopic tube, straight, with bayonet lock with flange, 40 mm x 165 mm x 40 mm	BEF-HDSTRGF	2067779
		Hygienic design telescopic tube, angled, with bayonet lock without flange, 23 mm x 125 mm x 73 mm	BEF-HDSTRW	2067778
Ĺ		Hygienic design telescopic tube, angled, with bayonet lock with flange, 40 mm x 125 mm x 76 mm	BEF-HDSTRWF	2067777

→ For additional accessories, please see page L-861

Detect all transparent objects with one device - Change mode via teach button













#### Additional information

Additional information
Detailed technical dataF-365
Ordering informationF-366
Dimensional drawings F-367
Characteristic curves F-368
Bar diagramsF-368
Light spot diameterF-368
Connection diagram F-369
Recommended accessories F-370



The stainless steel housing of the WL4SLG-3 Inox Hygiene photoelectric retro-reflective sensor, which is designed based on hygienic guidelines, is especially suited to machines in which hygiene is already part of the design. A press of a button allows operation in the detection mode for transparent and/ or non-transparent objects. This means that one device can be used to detect transparent vials and metallic needles. for example. This reduces the variety of sensors needed. The precise, highly

visible laser light spot ensures a high level of detection quality and facilitates alignment. Autocollimation technology ensures that the sensor reliably detects objects at close range as well as through small drilled holes. The photoelectric sensors also feature an IO-Link function, so that initial system performance diagnostics can be done independently. Furthermore, IO-Link permits the integration of additional functions such as meters directly into the sensor. There is no need for complex control programming.

#### At a glance

- Precise laser light spot, laser class 1
- Stainless steel housing with hygienic design
- Latest SICK proprietary ASIC and laser technologies for outstanding background suppression and ambient light immunity
- Teach-in pushbutton can be switched between detection of transparent and tiny non-transparent objects
- · ECOLAB certified, tested to IP 66, IP 67, IP 68 and IP 69K enclosure
- · IO-Link (optional)

#### Your benefits

- · Precise laser light spot for highly accurate switching
- · Washable stainless steel housing reduces bacterial contamination
- · Innovative hygienic design with sealed connections and unique patented membrane teach-in pushbutton
- · One sensor for detecting both transparent objects and tiny nontransparent objects. This reduces the variety of sensors and saves on storage costs
- Autocollimation permits detection through very small drilled holes
- · IO-Link facilitates, for example, effortless initial system performance diagnostics and uses additional sensor functions to reduce complex control programming

#### → www.mysick.com/en/W4SLG-3H

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



## **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	15.3 mm x 63.2 mm x 22.2 mm
Housing design	Hygiene
Housing design (light emission)	Rectangular, Slim
Mounting hole	M3
Sensing range max. 1)	0 m 4.5 m
Sensing range 1)	0 m 2 m
Type of light	Visible red light
Light source 2)	Laser
Light spot size (distance)	Ø 1 mm (500 mm)
Wave length	650 nm
Laser class 3)	1
Adjustment	Cable, Single teach-in button <sup>4)</sup> / Single teach-in button (depending on type)
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> REF-AC1000.

### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	$<$ 5 $V_{pp}$
Power consumption 3)	≤ 30 mA
Output type	PNP / NPN (depending on type)
Output function	Complementary
Switching mode	Dark-switching 4) / Light/dark-switching 5) (depending on type)
Output current I <sub>max.</sub>	≤ 100 mA
Response time <sup>6)</sup>	≤ 0.5 ms
Switching frequency 7)	± 1,000 Hz
Connection type	Male connector, M8 $^{8)}$ / Cable, 2 m $^{9)}$ (depending on type)
Mechanical connection	D12 adapter shaft
Circuit protection	A <sup>10)</sup> , B <sup>11)</sup> , C <sup>12)</sup>
Protection class	III
Weight	
Connector M8 8)	140 g
Cable 9)	180 g
IO-Link	- / ✔ (COM2) (depending on type)
Housing material	Stainless steel V4A (1.4404, 316L)
Optics material	PMMA



 $<sup>^{2)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 3)}$  EN60825-1:2008-05 & IEC 60825-1:2007-03 / CDRH 21 CFR 1040.10 & 1040.11.

<sup>4)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)

Enclosure rating	IP 66, IP 67, IP 68, IP 69K <sup>13)</sup>
Ambient operating temperature	-10 °C +50 °C
Ambient operating temperature extended <sup>14) 15)</sup>	-30 °C +55 °C
Ambient storage temperature	-30 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

## **Ordering information**

Other models available at www.mysick.com/en/W4SLG-3H

#### WL4SLG-3H

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max. 1)	Mechanical connection		Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.		
			Dark-	Cable, Single	Connector M8, 4-pin	Cd-195	WL4SLG-3F5234H	1058278		
		DND	switching 2) Light/dark-	teach-in button 3)	Cable, 4-wire, 2 m, PVC	Cd-212	WL4SLG-3F4134H	1058283		
0 m 4.5 m	D12 adapter	PNP		Light/dark-	Light/dark-	Light/dark-	Single teach-in	Connector M8, 4-pin	Cd-083	WL4SLG-3P5232H
	shaft		switching 4)	button	Cable, 4-wire, 2 m, PVC	Cd-094	WL4SLG-3P4132H	1058282		
		NPN	Light/dark- switching 4)	Single teach-in button	Cable, 4-wire, 2 m, PVC	Cd-094	WL4SLG-3N4132H	1058284		

<sup>1)</sup> REF-AC1000.

#### WL4SLG-3H, IO-Link

- Sensor principle: photoelectric retro-reflective sensor
- IO-Link: standard functions

Sensing range max. 1)			Switching mode	Adjustment	Connection	Connection diagram	Model name	Part no.
0 m 4.5 m	D12 adapter shaft	PNP	Light/dark- switching <sup>2)</sup>	Single teach-in button	Connector M8, 4-pin	Cd-098	WL4SLGC-3P5232H	1058277

<sup>1)</sup> REF-AC1000.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{4)}</sup>$  Q = dark-switching.

 $<sup>^{5)}</sup>$  Q = light-switching.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Tightening torque, max.: 0.6 Nm.

<sup>&</sup>lt;sup>9)</sup> Do not bend below 0 °C.

 $<sup>^{10)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> B = inputs and output reverse-polarity protected.

<sup>12)</sup> C = interference suppression.

<sup>&</sup>lt;sup>13)</sup> Only in case of correctly mounted IP 69K connecting cable.

 $<sup>^{14)}</sup>$  As of  $T_a$  = 50 °C, a max. supply voltage  $V_{max.}$  = 24 V and a max. load current  $I_{max.}$  = 50 mA is permitted.

<sup>&</sup>lt;sup>15)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

 $<sup>^{2)}</sup>$  Q = dark-switching.

<sup>3)</sup> Adjustment via cable (ET): white cable or PIN2 according to the desired sensitivity > 2 ... < 8 s or put > 8 s on L+ (PNP) or on M (NPN)


<sup>4)</sup> Q = light-switching.

 $<sup>^{2)}</sup>$  Q = light-switching.

## **Dimensional drawings**


Dimensions in mm (inch)


#### WL4SLG-3H, connector



- ① Center of receiver's optical axis
- ② Center of optical axis, sender
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- 3 Single teach-in button

#### WL4SLG-3H, cable






- ① Center of optical axis
- ② Status indicator LED, yellow: Status of received light beam
- 3 Status indicator LED green: power on
- 4 Single teach-in button

F

### **Characteristic curves**

### Operating reserve

#### WL4SLG-3H




① PLV14-A / PLH25-M12 / PLH25-D12

② P41F / REF-AC1000

### **Bar diagrams**

#### WL4SLG-3H



Sensing range

① PLV14-A / PLH25-M12 / PLH25-D12

② P41F / REF-AC1000

## **Light spot diameter**

#### WL4SLG-3H, overview

Radius in mm (inch)

12 (0.47) 10 (0.39) (0.31) (0.24) (0.16)(0.08)-2 (-0.08) (-0.16)-6 (-0.24) -8 (-0.31)

2 (6.56)

3 (9.84)

4 4.5 (13.12)(14.76)

Distance in m (feet)

#### Dimensions in mm (inch)

Vertical	Horizontal
< 1.0	< 1.0
(0.04)	(0.04)
1.5	1.2
(0.06)	(0.05)
4.3	2.6
(0.17)	(0.10)
11.3	5.6
(0.44)	(0.22)
	< 1.0 (0.04) 1.5 (0.06) 4.3 (0.17) 11.3


Vertical Horizontal

-10 (-0.39)

(-0.47)

1 (3.28)

Radius in mm (inch)



Vertical
Horizontal

## **Connection diagram**

Cd-083

Cd-094

Cd-098

Cd-195

$$\begin{array}{c|c} & & \\ \hline & brn & 1 \\ \hline & blk & 4 \\ \hline & wht & 2 \\ \hline & & \\ \hline & blu & 3 \\ \hline & & -(M) \\ \end{array}$$

## **Recommended accessories**

### Plug connectors and cables

#### Connecting cable (female connector-open), hygienic systems

- Cable material: PP
- Connector material: PP

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
00	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
	M8, 4-pin, angled		5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674
	Female connector,	Cable, open conductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
	M12, 4-pin, straight		5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
	Female connector,	Cable, open	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
		conductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

#### Universal bar clamp systems

• For product family: Hygienic Design BeftecHD for sensors with D12 adapter shaft

Figure	Material	Description	Model name	Part no.
		Hygienic design mounting tube with bayonet lock, 14.4 mm x 85.5 mm x 14.4 mm	BEF-HDSBR	4074403
		Hygienic design flange with seal, 40 mm x 12 mm x 40 mm	BEF-HDSF	4072880
	Hygienic Design, Stainless steel V4A	Hygienic design telescopic tube, straight, with bayonet lock without flange, $23\ mm\ x\ 153\ mm\ x\ 23\ mm$	BEF-HDSTRG	2067780
	(1.4404, 316L), Silicone (seal)	Hygienic design telescopic tube, straight, with bayonet lock with flange, $40\ \text{mm}\ x\ 165\ \text{mm}\ x\ 40\ \text{mm}$	BEF-HDSTRGF	2067779
		Hygienic design telescopic tube, angled, with bayonet lock without flange, $23\;\text{mm}\;x\;125\;\text{mm}\;x\;73\;\text{mm}$	BEF-HDSTRW	2067778
		Hygienic design telescopic tube, angled, with bayonet lock with flange, $40\ mm\ x\ 125\ mm\ x\ 76\ mm$	BEF-HDSTRWF	2067777

## Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
4	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
N	FIVIIVIA/ ADS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

F









The W8 is a high-quality, miniature photoelectric sensor family specially designed for close-range applications. Autocollimation, background suppression, and high switching frequencies of 2 kHz make these sensors ideal for a broad range of applications. The

series is comprised of the WTB8 photoelectric proximity sensor, the WL8 and WLG8 photoelectric retro-reflective sensor and the WSE8 photoelectric throughbeam sensor. The housing is designed with M3 threaded mounting holes that provide easy and secure mounting.

### At a glance

- · Miniature housing with M3 threaded mounting holes
- Switching frequency up to 2 kHz
- · Stainless steel mounting bracket (1.4301/304) BEF-W100-A included with delivery

### Your benefits

- · Highly flexible design and operational capabilities due to precise background suppression
- · Quick and easy mounting due to the universally compatible M3 threaded mounting holes
- · A fast switching frequency optimizes production processes
- · All necessary accessories are included with delivery, decreasing installation and procurement costs
- · Application versatility due to sensitivity adjustments, light/dark switching and a variety of connection options



## **Additional information**

Detailed technical dataF-373
Ordering informationF-374
Dimensional drawings F-375
AdjustmentsF-375
Characteristic curves F-376
Bar diagramsF-377
Connection diagram F-377
Recommended accessories F-377

#### → www.mysick.com/en/W8

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



### **Detailed technical data**

#### **Features**

	WTB8	WL8
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor
Detection principle	Background suppression	Autocollimation
Dimensions (W x H x D)	11 mm x 31 mm x 20 mm	
Housing design (light emission)	Rectangular	
Sensing range max.	5 mm 300 mm <sup>1)</sup> (depending on type)	0 m 4 m <sup>2)</sup>
Sensing range	20 mm 300 mm <sup>1)</sup> (depending on type)	0 3 m <sup>2)</sup>
Type of light	Visible red light	
Light source 3)	LED	
Wave length	650 nm	
Adjustment	Potentiometer, 4 turns	Potentiometer, 270 °

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	WTB8	WL8		
Supply voltage 1)	10 V DC 30 V DC			
Ripple <sup>2)</sup>	± 10 %			
Power consumption 3)	≤ 30 mA			
Output type	PNP, open collector / NPN, open collector (depe	ending on type)		
Switching mode	Light/dark-switching (manually selectable)			
Signal voltage PNP HIGH/LOW	Approx. $V_S - 1.8 V / 0 V$			
Signal voltage NPN HIGH/LOW	Approx. $V_S$ / < 1.8 V			
Output current I <sub>max.</sub>	≤ 100 mA			
Response time 4)	≤ 0.5 ms	≤ 25 ms		
Switching frequency 5)	1,000 Hz	2,000 Hz		
Connection type	Cable, 2 m <sup>6)</sup> / Male connector, M8 (depending on type)			
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , D <sup>9)</sup>			
Weight				
Cable	50 g			
Connector M8	10 g			
Polarisation filter	-	<b>✓</b>		
Housing material	ABS			
Optics material	PMMA			
Enclosure rating	IP 67			
Items supplied	Stainless steel mounting bracket (1.4301/304) BEF-W100-A	Stainless steel mounting bracket (1.4301/304) BEF-W100-A, Reflector P250		
Ambient operating temperature	-25 °C +55 °C			
Ambient storage temperature	-40 °C +70 °C			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_{A}$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{2)}\,\</sup>mbox{May}$  not exceed or fall short of  $\mbox{V}_{\mbox{\scriptsize S}}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{\</sup>scriptscriptstyle{7)}}\,\mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

## **Ordering information**

Other models available at www.mysick.com/en/W8

#### WTB8

• Sensor principle: photoelectric proximity sensor

Detection principle: background suppression

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 4 turns

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
			Cable, 3-wire, 2 m, PVC	Cd-043	WTB8-P1111	6033211
		PNP	Connector M8, 3-pin	Cd-045	WTB8-P2111	6033213
E 100	Ø C mana (100 mana)		Connector M8, 4-pin	Cd-066	WTB8-P2211	6033215
5 mm 100 mm	Ø 6 mm (100 mm)	NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WTB8-N1111	6033210
			Connector M8, 3-pin	Cd-045	WTB8-N2111	6033212
			Connector M8, 4-pin	Cd-066	WTB8-N2211	6033214
	Ø 6 mm (100 mm)	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WTB8-P1131	6033205
			Connector M8, 3-pin	Cd-045	WTB8-P2131	6033207
30 mm 300 mm			Connector M8, 4-pin	Cd-066	WTB8-P2231	6033209
		NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WTB8-N1131	6033204
			Connector M8, 3-pin	Cd-045	WTB8-N2131	6033206
			Connector M8, 4-pin	Cd-066	WTB8-N2231	6033208

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL8

Sensor principle: photoelectric retro-reflective sensor

• **Detection principle:** autocollimation

Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °


Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
0 m 4 m	Ø 30 mm (1 m)	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WL8-P1131	6033177
			Connector M8, 3-pin	Cd-045	WL8-P2131	6033180
			Connector M8, 4-pin	Cd-066	WL8-P2231	6033182
		NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WL8-N1131	6033176
			Connector M8, 3-pin	Cd-045	WL8-N2131	6033179
			Connector M8, 4-pin	Cd-066	WL8-N2231	6033181

<sup>&</sup>lt;sup>1)</sup> PL80A.

## **Dimensional drawings**


Dimensions in mm (inch)

#### WTB8



- ① Standard direction
- 2 Center of optical axis
- 3 Connection
- ④ Orange LED indicator: switching output active
- ⑤ LED indicator green: stability indicator
- ⑥ Threaded mounting hole M3, max. tightening torque: 0.6 Nm


#### WL8



- ① Threaded mounting hole M3, max. tightening torque: 0.6 Nm
- 2 Center of optical axis
- 3 Connection
- 4 Orange LED indicator: switching output active
- (5) LED indicator green: stability indicator


## **Adjustments**

#### WTB8



- $\ensuremath{\textcircled{4}}$  Orange LED indicator: switching output active
- ⑤ LED indicator green: stability indicator
- $\ensuremath{{\ensuremath{\bigcirc}}} \ensuremath{\ensuremath{\bigcirc}} \ensuremath{\ensuremath{\otimes}} \ensuremath{\ensuremath{\otimes}$
- 8 Light/ dark rotary switch:
  - L = light switching, D = dark switching

#### WL8




- ④ Orange LED indicator: switching output active
- ⑤ LED indicator green: stability indicator
- 6 Sensitivity adjustment
- ② Light/ dark rotary switch:
  - L = light switching, D = dark switching

F

### **Characteristic curves**

#### Black-white shift


#### WTB8, 100 mm



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


## Operating reserve

#### WL8



- ① PL80A
- ② P250
- ③ P45
- Reflective tape Diamond Grade


#### WTB8, 300 mm



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


## **Bar diagrams**

#### WTB8, 100 mm




- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### WL8



- Sensing range
- Sensing range max.
- ① PL80A
- ② P250
- ③ P45
- 4 Reflective tape Diamond Grade

#### WTB8, 300 mm



- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### **Connection diagram**

#### Cd-043

### Cd-045

#### Cd-066

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
\hline
& \text{wht} & 2 \\
\hline
& \text{blu} & 3 \\
\hline
& \text{l} & \text{c} & \text{(M)}
\end{array}$$

#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
1	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

## F

## Plug connectors and cables

#### Connecting cable (female connector-open), PVC

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con- ductor heads	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled		5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
Female connector, M8, 4-pin, angled	Female connector,	male connector, Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873	

## Female connector (ready to assemble)M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

## Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
, n		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861

F







### **Additional information**

Detailed technical dataF-381
Ordering informationF-382
Dimensional drawingsF-382
AdjustmentsF-382
Characteristic curves F-383
Bar diagramsF-383
Connection diagram F-383
Recommended accessories F-383

## **Product description**

The WL8G is a high-quality, miniature retro-reflective clear material photoelectric sensor for detection of transparent objects in close-range applications. Autocollimation optics enable the reflector to be positioned as close to the sensor's front face as necessary. The housing design, with M3 threaded mounting holes, ensures easy and secure installation.

### At a glance

- Autocollimation
- Standard miniature housing with M3 threaded mounting holes
- · Light/dark switching selectable via rotary switch
- · Adjustable sensing range
- · All necessary accessories (BEF-W100-A and P250) are included with delivery

#### Your benefits

- Reliable object detection of transparent objects even at the shortest distances (no blind spot) or through narrow gaps
- · Highly visible light spot makes alignment quick and easy
- Reliable detection of all materials, including small and/or transparent objects, min. attenuation 15 %
- All necessary accessories (bracket and reflector) are included with delivery, reducing installation and procurement costs
- M3 mounting hole provides quick installation

#### → www.mysick.com/en/W8G

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	11 mm x 31 mm x 20 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 3 m
Sensing range 1)	0 1.7 m
Type of light	Visible red light
Light source 2)	LED
Light spot size (distance)	Ø 70 mm (2 m)
Wave length	650 nm
Adjustment	Potentiometer, 270 °
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> PL80A.

### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	± 10 %
Power consumption 3)	≤ 30 mA
Output type	PNP, open collector / NPN, open collector (depending on type)
Switching mode	Light/dark-switching (manually selectable)
Signal voltage PNP HIGH/LOW	Approx. $V_S - 1.8 \text{ V} / 0 \text{ V}$
Signal voltage NPN HIGH/LOW	Approx. $V_S / < 1.8 V$
Output current I <sub>max.</sub>	100
Response time 4)	≤ 0.5 ms
Switching frequency 5)	1,000
Attenuation along light beam	≤ 20 %
Connection type	Cable, 2 m <sup>6)</sup> / Male connector, M8 (depending on type)
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , D <sup>9)</sup>
Weight	
Cable <sup>6)</sup>	50 g
Connector	10 g
Polarisation filter	V
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 67
Items supplied	Stainless steel mounting bracket (1.4301/304) BEF-W100-A, Reflector P250F
Ambient operating temperature	-25 °C +55 °C
Ambient storage temperature	-40 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{\</sup>scriptscriptstyle{7)}}\,\mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{\</sup>rm 8)}$  B = inputs and output reverse-polarity protected.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

## **Ordering information**

Other models available at www.mysick.com/en/W8G

#### WL8G

• Sensor principle: photoelectric retro-reflective sensor

Detection principle: autocollimation

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °


• Items supplied: stainless steel mounting bracket (1.4301/304) BEF-W100-A, Reflector P250F

Sensing range max. 1)	Output type	Connection	Connection diagram	Model name	Part no.
	PNP	Cable, 3-wire 2 m PVC	Cd-043	WL8G-P1131	6033184
		Connector M8, 3-pin	Cd-045	WL8G-P2131	6033186
0 m 3 m		Connector M8, 4-pin	Cd-066	WL8G-P2231	6033188
0 111 3 111	NPN	Cable, 3-wire 2 m PVC	Cd-043	WL8G-N1131	6033183
		Connector M8, 3-pin	Cd-045	WL8G-N2131	6033185
		Connector M8, 4-pin	Cd-066	WL8G-N2231	6033187

<sup>1)</sup> PL80A.


### **Dimensional drawings**

Dimensions in mm (inch)




- $\ensuremath{\text{\textcircled{1}}}$  Threaded mounting hole M3, max. tightening torque: 0.6 Nm
- 2 Center of optical axis
- 3 Connection
- ④ Orange LED indicator: switching output active

### **Adjustments**




- ④ Orange LED indicator: switching output active
- Sensitivity adjustment
- © Light/ dark rotary switch:L = light switching, D = dark switching

### **Characteristic curves**



- ① PL80A
- ② P250F
- ③ PL20F
- 4 PL10F

### **Bar diagrams**



- Sensing range
- Sensing range typ. max.
- ① PL80A
- ② P250F
- ③ PL20F
- 4 PL10F

## **Connection diagram**

## F

## Cd-043

Cd-045

Cd-066

$$\begin{array}{c|c} & brn & 1 \\ \hline & brn & 2 \\ \hline & blu & 3 \\ \hline & blk & 4 \\ \hline & Q \\ \end{array}$$

### **Recommended accessories**

Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
1	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

## Plug connectors and cables

#### Connecting cable (female connector-open), PVC

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled	ductor heads	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
3	r WIWIAY ADO	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
4	DAANAA /ADS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
Ø	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

### **Special reflectors**

Figure	Material	Description	Model name	Part no.
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861













#### **Additional information**

/ talantion and innormation
Detailed technical dataF-387
Ordering informationF-388
Dimensional drawings F-390
AdjustmentsF-391
Characteristic curvesF-392
Bar diagramsF-393
Connection diagram F-394
Recommended accessories F-395

## **Product description**

The W8 INOX is a miniature product family, especially for applications in harsh ambient conditions. The high-quality IP 69K stainless steel housing (1.4404/ SUS316L) in combination with high-performance PPSU and PEEK plastics make these sensors suitable for a broad range of applications. In addition to a highly visible LED light spot, the W8 INOX includes M3 threaded mounting holes that reduce mounting time. These compact, lightweight sensors provide maximum resistance to harsh wash down environments in the food and beverage industry. The four models - through-beam, retroreflective, energetic and background suppression (BGS) - provide reliable, high-performance solutions for harsh environments.

#### At a glance

- · Rugged IP 69K stainless steel housing 1.4404/316L
- Front screen made of high-performance PPSU plastic that is resistant to heat and chemicals
- · Potentiometer made of mechanically stable high-performance PEEK (polyether ketone) plastic
- · Constructed with FDA-approved materials
- Well-defined, highly visible light spot
- · M3 threaded mounting holes and stainless steel mounting bracket (1.4301/304) included with delivery

#### Your benefits

- High reliability due to an IP 69K stainless steel housing, which withstands aggressive cleaning agents or cooling **lubricants**
- Quick and easy mounting due to universally compatible M3 threaded mounting holes
- Compact housing saves space (equal to W8 plastic version)
- · Highly visible light spot provides easy alignment
- All necessary accessories are included, which simplifies installation

#### www.mysick.com/en/W8\_Inox

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



## **Detailed technical data**

### **Features**

	WTB8 Inox	WTE8 Inox	WL8 Inox	WSE8 Inox
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Energetic	Standard optics	-
Dimensions (W x H x D)	11 mm x 21 mm x 33.3	3 mm		
Housing design (light emission)	Rectangular			
Sensing range max.	5 mm 500 mm <sup>1)</sup> (depending on type)	0 mm 950 mm <sup>1)</sup>	0.01 m 6.5 m <sup>2)</sup>	0 m 45 m
Sensing range	5 mm 300 mm <sup>1)</sup> (depending on type)	0 mm 700 mm <sup>1)</sup>	0.01 m 4.5 m <sup>3)</sup>	0 m 20 m
Type of light	Visible red light			
Light source 4)	LED			
Angle of dispersion	-	Approx. 3°		Approx. 2.5°
Wave length	650 nm	645 nm		
Adjustment	Potentiometer, 4 turns	Potentiometer, 270 °		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	WTB8 Inox	WTE8 Inox	WL8 Inox	WSE8 Inox
Supply voltage 1)	10 V DC 30 V DC			
Ripple <sup>2)</sup>	± 10 %			
Power consumption 3)	≤ 30 mA			-
Power consumption, sender	-			$\leq$ 15 mA $^{4)}$
Power consumption, receiver	-			≤ 20 mA <sup>4)</sup>
Output type	PNP / NPN (depending	( on type)		
Switching mode	Light/dark-switching (se	electable via light/dark s	elector)	
Signal voltage PNP HIGH/LOW	Approx. $V_S - 1.8 V / 0 V$	1		
Signal voltage NPN HIGH/LOW	Approx. $V_S$ / < 1.8 V			
Output current I <sub>max.</sub>	100 mA			
Response time 5)	≤ 0.5 ms			
Switching frequency 6)	1,000 Hz			
Angle of reception	-			Approx. 15°
Connection type	Cable, 2 m $^{7)}$ / Male con	nnector, M8 (depending	on type)	
Circuit protection	A $^{8)}$ , B $^{9)}$ , D $^{10)}$			
Protection class	III			
Weight	83.6 g			
Polarisation filter	-		<b>✓</b>	-
Housing material	Stainless steel V4A (1.4	1404, 316L)		

F

<sup>&</sup>lt;sup>2)</sup> PL80A.

<sup>&</sup>lt;sup>3)</sup> P250A.

 $<sup>^{4)}</sup>$  Average service life of 100,000 h at T  $_{\!\scriptscriptstyle \Delta}$  = +25 °C.

	WTB8 Inox	WTE8 Inox	WL8 Inox	WSE8 Inox		
Enclosure rating	IP 69K					
Items supplied	Stainless steel mountin (1.4301/304) BEF-W10	_	Stainless steel mounting bracket (1.4301/304) BEF-W100-A, P250A reflector	Stainless steel mounting bracket (1.4301/304) BEF-W100-A		
Ambient operating temperature 11)	-30 °C +60 °C					
Ambient storage temperature	-40 °C +70 °C					
1) I to the color of the color		0.4				

<sup>&</sup>lt;sup>1)</sup> Limit values, reverse-polarity protected operation in short-circuit protected network max. 8 A.

## **Ordering information**

Other models available at www.mysick.com/en/W8\_Inox

#### WTB8 Inox

Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

· Switching mode: light/dark-switching

• Adjustment: potentiometer, 4 turns

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	Ø 8 mm (100 mm)	PNP	Cable, 3-wire 2 m PVC	Cd-043	WTB8-P1111V	6041457
			Connector M8, 3-pin	Cd-045	WTB8-P2111V	6041458
5 mm 150 mm			Connector M8, 4-pin	Cd-066	WTB8-P2211V	6041459
5 11111 150 111111			Cable, 3-wire 2 m PVC	Cd-043	WTB8-N1111V	6041453
		NPN	Connector M8, 3-pin	Cd-045	WTB8-N2111V	6041454
			Connector M8, 4-pin	Cd-066	WTB8-N2211V	6041455
		PNP	Cable, 3-wire 2 m PVC	Cd-043	WTB8-P1131V	6041465
			Connector M8, 3-pin	Cd-045	WTB8-P2131V	6041466
10 mm 500 mm	Ø 22 mm (250 mm)		Connector M8, 4-pin	Cd-066	WTB8-P2231V	6041467
10 11111 500 11111	Ø 22 mm (350 mm)	NPN	Cable, 3-wire 2 m PVC	Cd-043	WTB8-N1131V	6041461
			Connector M8, 3-pin	Cd-045	WTB8-N2131V	6041462
			Connector M8, 4-pin	Cd-066	WTB8-N2231V	6041463

 $<sup>^{1\! )}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Receiver without load.

 $<sup>^{\</sup>rm 5)}$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>6)</sup> With light/dark ratio 1:1.

 $<sup>^{7)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{8)}</sup>$  A =  $\rm V_{S}$  connections reverse-polarity protected.

 $<sup>^{9)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> D = outputs overcurrent and short-circuit protected.

 $<sup>^{11)}</sup>$  At an air humidity of 35 ... 95 %.

#### • Sensor principle: photoelectric proximity sensor

Detection principle: energetic

Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
0 mm 950 mm	Ø 35 mm (700 mm)		Cable, 3-wire 2 m PVC	Cd-043	WTE8-P1131V	6041473
		PNP	Connector M8, 3-pin	Cd-045	WTE8-P2131V	6041474
			Connector M8, 4-pin	Cd-066	WTE8-P2231V	6041475
		NPN	Cable, 3-wire 2 m PVC	Cd-043	WTE8-N1131V	6041469
			Connector M8, 3-pin	Cd-045	WTE8-N2131V	6041470
			Connector M8, 4-pin	Cd-066	WTE8-N2231V	6041471

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL8 Inox

Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
0.01 m 6.5 m	PNP Ø 245 mm (4.5 m) NPN		Cable, 3-wire 2 m PVC	Cd-043	WL8-P1131V	6041481
		PNP	Connector M8, 3-pin	Cd-045	WL8-P2131V	6041482
			Connector M8, 4-pin	Cd-066	WL8-P2231V	6041483
			Cable, 3-wire 2 m PVC	Cd-043	WL8-N1131V	6041477
		NPN	Connector M8, 3-pin	Cd-045	WL8-N2131V	6041478
			Connector M8, 4-pin	Cd-066	WL8-N2231V	6041479

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### WSE8 Inox

• Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °


Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
0 m 45 m	Ø 900 mm (20 m)	PNP	Cable, 3-wire 2 m PVC	Cd-049	WSE8-P1131V	6041489
			Connector M8, 3-pin	Cd-051	WSE8-P2131V	6041490
			Connector M8, 4-pin	Cd-057	WSE8-P2231V	6041491
		NPN	Cable, 3-wire 2 m PVC	Cd-049	WSE8-N1131V	6041485
			Connector M8, 3-pin	Cd-051	WSE8-N2131V	6041486
			Connector M8, 4-pin	Cd-057	WSE8-N2231V	6041487

F

## **Dimensional drawings**


Dimensions in mm (inch)

#### WTB8, 150 mm




- ① Standard direction
- 2 Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection
- $\colongraphit{@linewidth}{?}$  Threaded mounting hole M3, max. tightening torque of 1.8 Nm for M3 screw with washer, spring ring and mounting bracket ( 2 x 3.2 mm borehole)

#### WTE8




- 1 Threaded mounting hole M3, max. tightening torque of 1.8 Nm for M3 screw with washer, spring ring and mounting bracket ( 2 x 3.2 mm borehole)
- 2 Center of optical axis, receiver
- $\ensuremath{\mathfrak{G}}$  Center of optical axis, sender
- Connection

#### WTB8, 500 mm



- (1) Standard direction
- 2 Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection
- $\colongraphite{O}$  Threaded mounting hole M3, max. tightening torque of 1.8 Nm for M3 screw with washer, spring ring and mounting bracket ( 2 x 3.2 mm borehole)

#### WL8




- ① Threaded mounting hole M3, max. tightening torque of 1.8 Nm for M3 screw with washer, spring ring and mounting bracket ( 2 x 3.2 mm borehole)
- 2 Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection

- $\ \, \textcircled{1}$  Threaded mounting hole M3, max. tightening torque of 1.8 Nm for M3 screw with washer, spring ring and mounting bracket (  $2 \, x \, 3.2$  mm borehole)
- 2 Center of optical axis, sender and receiver
- 3 Connection

## **Adjustments**


#### WTB8



- ⑤ Orange LED indicator: switching output active
- LED indicator green:
   stability indicator light up when the light received is < 0.9 or > 1.1
   (based on switching threshold Q = 1)
- Sensing range adjustment: potentiometer, 4-turn
- 9 Light/ dark rotary switch:L = light switching, D = dark switching

#### WTE8, WL8

40.5 (1.59)



- ⑤ Orange LED indicator: switching output active
- LED indicator green: stability indicator light up when the light received is < 0.9 or > 1.1 (based on switching threshold Q = 1)
- ② Sensitivity control: potentiometer 270°
- 8 Light/ dark rotary switch:L = light switching, D = dark switching

#### WSE8




- Orange LED indicator: switching output active (only WE)
- (§) LED indicator green: stability indicator light up when the light received is < 0.9 or > 1.1 (based on switching threshold Q = 1)
- © Sensitivity control: potentiometer 270° on WE
- Light/ dark rotary switch:L = light switching, D = dark switching

#### **Characteristic curves**

#### Black-white shift

#### WTB8, 150 mm


% of sensing distance



- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTE8


% of functional reserves



- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

#### WTB8, 500 mm

% of sensing




- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### Operating reserve

#### WL8


% of functional reserves



- ① PL80A
- ② P250
- ③ PL40A
- 4 PL30A
- ⑤ PL20A
- 6 Reflective tape Diamond Grade (100 mm x 100 mm/3.94 inch x 3.94 inch)
- ⑦ P45


#### WSE8

% of functional reserves




## **Bar diagrams**

#### WTB8, 150 mm




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WTB8, 500 mm




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission




- Sensing range
- Sensing range max.
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

## WL8



- Sensing range
- Sensing range max.
- ① PL80A
- ⑤ PL20A
- ② P250 ③ PL40A
- 6 Reflective tape Diamond Grade
- 4 PL30A
- ⑦ P45

#### WSE8



Sensing range


Sensing range max.

## **Connection diagram**


### Cd-043

#### Cd-045











- ① Sender
- 2 Receiver

#### Cd-051




- ① Sender
- 2 Receiver

#### Cd-057



- ① Sender
- 2 Receiver

#### Cd-066



### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
1	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

### Plug connectors and cables

#### Connecting cable (female connector-open), hygienic systems

Cable material: PP

• Connector material: PP

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67, IP 69K	DOL-0803-G02MN	6033664
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67, IP 69K	DOL-0803-G05MN	6033665
			2 m, 3-wire	IP 67, IP 69K	DOL-0803-W02MN	6033667
	Female connector, M8, 3-pin, angled	Cable, open con- ductor heads	5 m, 3-wire	IP 67, IP 69K	DOL-0803-W05MN	6033668
	me, e pm, angrea		10 m, 3-wire	IP 67, IP 69K	DOL-0803-W10MN	6033669
00		Female connector, Cable, open con- M8, 4-pin, straight ductor heads	2 m, 4-wire	IP 67, IP 69K	DOL-0804-G02MN	6033670
			5 m, 4-wire	IP 67, IP 69K	DOL-0804-G05MN	6033671
	mo, i pin, oddigite		10 m, 4-wire	IP 67, IP 69K	DOL-0804-G10MN	6033672
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-0804-W02MN	6033673
	M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-0804-W05MN	6033674

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO8N for universal clamp bracket	BEF-KHS-N08N	2051616

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
J.	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.	
==	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097	

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

# **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861













# **Additional information**

Detailed technical dataF-399
Ordering informationF-400
Dimensional drawingsF-400
AdjustmentsF-400
Characteristic curves F-401
Bar diagramsF-401
Connection diagram F-401
Recommended accessories F-402



The WTB8L is a high-quality miniature photoelectric proximity sensor with laser emitter LEDs and outstanding background suppression specially designed for close-range applications. High switching frequencies of 2 kHz make these sensors suitable for a broad range of applications. The housing design, with M3 threaded mounting holes, ensures easy and secure mounting.

# At a glance

- · Laser class 1
- Background suppression
- · Standard miniature housing with M3 threaded mounting holes
- Switching frequency up to 2 kHz
- Light/dark switching via rotary switch
- Mounting bracket BEF-W100-A is included with delivery

### Your benefits

- · Highly flexible design and operational capabilities due to precise background suppression
- Reliable detection of small objects, regardless of color or surface qualities
- · Rapid switching frequency reliably detects objects travelling at high speeds which allows to optimize the production processes
- · Highly visible laser light spot simplifies alignment
- · All necessary accessories are included with delivery, reducing installation and procurement costs

#### → www.mysick.com/en/W8\_Laser

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Background suppression
Dimensions (W x H x D)	11 mm x 31 mm x 20 mm
Housing design (light emission)	Rectangular
Sensing range max.	5 mm 300 mm <sup>1)</sup> (depending on type)
Sensing range	20 mm 300 mm <sup>1)</sup> (depending on type)
Type of light	Visible red light
Light source 2)	Laser
Wave length	650 nm
Laser class	I
Adjustment	Potentiometer, 4 turns

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

Supply voltage 1)		10 V DC 30 V DC
Ripple <sup>2)</sup>		± 10 %
Power consumption 3)		≤ 30 mA
Output type		PNP, open collector / NPN, open collector (depending on type)
Switching mode		Light/dark-switching (manually selectable)
Signal voltage PNP HIGH/LOW		Approx. $V_S - 1.8 V / 0 V$
Signal voltage NPN HIGH/LOW		Approx. $V_S$ / < 1.8 V
Output current I <sub>max.</sub>		≤ 100 mA
Response time 4)		≤ 0.25 ms
Switching frequency 5)		2,000 Hz
Connection type		Cable, 2 m $^{\rm 6)}$ / Male connector, M8 (depending on type)
Circuit protection		A 7), B 8), D 9)
Weight		
	Cable 6)	50 g
	Connector	10 g
Housing material		ABS
Optics material		PMMA
Enclosure rating		IP 67
Items supplied		Stainless steel mounting bracket (1.4301/304) BEF-W100-A
Ambient operating temperature		-10 °C +50 °C
Ambient storage temperature		-40 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

F

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{\</sup>scriptscriptstyle{7)}}\,\mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{\</sup>rm 9)}$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/W8\_Laser

# WTB8L

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 4 turns


Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
			Cable, 4-wire 2 m PVC	Cd-116	WTB8L-P1111	6033223
		PNP	Connector M8, 3-pin	Cd-045	WTB8L-P2111	6033225
5 mm 100 mm	Ø 1 mm (100 mm)		Connector M8, 4-pin	Cd-078	WTB8L-P2211	6033227
5 mm 100 mm	Ø 1 mm (100 mm) Ø 1.5 mm (300 mm)		Cable, 4-wire 2 m PVC	Cd-116	WTB8L-N1111	6033222
		NPN	Connector M8, 3-pin	Cd-045	WTB8L-N2111	6033224
			Connector M8, 4-pin	Cd-078	WTB8L-N2211	6033226
			Cable, 4-wire 2 m PVC	Cd-116	WTB8L-P1131	6033217
		PNP	Connector M8, 3-pin	Cd-045	WTB8L-P2131	6033219
20 200			Connector M8, 4-pin	Cd-078	WTB8L-P2231	6033221
30 mm 300 mm			Cable, 4-wire 2 m PVC	Cd-116	WTB8L-N1131	6033216
		NPN	Connector M8, 3-pin	Cd-045	WTB8L-N2131	6033218
			Connector M8, 4-pin	Cd-078	WTB8L-N2231	6033220

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# **Dimensional drawings**

Dimensions in mm (inch)


#### WTB8L



- ① Standard direction
- ② Center of optical axis
- 3 Connection
- ④ Orange LED indicator: switching output active
- ⑤ LED indicator green: stability indicator
- 6 Threaded mounting hole M3, max. tightening torque: 0.6 Nm

# **Adjustments**

### WTB8L




- ④ Orange LED indicator: switching output active
- ⑤ LED indicator green: stability indicator
- ② Sensing range adjustment
- ® Light/ dark rotary switch: L = light switching, D = dark switching

# **Characteristic curves**


#### Black-white shift

### WTB8L, 100 mm



- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### WTB8L, 300 mm



- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


# **Bar diagrams**

### WTB8L, 100 mm



- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


#### WTB8L, 300 mm



- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


# **Connection diagram**

#### Cd-045



# Cd-078

### Cd-116



# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
. 4	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

# Plug connectors and cables

# Connecting cable (female connector-open), PVC

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open con- ductor heads	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled		5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
Female connector M8, 4-pin, angled	Female connector.	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled		5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
Se	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

<sup>→</sup> For additional accessories, please see page L-861

F

Miniature photoelectric sensors for standard applications





Available from June 2014



### **Additional information**

Detailed technical dataF-405
Ordering informationF-406
Dimensional drawingsF-408
AdjustmentsF-408
Connection diagram F-408
Recommended accessories F-409

# **Product description**

W100-2 miniature photoelectric sensors are compatible with all standard detection principles (through-beam photoelectric sensors, photoelectric retro-reflective sensors, photoelectric retro-reflective sensors for detecting transparent objects, energetic sensors, and sensors with background blanking), making them an ideal sensor family for detection applications.

The housing design includes M3 threaded mounting holes, spaced one inch apart, that allows for straightforward, standardized, and inexpensive mounting. As a result, the W100-2 product family offers an economical photoelectric sensor solution with outstanding performance.

### At a glance

- Reliable detection behavior, rugged housing and immunity to ambient light
- WT100-2 photoelectric proximity sensor (energetic or with background blanking)
- WL100-2 photoelectric retro-reflective sensor; variant available for detecting transparent objects
- WS/WE100-2 through-beam photoelectric sensor
- Various connection types available (standard: 2 m cable; M8 male connector, 3-pin; M8 male connector, 4-pin; male cable connector available on request)
- · Light/dark switching and sensitivity adjustment possible
- · Wide range of accessories

# Your benefits

- · Reliable detection in standard applications
- Short downtime and high throughput thanks to reliable object detection
- Ability to handle a wide range of detection principles within a single standardized housing, reducing the number of model variants
- Simple commissioning thanks to easily visible display LEDs
- Easy to set up thanks to user-friendly potentiometer (dependent on model)
- Standard housing that is compatible with many commonly used mounting
- Easy mounting thanks to 1-inch hole
- · High level of operating reserve minimizes susceptibility to contamination

#### www.mysick.com/en/W100-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

	WT100-2	WL100-2	WS/WE100-2
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Energetic / Background blanking (depending on type)	-	
Dimensions (W x H x D)	11 m x 31 m x 20 m		
Housing design (light emission)	Rectangular		
Sensing range max.	0 mm 1,000 mm <sup>1)</sup> (depending on type)	0.01 m 7.5 m <sup>2)</sup> (depending on type)	0 m 30 m
Sensing range	0 mm 750 mm <sup>1)</sup> (depending on type)	0.01 m 6 m <sup>2)</sup> (depending on type)	0 m 20 m
Type of light	Visible red light		
Light source 3)	LED		
Angle of dispersion	Approx. 6.8° / approx. 5° (depending on type)	Approx. 4°	± 7.2°
Wave length	632 nm		
Adjustment	Potentiometer		Potentiometer, 270 °
Special feature	-	Detection of transparent objects (depending on type)	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WT100-2	WL100-2	WS/WE100-2
Supply voltage 1)	10 V 30 V		-! 
Ripple 2)	± 10 %		
Power consumption 3)	≤ 30 mA		-
Power consumption, sender	-		$\leq$ 15 mA $^{3)}$
Power consumption, receiver	-		≤ 20 mA <sup>3)</sup>
Output type	PNP / NPN (depending on type	e)	
Switching mode	Light/dark-switching (manually	selectable)	
Signal voltage PNP HIGH/LOW	$U_V$ - 1,8 V / ca. 0 V		
Signal voltage NPN HIGH/LOW	Approx. $V_S$ / < 1.8 V		
Output current I <sub>max.</sub>	100 mA		
Response time 4)	≤ 0.5 ms		
Switching frequency	1,000 Hz		
Angle of reception	-		± 15°
Attenuation along light beam	-	≥ 20 %	-
Connection type	Cable, 2 m 5) / Male connector,	M8 (depending on type)	
Circuit protection	A <sup>6)</sup> , B <sup>7)</sup> , D <sup>8)</sup>		
Protection class	III		
Polarisation filter	-	✓ / - (depending on type)	-
Housing material	ABS/PC/POM		
Optics material	PMMA		

F

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

WS/WE100-2

WL100-2

Enclosure rating	IP 67		
Items supplied	Mounting bracket BEF-W100-A	Mounting bracket BEF-W100-A, Reflector P250	Mounting bracket BEF-W100-A
Ambient operating temperature	-25 °C +55 °C		
Ambient storage temperature	-40 °C +70 °C		
1) Limit values.			
2) May not avacad as fall about of V talasanaca			

WT100-2

# **Ordering information**

Other models available at www.mysick.com/en/W100-2

# WT100-2

• Sensor principle: photoelectric proximity sensor

• Switching mode: light/dark-switching

• Adjustment: potentiometer

• Items supplied: mounting bracket BEF-W100-A

Detection principle	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
				Cable, 3-wire, 2 m, PVC	Cd-043	WT100-2P1439	6052372
			PNP	Connector M8, 3-pin	Cd-045	WT100-2P3439	6052373
Energetic	0 mm 1,000 mm	Ø 55 mm		Connector M8, 4-pin	Cd-040	WT100-2P4439	6052374
Ellergetic	0 111111 1,000 111111	<sup>п</sup> (400 mm)		Cable, 3-wire, 2 m, PVC	Cd-043	WT100-2N1439	6052369
			NPN	Connector M8, 3-pin	Cd-045	WT100-2N3439	6052370
				Connector M8, 4-pin	Cd-040	WT100-2N4439	6052371
		Ø 8 mm (90 mm)	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WT100-2P1419	6052378
				Connector M8, 3-pin	Cd-045	WT100-2P3419	6052379
Background	4 mm 140 mm			Connector M8, 4-pin	Cd-040	WT100-2P4419	6052380
blanking	4 11111 140 111111			Cable, 3-wire, 2 m, PVC	Cd-043	WT100-2N1419	6052375
			NPN	Connector M8, 3-pin	Cd-045	WT100-2N3419	6052376
				Connector M8, 4-pin	Cd-040	WT100-2N4419	6052377

 $<sup>^{\</sup>mbox{\tiny $1$})}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

 $<sup>^{5)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{\</sup>rm 6)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{7)}</sup>$  B = output reverse-polarity protected.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

• Sensor principle: photoelectric retro-reflective sensor

• Polfilter: ✔

· Switching mode: light/dark-switching

• Adjustment: potentiometer

• Items supplied: mounting bracket BEF-W100-A, Reflector P250

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	Ø 250 mm (3.5 mm)	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WL100-2P1439	6052360
			Connector M8, 3-pin	Cd-045	WL100-2P3439	6052361
0.01 m 7.5 m			Connector M8, 4-pin	Cd-040	WL100-2P4439	6052362
0.01 m 7.5 m		NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WL100-2N1439	6052357
			Connector M8, 3-pin	Cd-045	WL100-2N3439	6052358
			Connector M8, 4-pin	Cd-040	WL100-2N4439	6052359

<sup>1)</sup> PL80A.

# WL100-2, detection of transparent objects

• Sensor principle: photoelectric retro-reflective sensor

• Polfilter: -

· Switching mode: light/dark-switching

• Adjustment: potentiometer

• Items supplied: mounting bracket BEF-W100-A, Reflector P250

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
0.01 m 3 m	Ø 200 mm (2 mm)	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WL100-2P1429	6052384
			Connector M8, 3-pin	Cd-045	WL100-2P3429	6052385
			Connector M8, 4-pin	Cd-040	WL100-2P4429	6052386
		NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WL100-2N1429	6052381
			Connector M8, 3-pin	Cd-045	WL100-2N3429	6052382
			Connector M8, 4-pin	Cd-040	WL100-2N4429	6052383

<sup>1)</sup> PL80A.

# WS/WE100-2

Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °


Items supplied: mounting bracket BEF-W100-A


Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	Ø 1,500 mm (12 mm)	PNP	Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE100-2P1439	6052366
			Connector M8, 3-pin	Cd-051	WS/WE100-2P3439	6052367
0 m 30 m			Connector M8, 4-pin	Cd-057	WS/WE100-2P4439	6052368
0 111 50 111		NPN	Cable, 3-wire, 2 m, PVC	Cd-049	WS/WE100-2N1439	6052363
			Connector M8, 3-pin	Cd-051	WS/WE100-2N3439	6052364
			Connector M8, 4-pin	Cd-057	WS/WE100-2N4439	6052365

# **Dimensional drawings**

Dimensions in mm (inch)


#### WT100, WL100






- ① Threaded mounting hole M3
- 2 Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection
- $\ensuremath{\mbox{\Large \Large \sc S}}$  LED indicator orange: switching output active
- 6 LED indicator green: stability indicator

#### **WS/WE100**






- ① Threaded mounting hole M3
- ② Center of optical axis, receiver
- $\ensuremath{\mathfrak{G}}$  Center of optical axis, sender
- 4 Connection
- ⑤ LED indicator orange: output active
- **6** LED indicator green: stability indicator
- 7 Sensing range adjustment: potentiometer, 270°
- 8 Light/ dark rotary switch:L = light switching, D = dark switching

# **Adjustments**

### W100-2



- $\ensuremath{\text{\textcircled{1}}}$  LED indicator orange: switching output active
- ② LED indicator green: power on
- 3 Sensing range adjustment: potentiometer
- 4 Light/ dark rotary switch:

L = light switching, D = dark switching

# **Connection diagram**

#### Cd-040




#### Cd-043




#### Cd-045






- ① Sender
- 2 Receiver

### Cd-051



- ① Sender
- ② Receiver

#### Cd-057



- ${\bf 1}{\bf 0} \, {\rm Sender}$
- 2 Receiver

# **Recommended accessories**

Plug connectors and cables

Connecting cable (female connector-open), PVC

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open conductor heads	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight		5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
	Female connector,	Cable, open	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled	conductor heads	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight con	conductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector, Cable, open	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871	
	conductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873	

### Male connector (ready to assemble)M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type termi- nals	РВТ	IP 67	STE-0803-G	6037322

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
8	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, plugable for metal plates	PL22-3	1004488

→ For additional accessories, please see page L-861

Miniature photoelectric laser sensor provides precise detection of objects in standard applications













### **Additional information**

Detailed technical dataF-413
Ordering informationF-414
Dimensional drawingsF-415
AdjustmentsF-415
Characteristic curvesF-416
Bar diagramsF-417
Light spot diameter F-417
Connection diagram F-417
Recommended accessories F-418

# **Product description**

The W100 Laser is a complete family of photoelectric sensors enclosed in a miniature housing. These sensors feature a laser sender LED that provides large sensing ranges for standard applications. The compact housing design

with M3 threaded mounting holes allows for quick and simple mounting. The W100 Laser is a great alternative to the standard W100, especially for applications that demand higher precision or a longer sensing range.

# At a glance

- Standard miniature housing with M3 threaded mounting holes
- · Long sensing range
- · Light/dark switching and sensitivity adjustment via rotary switch possible
- · Various versions are available, including through-beam, retro-reflective and energetic
- · Wide variety of accessories available
- Laser emitter LED, class 1

# Your benefits

- Reliable detection of small objects
- · Less contamination due to high optical operating reserve
- M3 threaded mounting holes provide easy installation
- · Compact housing easily fits in applications with limited space

### → www.mysick.com/en/W100\_Laser

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

# **Features**

	WT100L	WL100L	WS/WE100L
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Energetic	Standard optics	-
Dimensions (W x H x D)	11 mm x 31 mm x 20 mm		
Housing design (light emission)	Rectangular		
Sensing range max.	0 mm 450 mm <sup>1)</sup>	0.08 m 12 m <sup>2)</sup>	0 m 35 m
Sensing range	0 mm 400 mm	$0.08~m \dots 10~m^{2)}$	0 m 30 m
Type of light	Visible red light		
Light source 3)	Laser		
Light spot size (distance)	Ø 2 mm (400 mm)	Ø 12 mm (10 m)	Ø 30 mm (30 m)
Wave length	650 nm		
Laser class	1		
Adjustment	Potentiometer, 270 °		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WT100L	WL100L	WS/WE100L
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	± 10 %		
Power consumption <sup>3)</sup>	≤ 30 mA		-
Power consumption, sender	-		≤ 15 mA <sup>3)</sup>
Power consumption, receiver	-		≤ 20 mA <sup>3)</sup>
Output type	PNP, open collector / NPN, open	n collector (depending on type)	
Switching mode	Light/dark-switching (manually	selectable)	
Signal voltage PNP HIGH/LOW	$U_V$ - 1,8 V / ca. 0 V		
Signal voltage NPN HIGH/LOW	Approx. $V_S$ / < 1.8 V		
Output current I <sub>max.</sub>	100		
Response time 4)	< 0.25 ms		
Switching frequency 5)	2,000		
Connection type	Cable, 2 m $^{\rm 6)}$ / Male connector,	M8 (depending on type)	
Circuit protection	A 7), B 8), D 9)		
Weight			
Cable <sup>6)</sup>	50 g		
Connector	10 g		
Polarisation filter	-	<b>✓</b>	-
Housing material	ABS/PC/POM, ABS/PC (depend	ding on type)	
Optics material	PMMA		

Ē

<sup>&</sup>lt;sup>2)</sup> P250F.

 $<sup>^{\</sup>rm 3)}$  Average service life 50,000 h at T  $_{\!A}$  = +25  $^{\circ}$  C.

	WT100L	WL100L	WS/WE100L
Enclosure rating	IP 65		
Items supplied	Stainless steel mounting bracket (1.4301/304) BEF-W100-A	Stainless steel mount- ing bracket (1.4301/304) BEF-W100-A, Reflector P250F	2 Stainless steel mounting brackets (1.4301/304) BEF-W100-A
Ambient operating temperature	-10 °C +50 °C		
Ambient storage temperature	-40 °C +70 °C		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W100\_Laser

#### WT100L

Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Light spot size (distance): Ø 2 mm (400 mm)

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °

• Items supplied: stainless steel mounting bracket (1.4301/304) BEF-W100-A

Sensing range max. <sup>1)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
	PNP	Cable, 3-wire, 2 m, PVC	Cd-043	WT100L-F1141	6030702
		Connector M8, 3-pin	Cd-045	WT100L-F2141	6030703
0 mm 450 mm		Connector M8, 4-pin	Cd-066	WT100L-F2241	6030704
0 mm 450 mm	NPN	Cable, 3-wire, 2 m, PVC	Cd-043	WT100L-E1141	6030705
		Connector M8, 3-pin	Cd-045	WT100L-E2141	6030706
		Connector M8, 4-pin	Cd-066	WT100L-E2241	6030707

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### **WL100L**

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

• Light spot size (distance): Ø 12 mm (10 m)

· Switching mode: light/dark-switching

• Adjustment: potentiometer, 270 °

• Items supplied: stainless steel mounting bracket (1.4301/304) BEF-W100-A, Reflector P250F

Sensing range max. 1)	Output type	Connection	Connection diagram	Model name	Part no.
0.08 m 12 m		Cable, 3-wire, 2 m, PVC	Cd-043	WL100L-F1131	6030708
	PNP	Connector M8, 3-pin	Cd-045	WL100L-F2131	6030709
		Connector M8, 4-pin	Cd-066	WL100L-F2231	6030710
		Cable, 3-wire, 2 m, PVC	Cd-043	WL100L-E1131	6030711
	NPN	Connector M8, 3-pin	Cd-045	WL100L-E2131	6030712
		Connector M8, 4-pin	Cd-066	WL100L-E2231	6030713

<sup>1)</sup> P250F.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>8)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

# WS/WE100L


- Sensor principle: through-beam photoelectric sensor
- Light spot size (distance): Ø 30 mm (30 m)
- Switching mode: light/dark-switching
- Adjustment: potentiometer, 270 °
- Items supplied: 2 Stainless steel mounting brackets (1.4301/304) BEF-W100-A

Sensing range max.	Output type	Connection	Connection diagram	Model name	Part no.
	PNP	Cable, 3-wire, 2 m, PVC	Cd-047	WS/WE100L-F1131	6030714
		Connector M8, 3-pin	Cd-051	WS/WE100L-F2131	6030715
0 m 35 m		Connector M8, 4-pin	Cd-071	WS/WE100L-F2231	6030716
0 111 35 111	NPN	Cable, 3-wire, 2 m, PVC	Cd-047	WS/WE100L-E1131	6030717
		Connector M8, 3-pin	Cd-051	WS/WE100L-E2131	6030718
		Connector M8, 4-pin	Cd-071	WS/WE100L-E2231	6030719

# **Dimensional drawings**


Dimensions in mm (inch)


### WT100L, WL100L



(3) (3) (13.4) (13.4) (19.8.0.78) (19.8.0.78)

### WS/WE100L






- ① Threaded mounting hole M3
- 2 Center of optical axis, receiver
- 3 Center of optical axis, sender
- 4 Connection

- ① Threaded mounting hole M3
- ② Center of optical axis
- ③ Connection


# **Adjustments**

### WT100L, WL100L



- ⑤ Orange LED indicator: switching output active
- **6** LED signal strength indicator green:power on
- $\ensuremath{\text{\textcircled{?}}}$  Sensing range (WT) / sensitivity (WL) adjustment: potentiometer, 270  $^\circ$
- 8 Light/ dark rotary switch: L = light switching, D = dark switching

# WS/WE100L




- ④ Orange LED indicator: switching output active
- ⑤ LED signal strength indicator green:power on
- © Sensitivity adjustment 270°
- ② Light/ dark rotary switch: L = light switching, D = dark switching

# **Characteristic curves**

#### Black-white shift


### WT100L



- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


# Operating reserve

### WL100L




- ① P250F
- ② PL20F
- ③ PL10F

### WS/WE100L




### WT100L




- Sensing range
- Sensing range max.
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WS/WE100L




# **Light spot diameter**

# WT100L




All dimensions in mm (inch)

### **WL100L**



All dimensions in m (feet)


### **WL100L**



Sensing range

Sensing range max.

#### WS/WE100L



All dimensions in m (feet)


# **Connection diagram**


# Cd-043



#### Cd-045

# Cd-047





Cd-066

Cd-071

① Sender ② Receiver

# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
2	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521

# Plug connectors and cables

# Connecting cable (female connector-open), PVC

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-G02M	6010785
	M8, 3-pin, straight	ductor heads	5 m, 3-wire	IP 67	DOL-0803-G05M	6022009
//	Female connector.	Cable, open con-	2 m, 3-wire	IP 67	DOL-0803-W02M	6008489
	M8, 3-pin, angled ductor heads	' •	5 m, 3-wire	IP 67	DOL-0803-W05M	6022010
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-0804-G05M	6009872
	Female connector.	Cable, open con-	2 m, 4-wire	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-0804-W05M	6009873

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497

# Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm $$	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, Ø 23 mm	P25F-1	5319385
		Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm	P41F	5315128
2	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
0		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm $$	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

→ For additional accessories, please see page L-861

F



# G

# The packaging specialists - photoelectric sensors to optimize your applications

From harsh environments in the food and beverage industry to high-speed cigarette manufacturing, sensors are exposed to a variety of challenges. Due to high-performance electronics and sophisticated optics, small photoelectric sensors from SICK detect all objects, even under difficult conditions. The latest technologies, such as PinPoint LED, custom ASICs, µC or IO-Link provide outstanding performance in modern, functional housings.

#### Your benefits

- Outstanding sensor performance in small housings
- Reliable object detection of difficult targets using best-in-class technology
- A wide range of different sensor housings and connection systems ensures optimal integration of sensors in the system
- Many options for protective housings – super tough VISTAL™, metal or highly resistant plastic, ensures that the sensor can be installed without damage
- Wide range of accessories ensures easy installation, quick commissioning and maximum sensor performance for varying application needs





# **Small photoelectric sensors**

	Product selection			
	G10			W11G-2
<b>P</b>	W9-3			W12-2 Laser
	W9-3 Glass			W12G
	<b>W9L-3</b>			W12-3
	<b>W9LG-3</b>			performance in demanding applications  W14-2
<u> </u>	W11-2		•	demanding applications
	High-performance photoelectric sensors with application flexibility in industrial environments			W18-3

# Overview of small photoelectric sensors

	Hou							Sensor properties															
	Mat		лорс	11103		Enc	losure	e ratin	ng	Jens	,01 pi	ореги	.103										
	Plastic	Metal	VISTAL™	Explosion protection	PTFE coating	IP 65	99 dI	IP 67	₩ 69K	Photoelectric proximity sensor	Energetic	Background suppression	Foreground suppression	Photoelectric retro-reflective sensor	Autocollimation	Standard optics	Through-beam photoelectric sensor	IO-Link	AutoAdapt	Switching frequency ★ ≥ 2 kHz	AC/DC		
G10	_	_			_	_	_	_	_	_ "	_	_	_			0,		_		0, 7.			
G10 NEW																							
W9																							
W9-3																							
W9-3 Glass																							
W9L-3																							
W9LG-3																							
W11																							
W11-2																							
W11G-2																							
W12																							
W12-2 Laser																							
W12G																							
W12-3																							
W14																							
W14-2																							
W18																							
W18-3																							



1	
L	5

Optical properties							Special applications							Page		
Type of	f light/L	ight sen	der	Light spot geom- etry	Techno	ology										
LED infrared light	LED red light	Red laser light	PinPoint LED red light 🔭	Line-shaped light spot 🤺	Focused optics	SIRIC®	Hygienic and washdown zones	Detecting transparent objects	Detecting perforated objects	Detecting small objects	Detecting uneven, shiny objects	Detecting objects wrapped in film	Detecting objects with position tolerances	Detecting high-speed objects	Explosive areas	
																G-430
•					•					•						G-448
						•										G-462
						•										G-470
						•				•						G-484
						•										G-492
								•								G-504
						-	•			•				•		G-510
•	-		•					-								G-520
•	•		•	•	•	-			•	•						G-528
	•			•		•						-				G-544
_	_					_									_	
																G-556

# Photoelectric proximity sensors

	■ Maximum sensing range	Dimensions (W x H x D)	Page
W12-2 Laser	20 mm 200 mm	15.0 mm x 49.0 mm x 41.5 mm	G-510
W9L-3	25 mm 400 mm	12.2 mm x 52.2 mm x 23.6 mm	G-470
W12-3	20 mm 800 mm	15.6 mm x 48.5 mm x 42.0 mm	G-528
W9-3	20 mm 800 mm	12.2 mm x 52.2 mm x 23.6 mm	G-448
W18-3	10 mm 1,000 mm	17.6 mm x 75.5 mm x 33.5 mm	G-556
W11-2	20 mm 1,100 mm	15.6 mm x 48.5 mm x 42.0 mm	G-492
W14-2	20 mm 1,500 mm	17.6 mm x 75.5 mm x 33.5 mm	G-544
G10	20 mm 2,000 mm	20 mm x 50 mm x 51.5 mm	G-430


# Photoelectric retro-reflective sensors

	Maximum sensing range	Dimensions (W x H x D)	Page
W11G-2	0 m 4 m	15.6 mm x 48.5 mm x 42.0 mm	G-504
W12G	0 m 4 m	15.6 mm x 48.5 mm x 42.0 mm	G-520
W9LG-3	0 m 4.5 m	12.2 mm x 52.2 mm x 23.6 mm	G-484
W9-3	0 m 5 m	12.2 mm x 52.2 mm x 23.6 mm	G-448
W9-3 Glass	0 m 5 m	12.2 mm x 52.2 mm x 23.6 mm	G-462
W12-3	0 m 7 m	15.6 mm x 48.5 mm x 42.0 mm	G-528
W18-3	0 m 7 m	17.6 mm x 75.5 mm x 33.5 mm	G-556
W11-2	0.15 m 10 m	15.6 mm x 48.5 mm x 42.0 mm	G-492
W9L-3	0 m 12 m	12.2 mm x 52.2 mm x 23.6 mm	G-470
G10	0.08 m 15 m	20 mm x 50 mm x 51.5 mm	G-430
W14-2	0.15 m 17 m	17.6 mm x 75.5 mm x 33.5 mm	G-544
W12-2 Laser	0 m 18 m	15.0 mm x 49.0 mm x 41.5 mm	G-510

# Through-beam photoelectric sensors

	■ Maximum sensing range	Dimensions (W x H x D)	Page
W9-3	0 m 10 m	12.2 mm x 52.2 mm x 23.6 mm	G-448
W14-2	0 m 15 m	17.6 mm x 75.5 mm x 33.5 mm	G-544
W11-2	0 m 20 m	15.6 mm x 48.5 mm x 42 mm	G-492
W12-3	0 m 20 m	15.6 mm x 48.5 mm x 42 mm	G-528
W18-3	0 m 20 m	17.6 mm x 75.5 mm x 33.5 mm	G-556
G10	0 m 40 m	20 mm x 50 mm x 51.5 mm	G-430
W9L-3	0 m 60 m	12.2 mm x 52.2 mm x 23.6 mm	G-470
W12-2 Laser	0 m 80 m	15 mm x 49 mm x 41.5 mm	G-510

# **Product family overview**



→ G-430

→ G-462





W9L-

Laser precision in a rugged VISTAL™ housing



W9LG-3

Laser precision in a rugged VISTAL  $^{\mbox{\tiny TM}}$  housing for clear material detection



N11-2

High-performance photoelectric sensors with application flexibility in industrial environments

	12,2 mm x 52.2 mm x 23.6 mm  25 mm 400 mm  0 m 12 m	12.2 mm x 52.2 mm x 23.6 mm	15.6 mm x 48.5 mm x 42 mm
	25 mm 400 mm	12.2 mm x 52.2 mm x 23.6 mm	15.6 mm x 48.5 mm x 42 mm
		-	
		<del>-</del>	
	0 m 12 m		20 mm 1,100 mm
		0 m 4.5 m	0.05 m 10 m
	0 m 60 m	-	0 m 20 m
	Laser	Laser	PinPoint LED/LED
	Visible red light	Visible red light	Visible red light
	IP 66, IP 67, IP 69K	IP 66, IP 67, IP 69K	IP 66, IP 67, IP 69K
	Plastic VISTAL <sup>™</sup>	Plastic VISTAL <sup>™</sup>	Plastic
·			
	Tough VISTAL™ housing Precise laser light spot Photoelectric proximity sensor in laser classes 1 and 2 Photoelectric retro-reflective sensor with autocollimation optics and polar- izing filter; models available for clear material detection Through-beam photoelectric sensors with sensing ranges of up to 60 m SIRIC technology Connections: M8 and M12 plugs, cable as well as cable with plug M3 and M4 hole pattern	<ul> <li>Tough VISTAL™ housing</li> <li>Precise laser light spot, laser class 1</li> <li>Continuous switching threshold adjustment (CTA)</li> <li>Autocollimation optics and polarizing filter</li> <li>Teach-in</li> <li>SIRIC technology</li> <li>Connections: M8 and M12 plugs, cable as well as cable with plug</li> <li>M3 and M4 hole pattern</li> </ul>	<ul> <li>Uniform housing, mounting and connection systems</li> <li>Rugged sensors for industrial use</li> <li>PinPoint LED technology provides highly visible light spot</li> <li>Space-saving plastic housing in chemically, thermally or mechanically resistant designs</li> <li>Dovetail mounting – mounting holes and oblong holes</li> <li>Highly visible 360° status LEDs</li> </ul>
	→ G-470	→ G-484	→ G-492





Reliable detection of clear material objects - from PET bottles to transparent film



W12-2 Laser

High-performance photoelectric sensor family with laser optics



W12G

High-performance detection of transparent objects in metal housing

#### Tecnical data overview

Dimensions (W x H x D)	15.6 mm x 48.5 mm x 42 mm	15 mm x 49 mm x 41.5 mm	15.6 mm x 48.5 mm x 42 mm	
Sensing range max.				
Photoelectric proximity sensor	-	20 mm 50 mm	-	
		30 mm 200 mm		
Photoelectric retro-reflective	0 m 4 m	0 m 18 m	0 m 4 m	
sensor				
Through-beam photoelectric	-	0 m 80 m	_	
sensor				
Light source	LED	Laser	PinPoint LED/LED	
Type of light	Visible red light	Visible red light	Visible red light/Infrared light	
Enclosure rating	IP 66, IP 67, IP 69K	IP 67, IP 69K	IP 66, IP 67, IP 69K	
Housing material	Plastic	Metal/PTFE	Metal/PTFE	

#### At a glance

- · Retro-reflective for detection of clear material objects
- Rugged housing for industrial use
- · PinPoint LED technology with a highly visible light spot
- · Space-saving plastic housing in chemically, thermally or mechanically resistant designs
- · Dovetail mounting standard mounting holes and oblong holes
- Highly visible 360° status **LEDs**
- Simple sensitivity adjustment via potentiometer → G-504

- Best-in-class retro-reflective laser performance in a metal housing
- Teflon® coating available
- Precise autocollimation optics
- · Adjustable focus on retroreflective sensors
- · High switching frequency of 2.5 kHz
- Connection via cable or rotatable connector
- · Mounting options with through holes, blind holes, oblong holes and dovetail
- Laser protection class 1 or

- Rugged die-cast zinc housing with optional Teflon® coating
- Reliable detection of transparent objects
- · Precise autocollimation optics
- Robust sensors for industrial use
- Precise PinPoint LED
- Dovetail mounting mounting holes and oblong holes
- Highly visible status LEDs
- Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

→ G-510 → G-520

**Detailed information** 






Rugged metal housing provides exceptional performance in demanding applications



Cost-effective photoelectric sensors for demanding applications



Reliable object detection for demanding applications

15.6 mm x 48.5 mm x 42 mm	17.6 mm x 75.5 mm x 33.5 mm	17.6 mm x 75.5 mm x 33.5 mm	
20 mm 800 mm	20 mm 1,500 mm	10 mm 1,000 mm	
0 m 7 m	0.15 m 17 m	0 m 7 m	
	0.5 m 5 m		
0 m 20 m	0 m 15 m	0 m 20 m	
PinPoint-LED/LED	PinPoint-LED/LED	LED	
Visible red light/Infrared light	Visible red light/Infrared light	Visible red light/Infrared light	
IP 66, IP 67, IP 69K	IP 67	IP 65 / IP67	
Metal/PTFE	Plastic	Plastic	
Best-in-class optical performance	<ul> <li>Outstanding background suppression</li> </ul>	Best-in-class optical performance	
due to superior OES technology	with OES3 technology	due to superior OES technology	
Autocollimation with retro-reflective	<ul> <li>Highly visible and precise light spot</li> </ul>	Autocollimation optics	
sensors	due to PinPoint LED in selected	Background suppression with second	
Background and foreground sup-	products	sender LED	
pression with second emitter LED on	Slim, durable plastic housing	Slim, durable plastic housing	

- proximity sensors
- Highly visible, precise light spot and high-energy IR transmitters
- Rugged die-cast zinc housing, optional with Teflon® coating
- Mounting options with through holes, base blind holes, oblong through holes and dovetail
- Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link
- · Complete sensor family with proximity, retro-reflective and through-beam variants
- · Operation via double teach-in pushbutton or potentiometer
- · Wide variety of options for operation, connection, and optics

→ G-528













# **Product description**

One thing is for sure – thanks to Q-Lock, G10 sensors are mounted lightning fast, connected in the flick of a wrist, and get your line up and running within seconds! Tick, tock, done. Even in large-scale systems. The hawk's-eye of the G10 makes no compromises and detects exactly what it's meant to see, without being

distracted by dirt, grime or optical reflections. Always focused: Its acute optics increases productivity while the Q-Lock allows systems being set-up faster and more efficiently than ever before. All this at a price that is as sharply calculated as its vision. Count on it!

# At a glance

- Maximum optical window surface combined with a small sensor housing
- Sensing range up to 1,200 mm with background suppression performance
- PinPoint LED with bright and precise light spot
- Sensor variants in all major detection principles and with DC or AC/DC power supply
- · Transistor output or relay output
- Latest SICK ASIC chip technology
- Rugged sensor housing with metal sleeved mounting holes

### Your benefits

- G10 focuses on the essentials the user really needs – without compromising quality, reliability or performanager
- One sensor family serves all standard industrial and domestic applications
- Reliable object detection and long scanning ranges thanks to large optics and SICK ASIC technology
- Easy and fast sensor alignment due to small and highly visible PinPoint light spot
- Insensitive to dust and dirt on front lens or reflector
- Clever accessories reduce installation effort and safe time

# **Additional information**

C C UL) US PINPOINT

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-446

#### → www.mysick.com/en/G10

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

# **Features**

	GTB10	GTE10	GL10	GL10G	GSE10	
Sensor principle	Photoelectric proximity sensor		Photoelectric retro-reflective sensor		Through-beam photoelectric sensor	
Detection principle	Background suppression	Energetic	Standard optics		-	
Dimensions (W x H x D)						
DC	20 mm x 50 mm x 39 mm					
AC/DC	20 mm x 50 mm x 51.5 mm					
Housing design (light emission)	Rectangular	Rectangular				
Sensing range max.	20 mm 1,200 mm <sup>1)</sup> (depending on type)	20 mm 2,000 mm <sup>1)</sup> (depending on type)	0.05 m 15 m <sup>2)</sup> (depending on type)	$0.05~m$ $12~m$ $^{2)}$	0 m 40 m	
Sensing range	-	40 mm 1,500 mm <sup>1)</sup> (depending on type)	0.08 m 12 m <sup>2)</sup> (depending on type)	0.03 m 9.5 m <sup>2)</sup>	0 m 35 m	
Type of light	Visible red light/Infrared light (depending on type)		Visible red light		Visible red light/Infrared light (depending on type)	
Light source 3)	PinPoint LED/LED (depending on type)		PinPoint LED		PinPoint LED /LED (depending on type)	
Wave length						
Visible red light	625 nm					
Infrared light	850 nm		-		850 nm	
Adjustment	Potentiometer, Potentiometer, 270 ° (depending on type) 5 turns 270 °		ype)			
Special feature	-			Clear material detection	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	GTB10	GTE10	GL10	GL10G	GSE10
Supply voltage					
DC <sup>1)</sup>	10 V DC 30 V DC				
AC/DC <sup>2)</sup>	24 V AC/DC 240 V AC/DC			-	24 V AC/DC 240 V AC/DC
Ripple 3)	± 5 V <sub>pp</sub>				
Power consumption 4)					
DC	≤ 30 mA				
Current consumption					
AC/DC	≤ 0.6 VA			-	≤ 0.6 VA
Output type					
DC	PNP Open collecto	r/NPN Open collect	or (typabhängig)		
AC/DC	Relais, SPDT, elect	rically isolated 5)			
Switching mode					
DC	Light/dark-switchin	ng (selectable via lig	ght/dark selector)		



<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	GTB10	GTE10	GL10	GL10G	GSE10
Switching mode selector	Selectable via light	/dark selector			
Output current I <sub>max.</sub>	≤ 100 mA				
DC	≤ 100 mA				
Switching load max. (current/voltage)					
AC/DC	0,11 A (250 V DC)/ 3 A (250 V AC)	3 A (30 V DC)		-	0,11 A (250 V DC)/3 A (30 V DC)/ 3 A (250 V AC)
Response time					
DC <sub>e)</sub>	≤ 500 µs			≤ 500 µs/≤ 1 ms	≤ 500 µs
AC/DC	≤ 10 ms			-	≤ 10 ms
Switching frequency 7)					
DC	1,000 Hz			1,000 Hz/500 Hz	1,000 Hz
AC/DC	20 Hz			-	20 Hz
Connection type	Cable, 2 m 8)/Male	connector, M12 (de	epending on type)		
Circuit protection					
DC	A $^{9)}$ , B $^{10)}$ , D $^{11)}$				
AC/DC	A <sup>9)</sup> , C <sup>12)</sup>				
Protection class					
DC	Ш				
AC/DC	II				
Polarisation filter	-		V		-
Interference emission 13)					
AC/DC	EN 61000-6-3 (20:	11-09)			
Housing material	ABS/PMMA				
Enclosure rating	IP 67				
Relay switching cycles min.					
AC/DC	100.000 cycles (3	A)			
Usage category					
AC/DC	AC-15, DC-13, acco	ording to EN 60947	'-1		
EMC	EN 60947-5-2				
Test input					
DC	-				Sender OFF at "Test" 0 V
Ambient operating temperature	-30 °C +60 °C				
Ambient storage temperature	-40 °C +70 °C				
Weight					
Connector M12, 4-pin	Approx. 35 g				Approx. 70 g
Cable, 3-wire	Approx. 90 g				Approx. 180 g
Cable, 5-wire	Approx. 115 g			-	Approx. 230 g

 $<sup>^{\</sup>mbox{\tiny $1$})}$  Limit values, operation in short-circuit protected network max. 8 A.

<sup>&</sup>lt;sup>2)</sup> +- 10 %.

 $<sup>^{\</sup>rm 3)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>4)</sup> Without load.

<sup>&</sup>lt;sup>5)</sup> Provide suitable spark suppression for inductive or capacitive loads.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{8)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{9)}</sup>$  A =  $V_{S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>12)</sup> C = interference suppression.

 $<sup>^{13)}</sup>$  In the case of a DC supply (ref. to EN 61000-6-3) the length of cable between the supply source and the sensor must be < 30 m.

#### GTB10, DC

Sensor principle: photoelectric proximity sensor
 Detection principle: background suppression

Type of light: visible red light
 Supply voltage: 10 V DC ... 30 V DC
 Switching frequency: 1,000 Hz
 Switching mode: light/dark-switching

Sensing range max. 1)	Light spot size (dis- tance)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
				Cable, 3-wire,		-	GTB10-P1211	1065854
		PNP	Adjustable,	2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01	GTB10-P1212	1065856
		Ø 8 mm	potentiometer, 5 turns	Connector		-	GTB10-P4211	1064694
20 mm				M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01	GTB10-P4212	1065857
950 mm	(700 mm)		Adjustable,	Cable, 3-wire, 2 m, PVC	Cd-044	-	GTB10-N1211	1065858
						Mounting bracket BEF- G10DC01	GTB10-N1212	1065859
			potentiometer, 5 turns	Connector	0.1.000	-	GTB10-N4211	1065860
				M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01	GTB10-N4212	1065861

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### GTB10, AC/DC

Sensor principle: photoelectric proximity sensor
 Detection principle: background suppression

• Output type: relay

Supply voltage: 10 V DC ... 30 V DCSwitching frequency: 20 Hz

• Switching mode: light/dark-switching

Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Type of light	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
20 mm	Ø8mm	Visible	Adjustable,	Cable, 5-wire,	04.462	-	GTB10-R3811	1064686
950 mm	(700 mm)	red light	potentiometer, 5 turns	2 m, PVC	Cd-163	Mounting bracket BEF- G10UC01	GTB10-R3812	1065862
20 mm	Ø 22 mm	Infrared	Adjustable,	Cable, 5-wire,	04.462	-	GTB10-R3821	1065863
1,200 mm	(700 mm)	light	potentiometer, 5 turns	2 m, PVC	Cd-163	Mounting bracket BEF- G10UC01	GTB10-R3822	1065864

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### GTE10, DC

• Sensor principle: photoelectric proximity sensor

Detection principle: energetic
 Type of light: visible red light
 Supply voltage: 10 V DC ... 30 V DC

Switching frequency: 1,000 HzSwitching mode: light/dark-switching

Sensing range max. 1)	Light spot size (dis- tance)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
				Connector	0.1.000	-	GTE10-P4211	1064697
	20 mm Ø 28 mm	PNP	Adjustable,	M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01	GTE10-P4212	1065867
		FINE	potentiometer, 270 °	Cable, 3-wire,		-	GTE10-P1211	1065865
20 mm				2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01	GTE10-P1212	1065866
1,300 mm	(1,400 mm)		Adjustable,	Cable, 3-wire, 2 m, PVC	01044	-	GTE10-N1211	1065868
					Cd-044	Mounting bracket BEF- G10DC01	GTE10-N1212	1065869
		NPN	potentiometer, 270 °	Connector	0.1.000	-	GTE10-N4211	1065871
				M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01	GTE10-N4212	1065872

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### GTE10, AC/DC

Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

Output type: relay

Supply voltage: 10 V DC ... 30 V DCSwitching frequency: 20 Hz

• Switching mode: -

Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Type of light	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
20 mm	Ø 28 mm	Visible	Adjustable,	Cable, 5-wire,	04462	-	GTE10-R3811	1064688
1,300 mm	(1,400 mm)	red light	potentiometer, 270 °	2 m, PVC	Cd-163	Mounting bracket BEF- G10UC01	GTE10-R3812	1065873
20 mm	Ø 57 mm	Infrared	Adjustable,	Cable, 5-wire,	04462	-	GTE10-R3821	1065874
2,000 mm	(1,500 mm)	light	potentiometer, 270 °	2 m, PVC	Cd-163	Mounting bracket BEF- G10UC01	GTE10-R3822	1065875

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



#### GL10, DC

• Sensor principle: photoelectric retro-reflective sensor

Type of light: visible red light
 Supply voltage: 10 V DC ... 30 V DC
 Switching frequency: 1,000 Hz
 Switching mode: light/dark-switching

Sensing range max.	Light spot size (dis- tance)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.			
				Cable, 3-wire,		-	GL10-P1111	1065876			
			No/fix	2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01, Reflector P250	GL10-P1112	1065877			
			NO/ IIX	Connector		-	GL10-P4111	1065878			
				M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01, Reflector P250	GL10-P4112	1065879			
		PNP	PNP	PNP	PNP	Adjustable	Cable, 3-wire, 2 m, PVC	Cd-044	-	GL10-P1211	1065885
			Adjustable,	Cable, 3-wire, 2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01, Reflector P250	GL10-P1212	1065886			
			potentiometer, 270 °	Connector		-	GL10-P4211	1065890			
0.08 m 15 m <sup>1)</sup>	Ø 58 mm			M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01, Reflector P250	GL10-P4212	1065887			
0.08 m 12 m <sup>2)</sup>	(5 m)			Cable, 3-wire,		-	GL10-N1111	1065880			
			No/fix	2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01, Reflector P250	GL10-N1112	1065882			
			NO/ IIX	Connector		-	GL10-N4111	1065883			
		NDN		M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01, Reflector P250	GL10-N4112	1065884			
	NPN	INFIN		Cable, 3-wire,		-	GL10-N1211	1065888			
			Adjustable, potentiometer, 270 °	2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01, Reflector P250	GL10-N1212	1065889			
				Connector		-	GL10-N4211	1064700			
				M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01, Reflector P250	GL10-N4212	1065891			

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### GL10, AC/DC

• Sensor principle: photoelectric proximity sensor

• Output type: relay

Supply voltage: 10 V DC ... 30 V DCSwitching frequency: 20 Hz

• Switching mode: -

Sensing range max.	Light spot size (dis- tance)	Type of light	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
				Cable, 5-wire,		-	GL10-R3711	1065896
0.08 m 15 m <sup>1)</sup>	Ø 58 mm	Visible	No/fix	2 m, PVC	Cd-163	Mounting bracket BEF- G10UC01, Reflector P250	GL10-R3712	1065897
0.08 m	(5 m)	red light	Adjustable,	Cable 5 wire		-	GL10-R3811	1064689
12 m <sup>2)</sup>	2 m <sup>2)</sup> potentiometer, 270 ° Cable, 5-wire 2 m, PVC			Cd-163	Mounting bracket BEF- G10UC01, Reflector P250	GL10-R3812	1065898	

<sup>1)</sup> PL80A.

<sup>&</sup>lt;sup>2)</sup> P250.

<sup>&</sup>lt;sup>2)</sup> P250.

#### GL10, detecting objects wrapped in film

• Sensor principle: photoelectric retro-reflective sensor

Type of light: visible red light
 Supply voltage: 10 V DC ... 30 V DC
 Switching frequency: 500 Hz
 Switching mode: light-switching

Sensing range max.	Light spot size (distance)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
0.15 m 12 m <sup>1)</sup>	Ø 58 mm	PNP	No/fix	Connector M12, 4-pin	Cd-066	- Q-Lock mounting system BEF-KHSO12R01	GL10-P4551 GL10-P4554	1064702 1065893
0.15 m 10 m <sup>2)</sup>	(5 m)	NPN	ŕ	Cable, 3-wire, 2 m, PVC	Cd-044	-	GL10-N1551	1065892

<sup>1)</sup> PL80A.

#### GL10G, clear material detection

• Sensor principle: photoelectric retro-reflective sensor

Type of light: visible red light
Supply voltage: 10 V DC ... 30 V DC
Switching frequency: 500 Hz

• Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Output type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
				Connector		-	GL10G-P4251	1064704
0.15 m 12 m <sup>1)</sup>	Ø 58 mm	PNP	Adjustable,	M12, 4-pin	Cd-066	Mounting bracket BEF- G10DC01, Reflector P250	GL10G-P4252	1065894
0.15 m	(5 m)		270 °	Cable, 3-wire,		-	GL10G-N1251	1064705
10 m <sup>2)</sup>	NPN NPN		2 m, PVC	Cd-044	Mounting bracket BEF- G10DC01, Reflector P250	GL10G-N1252	1065895	

<sup>1)</sup> PL80A.

<sup>&</sup>lt;sup>2)</sup> P250.

<sup>&</sup>lt;sup>2)</sup> P250.

### GSE10, DC

• Sensor principle: through-beam photoelectric sensor

Type of light: visible red light
 Supply voltage: 10 V DC ... 30 V DC
 Switching frequency: 1,000 Hz
 Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Type of light	Out- put type	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
					Connector		-	GSE10-P4111	1065899
			PNP	No/fix	M12, 4-pin	Cd-073	Mounting bracket BEF- G10DC01 (2x)	GSE10-P4112	1065900
			PINP	Adjustable, potentiometer, 270 ° Connector M12, 4-pin		-	GSE10-P4211	1064706	
	Visible red light					Cd-073	Mounting bracket BEF- G10DC01 (2x)	GSE10-P4212	1065903
				Cable, 3-wire,		-	GSE10-N1111	1065901	
0 m			NPN	No/fix	2 m, PVC	Cd-061	Mounting bracket BEF- G10DC01 (2x)	GSE10-N1112	1065902
40 m	(50 m)		INFIN	Adjustable, potentiometer, 270 °	Cable, 3-wire, 2 m, PVC	Cd-061	-	GSE10-N1211	1065904
							Mounting bracket BEF- G10DC01 (2x)	GSE10-N1212	1065905
				Adjustable,	Connector		-	GSE10-P4221	1065906
	Infra- red light	Infra- red	potentiometer, 270 °	M12, 4-pin	Cd-073	Mounting bracket BEF- G10DC01 (2x)	GSE10-P4222	1065907	
			Adjustable, Cable, 3-wire,		-	GSE10-N1221	1065908		
		NPN	potentiometer, 270 °	2 m, PVC	Cd-061	Mounting bracket BEF- G10DC01 (2x)	GSE10-N1222	1065909	

#### GSE10, AC/DC

Sensor principle: through-beam photoelectric sensor


• Type of light: relay


Supply voltage: 10 V DC ... 30 V DC
Switching frequency: 1,000 Hz

• Switching mode: -

Sensing range max.	Light spot size (distance)	Type of light	Adjustment	Connection	Connection diagram	Items supplied	Model name	Part no.
				Cable, 5-wire,		-	GSE10-R3711	1065910
		Visible red	No/fix	2 m, PVC	Cd-170	Mounting bracket BEF- G10UC01 (2x)	GSE10-R3712	1065911
0 m	li	light	Adjustable, potentiometer, 270 °	Cable, 5-wire, 2 m, PVC		-	GSE10-R3811	1064691
40 m	(50 m)				Cd-170	Mounting bracket BEF- G10UC01 (2x)	GSE10-R3812	1065912
				Cable, 5-wire,		-	GSE10-R3721	1065913
		Infrared light	No/fix	2 m, PVC	Cd-170	Mounting bracket BEF- G10UC01 (2x)	GSE10-R3722	1065914

#### GTB10, DC, cable









- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on

#### GTB10, DC, connector








- ① Center of optical axis, sender
- ② Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on

#### GTB10, AC/DC, cable







50 (1.97)

- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- $\ensuremath{\textcircled{4}}$  LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on

#### GTE10, GL10, GL10G, DC, connector









- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- ④ LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on

#### GTE10, GL10, GL10G, DC, cable









- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on


#### GTE10, GL10, GL10G, AC/DC, cable






- ① Center of optical axis, sender
- ② Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on

#### **GSE10**, DC, connector








- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on


#### GSE10, DC, cable






- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on

#### GSE10, AC/DC, cable








- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole, Ø 4.2 mm
- 4 LED indicator yellow: Light received
- (5) LED signal strength indicator green:power on


### **Adjustments**

#### GTB10, GTE10, DC




- **6** Sensing range adjustment
- 7 Light/dark selector

# GL10, GL10G, GSE10, DC




- **6** Sensing range adjustment
- ② Light/dark selector

#### GTB10, GTE10, AC/DC



6 Sensing range adjustment

#### GL10, GL10G, GSE10, AC/DC




6 Sensing range adjustment

#### **Characteristic curves**

#### Black-white shift

## GTB10, redlight


% of sensing range



- 1 Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### GTB10, infrared light


% of sensing range



- ① Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on black, 6 % remission

#### GTE10, red light

#### Operating reserve




- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission

#### Operating reserve

#### GL10, DC, AC/DC


#### Operating reserve



- ① REF-IRF-56
- ② PL20A
- ③ PL30A
- **4** P250
- ⑤ PL40A
- **6** PL80A

#### GTE10, infrared light


#### Operating reserve



- ① Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### **GL10** logistics, DC


#### Operating Reserve



- ① REF-IRF-56
- ② PL20A
- 3 PL30A
- 4 P2505 PL40A
- 6 PL80A


#### GSE10, red light

#### Operating reserve




#### **GSE10**, infrared light

#### Operating reserve




### **Bar diagrams**

#### GTB10, redlight




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on black, 6 % remission

#### GTE10, red light




- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### GTB10, infrared light




- Sensing range
- Sensing range max.
- $\ensuremath{\textcircled{1}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

#### GTE10, infrared light




- Sensing range
- Sensing range max.
- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on black, 6 % remission

#### **GL10**




- Sensing range
- Sensing range max.
- ① REF-IRF-56
- ② PL20A
- ③ PL30A
- 4 P2505 PL40A
- 6 PL80A

#### GSE10, red light, infrared light



Sensing range

#### GL10, Logistik, DC




Sensing range


- Sensing range max.
- ① REF-IRF-56
- ② PL20A
- ③ PL30A
- **4** P250
- ⑤ PL40A
- 6 PL80A

### Light spot diameter


#### GTB10, redlight




### GTB10, infrared light




### GTE10, red light






GTE10, infrared light


#### GL10, AC/DC




**GL10, GL10G** 



GSE10, red light



**GSE10**, infrared light




### **Connection diagram**

#### Cd-044




#### Cd-061




- ① Sender
- 2 Receiver


#### Cd-163




#### Cd-170



① Sender 2 Receiver



Cd-073



- ① Sender
- 2 Receiver

#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Description	Material	Model name	Part no.
1	Mounting bracket for wall and floor mounting for G10 DC	Steel, zinc coated	BEF-G10DC01	2071258
	Mounting bracket for wall and floor mounting for G10 AC/DC		BEF-G10UC01	2071259

### Universal bar clamp systems

Figure	Description	Material	Model name	Part no.
	Q-Lock, bar clamp system for G10 and reflector P250	Die-cast zinc,	BEF-KHSQ12R01	2071260
	Q-Lock, bar clamp system for G10 and reflector P250, incl. sheet clamp	Steel, zinc coated	BEF-KHSQ12ZR01	2071262

### Device protection (mechanical)

Figure	Description	Material	Model name	Part no.
1	Weather protection hood for G10	Steel, zinc coated	BEF-G10WSG	2071960
	Weather protection hood for reflectors PL80A, P250, PL40A	Goot, Zillo Godicu	BEF-PL80AWSG	2071961

#### Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,		2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
100	M12, 4-pin, straight		5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
		Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
			5 m, 4-wire	IP 67	DOL-1204-W05M	6009867



### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
a de la companya de l	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
•		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	DMMA /ADC	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	DAMAMA /ADC	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861



High-performance sensors in a rugged **VISTAL™** housing











#### **Additional information**

Detailed technical dataG-449
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-459



The W9-3 sensors feature a compact, rugged housing made from VISTAL™, offers an outstanding mechanical robustness, Plus, proprietary optic and OES3 ASIC technology provides bestin-class sensing performance. The

W9-3 also includes unique connectivity options, mounting variability and optical specifications, making it the perfect solution for challenging automation applications. Add this advantage to your machine.

#### At a glance

- High-performance sensor in ultrarugged VISTAL™ housing
- PinPoint LED for highly visible and precise light spot
- Two emitter LEDs for best-in-class background suppression
- · Variable mounting with M3 or M4 hole pattern
- Wide range of connection options

#### Your benefits

- Robustness with the VISTAL<sup>™</sup> housing
- · Best in class performance
- · Wide variance in connection, mounting and optic

#### → www.mysick.com/en/W9-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



### **Detailed technical data**

#### **Features**

	WTB9-3	WTB9M4-3	WL9-3	WL9M4-3	WSE9-3	WSE9M4-3
Sensor principle			Photoelectric retro-reflective sensor		Through-beam photoelectric sensor	
Detection principle	Background su	ppression	Autocollimation	1	-	
Dimensions (W x H x D)		mm x 23.6 mm/ 2 mm x 23.6 mn			/	
Housing design (light emission)	Rectangular					
Mounting hole	M3	M4	M3	M4	M3	M4
Sensing range max.	20 mm 800 (depending on		0 m 5 m $^{2)}$ (depending on	type)	0 m 10 m	
Sensing range			0 m 3 m <sup>2)</sup> (depending on type)		0 m 7 m	
Type of light	Visible red light light (dependir	,	Visible red light			
Light source 4)	PinPoint LED /LED (depending on type)		PinPoint LED			
Wave length						
Visible red light	650 nm					
Infrared light	850 nm		-			
Adjustment	Potentiometer,	5 turns	Single teach-in	button	No adjustment	
Special feature	-		Focused optics	-		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	WTB9-3	WTB9M4-3	WL9-3	WL9M4-3	WSE9-3	WSE9M4-3
Supply voltage 1)	10 V DC 30 V DC					
Ripple 2)	< 5 V <sub>pp</sub>					
Power consumption 3)	≤ 30 mA					
Output type 4)	PNP/NPN (dep	ending on type)				
Output function	Complementar	у				
Switching mode 4)	Light/dark-swit	ching				
Output current I <sub>max.</sub> 5)	≤ 100 mA					
Connection type	Cable, 2 m <sup>8</sup> /Male connector, M8/Male connector, M12/Cable with connector, M12, 120 mm <sup>8</sup> (depending on type)					
Circuit protection	A $^{9)}$ , B $^{10)}$ , C $^{11)}$					
Protection class	III					
Weight						
Connector	13 g					
Cable/cable with connector	80 g					
Polarisation filter	-		<b>✓</b>		-	
Housing material	$VISTAL^TM$					
Optics material	PMMA					

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Object with 6 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 4)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25 °C.

	7

	WTB9-3	WTB9M4-3	WL9-3	WL9M4-3	WSE9-3	WSE9M4-3
Enclosure rating	IP 66/IP 67/IP	69K				
Test input sender off	-				Sender off	
Ambient operating temperature	-40 °C +60	°C				
Ambient storage temperature	-40 °C +75	°C				

 $<sup>^{1)}</sup>$  Limit values, operation in short-circuit protected network max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/W9-3

#### **WTB9-3**

• Detection principle: background suppression

• Mounting hole: M3

• Adjustment: potentiometer, 5 turns

• Switching mode: light/dark-switching (Q = light-switching.)

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Switching frequency <sup>2)</sup> / Response time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-094	WTB9-3P1161	1049043
					Cable, 4-wire, 5 m, PVC	Cd-094	WTB9-3P1261	1049044
				PNP	Connector M8, 4-pin	Cd-084	WTB9-3P2261	1049047
Visible	20 mm	Ø 4.5 mm	1,500 Hz/		Connector M12, 4-pin	Cd-084	WTB9-3P2461	1049049
red light	350 mm	(75 mm)	< 0.333 ms		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WTB9-3P3461	1049051
				NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WTB9-3N1161	1049052
				INFIN	Connector M12, 4-pin	Cd-084	WTB9-3N2461	1049053
		Ø 20 mm (250 mm)	1,000 Hz/ < 0.5 ms	PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WTB9-3P1111	1049042
	20 mm 500 mm				Connector M8, 4-pin	Cd-084	WTB9-3P2211	1049045
		(===:,,,			Connector M12, 4-pin	Cd-084	WTB9-3P2411	1049048
Infrared					Cable, 4-wire, 2 m, PVC	Cd-094	WTB9-3P1111S14	1052173
light					Connector M8, 4-pin	Cd-084	WTB9-3P2211S14	1052171
	20 mm	Ø 40 mm	200 Hz/	PNP	Connector M12, 4-pin	Cd-084	WTB9-3P2411S14	1052172
	800 mm	(400 mm)	< 2.5 ms		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WTB9-3P3411S14	1054431
				NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WTB9-3N1111S14	1050948

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

 $<sup>^{\</sup>scriptsize{3)}}$  Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

 $<sup>^{5)}</sup>$  As of Tu 50 °C, a max. load current Ilmax. = 50 mA is permitted.

<sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $\rm V_{S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

#### WTB9M4-3

• Detection principle: background suppression

Mounting hole: M4

• Adjustment: potentiometer, 5 turns

• Switching mode: light/dark-switching (Q = light-switching.)

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Switching frequency <sup>2)</sup> / Response time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-094	WTB9M4-3P1161	1051887
				PNP	Connector M8, 4-pin	Cd-084	WTB9M4-3P2261	1051889
Visible red light	20 mm 350 mm	20 mm Ø 4.5 mm 1,500 Hz/ 350 mm (75 mm) < 0.333 ms		Connector M12, 4-pin	Cd-084	WTB9M4-3P2461	1051891	
.ougc		(1.5)	0.000	NIDNI	Cable, 4-wire, 2 m, PVC	Cd-094	WTB9M4-3N1161	1051882
				NPN	Connector M8, 4-pin	Cd-084	WTB9M4-3N2261	1051885
					Cable, 4-wire, 2 m, PVC	Cd-094	WTB9M4-3P1111	1051886
Infrared	20 mm		PNP	Connector M8, 4-pin	Cd-084	WTB9M4-3P2211	1051888	
light	500 mm		< 0.5 ms		Connector M12, 4-pin	Cd-084	WTB9M4-3P2411	1051890
				NPN	Connector M12, 4-pin	Cd-084	WTB9M4-3N2411	1055145

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL9-3

Detection principle: autocollimation

• Type of light: visible red light

Mounting hole: M3

• **Switching mode**: light/dark-switching (Q = light-switching.)

Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Adjustment	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3P1162	1049054
					Connector M8, 4-pin	Cd-084	WL9-3P2262	1049058
0 m	Ø 2 mm	1,000 Hz/	Single teach-in	PNP	Connector M12, 4-pin	Cd-084	WL9-3P2462	1049061
0.4 m	, ,	- C		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9-3P3462	1049065	
				NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3N1162	1049068
				14114	Connector M12, 4-pin	Cd-084	WL9-3N2462	1049072
				PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3P1130	1049055
					Connector M8, 4-pin	Cd-084	WL9-3P2230	1049059
					Connector M12, 4-pin	Cd-084	WL9-3P2430	1049062
0 m 4 m	Ø 45 mm (1.5 m)	1,000 Hz/ < 0.5 ms	-		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9-3P3430	1049066
					Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3N1130	1049069
				NPN	Connector M8, 4-pin	Cd-084	WL9-3N2230	1049071
					Connector M12, 4-pin	Cd-084	WL9-3N2430	1049073

<sup>1)</sup> PL80A.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}$  Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>6)</sup> Signal transit time with resistive load.

Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Adjustment	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3P1132	1049056
				Cable, 4-wire, 5 m, PVC	Cd-094	WL9-3P1232	1049057	
				PNP	Connector M8, 4-pin	Cd-084	WL9-3P2232	1049060
0 m	Ø 45 mm	1,000 Hz/	Single teach-in		Connector M12, 4-pin	Cd-084	WL9-3P2432	1049063
5 m	(1.5 m)	< 0.5 ms	button		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9-3P3432	1049067
				NIDNI	Cable, 4-wire, 2 m, PVC	Cd-094	WL9-3N1132	1049070
				NPN	Connector M12, 4-pin	Cd-084	WL9-3N2432	1049074

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### WL9M4-3

• Detection principle: autocollimation

• Type of light: visible red light

• Mounting hole: M4

• **Switching mode**: light/dark-switching (Q = light-switching.)

Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Adjustment	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-094	WL9M4-3P1132	1051894
					Connector M8, 4-pin	Cd-084	WL9M4-3P2232	1051895
0 m	Ø 45 mm	1,000 Hz/	Single teach-in button	PNP	Connector M12, 4-pin	Cd-084	WL9M4-3P2432	1051896
5 m	(1.5 m)	< 0.5 ms			Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9M4-3P3432	1051907
				NIDNI	Cable, 4-wire, 2 m, PVC	Cd-094	WL9M4-3N1132	1051892
				NPN	Connector M8, 4-pin	Cd-084	WL9M4-3N2232	1051893

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### **WSE9-3**

• Type of light: visible red light

• Mounting hole: M3

• Switching mode: light/dark-switching (Q = light-switching.)

Sensing range max.	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Adjustment	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-074	WSE9-3P1130	1049075
			Connector M8, 4-pin	Cd-077	WSE9-3P2230	1049076		
		PNP	Connector M12, 4-pin	Cd-077	WSE9-3P2430	1049077		
0 m 10 m	Ø 25 mm (1.0 m)	1,000 Hz/ < 0.5 ms	-		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-077	WSE9-3P3430	1049078
					Cable, 4-wire, 2 m, PVC	Cd-074	WSE9-3N1130	1049079
		NPN	Connector M8, 4-pin	Cd-077	WSE9-3N2230	1055041		
					Connector M12, 4-pin	Cd-077	WSE9-3N2430	1049080

<sup>7)</sup> With light/dark ratio 1:1.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}$  Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>6)</sup> Signal transit time with resistive load.

• Type of light: visible red light

Mounting hole: M4

• Switching mode: light/dark-switching (Q = light-switching.)


Sensing range max.	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Adjustment	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-074	WSE9M4-3P1130	1051911
					Connector M8, 4-pin	Cd-077	WSE9M4-3P2230	1051912
0 m	Ø 25 mm (1.0 m)	1,000 Hz/ < 0.5 ms	-	PNP	Connector M12, 4-pin	Cd-077	WSE9M4-3P2430	1051913
10 m					Cable with connector M12, 4-pin, 120 mm	Cd-077	WSE9M4-3P3430	1054435
				NPN	Cable, 4-wire, 2 m, PVC	Cd-074	WSE9M4-3N1130	1051914
					Connector M8, 4-pin	Cd-077	WSE9M4-3N2230	1052938

<sup>7)</sup> With light/dark ratio 1:1.

### **Dimensional drawings**


Dimensions in mm (inch)

#### **WTB9-3**



- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Mounting hole M3 (Ø 3.1 mm)
- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- 6 Connection cable 2 m
- 7 Connector M8, 4-pin
- ® Connector M12, 4-pin


#### WTB9M4-3



- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Mounting hole M4 (Ø 4.1 mm)
- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- Connection cable
- 7 Connector M8, 4-pin
- 8 Connector M12, 4-pin


<sup>6)</sup> Signal transit time with resistive load.

#### WL9-3, WL9-3G



- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M3 (Ø 3.1 mm)
- 3 LED indicator yellow: Light received
- $\ensuremath{\textcircled{4}}$  LED signal strength indicator green:power on
- ⑤ Connecting cable or connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

#### WL9M4-3, WL9M4-3G




- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M4 (Ø 4.1 mm)
- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- ⑤ Connecting cable or connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

### **Adjustments**

#### **Potentiometer**



Single teach-in button



#### No adjustment possibility



- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- 9 Sensing range adjustment

- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- 8 Teach-in button


- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on

#### **Characteristic curves**

#### Black-white shift

#### WTB9-3, red light, 350 mm


% of sensing range



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB9-3, infrared light, 800 mm


% of scanning distance



- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB9-3, infrared light, 500 mm


% of sensing range



- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### Operating reserve


#### WL9-3, red light, 0.4 m



- ① PL80A
- ② PL40A
- ③ REF-IRF-56


#### WL9-3, red light, 5 m





- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- 6 REF-IRF-56


#### WL9-3, red light, 4 m



- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A
- ⑤ PL10F
- 6 REF-IRF-56


#### WSE9-3, red light, 10 m

#### Function reserve




#### **Bar diagrams**

#### WTB9-3, red light, 350 mm




- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB9-3, infrared light, 800 mm




- Sensing range
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WL9-3, red light, 4 m



- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A5 PL10F
- 6 REF-IRF-56


#### WSE9-3, red light, 10 m



Sensing range


Sensing range max.

#### WTB9-3, infrared light, 500 mm




- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WL9-3, red light, 0.4 m




- ① PL80A
- ② PL40A
- 3 REF-IRF-56

#### WL9-3, red light, 5 m




- ① PL80A
- ② P250F
- 3 PL40A
- 4 PL20F
- ⑤ PL10F
- 6 REF-IRF-56


#### WTB9-3, red light, 350 mm




#### WTB9-3, infrared light, 500 mm




### WTB9-3, infrared light, 800 mm




WL9-3, red light, 0.4 m



### WL9-3, red light, 4 m




WL9-3, red light, 5 m




### G

#### WSE9-3, red light, 10 m



### **Connection diagram**


#### Cd-074



 ${\bf 1} {\bf Sender}$ 

② Receiver

#### Cd-077



① Sender

② Receiver



#### **Recommended accessories**

### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Ctool sine costed	Mounting bracket for wall mounting	BEF-W160	5305197
0-0	Steel, zinc coated	Mounting bracket	BEF-WN-W9-2	2022855

#### **Mounting plates**

Figure	Material	Description	Model name	Part no.
44	Stainless steel	Adapter plate	BEF-AP-W9	2022734
0 0	PMMA, Brass (Br)	Fastening plate with threaded sleeve M3	BEF-GPM3-W9	4066039

### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.
11	Female connector,	Cable, open con-	2 m, 4-wire	PVC	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	PVC	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled	Cable, open con-	2 m, 4-wire	PVC	IP 67	DOL-0804-W02M	6009871
100		ductor heads	5 m, 4-wire	PVC	IP 67	DOL-0804-W05M	6009873
	Female connector,	Cable, open con-	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	TPU	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled		5 m, 4-wire	TPU	IP 67	DOL-1204-W05M	6009867

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

#### Masks



Figure	Description	Model name	Part no.
	Mask card, vertical/horizontal slots, slot width: 0.5 mm / 1.0 mm / 1.5 mm / 2.0 mm	BL-9-2	4033253

### Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	(sheet), Diecast zinc (clamp)	Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
	PMMA/ABS	Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
2		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549





W9-3

**High-performance sensors for clear** material detection in a rugged VISTAL™ housing















#### **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-466



### **Product description**

The WL9G-3 Clear Material photoelectric sensor family features a compact, rugged housing. They are high-performance sensors that are ideal for clear object detection. These sensors have a tough plastic housing made from VISTAL™, which offers outstanding mechanical

durability. The WL9G-3 Clear Material family also includes unique connectivity options, mounting variability and optical specifications, making it the perfect solution for challenging automation applications. Add this advantage to your machine.

#### At a glance

- High-performance sensor in ultrarugged VISTAL™ housing
- Best-in-class optical performance for transparent object detection
- Continuous threshold adaption
- PinPoint LED for highly visible and precise light spot
- · Variable mounting with M3 or M4 hole pattern
- · Wide range of connection options

#### **Your benefits**

- Tough VISTAL<sup>™</sup> housing provides reliable installation and operation
- · Best-in-class optical performance
- · Wide variety of connection, mounting and optical possibilities to solve many different applications

#### → www.mysick.com/en/W9-3\_Glass

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



### **Detailed technical data**

#### **Features**

	WL9G-3	WL9M4G-3
Sensor principle	Photoelectric retro-reflective sensor	
Detection principle	Autocollimation	
Dimensions (W x H x D)	12.2 mm x 50 mm x 23.6 mm 12.2 mm x 49.8 mm x 23.6 mm 12.2 mm x 52.2 mm x 23.6 mm (depending on type)	
Housing design (light emission)	Rectangular	
Mounting hole	M3	M4
Sensing range max. 1)	0 m 5 m	
Sensing range 1)	0 m 3 m	
Type of light	Visible red light	
Light source 2)	PinPoint LED	
Light spot size (distance)	Ø 45 mm (1.5 m)	
Wave length	650 nm	
Adjustment	Single teach-in button	
Continuous threshold adaption	V	
Special feature	Detection of transparent objects	

<sup>1)</sup> PL80A.

### Mechanics/electronics

	WL9G-3	WL9M4G-3
Supply voltage 1)	10 V DC 30 V DC	
Ripple 2)	< 5 V <sub>pp</sub>	
Power consumption 3)	≤ 20 mA	
Output type 4)	PNP/NPN (depending on type)	
Output function	Complementary	
Switching mode 4)	Light/dark-switching 4)	
Output current I <sub>max.</sub> 5)	≤ 100 mA	
Response time <sup>6)</sup>	< 0.5 ms	
Switching frequency 7)	1,000 Hz	
Connection type	Cable, 2 m <sup>8)</sup> /Male connector, M8/Male connect Cable with connector, M12, 120 mm <sup>8)</sup> (depending	
Circuit protection	A <sup>9)</sup> , B <sup>10)</sup> , C <sup>11)</sup>	
Protection class	III	
Weight		
Connector M8, 4-pin	13 g	
Cable/cable with connector	80 g	
Polarisation filter	<b>√</b>	
Housing material	VISTAL <sup>TM</sup>	

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WL9G-3	WL9M4G-3		
Optics material	PMMA			
Enclosure rating	IP 66/IP 67/IP 69K			
Ambient operating temperature	-40 °C +60 °C			
Ambient storage temperature	-40 °C +75 °C			

<sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

### **Ordering information**

Other models available at www.mysick.com/en/W9-3\_Glass

#### WL9G-3

• Mounting hole: M3

• Detection principle: autocollimation

Adjustment	Sensing range max. 1)	Switching mode <sup>2)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
Single teach-in button	() m h m	PNP Light/dark- switching NPN	PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WL9G-3P1132	1049081
				Connector M8, 4-pin	Cd-084	WL9G-3P2232	1049082
				Connector M12, 4-pin	Cd-084	WL9G-3P2432	1049083
				Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9G-3P3432	1049084
			NIDNI	Cable, 4-wire, 2 m, PVC	Cd-094	WL9G-3N1132	1049085
			INPIN	Connector M12, 4-pin	Cd-084	WL9G-3N2432	1054152

<sup>1)</sup> PL80A.

#### WL9M4G-3

• Mounting hole: M4

• Detection principle: autocollimation

Adjustment	Sensing range max. 1)	Switching mode <sup>2)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
				Cable, 4-wire, 2 m, PVC	Cd-094	WL9M4G-3P1132	1051898
Single teach-in button	Om 5m 5'	Light/dark- switching PNP	PNP	Connector M8, 4-pin	Cd-084	WL9M4G-3P2232	1051899
				Connector M12, 4-pin	Cd-084	WL9M4G-3P2432	1051900
			Cable with connector M12, 4-pin, 120 mm, PVC	Cd-084	WL9M4G-3P3432	1051910	
			NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WL9M4G-3N1132	1051897

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

 $<sup>^{5)}</sup>$  As of Tu 50  $^{\circ}\text{C},$  a max. load current Ilmax. = 50 mA is permitted.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{8)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{9)}</sup>$  A =  $\rm V_{S}$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.


<sup>&</sup>lt;sup>2)</sup> Q = light-switching.

<sup>&</sup>lt;sup>2)</sup> Q = light-switching.

### **Dimensional drawings**


Dimensions in mm (inch)

#### WL9G-3



- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M3 (Ø 3.1 mm)
- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- ⑤ Connecting cable or connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin


#### WL9M4G-3



- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M4 (Ø 4.1 mm)
- ③ LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- (5) Connecting cable or connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

### **Adjustments**


#### Single teach-in button



- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- 8 Teach-in button


### Characteristic curves

#### Operating reserve




- ① PL80A
- ② P250F
- ③ PL40A
- 4 PL20F
- ⑤ PL10F
- © REF-IRF-56

### **Bar diagrams**



- ② P250F
- ③ PL40A
- 4 PL20F
- ⑤ PL10F
- 6 REF-IRF-56

### **Light spot diameter**



#### **Connection diagram**

#### Cd-084

# brn: 1 + (L+)

$$\begin{array}{c|c} & \text{wht} & \underline{2} & \overline{Q} \\ & \text{blu} & \underline{3} & -(M) \\ \hline & & \text{blk} & \underline{4} & Q \end{array}$$

#### Cd-094



#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Ctool zing godtod	Mounting bracket for wall mounting	BEF-W160	5305197
	Steel, zinc coated	Mounting bracket	BEF-WN-W9-2	2022855

#### **Mounting plates**

Figure	Material	Description	Model name	Part no.
44	Stainless steel	Adapter plate	BEF-AP-W9	2022734
0	PMMA, Brass (Br)	Fastening plate with threaded sleeve M3	BEF-GPM3-W9	4066039

### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.
//	Female connector, M8, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	PVC	IP 67	DOL-0804-G02M	6009870
			5 m, 4-wire	PVC	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	PVC	IP 67	DOL-0804-W02M	6009871
			5 m, 4-wire	PVC	IP 67	DOL-0804-W05M	6009873
	Female connector, M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382
			5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866
	Female connector, M12, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	TPU	IP 67	DOL-1204-W02M	6009383
			5 m, 4-wire	TPU	IP 67	DOL-1204-W05M	6009867

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

#### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

#### Masks

Figure	Description	Model name	Part no.	
	Mask card, vertical/horizontal slots, slot width: 0.5 mm / 1.0 mm / 1.5 mm / 2.0 mm	BL-9-2	4033253	



# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
6		Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
-	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	DAMAMA /ADS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030


# **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

<sup>→</sup> For additional accessories, please see page L-861

G

# Laser precision in a rugged VISTAL™ housing





















#### **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-482

# **Product description**

Precise detection of small objects and object features. Reliable for use in harsh industrial environments. The W9L-3 laser photoelectric sensor offers a wider range of solutions than ever before. It is a complete product family, including photoelectric proximity sensors, photoelectric retro-reflective sensors and through-beam photoelectric switches. All sensors are equipped with the latest laser technology, protected by a rugged

VISTAL™ housing – for even stronger mechanical resistance and reliability. The W9L-3 range works using SICK's optimized ASIC technology; optical and electromagnetic interference is effectively suppressed for safe switching behavior in any environment. With its various connection, mounting and sensing options, the W9L-3 sensor family can solve a variety of application needs in the automation environment.

# At a glance

- Tough VISTAL™ housing
- Precise laser light spot
- Photoelectric proximity sensor in laser classes 1 and 2
- · Photoelectric retro-reflective sensor with autocollimation optics and polarizing filter; models available for clear material detection
- Through-beam photoelectric sensors with sensing ranges of up to 60 m
- SIRIC technology
- · Connections: M8 and M12 plugs, cable as well as cable with plug
- · M3 and M4 hole pattern

#### Your benefits

- Precise detection of small objects and object features
- Detection of objects even through small openings
- · Less machine downtime due to stable VISTAL™ housing as well as the suppression of optical interference
- The longest detection and sensing ranges in its class
- Best-in-class background suppression for photoelectric proximity sensors
- No blind spots, detection of shiny objects using photoelectric retroreflective sensors
- · A wide variety of connection and mounting options
- · Highly visible light spot simplifies alignment

#### www.mysick.com/en/W9L-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

	WTB9L-3	WTB9M4L-3	WL9L-3	WL9M4L-3	WSE9L-3
Sensor principle	Photoelectric proximity sensor		Photoelectric retro-reflective sensor		Through-beam photoelectric sensor
Detection principle	Background suppr	ession	Autocollimation		-
Dimensions (W x H x D)		x 23.6 mm/12.2 r m x 23.6 mm (dep	mm x 49.8 mm x 23.6 mm pending on type)		
Housing design (light emission)	Rectangular				
Mounting hole	M3	M4	M3	M4	M3
Sensing range max.	25 mm 400 mm (depending on type	•	0 m 12 m <sup>2)</sup>		0 m 60 m
Sensing range	25 mm 400 mm (depending on type	•	0 m 8 m <sup>2)</sup>		0 m 50 m
Type of light	Visible red light				
Light source 3)	Laser				
Wave length	650 nm				
Laser class 4)	1/2 (depending or	type)	1		
Adjustment	Potentiometer, 5 to	urns	Single teach-in button		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTB9L-3	WTB9M4L-3	WL9L-3	WL9M4L-3	WSE9L-3	
Supply voltage 1)	10 V DC 30 V DC					
Ripple 2)	< 5 V <sub>pp</sub>					
Power consumption 3)	≤ 30 mA					
Output type 4)	PNP/NPN (depend	ing on type)				
Output function	Complementary					
Switching mode 4)	Light/dark-switchir	ng				
Output current I <sub>max.</sub>	≤ 100 mA					
Connection type	Cable, 2 m <sup>5</sup> /Male connector, M8/Male connector, M12/ Cable with connector, M12, 120 mm <sup>5</sup> (depending on type)					
Circuit protection	A 6), B 7), C 8)					
Protection class	III					
Weight						
Connector	13 g					
Cable/cable with connector	80 g					
Polarisation filter	-		<b>✓</b>		-	
Housing material	VISTAL™					



<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>scriptscriptstyle (3)}$  Average service life 50,000 h at T  $_{\!A}$  = +25 °C.

<sup>&</sup>lt;sup>4)</sup> (IEC 60825-1/CDRH 21 CFR 1040.10 & 1040.11)

4		
	G	ì

	WTB9L-3	WTB9M4L-3	WL9L-3	WL9M4L-3	WSE9L-3
Optics material	PMMA				
Enclosure rating	IP 66/IP 67/IP 69K				
Ambient operating temperature	-10 °C +50 °C				
Ambient operating temperature extended <sup>11)</sup> <sup>12)</sup>	-30 °C +55 °C				
Ambient storage temperature	-30 °C +70 °C				

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W9L-3

#### WTB9L-3

Mounting hole: M3

• Switching mode: light/dark-switching (Q = light-switching.)

• Adjustment: potentiometer, 5 turns

Laser class	Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
					Cable, 4-wire, 2 m, PVC	Cd-095	WTB9L-3P1161	1058232
					Connector M8, 4-pin	Cd-083	WTB9L-3P2261	1058230
				PNP	Connector M12, 4-pin	Cd-083	WTB9L-3P2461	1058231
1	25 mm 300 mm	Ø 1 mm (170 mm)	1,000 Hz/ ≤ 0.5 ms		Cable with connector M12, 4-pin, 120 mm, PVC	Cd-083	WTB9L-3P3461	1058916
				NPN	Connector M8, 4-pin	Cd-083	WTB9L-3N2261	1062523
					Connector M12, 4-pin	Cd-083	WTB9L-3N2461	1062524
					Cable with connector M12, 4-pin, 120 mm, PVC	Cd-083	WTB9L-3N3461	1062525
			500 Hz/ ≤ 1 ms	PNP	Connector M8, 4-pin	Cd-083	WTB9L-3P2291	1058150
					Connector M12, 4-pin	Cd-083	WTB9L-3P2491	1058151
2	25 mm	Ø 0.9 mm			Cable with connector M12, 4-pin, 120 mm, PVC	Cd-083	WTB9L-3P3491	1058153
2	400 mm	400 mm (230 mm)			Connector M8, 4-pin	Cd-083	WTB9L-3N2291	1058146
				NPN	Connector M12, 4-pin	Cd-083	WTB9L-3N2491	1058149
					Cable with connector M12, 4-pin, 120 mm, PVC	Cd-083	WTB9L-3N3491	1058152

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Q = light-switching.

 $<sup>^{5)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> B = inputs and output reverse-polarity protected.

<sup>8)</sup> C = interference suppression.

 $<sup>^{9)}</sup>$  As of  $T_a$  = 50 °C, a max. supply voltage  $V_{max.}$  = 24 V and a max. load current  $I_{max.}$  = 50 mA is permitted.

 $<sup>^{10)}</sup>$  Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10 \, ^{\circ} \text{C}$ .

<sup>7)</sup> With light/dark ratio 1:1.

<sup>6)</sup> Signal transit time with resistive load.

#### WTB9M4L-3

• Mounting hole: M4

• Switching mode: light/dark-switching (Q = light-switching.)

• Adjustment: potentiometer, 5 turns

Laser	Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
			1.000 Hz/ ≤ 0,5 ms	PNP	Cable, 4-wire, 2 m, PVC	Cd-095	WTB9M4L-3P1161	1058188
1	25 mm 300 mm	Ø 1 mm (170 mm)			Connector M8, 4-pin	Cd-083	WTB9M4L-3P2261	1058186
	300 111111				Connector M12, 4-pin	Cd-083	WTB9M4L-3P2461	1058187
	25 mm 400 mm		500 Hz/ ≤ 1 ms	PNP	Cable, 4-wire, 2 m, PVC	Cd-095	WTB9M4L-3P1191	1058226
2					Connector M8, 4-pin	Cd-083	WTB9M4L-3P2291	1058224
					Connector M12, 4-pin	Cd-083	WTB9M4L-3P2491	1058225

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL9L-3

• Mounting hole: M3

• Switching mode: light/dark-switching (Q = light-switching.)

• Adjustment: single teach-in button

Laser class	Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
				Cable, 4-wire, 2 m, PVC	Cd-095	WL9L-3P1132	1058233	
	0 m 12 m	Ø 1 mm (500 mm)	1,000 Hz/ ≤ 0.5 ms	PNP	Connector M8, 4-pin	Cd-083	WL9L-3P2232	1058174
					Connector M12, 4-pin	Cd-083	WL9L-3P2432	1058175
1					Cable with connector M12, 4-pin, 120 mm, PVC	Cd-083	WL9L-3P3432	1058176
				NIDAL	Connector M8, 4-pin	Cd-083	WL9L-3N2232	1058172
				NPN	Connector M12, 4-pin	Cd-083	WL9L-3N2432	1058173

<sup>1)</sup> PL80A.

# WL9M4L-3

• Mounting hole: M4

• Switching mode: light/dark-switching (Q = light-switching.)

• Adjustment: single teach-in button

Laser class	Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
		Ø 1 mm (500 mm)	1,000 Hz/ ≤ 0.5 ms	PNP	Cable, 4-wire, 2 m, PVC	Cd-095	WL9M4L-3P1132	1058229
1	0 m 12 m				Connector M8, 4-pin	Cd-083	WL9M4L-3P2232	1058227
					Connector M12, 4-pin	Cd-083	WL9M4L-3P2432	1058228

<sup>&</sup>lt;sup>1)</sup> PL80A.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}\, Signal$  transit time with resistive load.

#### WSE9L-3


- Mounting hole: M3
- **Switching mode:** light/dark-switching (Q = light-switching.)
- Adjustment: single teach-in button

Laser class	Sensing range max. 1)	Light spot size (dis- tance)	Switching frequency <sup>2)</sup> /Re- sponse time <sup>3)</sup>	Output type	Connection	Connection diagram	Model name	Part no.
			1,000 Hz/ ≤ 0.5 ms	PNP	Cable, 4-wire, 2 m, PVC	Cd-231	WSE9L-3P1137	1058915
		Ø 1 mm (500 mm)			Connector M8, 4-pin	Cd-232	WSE9L-3P2237	1058182
1	0 m 60 m				Connector M12, 4-pin	Cd-232	WSE9L-3P2437	1058181
					Connector M8, 4-pin	Cd-232	WSE9L-3N2237	1058179
					Connector M12, 4-pin	Cd-232	WSE9L-3N2437	1058180

# **Dimensional drawings**


Dimensions in mm (inch)

#### WTB9L-3




- ① Center of optical axis, receiver
- ② Center of optical axis, sender
- 3 Mounting hole M3 (Ø 3.1 mm)
- ④ LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- **©** Connecting cable or connecting cable with connector
- 7 Connector M8, 4-pin
- ® Connector M12, 4-pin

#### WTB9M4L-3




- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Mounting hole M4 (Ø 4.1 mm)
- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- **©** Connecting cable or connecting cable with connector
- 7 Connector M8, 4-pin
- 8 Connector M12, 4-pin

#### WL9L-3




- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M3 (Ø 3.1 mm)
- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- ⑤ Connecting cable or connecting cable with connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

#### WL9M4L-3



- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M4 (Ø 4.1 mm)
- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- ⑤ Connecting cable or connecting cable with connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

#### WSE9L-3



- ① Centre of optical axis, sender and receiver
- 2 Mounting hole M3 (Ø 3.1 mm)
- ③ LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- (5) Connecting cable or connecting cable with connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

G


# **Adjustments**

#### **Potentiometer**



- 4 LED indicator yellow: Light received
- ⑤ LED signal strength indicator green:power on
- 9 Sensing range adjustment

### Single teach-in button




- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- 8 Teach-in button

# **Characteristic curves**

#### Black-white shift

#### WTB9L-3, laser class 1


% of sensing range



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

### WTB9L-3, laser class 2

% of sensing range




- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission




# Operating reserve

#### WL9L-3




- ① PL20A
- ② PL40A
- ③ PL80A
- 4 PL10F
- ⑤ PL20F
- ⑥ P250F
- ⑦ REF-AC1000

#### WSE9L-3




# **Bar diagrams**

#### WTB9L-3, laser class 1




- Sensing range typ. max.
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

#### WTB9L-3, laser class 2



- Sensing range typ. max.
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WL9L-3



① PL20A

② PL40A

③ PL80A


4 PL10F

⑤ PL20F

6 P250F

⑦ REF-AC1000


#### WSE9L-3



# **Light spot diameter**

#### WTB9L-3, laser class 1

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
50 mm	1.2	1.0
(1.97)	(0.05)	(0.04)
100 mm	1.1	1.0
(3.94)	(0.04)	(0.04)
200 mm	0.9	0.9
(7.87)	(0.04)	(0.04)
300 mm	0.8	0.8
(11.81)	(0.03)	(0.03)

Vertical
Horizontal

#### WTB9L-3, laser class 2

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
50 mm	1.2	1.0
(1.97)	(0.05)	(0.04)
100 mm	1.1	1.0
(3.94)	(0.04)	(0.04)
200 mm	0.9	0.9
(7.87)	(0.04)	(0.04)
400 mm	0.8	0.8
(15.75)	(0.03)	(0.03)

Vertical
Horizontal

#### WL9-3, Overview

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
6 m	15.2	7.6
(19.69 feet)	(0.60)	(0.30)
12 m	32.4	16.4
(39.37 feet)	(1.28)	(0.65)



#### WL9L-3 close up near range


Radius in mm (inch)



Vertical
Horizontal

#### WSE9L-3 overview

Radius in mm (inch)




#### Dimensions in mm (inch)

Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
5 m	15	11
(16.40 feet)	(0.59)	(0.43)
10 m	45	28
(32.81 feet)	(1.77)	(1.10)
60 m	336	200
(196.85 feet)	(13.23)	(7.87)

Vertical
Horizontal

#### WSE9L-3 close up near range

Radius in mm (inch)



Vertical Horizontal

# **Connection diagram**

Cd-083

$$\begin{array}{c|c} & brn & 1 \\ \hline & brn & 2 \\ \hline & wht & 2 \\ \hline & blu & 3 \\ \hline & blk & 4 \\ \hline & Q \\ \hline \end{array}$$

Cd-095

Cd-231

- ${\bf 1}{\bf 0} \, {\rm Sender}$
- 2 Receiver

Cd-232

- ${\bf 1}{\bf 0} \, {\rm Sender}$
- 2 Receiver

# **Recommended accessories**

# Mounting brackets/plates

# Mounting brackets

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Mounting bracket for wall mounting	BEF-W160	5305197
0-0		Mounting bracket	BEF-WN-W9-2	2022855

# **Mounting plates**

Figure	Material	Description	Model name	Part no.
0 0	PMMA, Brass (Br)	Fastening plate with threaded sleeve M3	BEF-GPM3-W9	4066039

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open conductor heads	2 m, 4-wire	PVC	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight		5 m, 4-wire	PVC	IP 67	DOL-0804-G05M	6009872
	Female connector, M8, 4-pin, angled	Cable, open	2 m, 4-wire	PVC	IP 67	DOL-0804-W02M	6009871
		conductor heads	5 m, 4-wire	PVC	IP 67	DOL-0804-W05M	6009873
	Female connector, M12, 4-pin, straight	Cable, open conductor heads	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382
100			5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866
	Female connector, M12, 4-pin, angled	′ '	2 m, 4-wire	TPU	IP 67	DOL-1204-W02M	6009383
			5 m, 4-wire	TPU	IP 67	DOL-1204-W05M	6009867

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M8, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-0804-W	6009975
	Female connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1204-W	6007303

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
<b>a</b>	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	(sheet), Diecast zinc (clamp)	Plate NO8 for universal clamp bracket	BEF-KHS-N08	2051607

# Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, Ø 23 mm	P25F-1	5319385
	PMMA/ABS	Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm	P41F	5315128
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
9		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
2		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
Ø		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

→ For additional accessories, please see page L-861

Laser precision in a rugged VISTAL™ housing for clear material detection





**SIRIC®** 









# Additional information

Additional information
Detailed technical dataG-485
Ordering information
Dimensional drawingsG-486
Adjustments
Characteristic curves
Light spot diameter
Connection diagram
Recommended accessories G-488

# **Product description**

Precise detection of small objects and object features. Reliable even in harsh industrial environments. Equipped with the latest laser technology as well as offering continuous switching threshold adjustment (CTA), the WL9LG-3 photoelectric retro-reflective sensor is the ideal solution for detecting transparent materials. The innovative technology is protected by a rugged VISTAL™ housing for even stronger mechanical resistance

and reliability. The WL9LG-3 range works using SICK's optimized ASIC technology, optical and electromagnetic interference is effectively suppressed for safe switching behavior in any environment. With various connection, mounting and sensing options, the WL9LG-3 sensor family is the ideal solution for a variety of application needs in the automation environment.

# At a glance

- Tough VISTAL™ housing
- Precise laser light spot, laser class 1
- · Continuous switching threshold adjustment (CTA)
- · Autocollimation optics and polarizing filter
- Teach-in
- · SIRIC technology
- Connections: M8 and M12 plugs, cable as well as cable with plug
- M3 and M4 hole pattern

# Your benefits

- · Precise detection of small objects and object features
- Detection of objects even through small openings
- Best-in-class for detecting transparent objects
- · Less machine downtime thanks to the stable VISTAL™ housing
- · No blind spots, also detects shiny objects
- Wide range of connection options
- · Multiple mounting options
- · Highly visible light spot simplifies alignment

#### → www.mysick.com/en/W9LG-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

# **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	12.2 mm x 50 mm x 23.6 mm/12.2 mm x 49.8 mm x 23.6 mm/ 12.2 mm x 52.2 mm x 23.6 mm (depending on type)
Housing design (light emission)	Rectangular
Mounting hole	M3
Sensing range max. 1)	0 m 4.5 m
Sensing range 1)	0 m 2 m
Type of light	Visible red light
Light source 2)	Laser
Light spot size (distance)	Ø 1 mm (500 mm)
Wave length	650 nm
Laser class 3)	1
Adjustment	Single teach-in button
Continuous threshold adaption	V
Special feature	Detection of transparent objects

<sup>&</sup>lt;sup>1)</sup> REF-AC1000.

# Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple	$<$ 5 $V_{pp}$
Power consumption <sup>2)</sup>	≤ 30 mA
Output type 3)	PNP
Output function	Complementary
Switching mode 3)	Light/dark-switching
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	≤ 0.5 ms
Switching frequency 5)	1,000 Hz
Connection type	Cable, 2 m <sup>6</sup> /Male connector, M8/Male connector, M12 (depending on type)
Circuit protection	A 7, B 8, C 9)
Protection class	III
Weight	
Connector	13 g
Cable/cable with connector	80 g
Polarisation filter	
Housing material	VISTAL
Optics material	PMMA

G

 $<sup>^{2)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>rm 3)}\,{\rm IEC}\,\,60825\text{-}1/{\rm CDRH}\,\,21\,{\rm CFR}\,\,1040.10\,\,\&\,\,1040.11.$ 

Enclosure rating	IP 66/IP 67/IP 69K
Ambient operating temperature	-10 °C +50 °C
Ambient operating temperature extended 10) 11)	-30 °C +55 °C
Ambient storage temperature	-30 °C +70 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W9LG-3

#### WL9LG-3

· Laser class: 1

• Light spot size (distance): Ø 1 mm (500 mm)

Mounting hole: M3Output type: PNP

• **Switching mode:** light/dark-switching (Q = light-switching.)

• Adjustment: single teach-in button


Sensing range max. 1)	Connection	Connection diagram	Model name	Part no.
	Cable, 4-wire, 2 m, PVC	Cd-095	WL9LG-3P1132	1058236
0 m 4.5 m	Connector M8, 4-pin	Cd-083	WL9LG-3P2232	1058234
	Connector M12, 4-pin	Cd-083	WL9LG-3P2432	1058235

<sup>1)</sup> REF-AC1000.

# **Dimensional drawings**

Dimensions in mm (inch)

#### WL9LG-3



- ① Centre of optical axis, sender and receiver
- ② Mounting hole M3 (Ø 3.1 mm)
- ③ LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- $\ensuremath{\ensuremath{\mathfrak{S}}}$  Connecting cable or connecting cable with connector
- 6 Connector M8, 4-pin
- 7 Connector M12, 4-pin

<sup>2)</sup> Without load.

 $<sup>^{3)}</sup>$  Q = light-switching.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $\rm V_{_{\rm S}}$  connections reverse-polarity protected.

<sup>8)</sup> B = inputs and output reverse-polarity protected.


<sup>9)</sup> C = interference suppression.

 $<sup>^{10)}</sup>$  As of  $T_a = 50\,^{\circ}$  C, a max. supply voltage  $V_{max.} = 24\,$  V and a max. load current  $I_{max.} = 50\,$  mA is permitted.

<sup>&</sup>lt;sup>11)</sup> Using the sensor below  $T_a = -10$  °C is possible, if the sensor is turned on at  $T_a > -10$  °C, then the environment cools down and the sensor is not disconnected from the supply voltage during the whole time. It is not allowed to turn on the sensor below  $T_a = -10$  °C.

# **Adjustments**

# Single teach-in button




- 3 LED indicator yellow: Light received
- 4 LED signal strength indicator green:power on
- ® Teach-in button

# **Characteristic curves**

# Operating reserve


#### WL9LG-3



- ① PLV14-A / PLH25-M12 / PLH25-D12
- 2 P41F / REF-AC1000

# **Light spot diameter**

#### Overview



## Dimensions in mm (inch)


Sensing range	Vertical	Horizontal
0.5 m	< 1.0	< 1.0
(1.64 feet)	(0.04)	(0.04)
1 m	1.5	1.2
(3.28 feet)	(0.06)	(0.05)
2 m	4.3	2.6
(6.56 feet)	(0.17)	(0.10)
4.5 m	11.3	5.6
(14.76 feet)	(0.44)	(0.22)





#### WL9LG-3, close up near range

Radius in mm (inch)




# **Connection diagram**

# Cd-083

### Cd-095





# **Recommended accessories**

# Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Mounting bracket	BEF-WN-W9-2	2022855

#### **Mounting plates**

Figure	Material	Description	Model name	Part no.
0	PMMA, Brass (Br)	Fastening plate with threaded sleeve M3	BEF-GPM3-W9	4066039

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 4-wire	PVC	IP 67	DOL-0804-G02M	6009870
	M8, 4-pin, straight	ductor heads	5 m, 4-wire	PVC	IP 67	DOL-0804-G05M	6009872
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	PVC	IP 67	DOL-0804-W02M	6009871
	M8, 4-pin, angled		5 m, 4-wire	PVC	IP 67	DOL-0804-W05M	6009873
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382
100	M12, 4-pin, straight		5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866
	Female connector,	· · ·	2 m, 4-wire	TPU	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled		5 m, 4-wire	TPU	IP 67	DOL-1204-W05M	6009867

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0804-G	6009974
W.	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1204-W	6007303

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
1	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	(sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865



# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
	FIVINIA/ ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
	DMANAA /ADC	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
1	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

# **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		,,,,		2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861

High-performance photoelectric sensors with application flexibility in industrial environments













# **Additional information**

/ total till of the control
Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories G-501

# **Product description**

The W11-2 photoelectric sensor family offers a complete technology with highperformance sensing capabilities for a wide range of automation applications. Whether for applications in material

handling or packaging, the W11-2 offers optimum performance in a small, rugged housing. These easy-to-use sensors provide dependable object detection and high reliability in industrial environments.

# At a glance

- · Uniform housing, mounting and connection systems
- Rugged sensors for industrial use
- · PinPoint LED technology provides highly visible light spot
- · Space-saving plastic housing in chemically, thermally or mechanically resistant designs
- Dovetail mounting mounting holes and oblong holes
- Highly visible 360° status LEDs

# Your benefits

- Reliable object detection due to superior ASIC technology with a high immunity to ambient light
- · PinPoint technology provides a bright, small and precise light spot that enables quick and easy sensor alignment
- Precise switching characteristics ensure high performance even in changing application conditions
- Highly visible 360° status LEDs provide quick and easy setup
- · Compact and rugged housing design easily fits in tight spaces
- · Uniform housing, mounting and connection systems simplify installation
- · Versatile mounting options, including dovetail, side mounting and standard mounting holes enable quick installation

#### www.mysick.com/en/W11-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

# **Features**

	WTB11-2	WTF11-2	WTE11-2	WL11-2	WSE11-2
Sensor principle	Photoelectric proxi	mity sensor		Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background sup- pression	Foreground sup- pression	Energetic	Standard optics	-
Dimensions (W x H x D)	15.6 mm x 48.5 m	nm x 42 mm			
Housing design (light emission)	Rectangular				
Sensing range max.	$20 \text{ mm} \dots$ $1,100 \text{ mm}^{1)}$ (depending on type)	35 mm 350 mm <sup>1)</sup>	40 mm 1,000 mm <sup>1)</sup>	0.05 m 10 m <sup>2)</sup> (depending on type)	0 m 20 m
Sensing range	20 mm 800 mm (de- pending on type)	35 mm 350 mm	40 mm 600 mm	0.05 m 8 m <sup>2)</sup> (depending on type)	0 m 15 m
Type of light	Visible red light				
Light source	LED <sup>3)</sup> PinPoint LED <sup>3)</sup> (depending on type)	LED 3)			
Angle of dispersion	-			Approx. 2.2°	Approx. 1.5°
Wave length	640 nm / 660 nm (de- pending on type)	640 nm	633 nm	640 nm	633 nm
Adjustment	Potentiometer, 5 to	urns	Single teach-in but	tton	-

 $<sup>^{1)}\,\</sup>mbox{Object}$  with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTB11-2	WTF11-2	WTE11-2	WL11-2	WSE11-2
Supply voltage 1)	10 V DC 30 V D	С			
Ripple 2)	≤ 5 V <sub>pp</sub>				
Power consumption	$\leq$ 40 mA $^{3)}$	≤ 30 mA <sup>3)</sup>	≤ 40 mA <sup>3)</sup>		-
Power consumption, sender	-				$\leq$ 25 mA $^{3)}$
Power consumption, receiver	-				$\leq$ 20 mA $^{3)}$
Output type	PNP/NPN (de- pending on type)	PNP	PNP/NPN (depend	ding on type)	
Output function	Complementary				
Switching mode	Light/dark-switchi	ng			
Signal voltage PNP HIGH/LOW	Uv - 2.5 V / appro	x. 0 V			
Signal voltage NPN HIGH/LOW	Approx. V <sub>S</sub> /< 2.5 V	-	Approx. VS / < 2.5	V	
Output current I <sub>max.</sub>	100 mA				
Response time 4)	≤ 2.5 ms				
Switching frequency 5)	200 Hz				
Connection type	Cable, 2 m <sup>6)</sup> Male connector, M12 (depending on type)	Male connector, M12	Cable, 2 m <sup>6)</sup> Male connector, M (depending on type		
Circuit protection	A $^{7)}$ /C $^{8)}$ /D $^{9)}$				
Protection class	II			<sup>10)</sup>	II

G

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WTB11-2	WTF11-2	WTE11-2	WL11-2	WSE11-2
Weight					
Connector	120 g				
Cable	200 g	-	200 g		
Polarisation filter	-			•	-
Housing material	ABS				
Optics material	PMMA				
Enclosure rating	IP 66/IP 67 /IP 69K		IP 66/IP 67	IP 66/IP 67/IP 69	K
Test input sender off	-				TE to 0 V
Ambient operating temperature	-30 °C +60 °C				
Ambient storage temperature	-40 °C +75 °C				

<sup>&</sup>lt;sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W11-2

#### WTB11-2

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 5 turns

Sensing range max. <sup>1)</sup>	Light source	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	LED	Ø 6 mm (200 mm)	PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WTB11-2P1131	1041377
20 mm 250 mm				Connector M12, 4-pin	Cd-083	WTB11-2P2431	1041376
20 mm 350 mm			NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WTB11-2N1131	1041379
				Connector M12, 4-pin	Cd-083	WTB11-2N2431	1041378
30 mm 1,100 mm	PinPoint- LED	Ø 6 mm (200 mm)	PNP	Connector M12, 4-pin	Cd-083	WTB11-2P2461	1044442
			NPN	Connector M12, 4-pin	Cd-083	WTB11-2N2461	1051818

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WTF11-2

• Switching mode: light/dark-switching

• Adjustment: potentiometer, 5 turns

Sensing range max. <sup>1)</sup>	Light source	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
35 mm 350 mm	LED	Ø 6 mm (200 mm)	PNP	Connector M12, 4-pin	Cd-083	WTF11-2P2431	1041380

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{7)}</sup>$  A =  $\rm V_{S}$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>10)</sup> Reference voltage DC 50 V.

# WTE11-2

Switching mode: light/dark-switching

• Adjustment: single teach-in button

Sensing range max. 1)	Light source	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	150	Ø 90 mm (600 mm)	PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WTE11-2P1132	1041382
40 1 000				Connector M12, 4-pin	Cd-083	WTE11-2P2432	1041381
40 mm 1,000 mm	LED		NPN	Cable, 4-wire, 2 m, PVC	Cd-094	WTE11-2N1132	1041384
				Connector M12, 4-pin	Cd-083	WTE11-2N2432	1041383

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# WL11-2

• Switching mode: light/dark-switching

Polarisation filter: ✔

Sensing range max. <sup>1)</sup>	Light source	Light spot size (distance)	Output type	Adjustment	Connection	Connection diagram	Model name	Part no.
	LED	Ø 50 mm (3 m)	PNP	-	Cable, 4-wire, 2 m, PVC	Cd-094	WL11-2P1130	1041386
					Connector M12, 4-pin	Cd-083	WL11-2P2430	1041385
0.15 m 10 m				Single teach- in button	Connector M12, 4-pin	Cd-083	WL11-2P2432	1048542
			NPN	-	Cable, 4-wire, 2 m, PVC	Cd-094	WL11-2N1130	1041388
					Connector M12, 4-pin	Cd-083	WL11-2N2430	1041387

<sup>1)</sup> PL80A

# WL11-2, detecting objects wrapped in film

• Switching mode: light/dark-switching

Polarisation filter:

Sensing range max. <sup>1)</sup>	_	Light spot size (distance)			Connection	Connection diagram	Model name	Part no.
0.05 m 3 m	LED	Ø 50 mm (3 m)	PNP	-	Connector M12	Cd-083	WL11-2P2430S05	1056080

<sup>1)</sup> PL80A

# WSE11-2

• Switching mode: light/dark-switching

• Adjustment: -


Sensing range max. <sup>1)</sup>	Light source	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
			PNP	Cable, 4-wire, 2 m, PVC	Cd-088	WSE11-2P1130	1057572
0 m 20 m	LED	Ø 220 mm (15 m)	PNP	Connector M12, 4-pin	Cd-084	WSE11-2P2430	1057571
0 m 20 m			NPN	Cable, 4-wire, 2 m, PVC	Cd-088	WSE11-2N1130	1057574
				Connector M12, 4-pin	Cd-084	WSE11-2N2430	1057573

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# **Dimensional drawings**


Dimensions in mm (inch)

#### WTB11-2, WTF11-2




- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Mounting hole ø 4.2 mm
- 7 Sensing range adjustment: potentiometer
- ® Connection

#### WL11-2




- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Mounting hole ø 4.2 mm
- 6 M12 connector, 4-pin or cable

#### WTE11-2




- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- ⑤ Mounting hole ø 4.2 mm
- 6 Sensitivity setting; single teach-in button
- 7 Connector M12 or cable

### WL11-2, teach-in button




- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Status indicator LED green: power on
- ⑤ Mounting hole ø 4.2 mm
- 6 Connector M12, 4-pin



- ① Center of optical axis
- ② Status indicator LED green: power on
- 3 Status indicator LED, yellow: Status of received light beam
- 4 Mounting hole ø 4.2 mm
- ⑤ M12 connector, 4-pin or cable


# **Adjustments**

# WTB11-2, WTF11-2




- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 7 Sensing range adjustment: potentiometer

#### WTE11-2, WSE11-2




- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam
- 6 Adjustment sensing range: single teach-in button

#### WL11-2



- 3 Status indicator LED green: power on
- 4 Status indicator LED, yellow: Status of received light beam

# WL11-2, teach-in button




- ② LED indicator yellow: Light received
- 3 LED indicator, green: power on, teach-in mode I, LED indicator, blue: teach-in mode II
- 6 Single teach-in button, Function 1: teach-in sensitivity on reflector, Function 2: change operation/teach-in mode

# **Characteristic curves**


#### Black-white shift

#### WTB11-2, 350 mm




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WTF11-2




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### WTB11-2, 1,100 mm



- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### WTE11-2



- 1 Sensing range on gray, 18 % remission
- ② Sensing range on white, 90 % remission


# Operating reserve

#### WL11-2




- ① PL80A
- ② C110A
- ③ PL50A
- 4 PL40A ⑤ PL30A
- @ PL20A
- 7 Reflective tape Diamond Grade

#### WSE11-2



# **Bar diagrams**


#### WTB11-2, 350 mm



#### Sensing range

- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


#### WTB11-2, 1,100 mm



#### Sensing range

- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WTF11-2



- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


#### WL11-2

1	0.05	/0.15						8		10	
2	0.05	/0.15			5		7				
3	0.05	/0.15			5		7				
4	0.05	/0.15			5		7				
<b>(5)</b>	0.05	/0.15	3.	5	5						
6	0.05	/0.15	3	4							
7	0.1/	0.3 <b>1</b> .	5 								
	)				4		3		3	1	n
`	-		- 56)	(13	.12)		.69)		.25)	(32.	
		•		•	,	•	Ĺ	•		m (fe	et)

Sensing range

- Sensing range typ. max.
- ① PL80A
- ② C110A
- ③ PL50A
- 4 PL40A
- ⑤ PL30A
- @ PL20A
- 7 Reflective tape Diamond Grade

#### WTE11-2



Sensing range typ. max.

① Sensing range on black, 6 % remission

Sensing range


- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

# **Connection diagram**

#### Cd-083

$$\begin{array}{c|c} & bm & 1 \\ \hline & bm & 2 \\ \hline & blu & 3 \\ \hline & blu & 4 \\ \hline & Q \\ \end{array}$$

#### Cd-088



- ① Sender
- 2 Receiver

#### Cd-084

$$\begin{array}{c|c}
\hline
& \text{bin} & 1 \\
\hline
& \text{wht} & 2 \\
\hline
& \text{blu} & 3 \\
\hline
& \text{olk} & 4 \\
\hline
& Q
\end{array}$$

#### Cd-094

# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
10_	Stainless staal	Mounting bracket, large	BEF-WG-W12	2013942
3	Stainless steel	Mounting bracket, small	BEF-WK-W12	2012938

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	Female connector, M12, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
1	Female connector, M12, 5-pin, straight	Cable, open con- ductor heads	2 m, 5-wire	IP 67	DOL-1205-G02M	6008899
	Female connector, M12, 5-pin, angled	Cable, open con- ductor heads	2 m, 5-wire	IP 67	DOL-1205-W02M	6008900

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

# Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	STE-1204-W	6022084

G

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
9		Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
		Plate N04 for universal clamp bracket	BEF-KHS-N04	2051610

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
4	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W12-3	2045175

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
***		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

# Terminal and alignment brackets

# **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Double clamp bracket for dovetail mounting	BEF-DKH-W12	2013947
		Clamping block for dovetail mounting	BEF-KH-W12	2013285

<sup>→</sup> For additional accessories, please see page L-861

G

Reliable detection of clear material objects - from PET bottles to transparent film

















#### Additional information

Additional information
Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories G-507

# **Product description**

WL11G-2 represents glass photoelectric sensor technology designed optimally for individual applications, thus enabling a wide range of applications in very different areas of automation technology. Whether in filling or packaging

SICK

technology, WL11G-2 offers optimum performance in a small robust housing, dependable object detection - everything from PET bottles to film - in the range up to 4 m, PinPoint LED, and high reliability in industrial environments.

#### At a glance

- Retro-reflective for detection of clear material objects
- Rugged housing for industrial use
- PinPoint LED technology with a highly visible light spot
- Space-saving plastic housing in chemically, thermally or mechanically resistant designs
- Dovetail mounting standard mounting holes and oblong holes
- Highly visible 360° status LEDs
- · Simple sensitivity adjustment via potentiometer

#### Your benefits

- Superior ASIC ensures reliable detection of transparent objects
- · PinPoint LED technology provides a bright, small and precise light spot that enables quick and easy sensor alignment
- Precise switching characteristics ensure high performance even in changing application conditions
- · Highly visible 360° status LEDs provide fast and easy commissioning
- · Rugged housing design withstands harsh environments, reducing downtime and maintenance effort
- · Uniform housing, mounting and connection systems reduce mounting and installation time
- · High immunity to optical interferences reduces false readings and downtime

#### → www.mysick.com/en/W11G-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



#### **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	15.6 mm x 48.5 mm x 42 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 4 m
Sensing range 1)	0 m 4 m
Type of light	Visible red light
Light source 2)	LED
Light spot size (distance)	Ø 25 mm (1.5 m)
Angle of dispersion	Approx. 1.5°
Wave length	640 nm
Adjustment	Potentiometer, 11 turns
Special feature	Detection of transparent objects

<sup>1)</sup> PL80A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>
Power consumption 3)	≤ 30 mA
Output type	PNP/NPN (depending on type)
Output function	Complementary
Switching mode	Light/dark-switching
Switching mode selector	Selectable via L/D control wire, 0 V or not connected, light-switching, Uv, dark-switching
Signal voltage PNP HIGH/LOW	Uv – 3 V / approx. 0 V
Signal voltage NPN HIGH/LOW	Approx. Uv / < 3 V
Output current I <sub>max.</sub>	100 mA
Response time 4)	≤ 330 µs
Switching frequency 5)	1,500 Hz
Attenuation along light beam	> 8 %
Connection type	Male connector, M12/Cable with connector, M12 (depending on type)
Circuit protection	A <sup>6)</sup> , C <sup>7)</sup> , D <sup>8)</sup>
Protection class	II
Weight	120 g
Polarisation filter	V
Housing material	ABS
Optics material	PMMA
Enclosure rating	IP 66/IP 67/IP 69K
Ambient operating temperature	-30 °C +60 °C
Ambient storage temperature	-40 °C +75 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

G

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at T  $_{\!\scriptscriptstyle \Delta}$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

Other models available at www.mysick.com/en/W11G-2

#### WL11G-2


- Adjustment: potentiometer, 11 turns
- Polarisation filter:

Sensing range max. <sup>1)</sup>	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0 m 4 m	PNP, NPN	Light/dark-switching	Connector M12, 5-pin	Cd-144	WL11G-2B2531	1041390
	PNP	Light/dark-switching 2)	Cable with connector M12, 4-pin	Cd-101	WL11G-2K3431	1048313

<sup>&</sup>lt;sup>1)</sup> PL80A.

# **Dimensional drawings**


Dimensions in mm (inch)





- ① Center of optical axis
- ② Status indicator LED green: power on
- ③ Status indicator LED, yellow: Status of received light beam
- 4 Mounting hole ø 4.2 mm
- Sensitivity adjustment: poti

# **Adjustments**




- ② Status indicator LED green: power on
- $\ensuremath{\mathfrak{J}}$  Status indicator LED, yellow: Status of received light beam
- Sensitivity adjustment

<sup>2)</sup> Pin 2 / Pin 4 swapped over.


#### **Characteristic curves**

#### Operating reserve



- ① PL80A
- ② C110A
- 3 P250F
- 4 PL50A
- ⑤ PL40A
- **6** PL30A
- ⑦ PL20A
- 8 Reflective tape Diamond Grade

# **Bar diagrams**



- Sensing range
- ① PL80A
- ② C110A
- ③ P250F
- 4 PL50A
- ⑤ PL40A
- 6 PL30A
- ⑦ PL20A
- ® Reflective tape Diamond Grade

# **Connection diagram**

#### Cd-101

#### Cd-144

#### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
10-	Stainless steel	Mounting bracket, large	BEF-WG-W12	2013942
3	Starriess steer	Mounting bracket, small	BEF-WK-W12	2012938

# G

#### Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	Female connector, M12, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	Female connector, M12, 5-pin, straight	Cable, open con- ductor heads	2 m, 5-wire	IP 67	DOL-1205-G02M	6008899
	Female connector, M12, 5-pin, angled	Cable, open con- ductor heads	2 m, 5-wire	IP 67	DOL-1205-W02M	6008900

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
9		Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
ð		Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

#### Device protection (mechanical)

#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W12-3	2045175

#### Terminal and alignment brackets

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	0	Double clamp bracket for dovetail mounting	BEF-DKH-W12	2013947
	Steel, zinc coated	Clamping block for dovetail mounting	BEF-KH-W12	2013285

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	DAMAMA /A DC	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
)	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
2	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
1	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030
	Reflective tape "Diamond Grade", self-adhesive, customizable size by sheet, width max. 74.9 cm, length max. 91.4 cm	REF-DG-K	4019634

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861











#### **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-518

#### **Product description**

The W12L-2 series of photoelectric sensors features laser technology that is optimally designed for individual applications. These sensors provide reliable object detection, fast response times and are enclosed in a rugged metal housing, which is ideal for use in all types of industrial applications.

### At a glance

- Best-in-class retro-reflective laser performance in a metal housing
- Teflon® coating available
- Precise autocollimation optics
- Adjustable focus on retro-reflective sensors
- High switching frequency of 2.5 kHz
- · Connection via cable or rotatable connector
- Mounting options with through holes, blind holes, oblong holes and dovetail
- · Laser protection class 1 or 2

#### Your benefits

- Reliable object detection of small objects due to superior ASIC (application-specific integrated circuit) technology combined with innovative laser technology
- Red light laser technology provides quick and easy alignment of sensor
- Rugged metal housing (available with Teflon® coating) withstands harsh environments
- · Laser protection class 1 or 2 for eye
- · Resistance to optical interference reduces false readings and downtime
- Rotatable connector provides easy installation

#### www.mysick.com/en/W12-2\_Laser

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	WT12L-2	WL12L-2	WS/WE12L-2
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Autocollimation	-
Dimensions (W x H x D)	15 mm x 49 mm x 41.5 mm		
Housing design (light emission)	Rectangular		
Sensing range max.	20 mm 50 mm <sup>1)</sup> 30 mm 200 mm <sup>2)</sup> (depending on type)	0 m 18 m <sup>3)</sup> (depending on type)	0 m 80 m (depending on type)
Focus	45 mm 100 mm (depending on type)	-	
Type of light	Visible red light		
Light source	Laser 4)		Laser <sup>4)</sup> /Laser <sup>4) 5)</sup> (depending on type)
Wave length	650 nm		
Laser class	1/2 (depending on type)		
Adjustment	Potentiometer		

 $<sup>^{1)}</sup>$  Object with 6 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WT12L-2	WL12L-2	WS/WE12L-2		
Supply voltage 1)	10 V DC 30 V DC				
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>				
Power consumption 3)	≤ 55 mA		-		
Power consumption, sender	-		≤ 45 mA <sup>3)</sup>		
Power consumption, receiver	-		≤ 15 mA <sup>3)</sup>		
Output type	PNP, NPN		PNP/NPN (depending on type)		
Switching mode	Light switching, Dark-switching	Light switching, Dark-switching			
Switching mode selector	Selectable via L/D control wire switching, Uv, dark-switching	Selectable via L/D control wire			
Signal voltage PNP HIGH/LOW	Uv - < 2 V, Uv/0 V, <= 1.5 V	Uv - < 2.9 V, Uv V/0 V <= 1.5 \	5 V		
Signal voltage NPN HIGH/LOW	Uv - < 2 V, Uv/0 V, <= 1.5 V	< 2 V, Uv/0 V, <= 1.5 V Uv - < 2.9 V, Uv V/0 V <= 1.5 V			
Output current I <sub>max.</sub>	100 mA				
Response time	≤ 200 µs <sup>4)</sup>	$\leq$ 500 µs $^{4)}/\leq$ 200 µs $^{4)}$ (depend	ding on type)		
1.000 Hz <sup>5)</sup>	-	≤ 500 µs			
2.500 Hz <sup>5)</sup>	≤ 200 µs				
Connection type	Male connector, M12	Male connector, M12 Cable, 2 m (depending on type)	Male connector, M12		
Circuit protection	A <sup>6)</sup> , C <sup>7)</sup> , D <sup>8)</sup>				
Protection class	II				
Weight	130 g		260 g		



 $<sup>^{\</sup>rm 2)}$  Objects to be sensed with 18 % reflectivity (based on DIN 5033 white standard)

<sup>&</sup>lt;sup>3)</sup> PL80A.

 $<sup>^{4)}</sup>$  Average service life 50,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

<sup>&</sup>lt;sup>5)</sup> Parallel light beam.

	WT12L-2	WL12L-2	WS/WE12L-2
Polarisation filter	-	✓	-
Enclosure rating	IP 67/IP 69K		
Ambient operating temperature	-10 °C +50 °C		
Ambient storage temperature	-25 °C +75 °C		

<sup>&</sup>lt;sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W12-2\_Laser

#### WT12L-2, fixed sensing range, 6% remission

• Adjustment: potentiometer

• Switching mode: light-switching, dark-switching

Lase		Switching frequency		Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
2	20 mm 50 mm	2,500 Hz	45 mm	Ø 0.1 mm (45 mm)	PNP, NPN	Connector M12, 5-pin	Cd-145	WT12L-2B510	1017959

<sup>1)</sup> Object with 6 % reflectance (referred to standard white, DIN 5033)

#### WT12L-2

• Adjustment: potentiometer

• Switching mode: light-switching, dark-switching

• Connection diagram: cd-145

Laser class	Sensing range max. <sup>1)</sup>	Switching frequency	Focus	Light spot size (distance)	Output type	Connection	Housing material	Model name	Part no.	
1	30 mm 200 mm	2,500 Hz	100 mm	Ø 0.2 mm (100 mm)	PNP, NPN	Connector M12, 5-pin	Metal	WT12L-2B551	1047958	
			2,500 Hz	45 mm	Ø 0.1 mm (45 mm)	PNP, NPN	Connector M12, 5-pin	Metal	WT12L-2B530	1018250
2	2 200 mm 2,500 Hz			2 500 Hz	80 mm	Ø 0.2 mm (80 mm)	PNP, NPN	Connector M12, 5-pin	Metal	WT12L-2B540
		100 mm	Ø 0.2 mm	PNP. NPN	Connector M12, 5-pin	Metal	WT12L-2B550	1017904		
		100 111111	(100 mm)	PINP, INPIN	Connector Wi12, 5-pin	PTFE	WT12L-2B550T01	1018582		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Objects to be sensed with 18 % reflectivity (based on DIN 5033 white standard)

#### WL12L-2

• Adjustment: potentiometer

• Switching mode: light-switching, dark-switching

Laser class	Sensing range max. 1)	Switching frequency		Output type	Connection	Connection diagram	Model name	Part no.
1	0 m 18 m	1,500 Hz	Ø 0.8 mm (300 mm)	PNP, NPN	Connector M12, 5-pin	Cd-145	WL12L-2B531	1047959
	0 m 15 m	2,500 Hz	Ø 0.8 mm (300 mm)	PNP, NPN	Connector M12, 5-pin	Cd-145	WL12L-2B520	1018253
2	0 m	2.500 Hz	Ø 0.8 mm (300 mm)	PNP, NPN	Cable, 4-wire 2 m	Cd-089	WL12L-2P130	1022041
	18 m	2,500 HZ	ע 0.6 וווווו (300 וווווו)	PNP, NPN	Connector M12, 5-pin	Cd-145	WL12L-2B530	1018252

<sup>1)</sup> PL80A.

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

#### WS/WE12L-2


• Connection: connector M12, 4-pin

Laser class		Switching frequency	Light spot size (distance)	Output type	Adjustment	Connection diagram	Model name	Part no.
1	0 m 80 m	1,000 Hz	Ø 150 mm (60 m)	PNP	-	Cd-077	WS/WE12L-2P431	1047960
	0 m	2.500 Hz	Ø 1 mm (1 m)	PNP	Potentiometer	Cd-077	WS/WE12L-2P410	1018256
2	10 m	2,500 HZ	Ø I IIIII (I III)	NPN	Potentiometer	Cd-077	WS/WE12L-2N410	1018257
2	0 m	0 F00 H-	Ø 450 (00 )	PNP	-	Cd-077	WS/WE12L-2P430	1018254
	80 m 2,500 Hz	Ø 150 mm (60 m)	NPN	-	Cd-077	WS/WE12L-2N430	1018255	

# **Dimensional drawings**


Dimensions in mm (inch)

#### WT12L-2



- $\ensuremath{\textcircled{1}}$  Operating indicator, green
- ② LED reception indicator, yellow
- 3 Optical axis, receiver
- 4 Optical axis, sender
- 6 Mounting hole, Ø 4.2 mm
- 7 Sensing range adjustment


#### WL12L-2, WS/WE12L-2



- ① Operating indicator, green
- 2 LED reception indicator, yellow
- 3 Center of optical axis
- (5) Mounting hole, Ø 4.2 mm
- 6 Focal adjustment
- 7 Sensitivity adjustment


# **Adjustments**

#### WT12L-2




- ① Operating indicator, green
- $\ensuremath{\mathfrak{D}}$  LED reception indicator, yellow
- ② Sensing range adjustment

#### WL12L-2



- ① Operating indicator, green
- ② LED reception indicator, yellow
- 6 Focal adjustment
- 7 Sensitivity adjustment

#### WS/WE12L-2




- ① Operating indicator (WS above only)
- 6 Focal adjustment (WS)

#### **Characteristic curves**

#### Black-white shift

#### WT12L-2




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission
- 4 Sensing range on black, 6 % remission, fix




#### Operating reserve

#### WL12L-2, 18 m




- ① PL80A
- ② PL50A
- 3 Reflective tape Diamond Grade

#### WS/WE12L-2, 80 m




#### WL12L-2, 15 m



- ① PL80A
- 2 PL50A
- 3 Reflective tape Diamond Grade

#### WS/WE12L-2, 10 m




G

**Bar diagrams** 

1		30					17	0				
2		30							200			
3		30							200			
4		20 50	O									
(	)	40 (1.57	7)	(3.:	12	20 72)		50 30)	20 (7.5	00 87)		
					Distance in mm (inch)							

- Sensing range
- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission
- 4 Sensing range on black, 6 % remission, fix

#### WL12L-2, 18 m




Sensing range

Sensing range typ. max.

- ① PL80A
- ② PL50A
- ③ PL40A
- **④** P250
- 5 PL30A6 PL20A
- 7 Reflective tape Diamond Grade

#### WL12L-2, 15 m




Sensing range

Sensing range typ. max.


- ① PL80A
- ② PL50A
- ③ PL40A
- 4 P250
- ⑤ PL30A⑥ PL20A
- 7 Reflective tape Diamond Grade

#### WS/WE12L-2, 80 m



Sensing range/sensing range typ. max.


#### WS/WE12L-2, 10 m



Sensing range/sensing range typ. max.

# **Light spot diameter**

#### WT12L-2



# **Connection diagram**

Cd-077

1 blu 3 - (M)

① Sender 2 Receiver

brn: 1 + (L+)

Cd-089

<u>brn 1 1</u> + (L+) wht 2 Q<sub>NPN</sub> blu 3 - (M)

Cd-145

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
10_	Stainless staal	Mounting bracket, large	BEF-WG-W12	2013942
3	Stainless steel	Mounting bracket, small	BEF-WK-W12	2012938

#### Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
100	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector, M12, 4-pin, angled		2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
		Cable, open con- ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867
			10 m, 4-wire	IP 67	DOL-1204-W10M	6010541
11	Female connector,	Cable, open con-	2 m, 5-wire	IP 67	DOL-1205-G02M	6008899
100	M12, 5-pin, straight	ductor heads	5 m, 5-wire	IP 67	DOL-1205-G05M	6009868
	Female connector, M12, 5-pin, angled	· · ·	2 m, 5-wire	IP 67	DOL-1205-W02M	6008900
			5 m, 5-wire	IP 67	DOL-1205-W05M	6009869

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303
	Female connector, M12, 5-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1205-G	6009719
1	Female connector, M12, 5-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1205-W	6009720

# Terminal and alignment brackets

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.		
	Steel, zinc coated	Clamping block for dovetail mounting	BEF-KH-W12	2013285		



# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
	(sheet), Diecast zinc (clamp)	Plate NO3 for universal clamp bracket	BEF-KHS-N03	2051609

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, Ø 23 mm  Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm  PMMA/ABS  Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm		5319385
				5315128
	PMMA/ABS			5311210
	\$ F F	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
a a		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### Reflective tape

Figure	Description	Model name	Part no.
1	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

→ For additional accessories, please see page L-861



























#### Additional information

Additional information
Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Bar diagrams
Light spot diameter
Connection diagram
Recommended accessories G-525

#### **Product description**

The W12G photoelectric sensors provide reliable detection of transparent objects. Everything from PET bottles to thin, transparent films is detected. The W12G features a rugged metal housing with

high electromagnetic compatibility, high immunity to chemical and thermal conditions, and excellent resistance to high pressure cleaning.

#### At a glance

- · Rugged die-cast zinc housing with optional Teflon® coating
- Reliable detection of transparent objects
- Precise autocollimation optics
- Robust sensors for industrial use
- Precise PinPoint LED

- Dovetail mounting mounting holes and oblong holes
- Highly visible status LEDs
- · Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

#### Your benefits

- · Reliable detection of transparent objects - from PET bottles to transparent film - due to superior ASIC (application-specific integrated circuit) technology
- High immunity to ambient conditions reduces false readings
- Red PinPoint LED provides quick and easy alignment of sensor
- Precise switching characteristics, fast response times and high performance ensure superior reliability and productivity in nearly every application type
- · Withstands mechanical, thermal, chemical and electromagnetic factors, providing increased industrial reliability
- · Flexible mounting and installation due to rotatable connector and versatile mounting options
- · IO-Link provides easy data access from the PLC
- · Quick and easy configuration

#### → www.mysick.com/en/W12G

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric retro-reflective sensor
Detection principle	Autocollimation
Dimensions (W x H x D)	15.6 mm x 48.5 mm x 42 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	0 m 4 m
Type of light	Visible red light/Infrared light (depending on type)
Light source	LED <sup>2)</sup> /PinPoint LED <sup>2)</sup> (depending on type)
Angle of dispersion	Approx. 1.5°
Wave length	
Visible red light	640 nm/660 nm (depending on type)
Infrared light	850 nm
Adjustment	Potentiometer, 11 turns/Single teach-in button $^{3/4)}$ (depending on type)
Continuous threshold adaption	-/✔ (depending on type)
Special feature	Detection of transparent objects

<sup>1)</sup> PL80A.

#### Mechanics/electronics

Supply voltage 1)	10 V DC 30 V DC
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>
Power consumption	≤ 40 mA <sup>3)</sup>
Output type	PNP/NPN/PNP, NPN (depending on type)
Output function	Complementary
Switching mode	Light switching/Dark-switching/Light/dark-switching (depending on type)
Switching mode selector	Selectable via L/D control wire
Signal voltage PNP HIGH/LOW	$>$ Uv - 3 V/ca. 0 V/approx. $V_S$ - 2.5 V/0 V (depending on type)
Signal voltage NPN HIGH/LOW	Approx. Uv/< 3 V/approx. $V_S$ /< 2.5 V (depending on type)
Output current I <sub>max.</sub>	100 mA
Response time	≤ 330 µs <sup>4)</sup>
Switching frequency 5)	1,500 Hz
Connection type	Male connector, M12
Circuit protection	
With automatic threshold adaption (AutoAdapt)	A <sup>6</sup> , B <sup>9</sup> , C <sup>7</sup> , D <sup>8</sup>
Without automatic threshold adaption (AutoAdapt)	A <sup>6</sup> , C <sup>7</sup> , D <sup>8</sup>
Protection class	II .
Weight	120 g
Polarisation filter	V
IO-Link	V
Housing material	Zinc diecast
Optics material	PMMA, PMMA, PTFE-coated (depending on type)
Enclosure rating	IP 66, IP 67, IP 69K
Operating mode	Mode I, 10 $\%$ attenuation, Mode II, 18 $\%$ attenuation
Plausibility output, stable detection	Approx. 0 V/approx. $V_S$ (depending on type)

G

 $<sup>^{2)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{\</sup>mbox{\tiny 3)}}$  Mode I, 10 % attenuation.

 $<sup>^{\</sup>scriptscriptstyle 4)}$  Mode II, 18 % attenuation.

Plausibility output, unstable detection	V <sub>S</sub> - 2.5 V/approx. 1.5 V (depending on type)
Ambient operating temperature	-40 °C +60 °C (depending on type)
Ambient storage temperature	-40 °C +75 °C

 $<sup>^{1)}</sup>$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W12G

#### WL12G, metal

#### • Housing material: metal

Type of light	Sensing range max. 1)	Light spot size (dis- tance)	Con- tinuous threshold adaption	Output type	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
Visible red light				PNP	Light switching Dark-switching	Potentiome- ter, 11 turns	Connector M12, 4-pin	Cd-087	WL12G-302431	1041457
	0 m	Ø 25 mm	_	PNP, NPN	Light switching Dark-switching	Potentiome- ter, 11 turns	Connector M12, 5-pin	Cd-144	WL12G-3B2531	1041456
	4 m	(1.5 m)	V	PNP	Light switching Dark-switching	Single teach- in button <sup>2) 3)</sup>	Connector M12, 5-pin	Cd-146	WL12G-3P2572	1053535
			•	NPN	Light switching Dark-switching	Single teach- in button <sup>2) 3)</sup>	Connector M12, 5-pin	Cd-146	WL12G-3N2572	1053530
Infrared light	0 m 4 m	Ø 100 mm (3 m)	~	PNP	Light switching Dark-switching	Single teach- in button <sup>2) 3)</sup>	Connector M12, 5-pin	Cd-233	WL12G-3P2582	1053536

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

 $<sup>^{5)}</sup>$  With light/dark ratio 1:1.

 $<sup>^{\</sup>rm 6)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{7)}</sup>$  C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{9)}</sup>$  B = inputs and output reverse-polarity protected.

 $<sup>^{2)}\,\</sup>text{Mode I, }10~\%$  attenuation.

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Mode II, 18 % attenuation.

#### WL12G, PTFE

• Housing material: PTFE

• Type of light: visible red light

Se	nsing range max. <sup>1)</sup>	Light spot size (dis- tance)	Con- tinuous threshold adaption		Switching mode	Adjust- ment <sup>2) 3)</sup>	Connection	Con- nection diagram	Model name	Part no.
(	0 m 4 m	Ø 25 mm (1.5 m)	V	PNP	Light/dark- switching	Single teach- in button	Connector M12, 5-pin	Cd-146	WL12G-3P2572T01	1053546

<sup>&</sup>lt;sup>1)</sup> PL80A.

#### WL12G, metal alarm output

• Housing material: metal

• Type of light: visible red light

Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Con- tinuous threshold adaption		Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m 4 m	Ø 25 mm	5 mm	PNP	Light/dark- switching	Single teach- in button <sup>2) 3)</sup>	Connector M12, 5-pin	Cd-147	WL12G-3V2572	1053537
0 III 4 M	0 m 4 m (1.5 m)		NPN	Light/dark- switching	Single teach- in button <sup>2) 3)</sup>	Connector M12, 5-pin	Cd-147	WL12G-3W2572	1053538

<sup>1)</sup> PL80A.

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Mode II, 18 % attenuation.



WL12G, metal IO-Link

- Housing material: metal
- Type of light: visible red light
- Output type: PNP
- Switching mode: light/dark-switching
- Adjustment: single teach-in button (Mode I, 10 % attenuation.) (Mode II, 18 % attenuation.)
- Continuous threshold adaption: ✔

Sensing range max. 1)	Light spot size (distance)	IO-Link	Advanced functions	Connection	Connection diagram	Model name	Part no.
		Standard functions	-		Cd-098	WL12GC-3P2472	1054087
Ø 25 mm	Ø 25 mm		Timer, False Tripping Suppression (Debouncing)	Connector M12, 4-pin		WL12GC-3P2472A70	1067778
0 m 4 m	0 m 4 m (1.5 m)	Standard functions, advanced functions	High-Speed Counter, False Tripping Suppression (Debouncing)			WL12GC-3P2472A71	1067779
		Time Stamp, False Tripping Suppression (Debouncing)			WL12GC-3P2472A91	1061063	

<sup>1)</sup> PL80A.



<sup>2)</sup> Mode I, 10 % attenuation.

<sup>3)</sup> Mode II, 18 % attenuation.


 $<sup>^{2)}\,\</sup>text{Mode I, }10~\%$  attenuation.

<sup>&</sup>lt;sup>2)</sup> Mode I, 10 % attenuation.

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Mode II, 18 % attenuation.

# **Dimensional drawings**


Dimensions in mm (inch)



- ① Optical axis
- 2 LED indicator yellow: Light received
- 3 Green LED indicator: supply voltage active
- ④ M4 threaded mounting hole, 4 mm deep
- 3 Mounting hole, Ø 4.2 mm
- 6 Sensitivity adjustment: poti
- 7 Connection


### **Adjustments**

#### Potentiometer




- ② LED indicator yellow: Light received
- 3 Green LED indicator: supply voltage active
- 6 Sensitivity adjustment: poti

#### Singel teach-in button




- 2 LED indicator yellow: Light received
- 3 LED indicator, green: power on, teach-in mode I,LED indicator, blue: teach-in mode II
- 6 Single teach-in button, Function 1: teach-in sensitivity on reflector, Function 2: change operation/ teach-in mode

# **Bar diagrams**



- Sensing range max.
- ① PL80A
- ② C110A
- ③ P250F
- 4 PL50A
- ⑤ PL40A
- 6 PL30A
- ⑦ PL20A
- 8 REF-IRF-56


# **Light spot diameter**



# **Connection diagram**


Cd-087	7
brn	1

#### Cd-144



#### Cd-146

Cd-147



Cd-233

### **Recommended accessories**

#### Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
10-	Stainless staal	Mounting bracket, large	BEF-WG-W12	2013942
13	Stainless steel	Mounting bracket, small	BEF-WK-W12	2012938

#### Plug connectors and cables

#### Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867
	Female connector, M12, 5-pin, straight	Cable, open con- ductor heads	5 m, 5-wire	IP 67	DOL-1205-G05M	6009868
11	Female connector, M12, 5-pin, angled	· · ·	2 m, 5-wire	IP 67	DOL-1205-W02M	6008900
100			5 m, 5-wire	IP 67	DOL-1205-W05M	6009869

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303
	Female connector, M12, 5-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1205-G	6009719
	Female connector, M12, 5-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1205-W	6009720

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
9		Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
		Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610



#### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W12-3	2045175

# Terminal and alignment brackets

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Double clamp bracket for dovetail mounting	BEF-DKH-W12	2013947
		Clamping block for dovetail mounting	BEF-KH-W12	2013285

#### Reflectors

#### Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089
0	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

#### **Reflective tape**

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

#### **Special reflectors**

Figure	Material	Description	Model name	Part no.
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

→ For additional accessories, please see page L-861



Rugged metal housing provides exceptional performance in demanding applications







#### **Additional information**

**ECOLAB O IO**-Link

Detailed technical data	.G-529
Ordering information	.G-530
Dimensional drawings	.G-534
Adjustments	.G-537
Characteristic curves	.G-537
Bar diagrams	.G-540
Light spot diameter	.G-541
Connection diagram	.G-541
Recommended accessories	.G-542

# **Product description**

The W12-3 family features a complete range of photoelectric sensors that are enclosed in a metal housing. There are a large number of variations that are available, including proximity, retro-reflective, through-beam, special laser and clear material versions. These sensors offer

many advantages over conventional optical sensors due to their reliable object detection and monitoring capabilities. Whether in packaging, pharmaceutical, or the food and beverage industries – the W12 family provides a solution for any application.

#### At a glance

- Best-in-class optical performance due to superior OES technology
- Autocollimation with retro-reflective sensors
- Background and foreground suppression with second emitter LED on proximity sensors
- Highly visible, precise light spot and high-energy IR transmitters
- Rugged die-cast zinc housing, optional with Teflon® coating
- Mounting options with through holes, base blind holes, oblong through holes and dovetail
- Flexible sensor settings, monitoring, advanced diagnostics, and visualization thanks to IO-Link

#### **Your benefits**

- Reliable detection due to superior ASIC (application-specific integrated circuit) technology and immunity to optical interference factors from the industrial environment
- PinPoint LED technology provides a bright, small and precise light spot that enables quick and easy sensor alignment
- Precise switching characteristics ensure reliable object detection, reducing downtime caused by re-adjusting sensors during recipe changes
- Wide range of products enclosed in a rugged metal housing enables application flexibility in a broad range of industrial environments
- Flexible mounting options reduce installation time
- IO-Link provides easy data access from the PLC
- · Quick and easy configuration
- Quick and easy integration using function blocks

#### → www.mysick.com/en/W12-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	WTB12-3	WTF12-3	WL12-3	WSE12-3		
Sensor principle	3		Photoelectric retro- reflective sensor	Through-beam photo- electric sensor		
Detection principle	Background suppression	Foreground suppression	Autocollimation	-		
Dimensions (W x H x D)	15.6 mm x 48.5 mm x	42 mm				
Housing design (light emission)	Rectangular					
Sensing range max.	20 mm 800 mm <sup>1)</sup> (depending on type)	30 mm 500 mm <sup>1)</sup> (depending on type)	0 m 7 m <sup>2)</sup> (depending on type)	0 m 20 m		
Sensing range	20 mm 800 mm (depending on type)	30 mm 500 mm (depending on type)	0 m 5 m <sup>2)</sup> (depending on type)	0 m 15 m		
Type of light	Visible red light/Infra- red light (depending on type)	Visible red light				
Light source	LED <sup>3)</sup> /PinPoint LED <sup>3)</sup> (depending on type)	LED 3)				
Angle of dispersion	-		Approx. 1.5°/5° (depending on type)	Approx. 1.5°		
Wave length						
Visible red light	660 nm/640 nm (depe	ending on type)	640 nm			
Infrared light	850 nm/880 nm (depending on type)	-				
Adjustment	Potentiometer, 5 turns/ (depending on type)	turns/Single teach-in button/Double teach-in button/Cable be)				
Special feature	Line-shaped light spot (depending on type)	-	Focused optics (depending on type)	-		

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### Mechanics/electronics

	WTB12-3	WTF12-3	WL12-3	WSE12-3			
Supply voltage 1)	10 V DC 30 V DC						
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>						
Power consumption <sup>3)</sup>	≤ 30 mA ≤ 60 mA (depending on type)	≤ 30 mA ≤ 45 mA (depending on type)	≤ 30 mA ≤ 100 mA (depending on type)	-			
Power consumption, sender 3)	-			≤ 30 mA			
Power consumption, receiver <sup>3)</sup>	-	-					
Output type	PNP/NPN (depending on type)						
Output function	Complementary						
Switching mode	Light/dark-switching/D	ark-switching (dependir	g on type)				
Signal voltage PNP HIGH/LOW	> Uv - 2,5 V/ca. 0 V						
Signal voltage NPN HIGH/LOW	Approx. VS/< 2.5 V						
Output current I <sub>max.</sub>	100 mA						
Response time							
Switching frequency 750 Hz 5)	≤ 700 µs <sup>4)</sup>	-					
Switching frequency 1,500 Hz <sup>5)</sup>	≤ 330 µs <sup>4)</sup>						
Switching frequency 5,000 Hz 5)	-		≤ 100 µs <sup>4)</sup>	-			
Connection type	Male connector, M12/0	Cable/Cable, 3 m 6) (dep	ending on type)				

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WTB12-3	WTF12-3	WL12-3	WSE12-3
Circuit protection	A 7), C 8), D 9)			
Protection class	II			
Weight				
Connec	or 200 g 280 g	200 g	200 g 250 g	200 g
Cal	le 120 g			
Polarisation filter	-		✓ (depending on type)	-
IO-Link	✓ (depending on type)			
Enclosure rating	IP 66, IP 67, IP 69K			
Test input sender off	-			TE to 0 V
Ambient operating temperature	-40 °C +60 °C			
Ambient storage temperature	-40 °C +75 °C			

<sup>&</sup>lt;sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W12-3

#### WTB12-3

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching mode: light/dark-switching

Type of light	Sensing range max. 1)	Light spot size (distance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
	35 mm 100 mm	Ø 2 mm (60 mm)	PNP	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WTB12-3P2441	1041421
				Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTB12-3P1131	1041413
			PNP	rotentionneter, 5 turns	Connector M12, 4-pin	Cd-083	WTB12-3P2431	1041411
Visible	20 mm	Ø 6 mm		Double teach-in button	Connector M12, 4-pin	Cd-083	WTB12-3P2433	1041412
red light 350 mm	(200 mm)		Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTB12-3N1131	1041418	
			NPN	roteiltiometer, 5 turns	Connector M12, 4-pin	Cd-083	WTB12-3N2431	1041416
				Double teach-in button	Connector M12, 4-pin	Cd-083	WTB12-3N2433	1041417
	50 mm 800 mm	Ø 9 mm (400 mm)	PNP	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WTB12-3P2461S01	1051967
				Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTB12-3P1111	1041424
			PNP		Cable, 4-wire 3 m PVC	Cd-094	WTB12-3P1711	1041426
			PINP		Connector M12, 4-pin	Cd-083	WTB12-3P2411	1041422
Infrared	20 mm	15 mm x 15 mm		Double teach-in button	Connector M12, 4-pin	Cd-083	WTB12-3P2413	1041423
light	600 mm	(200 mm)			Cable, 4-wire 2 m PVC	Cd-094	WTB12-3N1111	1041429
			NPN	Potentiometer, 5 turns	Cable, 4-wire 3 m PVC	Cd-094	WTB12-3N1711	1041430
					Connector M12, 4-pin	Cd-083	WTB12-3N2411	1041427
			Double teach-in button	Connector M12, 4-pin	Cd-083	WTB12-3N2413	1041428	

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>8)</sup> C = interference suppression.

<sup>&</sup>lt;sup>9)</sup> D = outputs overcurrent and short-circuit protected.

#### WTB12-3, line-shaped light spot

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Type of light: visible red light
- Switching mode: light/dark-switching

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
30 mm 500 mm	50 mm x 5 mm (200 mm)	PNP	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WTB12-3P2461S58	1047850

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Type of light: visible red light
- Switching mode: light/dark-switching
- Output type: PNP
- Adjustment: cable, single teach-in button

Sensing range max. 1)	Light spot size (distance)	IO-Link	Advanced functions	Connection	Connection diagram	Model name	Part no.
		Standard functions	-			WTB12C-3P2432	1067771
20 mm	nm (200 mm) function advant	0	Timer, False Tripping Suppression (Debouncing)	Connector M12, 4-pin	Cd-098	WTB12C-3P2432A70	1067772
350 mm		functions, advanced High	High-Speed Counter, False Tripping Suppression (Debouncing)			WTB12C-3P2432A71	1067773
	Turiodons	Time Stamp, False Tripping Suppression (Debouncing)			WTB12C-3P2432A91	1060222	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WTF12-3

- Sensor principle: photoelectric proximity sensor
- Detection principle: foreground suppression
- Type of light: visible red light
- Switching mode: light/dark-switching

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
			Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTF12-3P1131	1041406
		PNP		Connector M12, 4-pin	Cd-083	WTF12-3P2431	1041404
30 mm 175 mm	Ø 2 mm		Double teach-in button	Connector M12, 4-pin	Cd-083	WTF12-3P2433	1041405
30 11111 173 11111	(60 mm)	NPN	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTF12-3N1131	1041410
				Connector M12, 4-pin	Cd-083	WTF12-3N2431	1041408
			Double teach-in button	Connector M12, 4-pin	Cd-083	WTF12-3N2433	1041409

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



Sensing range max. 1)	Light spot size (distance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
	Ø 7 mm (300 mm)	PNP	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WTF12-3P1141	1041402
20				Connector M12, 4-pin	Cd-083	WTF12-3P2441	1041400
30 mm 500 mm			Single teach-in button	Connector M12, 4-pin	Cd-083	WTF12-3P2443	1041401
		NPN	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WTF12-3N2441	1041403

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL12-3

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

• Switching mode: light/dark-switching

• Type of light: visible red light

• Light spot size (distance): Ø 100 mm (3 m)

Sensing range max. 1)	Polarisation filter	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
			Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3P1131	1041437
		PNP		Cable, 4-wire 3 m PVC	Cd-094	WL12-3P1731	1041438
	V			Connector M12, 4-pin	Cd-083	WL12-3P2431	1041436
		•		Cable, 4-wire 2 m PVC	Cd-094	WL12-3N1131	1041441
0 m 7 m	NP	NPN	Potentiometer, 5 turns	Cable, 4-wire 3 m PVC	Cd-094	WL12-3N1731	1041442
0 111 7 111				Connector M12, 4-pin	Cd-083	WL12-3N2431	1041440
		PNP	Datantiamatan E tuma	Cable, 4-wire 2 m PVC	Cd-094	WL12-3P1141	1041445
		PINP	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WL12-3P2441	1041444
	-	NIDNI	PN Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3N1141	1041447
		NPN		Connector M12, 4-pin	Cd-083	WL12-3N2441	1041446

<sup>1)</sup> PL80A.

# WL12-3, alarm output

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation
- Switching mode: dark-switching
- Type of light: visible red light
- Light spot size (distance): Ø 100 mm (3 m)

Sensing range max. 1)	Polarisation filter	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m 7 m	V	PNP	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-110	WL12-3V2431	1041537

<sup>1)</sup> PL80A.

#### WL12-3, focused optics

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation
- Switching mode: light/dark-switching
- Type of light: visible red light
- Light spot size (distance): Ø 2 mm (90 mm)

Sensing range max. <sup>1)</sup>	Polarisation filter	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m 2 m		PNP	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3P1151	1041449
	V			Connector M12, 4-pin	Cd-083	WL12-3P2451	1041448
	•	NPN	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3N1151	1041451
		INPIN	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-083	WL12-3N2451	1041450
	PNP	DND	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3P1161	1041453
		rotentionneter, 5 turns	Connector M12, 4-pin	Cd-083	WL12-3P2461	1041452	
	_	NPN	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-094	WL12-3N1161	1041455
	NPN			Connector M12, 4-pin	Cd-083	WL12-3N2461	1041454

<sup>1)</sup> PL80A.



WL12-3, IO-Link

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: autocollimation
- Type of light: visible red light
- Output type: PNP
- Switching mode: light/dark-switching
- Adjustment: cable, single teach-in button

Sensing range max. 1)	Polarisation filter	IO-Link	Advanced functions	Connection	Con- nection diagram	Model name	Part no.
0 m 7 m		Standard functions	-	Connector	Cd-098	WL12C-3P2432	1067774
	V	Standard	Timer, False Tripping Suppression (Debouncing)			WL12C-3P2432A70	1067775
		functions, advanced	High-Speed Counter, False Tripping Suppression (Debouncing)	M12, 4-pin	Cu-096	WL12C-3P2432A71	1067776
		functions	Time Stamp, False Tripping Suppression (Debouncing)			WL12C-3P2432A91	1067777

<sup>1)</sup> PL80A.

#### WSE12-3

- Sensor principle: through-beam photoelectric sensor
- Switching mode: light/dark-switching
- Type of light: visible red light

Sensing range max.	Light spot size (distance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
0 m 20 m		PNP	Potentiometer, 5 turns	Cable, 4-wire 2 m PVC	Cd-088	WSE12-3P1131	1041460
	Ø 220 mm			Connector M12, 4-pin	Cd-072	WSE12-3P2431	1041459
	(15 mm)	NIDNI	Data atia arata a Etama	Cable, 4-wire 2 m PVC	Cd-088	WSE12-3N1131	1041463
		NPN	Potentiometer, 5 turns	Connector M12, 4-pin	Cd-072	WSE12-3N2431	1041462







Sensor principle: through-beam photoelectric sensor

Type of light: visible red light
 Light spot size: Ø 220 mm (15 mm)
 Switching mode: light/dark-switching


• Output type: PNP


Sensing range max.	IO-Link	Advanced functions	Connection	Connection diagram	Model name	Part no.
0 m 20 m Standard functions	Standard functions	-	Connector	Cd-268	WSE12C-3P2430	1067780
		Timer, False Tripping Suppression (Debouncing)			WSE12C-3P2430A70	1067781
	Standard functions, advanced functions	High-Speed Counter, False Tripping Suppression (Debouncing)	M12, 4-pin		WSE12C-3P2430A71	1067782
		Time Stamp, False Tripping Suppression (Debouncing)			WSE12C-3P2430A91	1067783


# **Dimensional drawings**

Dimensions in mm (inch)

#### WTB12-3, potentiometer









- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Status indicator LED green: power on
- $\ensuremath{\mathfrak{D}}$  Status indicator LED, yellow: Status of received light beam
- 6 M4 threaded mounting hole, 4 mm deep
- 7 Mounting hole, Ø 4.2 mm
- ® Sensing range adjustment: potentiometer
- © Connection

#### WTB12-3, double teach-in button




- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 M4 threaded mounting hole, 4 mm deep
- 7 Mounting hole, Ø 4.2 mm
- Sensing range adjustment: double teach-in button
- Connection

#### WTF12-3, potentiometer




#### WTB12-3, IO-Link



- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- ④ Green LED indicator: supply voltage active
- ⑤ LED indicator yellow: Light received
- **6** M4 threaded mounting hole, 4 mm deep
- 7 Mounting hole, Ø 4.2 mm
- Adjustment sensing range: single teach-in button
- Connection
- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- M4 threaded mounting hole, 4 mm deep
- 7 Mounting hole, Ø 4.2 mm
- Sensing range adjustment: potentiometer
- Connection




#### WTF12-3, single teach-in button




- ① Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Status indicator LED green: power on
- 3 Status indicator LED, yellow: Status of received light beam
- **6** M4 threaded mounting hole, 4 mm deep
- ⑦ Mounting hole, Ø 4.2 mm
- ® Sensing range adjustment: potentiometer
- Connection

#### WL12-3, WSE12-3




#### WTF12-3, IO-Link



- $\ensuremath{\boxdot}$  Standard direction of the material being detected
- 2 Optical axis, receiver
- 3 Optical axis, sender
- 4 Green LED indicator: supply voltage active
- ⑤ LED indicator yellow: Light received
- 6 M4 threaded mounting hole, 4 mm deep
- 7 Mounting hole, Ø 4.2 mm
- ® Adjustment sensing range: single teach-in button
- Connection
- ① Optical axis
- 2 LED indicator yellow: Light received
- ③ Green LED indicator: supply voltage active
- ④ M4 threaded mounting hole, 4 mm deep
- ⑤ Mounting hole, Ø 4.2 mm
- 6 Sensitivity adjustment: poti
- 7 Connection


### **Adjustments**

# WTB12-3, WTF12-3, potentiometer




- ④ Green LED indicator: supply voltage active
- ⑤ LED indicator yellow: Light received
- Sensing range adjustment: potentiometer

# WTB12-3, WTF12-3, double teach-in button




- ④ Green LED indicator: supply voltage active
- ⑤ LED indicator yellow: Light received
- Sensing range adjustment: double teach-in button

#### WTB12-3, WTF12-3, IO-Link



- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- **8** Adjustment sensing range: single teach-in button

#### WL12-3, WSE12-3




- 2 LED indicator yellow: Light received
- ③ Green LED indicator: supply voltage active
- Sensitivity adjustment: poti

#### **Characteristic curves**


#### Black-white shift

#### WTB12-3, red light, 350 mm




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB12-3, red light, 800 mm




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WTB12-3, infrared light




- 1 Sensing range on black, 6 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTF12-3, 500 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission


#### WTF12-3, 175 mm



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


#### Operating reserve

#### WL12-3




- ① Reflector type PL80A
- 2 Reflector type C110A
- Reflector type PL20A
- ? Reflective tape

#### WSE12-3



#### WL12-3, focused




- ① Reflector type C110A
- 2 Reflector type PL80A
- 3 Reflector type P205
- Reflector type PL50A
- ⑤ Reflector type PL40A
- 6 Reflector type PL30A
- Reflector type PL20A Reflector type DG/IRF6000

G


# **Bar diagrams**

### WTB12-3, red light, 350 mm




- Sensing range
- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### WTF12-3, 175 mm




- Sensing range
- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WL12-3




- Sensing range
- ① PL80A ② C110A
- ③ PL50A
- 4 PL40A
- ⑤ PL30A
- 6 PL20A
- 7 Reflective tape Diamond Grade

### WSE12-3




#### WTB12-3, infrared light



Sensing range

- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


### WTF12-3, 500 mm



Sensing range

- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WL12-3, focused



Sensing range

⑤ PL40A Diamond Grade

① C110A ② PL80A ③ P250F

6 C30A ⑦ PL20A


4 PL50A

8 Reflective tape

Sensing range typ. max.

# **Light spot diameter**

### WTB12-3, line shaped light spot





<sup>\*</sup>The angle of reception is smaller than the angle of dispersion therefore the effective length of the light spot is smaller than the real visible line-shaped light spot.

(0.2 x 3.35) (0.2 x 1.38)\*

# **Connection diagram**

### Cd-072





### Cd-083

② Receiver

### Cd-088

### Cd-094

① Sender 2 Receiver

#### Cd-110

## Cd-268

$$\begin{array}{c|c}
\hline
2 \\
\hline
\text{bin} & 1 \\
\hline
\text{blu} & 2 \\
\hline
\text{blu} & 3 \\
\hline
\text{blk} & 4 \\
\hline
\text{of C}
\end{array}$$

$${\bf 1} {\bf Sender}$$

2 Receiver

# **Recommended accessories**

# Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
		Mounting bracket, large	BEF-WG-W12	2013942
8	Stainless steel	Mounting bracket, small	BEF-WK-W12	2012938

# Plug connectors and cables

## Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.			
	Female connector,	Cable, open con-	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382			
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866			
	Female connector,		2 m, 4-wire	TPU	IP 67	DOL-1204-L02M	6027945			
	M12, 4-pin, angled,	Cable, open con- ductor heads	5 m, 4-wire	TPU	IP 67	DOL-1204-L05M	6027944			
	with 3 LEDs						J III, 4-WIIE	PVC	IP 67, IP 69K	DOL-1204-L05MN
	Female connector, M12, 4-pin, angled	Cable, open con-	2 m, 4-wire	TPU	IP 67	DOL-1204-W02M	6009383			
			5 m, 4-wire	TPU	IP 67	DOL-1204-W05M	6009867			
			10 m, 4-wire	TPU	IP 67	DOL-1204-W10M	6010541			

# Masks

Figure	Description	Model name	Part no.
22 25 12 12	Mask card for WS/WE12-3 with 2 self-adhesive masks each for sender and receiver, slot width X: $0.5 \ \text{mm}/1.0 \ \text{mm}/2.0 \ \text{mm}$	BL-12-SKN	4031815

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
		Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608
9	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
ð		Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Device protection (mechanical)

## Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W12-3	2045175

### Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	,	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.	
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244	

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

# Terminal and alignment brackets

### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Ctaal sine acctad	Double clamp bracket for dovetail mounting	BEF-DKH-W12	2013947
	Steel, zinc coated	Clamping block for dovetail mounting	BEF-KH-W12	2013285

→ For additional accessories, please see page L-861











## **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories G-553

# **Product description**

The W14-2 series of photoelectric sensors from SICK offers reliable object detection at a cost-effective price for typical conveyor, packaging and automation applications. These sensors include features that help to simplify mounting and installation, which helps increase ease of use. Proximity, retro-reflective and through-beam versions are available with different options (mounting,

LED, and technology) to suit application requirements. Variants with PinPoint LED technology, for example, have a bright, focused light spot that permits quick and easy alignment of the sensor to the detected object. An extensive range of accessories is available, including mounting systems, sensor protection equipment, reflectors, and connection systems.

# At a glance

- Outstanding background suppression with OES3 technology
- Highly visible and precise light spot due to PinPoint LED in selected products
- Slim, durable plastic housing
- Complete sensor family with proximity, retro-reflective and through-beam variants

### Your benefits

- Reliable object detection at a costeffective price
- PinPoint LED technology provides a highly visible red light that enables quick and easy setup
- Broad product range gives users a variety of choices to fit their application
- Rugged plastic housing in a slim design simplifies installation
- Quick and easy installation using SICK accessories saves time

### → www.mysick.com/en/W14-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	WT14-2	WL14-2	WS/WE14-2
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression/ energetic (depending on type)	Standard optics	-
Dimensions (W x H x D)	17.6 mm x 75.5 mm x 33.5 mm	n	
Housing design (light emission)	Rectangular		
Sensing range max.	20 mm 1,500 mm <sup>1)</sup> (depending on type)	0.15 m 17 m <sup>2)</sup> (depending on type)	0 m 15 m
Sensing range	50 mm 1,500 mm <sup>1)</sup> (depending on type)	$0.15~\text{m}$ 12 m $^{2)}$ (depending on type)	0 m 10 m
Type of light	Visible red light/Infrared light (depending on type)	Visible red light	
Light source	LED 3)/PinPoint-LED 3) (depending	ng on type)	LED 3)
Angle of dispersion	-	Approx. 2°/approx. 0.9° (depending on type)	-
Wave length			
Visible red light	675 nm/637 nm (depending on type)	645 nm/637 nm (depending on type)	645 nm
Infrared light	870 nm	-	
Adjustment	Potentiometer, 4 turns Single teach-in button (depending on type)	Single teach-in button	-
Special feature	Line-shaped light spot (depending on type)	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WT14-2	WL14-2	WS/WE14-2
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	5 V <sub>pp</sub>		
Power consumption	$\leq$ 25 mA $^{3)}$ $\leq$ 55 mA $^{3)}$ (depending on type)	≤ 35 mA <sup>3)</sup>	-
Power consumption, sender	-		35 mA <sup>3)</sup>
Power consumption, receiver	-		25 mA <sup>3)</sup>
Output type	PNP/NPN (depending on t	ype)	
Output function	Complementary		
Switching mode	Light/dark-switching		
Output current I <sub>max.</sub>	≤ 100 mA		
Response time 4)	≤ 2.5 ms		
Switching frequency 5)	200 Hz		
Connection type	Cable, 2 m <sup>6)</sup> Male connector, M12 (depending on type)	Cable, 2 m <sup>6)</sup> Male connector, M12 Cable with connector, M12 <sup>6)</sup> (depending on type)	Cable, 2 m <sup>6)</sup> Male connector, M12 (depending on type)
Circuit protection	A 7), C 8), D 9)		

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_{A}$  = +25 °C.

	WT14-2	WL14-2	WS/WE14-2
Weight			
Connector M12, 4-pin	40 g		
Cable/cable with connector	120 g		
Polarisation filter	-	<b>✓</b>	-
Housing material	ABS		
Optics material	PMMA		
Enclosure rating	IP 67		
Ambient operating temperature	-30 °C +60 °C	-25 °C +60 °C	
Ambient storage temperature	-40 °C +70 °C		

 $<sup>^{1)}</sup>$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W14-2

### WT14-2

• Sensor principle: photoelectric proximity sensor

• Switching mode: light/dark-switching

Detec- tion principle	Type of light	Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
			Ø 10 mm	PNP	Potentiometer,	Cable, 4-wire 2 m PVC	Cd-094	WT14-2P132	1026055
	Visible red light	20 mm		PNP	4 turns	Connector M12, 4-pin	Cd-083	WT14-2P432	1026056
	visible red light	250 mm	(250 mm)	NPN	Potentiometer,	Cable, 4-wire 2 m PVC	Cd-094	WT14-2N132	1026072
Back-				NPN	4 turns	Connector M12, 4-pin	Cd-083	WT14-2N432	1026057
ground suppres-	Visible red light (PinPoint LED)	20 mm 1,300 mm	Ø 7 mm (300 mm)	PNP	Potentiometer, 4 turns	Connector M12, 4-pin	Cd-083	WT14-2P432S08	1045104
sion	sion	20 mm	Ø 14 mm (300 mm)	PNP	Potentiometer, 4 turns	Cable, 4-wire 2 m PVC	Cd-094	WT14-2P122	1026051
	Infrared light					Connector M12, 4-pin	Cd-083	WT14-2P422	1026052
	ililialeu ligit	500 mm		NPN	PN Potentiometer, 4 turns	Cable, 4-wire 2 m PVC	Cd-094	WT14-2N122	1026053
						Connector M12, 4-pin	Cd-083	WT14-2N422	1026054
				PNP	Single teach-in	Cable, 4-wire 2 m PVC	Cd-094	WT14-2P111	1026058
Energetic	Infrared light	50 mm 1,500 mm	Ø 56 mm (1,000 mm)	FINE	button	Connector M12, 4-pin	Cd-083	WT14-2P411	1026059
Litergette	ilinaieu light			NDN	Single teach-in	Cable, 4-wire 2 m PVC	Cd-094	WT14-2N111	1026060
			NPN	button	Connector M12, 4-pin	Cd-083	WT14-2N411	1026062	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>rm 4)}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  Do not bend below 0 °C.

 $<sup>^{\</sup>rm 7)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

<sup>8)</sup> C = interference suppression.

<sup>&</sup>lt;sup>9)</sup> D = outputs overcurrent and short-circuit protected.

## WT14-2, line-shaped light spot

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Switching mode: light/dark-switching

Type of light	Sensing range max. 1)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
Infrared light	20 mm 500 mm	PNP	Potentiometer, 4 turns	Connector M12, 4-pin	Cd-083	WT14-2P422S03	1041679

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WL14-2

• Sensor principle: photoelectric retro-reflective sensor

Detection principle: standard opticsSwitching mode: light/dark-switching

Polarisation filter: ✔

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Out- put type	Adjustment	Connection	Con- nection diagram	Model name	Part no.
			PNP	_	Cable, 4-wire 2 m PVC	Cd-094	WL14-2P130	1026050
Visible red light	Visible red light 0.15 m	Ø 140 mm	PINP		Connector M12, 4-pin	Cd-083	WL14-2P430	1026049
(LED)	6 m	(4 m)	NPN	-	Cable, 4-wire 2 m PVC	Cd-094	WL14-2N130	1026047
					Connector M12, 4-pin	Cd-083	WL14-2N430	1026048
Visible red light (PinPoint LED)	0.15 m 17 m	Ø 30 mm (2 m)	PNP	Single teach-in button	Connector M12, 4-pin	Cd-083	WL14-2P431	1050271

<sup>1)</sup> PL80A.

## WL14-2, detecting objects wrapped in film

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

• Switching mode: light/dark-switching

Polarisation filter:

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Out- put type	Connection	Con- nection diagram	Model name	Part no.
			1 PNP	Cable with connector M12, 4-pin 0.29 m PVC	Cd-101	WL14-2K930S11	1046864
Visible red light	0.5 m 5 m	.5 m Ø 140 mm 5 m (4 m)		Cable with connector M12, 4-pin 0.1 m PVC	Cd-083	WL14-2P030S13	1051200
	<b>5</b>			Connector M12, 4-pin	Cd-083	WL14-2P430S03	1029850

<sup>&</sup>lt;sup>1)</sup> PL80A.

## WS/WE14-2


Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching

Type of light	Sensing range max.	Light spot size (dis- tance)	Out- put type	Connection	Con- nection diagram	Model name	Part no.
		Ø 300 mm (10 mm)	PNP	Cable, 4-wire 2 m PVC	Cd-074	WS/WE14-2P130	1026430
Visible wad light	0 m			Connector M12, 4-pin	Cd-072	WS/WE14-2P430	1026431
Visible red light 15 m	15 m		NPN	Cable, 4-wire 2 m PVC	Cd-074	WS/WE14-2N130	1026432
				Connector M12, 4-pin	Cd-072	WS/WE14-2N430	1026433




### WT14-2, potentiometer



- ① Standard direction of the material being detected
- ② Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Mounting hole ø 4.1 mm
- ⑤ Status indicator LED, yellow: Status of received light beam
- **6** Status indicator LED green: power on
- 7 Potentiometer
- ® Connector M12, 4-pin or 2 m cable


## WT14-2, single teach-in button



- ① Standard direction of the material being detected
- ② Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Mounting hole  $\emptyset$  4.1 mm
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Status indicator LED green: power on
- $\ensuremath{{\mbox{$7$}}} \ensuremath{\mbox{Teach-in button}}$
- ® Connector M12, 4-pin or 2 m cable




### WL14-2



- ① Center of optical axis, sender
- 2 Center of optical axis, receiver
- 3 Mounting hole ø 4.1 mm
- Status indicator LED, yellow: Status of received light beam
- ⑤ Status indicator LED green: power on
- 6 Connector M12, 4-pin or 2 m cable


## WS/WE14-2



- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Mounting hole ø 4.1 mm
- 4 Status indicator LED, yellow: Status of received light beam
- $\ensuremath{\mathfrak{D}}$  Status indicator LED green: power on
- 6 Connector M12, 4-pin or 2 m cable


# **Adjustments**

#### **Potentiometer**



⑦ Sensing range adjustment: potentiometer, 4-turn

### Single teach-in button




① Teach-in button

## **Characteristic curves**


### Black-white shift

### WT14-2, red light, 250 mm




- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WT14-2, infrared light, 500 mm




- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

### WT14-2, red light, 1300 mm



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


### WT14-2, infrared light, 1500 mm



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


# Operating reserve

## WL14-2, 6 m




- ① PL80A
- ③ PL40A
- ⑤ PL20A
- 7 Reflective tape Diamond Grade

### WS/WE14-2



### WL14-2, 17 m



- ① PL80A
- ② PL40A
- ③ Reflective tape REF-IRF-56

G

# **Bar diagrams**


### WT14-2, red light, 250 mm



Sensing range

- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


### WT14-2, infrared light, 500 mm



Sensing range

- 1 Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WL14-2, 6 m




Sensing range

Sensing range max.

- ① PL80A
- ② PL50A
- ③ PL40A
- 4 PL30A
- ⑤ PL20A⑥ C110A
- 7 Reflective tape Diamond Grade


#### WS/WE14-2



Sensing range

Sensing range typ. max.


#### WT14-2, red light, 1300 mm



Sensing range

- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WT14-2, infrared light, 1500 mm




Sensing range

Sensing range typ. max.

- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

### WL14-2, 17 m



Sensing range


Sensing range max.

- ① PL80A
- ② PL40A
- 3 Reflective tape REF-IRF-56

- + (L+)


# **Connection diagram**

### Cd-072



- ① Sender
- 2 Receiver

### Cd-074



- ① Sender
- 2 Receiver

#### Cd-083



# Cd-094



### Cd-101

$$\begin{array}{c|c} & & brn; \ 1 \\ \hline & whti \ 2 \\ \hline & blu; \ 3 \\ \hline & blk; \ 4 \\ \hline \end{array} \begin{array}{c} Q \\ \hline & Q \\ \hline \end{array}$$

# **Recommended accessories**

# Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Charl sine costed	Mounting bracket	BEF-WN-W14	2019084
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W18	2009317

# Plug connectors and cables

# Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled		5 m, 4-wire	IP 67	DOL-1204-W05M	6009867



# G

## Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

## Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
1	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
9	Zinc plated steel	Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
ð	(sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (protective hous-	Post of the large of the continued allowers	BEF-SG-W14	2058124
1	ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601

# Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
8	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

















# Additional information

Additional information
Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories G-568

# **Product description**

SICK's W18-3 photoelectric sensor series reliably detects objects under difficult application conditions. Different variants are available, including proximity sensors with high-precision background suppression, retro-reflective sensors with autocollimation and through-beam sensors with high operating reserves.

These sensors are immune to ambient light, background reflections and light absorbing objects, making them a reliable sensor solution. The W18-3 series can also be customized according to the customer's requirements in critical applications.

# At a glance

- · Best-in-class optical performance due to superior OES technology
- · Autocollimation optics
- Background suppression with second sender LED
- · Slim, durable plastic housing
- Operation via double teach-in pushbutton or potentiometer
- · Wide variety of options for operation, connection, and optics

### Your benefits

- · Reliable object detection due to bestin-class background suppression and resistance to ambient light
- · A wide range of product variants provides increased user flexibility
- · Less downtime in industrial environments

### → www.mysick.com/en/W18-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

# **Features**

	WT18-3	WT18-3 Ex	WL18-3	WL18-3 Ex	WS/WE18-3
Sensor principle	Photoelectric proximity sensor		Photoelectric retro	Photoelectric retro-reflective sensor	
Detection principle	Background suppr	ression	Autocollimation		-
Dimensions (W x H x D)	17.6 mm x 75.5 m	nm x 33.5 mm			
Housing design (light emission)	Rectangular				
Sensing range max.	10 mm 1,000 mm <sup>1)</sup> (depending on type)	10 mm 1,000 mm <sup>1)</sup>	0 m 7 m <sup>2)</sup>	0 m 7 m <sup>2)</sup>	
Sensing range	50 mm 1,000 mm <sup>1)</sup> (depending on type)	50 mm 1,000 mm <sup>1)</sup>	0 m 5 m <sup>2)</sup>		-
Type of light	Visible red light/ Infrared light (depending on type)		Visible red light		Visible red light/ Infrared light (depending on type)
Light source 3)	LED				
Wave length					
Visible red light	675 nm	-	645 nm		
Infrared light	870 nm		-		880 nm
Adjustment	Potentiometer, 4 turns Double teach-in button Single teach-in button (depending on type)	Potentiometer, 4 turns	Potentiometer, 1 to	urn	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WT18-3	WT18-3 Ex	WL18-3	WL18-3 Ex	WS/WE18-3
Supply voltage 1)	10 V DC 30 V D	С			
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>				
Power consumption	40 mA <sup>3)</sup> 55 mA <sup>3)</sup>	55 mA <sup>3)</sup>	40 mA <sup>3)</sup>		-
Power consumption, sender	-				< 45 mA <sup>3)</sup>
Power consumption, receiver	-				< 35 mA <sup>3)</sup>
Output type	PNP/NPN (de- pending on type)	PNP	PNP/NPN (de- pending on type)	PNP	PNP/NPN (de- pending on type)
Output function	Complementary				
Switching mode	Light/dark-switchi	ng			
Output current I <sub>max.</sub>	100 mA				
Response time 4)	< 700 µs		< 500 µs		
Switching frequency 5)	700 Hz		1,000 Hz		
Angle of reception					
Visible red light	-		1,8°		1,5°
Infrared light	-		-		4,5°

G

<sup>2)</sup> PL80A

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WT18-3	WT18-3 Ex	WL18-3	WL18-3 Ex	WS/WE18-3
Connection type	Cable, 2 m <sup>6)</sup> Male connector, M12 (depending on type)	Cable with connector, M12 <sup>6)</sup>	Cubic connector Cable <sup>6)</sup> Male connector, M12 (depending on type)	Cable with connector, M12 <sup>6)</sup>	Cubic connector Cable <sup>6)</sup> Male connector, M12 (depending on type)
Circuit protection	A 7), C 8), D 9)				
Weight					
Cubic connector	-		70 g	-	70 g
Connector	-		40 g	-	40 g
Cable with connector	-	300 g	-	300 g	-
Cable, 4-wire	120 g/260 g	-	120 g	-	120 g
Cable, 5-wire	-		170 g	-	
Polarisation filter	-		V		-
Housing material	ABS				
Optics material	PMMA				
Enclosure rating	IP 67		IP 67/IP 65 (depending on type)	IP 67	IP 67/IP 65 (depending on type)
Test input sender off	-		TE to 0 V/ TE to V <sub>S</sub> (depending on type)	-	TE to 0 V
ATEX marking	-	EX II 3D IP67 T70 °C, EX II 3G EEx nA II T4 X <sup>10)</sup>	-	EX II 3D IP67 T70 °C, Ex II 3G EEx nA II T4 X <sup>10)</sup>	-
Hazardous area category	-	3D, 3G	-	3D, 3G	-
Test input	-		-/~	-	
Ambient operating temperature	-40 °C +60 °C				
Ambient storage temperature	-40 °C +75 °C				

 $<sup>^{\</sup>scriptsize 1)}$  Limit values, operation in short-circuit protected network max. 8 A.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>8)</sup> C = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>&</sup>lt;sup>10)</sup> Conformity with directives. Explosion prevention: Directive 94/9/EC.

# **Ordering information**

Other models available at www.mysick.com/en/W18-3

## WT18-3

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Switching mode: light/dark-switching

Type of	Sensing	Light spot size	Output	Adjustment	Connection	Connection	Model name	Part no.						
light	range max. 1)	(distance)	type			diagram								
					Cable, 4-wire 2 m PVC	Cd-094	WT18-3P130	1025895						
				Potentiometer, 4 turns	Cable, 4-wire 5 m PVC	Cd-094	WT18-3P230	1026559						
			PNP		Connector M12, 4-pin	Cd-083	WT18-3P430	1025896						
				Double teach-in	Cable, 4-wire 2 m PVC	Cd-094	WT18-3P131	1026034						
Visible red light	10 mm 600 mm	Ø 15 mm (300 mm)		button	Connector M12, 4-pin	Cd-083	WT18-3P431	1026032						
	000	(000)		Potentiometer,	Cable, 4-wire 2 m PVC	Cd-094	WT18-3N130	1025897						
			NPN	4 turns	Connector M12, 4-pin	Cd-083	WT18-3N430	1025898						
			INPIN	Double teach-in button	Cable, 4-wire 2 m PVC	Cd-094	WT18-3N131	1028040						
					Connector M12, 4-pin	Cd-083	WT18-3N431	1026035						
				Potentiometer, 4 turns	Cable, 4-wire 2 m PVC	Cd-094	WT18-3P110	1025887						
					Cable, 4-wire 5 m PVC	Cd-094	WT18-3P210	1025888						
			PNP		Connector M12, 4-pin	Cd-083	WT18-3P410	1025889						
	10 mm	Ø 20 mm		Double teach-in	Cable, 4-wire 2 m PVC	Cd-094	WT18-3P111	1026033						
	700 mm	(400 mm)		button	Connector M12, 4-pin	Cd-083	WT18-3P411	1026031						
Infrared					Cable, 4-wire 2 m PVC	Cd-094	WT18-3N110	1025891						
light			NPN	Potentiometer, 4 turns	Cable, 4-wire 5 m PVC	Cd-094	WT18-3N210	1025892						
					Connector M12, 4-pin	Cd-083	WT18-3N410	1025893						
					Cable, 4-wire 2 m PVC	Cd-094	WT18-3P120	1025904						
	10 mm	Ø 30 mm		Potentiometer, 4 turns	Connector M12, 4-pin	Cd-083	WT18-3P420	1025905						
	1,000 mm		PNP	T tullio	Conflector Wi12, 4-pin	Cd-102	WT18-3K420	1061203						
			. ,		,	,	,	, ,	,		Double teach-in button	Connector M12, 4-pin	Cd-083	WT18-3P421

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WT18-3 Ex

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching mode: light/dark-switching
- Type of light: visible red light
- Connection: cable with connector M12, 4-pin 0.29 m PVC

Sensing range max. 1)	Light spot size (distance)	Output type	Adjustment	Hazardous area category	Connection diagram	Model name	Part no.
10 mm 1,000 mm	Ø 30 mm (600 mm)	PNP	Potentiometer, 4 turns	3D, 3G	Cd-083	WT18X-3P920	1029901

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



### WL18-3

• Sensor principle: photoelectric retro-reflective sensor

Detection principle: autocollimation

• Switching mode: light/dark-switching

• Type of light: visible red light

• Polarisation filter: 🗸

Sensing range max. 1)	Light spot size (distance)	Output type	Adjustment	Test input	Connection	Connection diagram	Model name	Part no.	
			Potentiometer, 1 turn		Cable, 4-wire 2 m PVC	Cd-094	WL18-3P130	1025909	
		DND			_	Connector M12, 4-pin	Cd-083	WL18-3P430	1025911
	a.40 (0 )	PNP		Cubic connector, 6-pin	Cd-178	WL18-3P630	1025912		
0 m 7 m					•	Cable, 5-wire 2 m PVC	Cd-141	WL18-3P730	1026029
0 111 7 111	Ø 40 mm (2 m)	NPN			Cable, 4-wire 2 m PVC	Cd-094	WL18-3N130	1025913	
				_	Connector M12, 4-pin	Cd-083	WL18-3N430	1025915	
				.,	Cubic connector, 6-pin	Cd-178	WL18-3N630	1025916	
				/	Cable, 5-wire 2 m PVC	Cd-141	WL18-3N730	1026030	

<sup>1)</sup> PL80A.

### WL18-3 Ex

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: autocollimation

• Switching mode: light/dark-switching

• Type of light: visible red light

• Polarisation filter: 🗸

• Connection: cable with connector M12, 4-pin 0.29 m PVC

Sensing range max. 1)	Light spot size (distance)	Output type	Adjustment	Hazardous area category	Connection diagram	Model name	Part no.
0 m 7 m	Ø 40 mm (2 m)	PNP	Potentiometer, 1 turn	3D, 3G	Cd-083	WL18X-3P930	1029902

<sup>1)</sup> PL80A.

# WS/WE18-3

• Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching


Type of light	Sensing range max.	Light spot size (distance)	Output type	Adjustment	Connection	Connection diagram	Model name	Part no.			
			Potentiometer, 1 turn	Cable, 4-wire 2 m PVC	Cd-074	WS/WE18-3P130	1025922				
		PNP		Connector M12, 4-pin	Cd-072	WS/WE18-3P430	1025923				
Visible red light	0 m 20 m	Ø 450 mm (15 m)	~				I carri	Cubic connector, 6-pin	Cd-075	WS/WE18-3P630	1025924
rod light			NPN	Potentiometer, 1 turn	Cable, 4-wire 2 m PVC	Cd-074	WS/WE18-3N130	1025925			
			INPIN		Cubic connector, 6-pin	Cd-075	WS/WE18-3N630	1025926			
Infrared	0 m 20 m	Ø 950 mm	PNP	Potentiometer,	Cable, 4-wire 2 m PVC	Cd-074	WS/WE18-3P110	1025928			
light	0 111 20 111	(15 m)		1 turn	Connector M12, 4-pin	Cd-072	WS/WE18-3P410	1025927			




# **Dimensional drawings**

Dimensions in mm (inch)


### WT18-3, potentiometer







- $\ensuremath{\text{\textcircled{1}}}$  Standard direction of the material being detected
- 2 Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Mounting hole ø 4.1 mm
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Status indicator LED green: power on
- 7 Sensing range adjustment: potentiometer, 4-turn
- ® Connector M12, 4-pin or 2 m cable or cubic plug, 6-pin

### WTB18-3, double teach-in button








- ① Standard direction of the material being detected
- 2 Center of optical axis, sender
- 3 Center of optical axis, receiver
- 4 Mounting hole ø 4.1 mm
- 3 Status indicator LED, yellow: Status of received light beam
- **6** Status indicator LED green: power on
- 7 Sensing range adjustment: double teach-in button
- ® Connector M12, 4-pin or 2 m cable

G


#### WT18-3 Ex



- $\textcircled{1} \ \mathsf{LED} \ \mathsf{indicator}$
- ② Sensing range adjustment
- 3 Center of optical axis, sender
- ④ Center of optical axis, receiver
- ⑤ Mounting hole ø 4.1 mm
- 6 Connection


## WL18-3, WS/WE18-3





- $\ensuremath{\ensuremath{\mathbb{O}}}$  Center of optical axis
- 3 Status indicator LED, yellow: Status of received light beam
- ④ Status indicator LED green: power on
- ⑤ Sensitivity control; Potentiometer 270° on WE
- © Connector M12, 4-pin or 2 m cable or cubic plug, 6-pin


### WL18-3 Ex



- ① LED indicator
- ② Sensing range adjustment
- 3 Center of optical axis, sender
- 4 Mounting hole ø 4.1 mm
- © Connection


# **Adjustments**

### Potentiometer




① Sensing range adjustment: potentiometer, 4-turn

# Double teach-in button



① Sensing range adjustment: double teach-in button

# Single teach-in button




① Teach-in button



## **Characteristic curves**


### Black-white shift

### WT18-3, red light




- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

### WT18-3 (Ex), infraret, 1,000 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

### WT18-3, infrared, 700 mm




- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission




## Operating reserve

### WL18-3, WL18-3 Ex




- ① PL80A
- ② C110A
- ⑤ PL30A
- 7 Reflective tape Diamond Grade

### WS/WE18-3



# **Bar diagrams**


### WT18-3, red light



### Sensing range

- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

### WT18-3, infrared, 700 mm




### Sensing range

- ① Sensing range on black, 6 % remission
- 3 Sensing range on white, 90 % remission

G


### WT18-3 (Ex), infrared, 1,000 mm




Sensing range

- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

## WS/WE18-3



WL18-3, WL18-3 Ex



Sensing range


Sensing range max.

- ① PL80A
- ② C110A
- ③ PL50A
- 4 PL40A
- ⑤ PL30A
- **6** PL20A
- Reflective tape Diamond Grade

W18-3


# **Connection diagram**


### Cd-072




- ① Sender
- 2 Receiver


### Cd-075





# Cd-074






- ① Sender
- 2 Receiver

### Cd-083


$$\begin{array}{c|c} & brn & 1 \\ \hline & brn & 2 \\ \hline & blu & 3 \\ \hline & blk & 4 \\ \hline & Q \\ \end{array}$$


### Cd-094



- ① Sender
- 2 Receiver

### Cd-102





### Cd-178

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
 & \text{blu} & 2 \\
 & & 3 \\
 & & 3 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1 \\
 & & 1$$

# **Recommended accessories**

# Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Charl sine costed	Mounting bracket	BEF-WN-W14	2019084
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W18	2009317

# Plug connectors and cables

## Connecting cable (female connector-open)

Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector, M12, 4-pin, angled	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
		ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
1	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
9	Zinc plated steel	Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
	(sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Device protection (mechanical)

# Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (protective hous-	Duck sking have in a few points and a larger	BEF-SG-W14	2058124
1	ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601

# Reflectors

## Angular


Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
, n	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549







# Sturdiness is their strength: SICK's compact sensors

The harsh climate of a port, the high temperature of a steel mill, or a through-put-optimized logistics center: the challenge for sensors is precise and reliable functioning even under the least favorable conditions. This is achieved with the latest PinPoint LEDs, intelligent ASIC,  $\mu$ C and IO-Link technology together with rugged plastic or metal housings. An extensive range of specialized accessories ensures broader application options including even the most extreme cases.

### Your benefits

- The large sensing range and high operating reserves ensure a high level of reliability during use
- Extremely resistant to vibrations and immune to ambient conditions
- Reliable operation in ambient light, with optical reflections, and when devices are mounted opposite one another
- Reduces setup costs, e.g., in case of format adjustment using an IO-Link sensor communication interface
- PinPoint technology can replace laser photoelectric proximity sensors in some applications, eliminating the need for laser safety measures, and the service life of the PinPoint LED is double that of conventional laser diodes





# **Compact photoelectric sensors**

Product selection		
W23-2		W27-3 Ex
W24-2		W250-2
W24-2 Ex		W280-2
W27-2 Laser		W280L-2 Long Range
W27-3		W2000

# **Overview of compact photoelectric sensors**

	Housing properties				Sensor properties									
	Materia	<u> </u>		Enclosu	ure rating	ξ								
	Plastic	Metal	Explosion protection housing	99 dI	IP 67	₩ 969 К	Photoelectric proximity sensor	Energetic	Background suppres- sion	Photoelectric retro-reflective sensor	Standard optics	Through-beam photoelectric sensor	AC/DC	
W23														
W23-2	•							•						
W24														
W24-2														
W24-2 Ex	•		•		•									
W27														
W27-2 Laser	•				•									
W27-3					•									
W27-3 Ex					•									
W250														
W250-2														
W280														
W280-2				•			•	•						
W280L-2 Long Range NEW	•				•		•							
W2000								•						



Optical propert	ies				Special applica	ations		Page
Type of light/Li	pe of light/Light sender							
LED infrared light	LED red light	Red laser light 🖈	PinPoint LED 🛧	SIRIC®	Detecting small objects	Detecting objects wrapped in film	Explosive areas	
5	3	ŭ	<u>r</u> 5	<u>r</u>	<u>0</u> 5	۵۶	ம	
			•			•		H-580
•	•			•				H-590
•	•			•			•	H-602
		•		•	•			H-610
•	•		•	•		•		H-616
•	•			•			•	H-632
	•							H-640
	_							
	•							H-654
		•			•			H-666
	•							H-672



# Photoelectric proximity sensors

	Maximum sensing range	Dimensions (W x H x D)	Page
W27-2 Laser	100 mm 800 mm	24.6 mm x 80 mm x 53.5 mm	H-610
W250-2	100 mm 1,000 mm	20 mm x 65 mm x 43.9 mm	H-640
W27-3 Ex	30 mm 1,600 mm	31.4 mm x 112.3 mm x 70.4 mm	H-632
W280-2	10 mm 2,000 mm	23.5 mm x 74.5 mm x 63 mm	H-654
W27-3	30 mm 2,000 mm	24.6 mm x 80.6 mm x 54 mm	H-616
W24-2 Ex	40 mm 2,000 mm	27 mm x 87.5 mm x 65 mm	H-602
W23-2	50 mm 2,300 mm	24.6 mm x 80.6 mm x 54 mm	H-580
W24-2	100 mm 2,500 mm	27 mm x 87.5 mm x 65 mm	H-590
W2000	0 mm 3,500 mm	45 mm x 73.7 mm x 48.6 mm	H-672
W280L-2 Long Range	200 mm 18,000 mm	23.5 mm x 76 mm x 55.8 mm	H-666

# Photoelectric retro-reflective sensors

	■ Maximum sensing range	Dimensions (W x H x D)	Page
W23-2	0.01 m 12 m	24.6 mm x 80.6 mm x 54 mm	H-580
W27-3 Ex	0.01 m 15 m	31.4 mm x 112.3 mm x 70.4 mm	H-632
W250-2	0.01 m 15 m	20 mm x 65 mm x 43.9 mm	H-640
W280-2	0.01 m 15 m	23.5 mm x 74.5 mm x 63 mm	H-654
W2000	0 m 15 m	45 mm x 73.7 mm x 48.6 mm	H-672
W27-3	0.1 m 19 m	24.6 mm x 80.6 mm x 54 mm	H-616
W24-2 Ex	0 m 22 m	27 mm x 87.5 mm x 65 mm	H-602
W24-2	0 m 22 m	27 mm x 87.5 mm x 65 mm	H-590

# Through-beam photoelectric sensors

	Maximum sensing range	Dimensions (W x H x D)	Page
W27-3	0 m 35 m	24.6 mm x 80.6 mm x 54 mm	H-616
W27-3 Ex	0 m 35 m	31.4 mm x 112.3 mm x 70.4 mm	H-632
W250-2	0 m 50 m	20 mm x 65 mm x 43.9 mm	H-640
W2000	0 m 50 m	45 mm x 73.7 mm x 48.6 mm	H-672
W24-2	0 m 60 m	27 mm x 87.5 mm x 65 mm	H-590
W280-2	0 m 60 m	23.5 mm x 74.5 mm x 63 mm	H-654





## **Product family overview**











Simple, economical and reliable


Long-range sensor with a metal housing for harsh environments

W24-2 Ex

W24-2 for use in Category 2G explosive environments (gas)

Lechical	l data	overview
ICCIIICA	uata	OVCIVICAN

Dimensions (W x H x D)	24.6 mm x 80.6 mm x 54 mm	27 mm x 87,5 mm x 65 mm	27 mm x 87.5 mm x 65 mm	
Sensing range max.				
Photoelectric proximity sensor	50 mm 2,300 mm	100 mm 2,500 mm	40 mm 2,000 mm	
Photoelectric retro-reflective	0.1 m 12 m	0 m 22 m	0 m 22 m	
sensor				
Through-beam photoelectric	-	0 m 60 m	-	
sensor				
Supply voltage	DC	DC, AC/DC	-	
Light source	LED/PinPoint LED	LED	LED	
Type of light	Visible red light/Infrared light	Visible red light/Infrared light	Visible red light/Infrared light	
Enclosure rating	IP 67	IP 67, IP 69K	IP 67	
Housing material	Plastic	Metal	Metal	
At a glance				



- · Photoelectric proximity sensors with background suppression
- · Intense red emitting LED with consistent light spot on PinPoint models
- · Retro-reflective versions provided with and without adjustment
- Teach-in pushbutton on energetic proximity versions for quick, repeatable commissioning
- Cable or M12 connection

→ H-580

- IP 69K-tested die-cast zinc housing
- Terminal chamber protected by the housing
- Immune to ambient light and crosstalk
- Selectable PNP/NPN, light/ dark output
- · Variants with DC voltage and universal AC/DC voltage with UL approval
- Optional test input, time delays, alarm output and front screen heating also available in high-power version.
- M12 or terminal chamber connection: both 90° rotatable

→ H-590

- Classification: EX II 2G Ex ia op is IIC T4 according to Directive 94/9/EC (ATEX)
- Corresponds to Category
- Output type: EN 60947-5-6 (NAMUR)
- M12 or terminal chamber connection: 90° rotatable
- Durable metal housing
- · Precise background suppression

→ H-602



**Detailed information** 



W27-2 Laser

Photoelectric proximity sensor with a small laser light spot and a large sensing range



Precise, durable and powerful solution for a wide range of applications



Ready-to-install sensors compliant with ATEX category 3G/3D

24.6 mm x 80 mm x 53.5 mm	24.6 mm x 80.6 mm x 54 mm	31.4 mm x 112.3 mm x 70.4 mm
100 mm 800 mm	30 mm 2,000 mm	30 mm 1,600 mm
-	0.1 m 19 m 0.1 m 3 m	0.1 m 15 m
-	0 m 35 m	0 m 35 m
DC	DC, AC/DC	-
Laser	LED/PinPoint LED	LED
Visible red light	Visible red light/Infrared light	Visible red light/Infrared light
IP 67	IP 65, IP 66, IP 67, IP 69K	IP 67
Plastic	Plastic	Plastic/Metal/Stainless steel
2 mm diameter light spot at a distance of 400 mm	<ul> <li>Intense visible red emitter LED with consistent light spot for PinPoint</li> </ul>	• Classification: EX II 3G EX nA op is IIB T4 Gc X, EX II 3D EX tc IIIB T135°C

- Precise adjustable background suppression
- · Visible red laser LED
- · Sensing range adjustment via potentiometer

→ H-610

• UL approval

- versions
- Long sensing ranges with IR LED achieve up to 2500 mm
- Precise background suppression for detection of multi-colored objects
- Universal DC or DC/AC supply voltage

→ H-616

• Operating temperature: -40 °C - +60 °C

- Dc IP67 X according to Directive 94/9/EC (ATEX)
- · Corresponds to category 3D/3G
- · Conform to standards and ready-toinstall: Sensor and additional protective housing (stainless steel 1.4301)
- Long sensing range with IR LED
- High level of operating reserve
- · Resistant to ambient light, optical reflections, and crosstalk from other photoelectric devices

→ H-632

## **Product family overview**







High performance in a compact housing with universal AC/DC voltage



Sensor kit with mounting bracket and reflector

		_
Tecnica	l data	overview

Dimensions (W x H x D)	20 mm x 65 mm x 43,9 mm 20 mm x 60 mm x 43,9 mm	23,5 mm x 74,5 mm x 63 mm	
Sensing range max.			
Photoelectric proximity sensor	100 mm 1.000 mm	10 mm 2.000 mm	
Photoelectric retro-reflective sensor	0,01 m 15 m	0,01 m 15 m	
Through-beam photoelectric sensor	0 m 50 m	0 m 60 m	
Supply voltage	DC, AC/DC	DC, AC	
Light source	BrightLight-LED	BrightLight-LED	
Type of light	Visible red light	Visible red light	
Enclosure rating	IP 67	IP 66, IP 67	
Housing material	Plastic	Plastic	
At a glance			

- · Highly visible red light spot thanks to the Bright Light LED
- Potentiometer for adjusting sening range
- Operating mode (light/dark) selectable via control wire
- Cable or rotatable M12 connector
- Versions for 10 30 V DC or 24 240 V DC/ 24 - 240 V AC voltage supply in compact design
- Stainless steel mounting bracket BEF-W250 included in delivery

- Highly visible red light spot thanks to the BrightLight LED
- Potentiometer for adjusting sensing range
- Light/dark switching (DC devices only)
- Rotatable connector, cable connection or terminal chamber
- Versions for 10 30 V DC or 24 240 V DC/AC voltage supply
- AC/DC (-2Hxxxx) devices are compliant with EN61000-6-3 (electromagnetic interference for "residential, commercial and light-industrial environments")
- · Stainless steel mounting bracket and P250 reflector (for WL280 only) are included in delivery

**Detailed information** → H-640 → H-654





#### W280L-2 Long Range

Laser class 1 photoelectric proximity sensors – great performance, simple operation



N2000

Power, flexibility and reliability for long-range applications  $% \left( 1\right) =\left( 1\right) \left( 1$ 

23,5 mm x 76 mm x 55,8 mm	45 mm x 73.7 mm x 48.6 mm
200 mm 18.000 mm	0 m 3.5 m
-	0 m 15 m
-	0 m 50 m
DC	DC / AC/DC
Laser	LED
Visible red light	Infrared light / visible red light
IP 67	IP 67, NEMA 6
Plastic	Plastic

- WTT280L-2: sensing range up to 4 m
- WLT280L-2: sensing range up to 18 m
- Complete background suppression: very small black/white shift, insensitive against reflections from the background (e.g. shiny metal, window, safety vest)
- Visible red class 1 laser light
- Version 1: with 1 x switching output and light/dark switch, version 2: with 2 x switching outputs and light/dark switch
- · Disable laser by wire
- Reliable detection also in very fast production processes thanks to the switching frequency of 1000 Hz

- · Rugged, plastic housing
- · Crosstalk and ambient light immunity
- Adjustable sensing range
- Signal strength indicator
- IP 67/NEMA 6 enclosure rating



→ H-666 → H-672











## **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-588

## **Product description**

The W23-2 family is widely used due its economical price structure and ease of installation. Standard sensor types as proximity and retro-reflective are offered in their simplified versions. The W23-2 type has become one of the most widely used photoelectric sensors, particularly in handling and warehouse systems. Users appreciate its three key qualities - simplicity, tamper-proofing and reliability.

This family also offers special versions, including a retro-reflective variant for detection of plastic wrapped pallets. Laser and PinPoint background suppression variants for detection of small targets further enhance the product offering. A wide range of accessories is available for mechanical and electrical integration in systems.

# At a glance

- Energetic photoelectric sensor with easy teach-in
- · Photoelectric proximity sensors with background suppression
- · Intense red emitting LED with consistent light spot on PinPoint models
- · Retro-reflective versions provided with and without adjustment
- Teach-in pushbutton on energetic proximity versions for quick, repeatable commissioning
- · Cable or M12 connection

## Your benefits

- Teach-in pushbutton option for quick commissioning
- Easy alignment with PinPoint LED and laser technology
- 360° LEDs provide device status indication from multiple angles

#### → www.mysick.com/en/W23-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

### **Features**

	WT23-2	WTE23-2	WL23-2
Sensor principle	Photoelectric proximity sensor		Photoelectric retro-reflective sensor
Detection principle	Background suppression	Energetic	Standard optics
Dimensions (W x H x D)	24.6 mm x 80.6 mm x 54 mm		
Housing design (light emission)	Rectangular		
Sensing range max.	50 mm 1,000 mm <sup>1)</sup> (depending on type)	50 mm 2,300 mm <sup>1)</sup>	0.1 m 12 m <sup>2)</sup> (depending on type)
Sensing range	100 mm 1,000 mm (depending on type)	30 mm 2,000 mm	0.3 m 9 m <sup>2)</sup> (depending on type)
Type of light	Infrared light/visible red light (depending on type)	Infrared light	Visible red light
Light source	LED 3)		LED <sup>3</sup> /PinPoint LED <sup>3</sup> (depending on type)
Wave length			
Infrared light	880 nm		-
Visible red light	660 nm	-	660 nm
Adjustment	Potentiometer	Single teach-in button	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	WT23-2	WTE23-2	WL23-2
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>		
Power consumption	$\leq$ 35 mA $^{3}$ / $\leq$ 30 mA $^{3}$ (depending on type)	≤ 35 mA <sup>3)</sup>	
Output type	PNP/NPN (depending on type)		
Output function	Complementary		
Switching mode	Light/dark-switching		
Signal voltage PNP HIGH/LOW	Approx. $V_S - 2.5 V / 0 V$		
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.5 V		
Output current I <sub>max.</sub>	≤ 100 mA		
Response time	≤ 2.5 ms <sup>4)</sup>		$\leq$ 2.5 ms $^{4}$ / $\leq$ 3.5 ms $^{4}$ ) (depending on type)
Switching frequency	200 Hz <sup>5)</sup>		200 Hz $^{5)}$ /± 150 Hz $^{5)}$ (depending on type)
Connection type	Cable, 2 m <sup>6)</sup> Male connector, M12 Cable with connector, M12, 27(depending on type)	0 mm <sup>6)</sup>	
Circuit protection	A 7), C 8), D 9)		
Protection class <sup>10)</sup>	II		
Weight			
Connector M12, 4-pin	100 g		
Cable with connector M12, 4-pin	120 g	-	120 g
Cable, 4-wire	-		180 g
Polarisation filter	-		✓



<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25  $^{\circ}$  C.

	WT23-2	WTE23-2	WL23-2
Housing material	ABS		
Optics material	PMMA		
Enclosure rating	IP 67		
Ambient operating temperature	-25 °C +60 °C		
Ambient storage temperature	-40 °C +70 °C		

 $<sup>^{1)}</sup>$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W23-2

#### WT23-2

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Switching mode: light/dark-switching

• Adjustment: potentiometer

Type of light	Light source	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.							
				DND	Compostor MAQ A min	Cd-083	WT23-2P2421	1027778							
Infrared light	LED	50 mm 1.000 mm	Ø 50 mm (800 mm)	~ ~ ~	~ ~ ~	(800 mm)	~ ~ ~	000 mm (800 mm)	~ ~ ~	9 30 111111		Connector Wi12, 4-pin	Cd-101	WT23-2K2421	1028068
B.i.c		2,000 11111							Connector M12, 4-pin	Cd-083	WT23-2N2421	1028073			
Visible		50 mm	Ø 30 mm		Connector M12, 4-pin	Cd-083	WT23-2P2441	1027779							
red light	LED	800 mm	(800 mm)	PNP	Cable with connector M12, 4-pin, 270 mm, PVC	Cd-083	WT23-2P3441	1028066							



#### WTE23-2

Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Type of light: visible red light

• Switching mode: light/dark-switching

• Adjustment: single teach-in button

Light source	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.
LED	50 mm	Ø 160 mm	PNP	Connector M12, 4-pin	Cd-083	WTE23-2P2412	1027781
LED	2,300 mm	(2,000 mm)	NPN	Connector M12, 4-pin	Cd-083	WTE23-2N2412	1027782

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)



 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>10)</sup> Reference voltage: 50 V DC.

#### WL23-2

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Type of light: visible red light
- Switching mode: light/dark-switching

Light source	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.
	0.1 m 10 m	Ø 45 mm (2.7 m)	PNP	Cable, 4-wire, 2 m, PVC	Cd-094	WL23-2P1130	1027784
				Connector M12, 4-pin	Cd-083	WL23-2P2430	1027785
LED				Cable with connector M12, 4-pin, 270 mm, PVC	Cd-083	WL23-2P3430	1027786
			NPN	Connector M12, 4-pin	Cd-083	WL23-2N2430	1027787
PinPoint LED	0.1 m 12 m	Ø 45 mm (2.7 m)	PNP	Connector M12, 4-pin	Cd-083	WL23-2P2460	1044165

<sup>1)</sup> PL80A.

### WL23-2, detecting objects wrapped in film

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Type of light: visible red light
- Switching mode: light/dark-switching


Light source	Sensing range max. 1)	Light spot size (distance)	_	Connection	Connection diagram	Туре	Part no.
LED	0.1 m 4 m	Ø 45 mm (2.7 m)	PNP	Connector M12, 4-pin	Cd-083	WL23-2P2430S01	1041159

<sup>1)</sup> PL80A.

# **Dimensional drawings**

Dimensions in mm (inch)


#### WT23-2, potentiometer



- ① Standard direction of the material being detected
- 2 Optical axis, sender
- 3 Optical axis, receiver
- 4 Mounting hole ø 5.2 mm
- ⑤ Status indicator LED green: power on
- **(6)** Status indicator LED, yellow: Status of received light beam
- 7 Sensing range adjustment: potentiometer



#### WTE23-2, single teach-in button



① Optical axis, sender

**4 5** 


 $\bigcirc$ 

6

23 (0.91)

- 2 Optical axis, receiver
- 3 Mounting hole ø 5.2 mm
- 4 Status indicator LED green: power on
- $\ensuremath{\mathfrak{D}}$  Status indicator LED, yellow: Status of received light beam
- **6** Adjustment sensing range: single teach button

### WL23-2





- ① Optical axis, sender
- 2 Optical axis, receiver
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam

# Adjustments

## Potentiometer

#### Single teach-in button





① Sensing range adjustment: potentiometer

① Adjustment sensing range: single teach button




### **Characteristic curves**

#### Black-white shift


#### WT23-2, infrared

% of sensing range



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


#### WT23-2, energetic



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WT23-2, redlight

% of sensing range




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission



#### Operating reserve

#### WL23-2


#### Operating reserve



- ① PL80A
- ② PL40A
- 3 C110A
- 4 PL20A

#### WL23-2, PinPoint


#### Operating reserve



- ① PL80A
- ② PL40A
- 3 C110A
- 4 PL20A


# **Bar diagrams**

#### WT23-2, infrared




- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

## WT23-2, redlight




- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### WT23-2, energetic



- 1 Sensing range on black, 6 % remission 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

# WL23-2



Operating range

Scanning range typ. max.

- ① PL80A
- ② PL40A
- 3 C110A
- 4 PL20A



#### WL23-2, PinPoint

1	0.1/ 0.3				9	12
2	0.1/ 0.3			7	10	
3	0.1/ 0.5			7		11
4	0.1/ 0.3	4	6			
(5)	0.1/ 0.3			7	10	
6	0.1/ 0.3 -1	.5 2.5				
(	) 2	2 4	1 (	60) (26	8 1	0 12

(6.56) (13.12) (19.69) (26.25) (32.81) (39.37)

Distance in m (feet)

Sensing range

Sensing range max.

① PL80A

② PL40A

3 C110A

4 PL20A

⑤ P250


6 Reflective tape Diamond Grade

# **Connection diagram**

#### Cd-083

#### Cd-094

#### Cd-101





# **Recommended accessories**

## Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
		Mounting bracket with hinged arm	BEF-WN-MULTI	2064469
	Steel, zinc coated	Mounting bracket	BEF-WN-W23	2019085
		Mounting bracket with hinged arm	BEF-WN-W27	2009122

# Plug connectors and cables

### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight		5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled		5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N04 for universal clamp bracket	BEF-KHS-N04	2051610

## Device protection (mechanical)

### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601
1	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240



## Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
0		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
8	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

### Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861













# **Product description**

The W24 features a rugged metal housing that has passed IP 69K testing, which ensures reliability in harsh industrial conditions. These sensors are highly resistant to ambient light and offer a very long sensing range with a high operating reserve. As a result, there are optional a standard front lens heating or a high-power front lens heating versions, similar to automotive rear window defrost, for use in environments with extreme temperatures fluctuation. An

alarm output option enables early detection of contamination, reducing downtime that results from contamination interruptions. Variants with DC voltage and universal voltage DC/AC and multiple connectivity options provide additional flexibility within the W24 family.

The sensors are conform with the 2G category for explosive zones, which enhances their range of applications even

## At a glance

- IP 69K-tested die-cast zinc housing
- Terminal chamber protected by the housing
- Immune to ambient light and cross-
- Selectable PNP/NPN, light/dark output
- · Variants with DC voltage and universal AC/DC voltage with UL approval
- · Optional test input, time delays, alarm output and front screen heating also available in high-power version.
- M12 or terminal chamber connection: both 90° rotatable

#### Your benefits

- Rugged metal housing that has passed IP 69K testing offers reliability and a long service life
- Immune to ambient light and crosstalk, which improves detection security
- · Long-range retro-reflective and through-beam versions have a very high operating reserve, which ensures reliable operation even when if sensor is contaminated
- · Ensuring reliable operation in environments with temperatures fluctuation due to standard or high-power front lens heating (prevention and reduction of condensation water on the front lens)
- Variants with DC voltage and universal AC/DC voltage provide installation flexibility

# **Additional information**

Detailed technical dataH-591
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-599

#### → www.mysick.com/en/W24-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

### **Features**

		DC		AC/DC			
	WT24-2	WL24-2	WS/WE24-2	WT24-2	WL24-2	WS/WE24-2	
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	
Detection principle	Background suppression	Standard optics	-	Background suppression	Standard optics	-	
Dimensions (W x H x D)	27 mm x 87.5	mm x 65 mm					
Housing design (light emission)	Rectangular						
Sensing range max.	$100 \text{ mm} \dots$ $2,500 \text{ mm}^{1)}$ (depending on type)	$0~\text{m}$ $22~\text{m}^{\ 2)}$	0 m 60 m	$100 \text{ mm} \dots$ $2,500 \text{ mm}^{1)}$ (depending on type)	0 m 22 m <sup>2)</sup>	0 m 60 m	
Sensing range	$100 \text{ mm} \dots$ $2,500 \text{ mm}^{1)}$ (depending on type)	$0~\text{m}$ $15~\text{m}^{\ 2)}$	0 m 50 m	100 mm 2,500 mm <sup>1)</sup> (depending on type)	0 m 15 m $^{2)}$	0 m 50 m	
Type of light	Infrared light/ Visible red light visible red light (depending on type)			Infrared light/ visible red light (depend- ing on type)	Visible red light		
Light source 3)	LED						
Angle of dispersion	-		Approx. 1°	-		Approx. 1°	
Adjustment	Potentiometer						
Time type	Switch on delay/time delay off						
Delay time	Adjustable via t	ime delay select	or switch: 0.5 s	10 s			
Alarm output	-/✔ (dependir	ng on type)					
Alarm output	-/ <b>v</b> (dependir	ng on type)					

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

		DC			AC/DC	
	WT24-2	WL24-2	WS/WE24-2	WT24-2	WL24-2	WS/WE24-2
Supply voltage	10 V DC 30 V	/ DC		12 V DC 240 V DC $^{\mbox{\tiny 1)}}/24$ V AC 240 V AC		
Ripple 3)	< 5 V <sub>pp</sub>			-		
Current consumption	$\leq$ 50 mA <sup>4)</sup>		-	-		
With dynamic front lense heating	$\leq$ 150 mA $^{4)}$					
Current consumption, sender	-		50 mA <sup>4)</sup>	-		
With dynamic front lense heating	-		150 mA 4)	-		
Current consumption, receiver	-		40 mA 4)	-		
With dynamic front lense heating	-		140 mA 4)	-		
Power consumption	-			< 2 VA		
Output type	PNP/NPN (sele	ctable via NPN/	PNP selector)	Relay, electrica	lly isolated 5)	
Output function	-			Change-over co	ntacts	
Switching mode	Light/dark-swit (selectable via	ching light/dark rotary	switch)	Light/dark-swite (selectable via	_	y switch)
Output current I <sub>max.</sub>	≤ 100 mA	-	≤ 100 mA	100 mA	-	
Switching current (switching voltage)	-			4 A (250 V AC)/	/4 A (24 V DC)	
Response time	$\leq$ 500 $\mu$ s <sup>6)</sup>			≤ 10 ms		
Switching frequency 7)	1,000 Hz			10 Hz		



 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\!_{A}}$  = +25 °C.

		DC			AC/DC	
	WT24-2	WL24-2	WS/WE24-2	WT24-2	WL24-2	WS/WE24-2
Angle of reception	-		Approx. 2.5°	-		Approx. 2.5°
Connection type	Male connector (depending on	r, M12 <sup>8)/</sup> Termina type)	als with gland <sup>8)</sup>	Terminals with	gland <sup>8)</sup>	
Circuit protection	A $^{9)}$ , C $^{10)}$ , D $^{11)}$			A $^{9)}$ , C $^{10)}$		
Protection class	II <sup>12)</sup>			II <sup>13)</sup>		
Weight	330 g		660 g	330 g		660 g
Polarisation filter	-	<b>✓</b>	-	-	<b>✓</b>	-
Front screen heating	-/✔ (dependir	ng on type)				
Housing material	Zinc diecast					
Optics material	PMMA, glass (	depending on ty	pe)	PMMA		
Enclosure rating	IP 69K/IP 67 (	depending on ty	pe)	IP 69K		
Usage category	-			AC-15, DC-13,	according to EN	60947-1
Test input sender off	TE to 0 V			-		
Ambient operating temperature	-40 °C +60	°C				
Ambient storage temperature	-40 °C +75	°C				

 $<sup>^{1)}</sup>$  Limit values, operation in short-circuit protected network max. 8 A.

Other models available at www.mysick.com/en/W24-2

## WT24-2, DC

Sensor principle: photoelectric proximity sensorDetection principle: background suppression

Light source: LEDOutput type: NPN, PNP

• Switching mode: light/dark-switching

• Adjustment: potentiometer

Type of light	Sensing range max. 1)	Light spot size (distance)	Connection	Alarm output	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.
			O		-	-	Cd-117	WT24-2B410	1016933
		Ø 80 mm	Connector M12, 4-pin	-	<b>✓</b> 2)	~	Cd-117	WT24-2B420	1017885
Infrared	100 mm		Connector M12, 5-pin	~	-	-	Cd-150	WT24-2V510	1017855
light 2,500 mm	(2,500 mm)			-	-	Cd-120	WT24-2B210	1016931	
			Terminal connection with M16 gland	_	~	~	Cd-120	WT24-2B220	1017882
					<b>✓</b> 2)	~	Cd-121	WT24-2V220	1017886
			Connector M12, 4-pin	-	-	-	Cd-117	WT24-2B440	1016934
			Connector M40 E nin	<b>/</b>	-	-	Cd-150	WT24-2V540	1017888
Visible	100 mm	Ø 40 mm	Connector M12, 5-pin	•	<b>✓</b> 3)	~	Cd-150	WT24-2V550S12	1019468
	1,200 mm	(1,200 mm)			-	-	Cd-120	WT24-2B240	1017813
			Terminal connection with M16 gland	-	~	~	Cd-120	WT24-2B250	1017883
			20 glaria	~	<b>✓</b> 2)	<b>/</b>	Cd-121	WT24-2V250	1017887

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)



<sup>&</sup>lt;sup>2)</sup> +- 10 %.

 $<sup>^{\</sup>rm 3)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>4)</sup> Without load.

<sup>&</sup>lt;sup>5)</sup> Provide suitable spark suppression for inductive or capacitive loads.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{8)}</sup>$  Connection rotable by 90  $^{\circ}$  .

 $<sup>^{9)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> C = interference suppression.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>&</sup>lt;sup>12)</sup> Reference voltage: 50 V DC. <sup>13)</sup> Rated voltage: 250 V AC/DC.

**Ordering information** 

 $<sup>^{2)}</sup>$  Static, low heat output, use in +5  $^{\circ}$  C ... +15  $^{\circ}$  C.

<sup>&</sup>lt;sup>3)</sup> Dynamic, high heat output, application for quickly changing temperatures between -5° C ... +10° C, Front screen material: Glass.

### WL24-2, DC

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

Light source: LEDOutput type: NPN, PNP

• Switching mode: light/dark-switching

• Adjustment: potentiometer

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Connection	Alarm output	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.
			Connector M12, 4-pin	_	-	-	Cd-117	WL24-2B430	1017860
			Connector Wi12, 4-pin	-	<b>✓</b> 2)	~	Cd-117	WL24-2B440	1017879
				-	-	Cd-150	WL24-2V530	1017881	
			Connector M12, 5-pin	n 🗸	<b>✓</b> 2)	~	Cd-150	WL24-2V540	1018025
Visible red light	0 m 22 m	Ø 250 mm (15 mm)			<b>✓</b> 3)	-	Cd-150	WL24-2V530S04	1023550
6		(10)			-	-	Cd-120	WL24-2B230	1015852
			Terminal connection	-	<b>✓</b> 2)	~	Cd-120	WL24-2B240	1017859
			with M16 gland		-	-	Cd-121	WL24-2V230	1017880
			<b>~</b>	•	<b>✓</b> 2)	~	Cd-121	WL24-2V240	1018024

<sup>1)</sup> PL80A.

## WS/WE24-2, DC

• Sensor principle: through-beam photoelectric sensor

Light source: LEDOutput type: NPN, PNP

• Switching mode: light/dark-switching

• Adjustment: potentiometer

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Connection	Alarm output	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.
			Compostor M42 4 min		-	~	Cd-118	WS/WE24-2B430	1017853
			Connector M12, 4-pin	-	<b>✓</b> 1)	~	Cd-118	WS/WE24-2B440	1017875
	d 0 m 60 m		Connector M12, 5-pin		-	-	Cd-119	WS/WE24-2V530	1017877
Visible red				<b>/</b>	<b>✓</b> 2)	-	Cd-119	WS/WE24-2V530S01	1023549
			Terminal connection with M16 gland	-	-	~	Cd-097	WS/WE24-2B230	1017861
				~	-	-	Cd-097	WS/WE24-2V230	1017876
				-	<b>✓</b> 1)	~	Cd-097	WS/WE24-2B240	1017862

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Static, low heat output, use in +5  $^{\circ}$  C ... +15  $^{\circ}$  C.



<sup>&</sup>lt;sup>2)</sup> Static, low heat output, use in +5° C ... +15° C.

<sup>&</sup>lt;sup>3)</sup> Dynamic, high heat output, application for quickly changing temperatures between -5° C ... +10° C, Front screen material: Glass.

<sup>&</sup>lt;sup>2)</sup> Dynamic, high heat output, application for quickly changing temperatures between -5° C ... +10° C, Front screen material: Glass.

### WT24-2, AC/DC

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

Light source: LEDOutput type: relay

• Switching mode: light/dark-switching (Provide suitable spark suppression for inductive or capacitive loads.)

• Adjustment: potentiometer

Type of light	Sensing range max. 1)	Light spot size (distance)	Connection	Front screen heating	Time func- tions	Connection diagram	Туре	Part no.
Infrared	100 mm	Ø 80 mm	Terminal connection	-	-	Cd-167	WT24-2R210	1016932
light	2,500 mm	(2,500 mm)	with M16 gland	<b>✓</b> 2)	<b>✓</b>	Cd-167	WT24-2R220	1016854
Visible	100 mm	Ø 40 mm	Terminal connection	-	-	Cd-167	WT24-2R240	1017854
red light	1,200 mm	(1,200 mm)	with M16 gland	<b>✓</b> 2)	<b>V</b>	Cd-167	WT24-2R250	1016820

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WL24-2, AC/DC

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

Light source: LEDOutput type: relay

• Switching mode: light/dark-switching (Provide suitable spark suppression for inductive or capacitive loads.)

• Adjustment: potentiometer

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Connection	Front screen heating	Time func- tions	Connection diagram	Туре	Part no.
Visible red	0 m	Ø 250 mm	Terminal connection	-	-	Cd-167	WL24-2R230	1017857
light	22 m	(15 mm)	with M16 gland	<b>✓</b> 2)	<b>v</b>	Cd-167	WL24-2R240	1017858

<sup>&</sup>lt;sup>1)</sup> PL80A.

 $<sup>^{2)}</sup>$  Static, low heat output, use in +5  $^{\circ}$  C ... +15  $^{\circ}$  C.



### WS/WE24-2, AC/DC

• Sensor principle: through-beam photoelectric sensor

Light source: LEDOutput type: relay

· Switching mode: light/dark-switching (Provide suitable spark suppression for inductive or capacitive loads.)

• Adjustment: potentiometer

Type of light	Sensing range max.	Light spot size (distance)	Connection	Front screen heating	Time func- tions	Connection diagram	Туре	Part no.
Visible red	0 m	Ø 700 mm	Terminal connection	-	-	Cd-127	WS/WE24-2R230	1017863
light	60 m	(50 mm)	with M16 gland	<b>✓</b> 1)	~	Cd-127	WS/WE24-2R240	1017864


<sup>1)</sup> Static, low heat output, use in +5° C ... +15° C.

<sup>&</sup>lt;sup>2)</sup> Static, low heat output, use in +5° C ... +15° C.

# **Dimensional drawings**


Dimensions in mm (inch)

#### WT24-2




- ① Alignment sight
- ② LED signal strength indicator
- 3 Standard direction of the material being detected
- 4 Center of optical axis, sender
- ⑤ Centre of optical axis, receiver (close range)
- **(6)** Centre of optical axis, receiver (far range)
- 7 M5 threaded mounting hole, 6 mm deep
- ® M5 threaded mounting hole, through-hole
- $\ensuremath{\mathfrak{G}}$  M16 screw fixing and plug rotatable by 90°

#### WL24-2



- ① Alignment sight
- ② LED signal strength indicator
- 3 Center of optical axis, sender
- 4 Center of optical axis, receiver
- ⑤ M5 threaded mounting hole, 6 mm deep
- **⑥** M5 threaded mounting hole, through-hole
- 7 M16 screw fixing and plug rotatable by 90°

#### WS/WE24-2



 ${\bf \textcircled{1}} \ {\bf Alignment \ sight}$ 

6.5

87.5 (3.44)

(0.19)

11.8 (0.46)


М5

- ② LED signal strength indicator
- 3 Center of optical axis
- 4 M5 threaded mounting hole, 6 mm deep
- S M5 threaded mounting hole, through-hole
- 6 M16 screw fixing and plug rotatable by 90°




## **Adjustments**

# WT24-2, WL24-2, WS/WE24-2, DC




- ② LED signal strength indicator
- M Adjustment sensing range (WT) / sensitivity (WL, WS/WE)
- 1 Light/dark selector
- 2 NPN/ PNP selector

#### WT24-2, WL24-2, WS/WE24-2, AC/DC




- ② LED signal strength indicator
- Madjustment sensing range (WT) / sensitivity (WL, WS/WE)
- 1 Light/dark selector

#### WT24-2, WL24-2, WS/WE24-2, AC/DC, with time functions



- ② LED signal strength indicator
- ① Adjustment sensing range (WT) / sensitivity (WL, WS/WE)
- 1 Light/dark selector
- 2 Time control t<sub>2</sub>=OFF-delay
- B Time control  $t_1$ =ON-delay
- (4) Time delay selector switch

#### WT24-2, WL24-2, WS/WE24-2, DC, with time functions




- ② LED signal strength indicator
- 8 Sensitivity adjustment
- 9 Light/dark selector
- 10 NPN/ PNP selector
- 1 Time control t<sub>2</sub>=OFF-delay
- ② Time control t₁=ON-delay
- <sup>®</sup> Time delay selector switch

## **Characteristic curves**


#### Black-white shift

#### WT24-2, infrared light



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WT24-2, red light




- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission




### Operating reserve

#### WL24-2




- ① PL80A
- ② PL50A
- 3 PL40A4 PL30A
- ⑤ PL20A
- 6 Reflective tape Diamond Grade
- ⑦ C110A

#### WS/WE24-2




## **Bar diagrams**

### WT24-2, infrared light



- Sensing range
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission


### WT24-2, red light



- Sensing range
- $\ensuremath{\textcircled{1}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission



#### WL24-2



Sensing range

Sensing range max.

① PL80A

② PL50A


③ PL40A

4 PL30A

⑤ PL20A

**6** Reflective tape Diamond Grade

#### WS/WE24-2





Sensing range

Sensing range max.

# **Connection diagram**

#### Cd-097







#### Cd-117



② Receiver

#### Cd-118






① Sender

2 Receiver


#### Cd-119




① Sender

② Receiver


#### Cd-120




#### Cd-121




#### Cd-127






- ① Sender
- 2 Receiver

#### Cd-150



#### Cd-167



# **Recommended accessories**

## Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
6	Stainless steel	Mounting bracket, small	BEF-WK-W24	4027532
	Stainless steel (1.4301)	Mounting bracket	BEF-WN-W24	2015248

# П

## Plug connectors and cables

#### Connecting cable (female connector-open)

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Cable material	Enclosure rating	Connecting cable	Model name	Part no.
			PVC	IP 67	2 m, 4-wire	DOL-1204-G02M	6009382
	Female connector,	Cable, open con-	PVC	11 07	5 m, 4-wire	DOL-1204-G05M	6009866
	M12, 4-pin, straight	ductor heads	PUR, halo-	IP 65, IP 68, IP 69K	2 m, 4-wire	DOL-1204-G02MC	6025900
			gen-free		5 m, 4-wire	DOL-1204-G05MC	6025901
			PVC	IP 67	2 m, 4-wire	DOL-1204-W02M	6009383
	Female connector,	Cable, open con-	PVC	IP 67	5 m, 4-wire	DOL-1204-W05M	6009867
	M12, 4-pin, angled	ductor heads	PUR, halo-	IP 65, IP 68,	2 m, 4-wire	DOL-1204-W02MC	6025903
19			gen-free	IP 69K	5 m, 4-wire	DOL-1204-W05MC	6025904

Figure	Connection type head A	Connection type head B	Cable material	Enclosure rating	Connecting cable	Model name	Part no.
11			PVC	IP 67	2 m, 5-wire	DOL-1205-G02M	6008899
1.00	Female connector,	Cable, open con-	PVC	IF 07	5 m, 5-wire	DOL-1205-G05M	6009868
	M12, 5-pin, straight	ductor heads	PUR, halo-		2 m, 5-wire	DOL-1205-G02MC	6025906
1			gen-free		5 m, 5-wire	DOL-1205-G05MC	6025907
			PVC	IP 67	2 m, 5-wire	DOL-1205-W02M	6008900
	Female connector, M12, 5-pin, angled	Cable, open con-	PVC	11 07	5 m, 5-wire	DOL-1205-W05M	6009869
//		ductor heads	PUR, halo-	IP 65, IP 68,	2 m, 5-wire	DOL-1205-W02MC	6025909
19			gen-free	IP 69K	5 m, 5-wire	DOL-1205-W05MC	6025910

### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1204-W	6007303
	Female connector, M12, 5-pin, straight	Screw-type terminals	PBT	IP 67	DOS-1205-G	6009719
	Female connector, M12, 5-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1205-W	6009720

# Alignment aids

Figure	Description	Model name	Part no.
	Adapter for alignment aid AR60	Adapter AR60 for W24-2	4032976

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Device protection (mechanical)

### **Cooling elements**

Figure	Description	Model name	Part no.
1	Water cooling plate	BEF-KP-W24	2015071



### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Aluminum (anodised)	Dust protection tube, air-purged	OBS-W24	2015069
(1)	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240
	Aluminum (anodised)	Weather hood	OBW-W24	2015070
THE	Aluminum (anodised)	Weather hood	WSG1-01	1018470

## Reflectors

#### **Angular**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
, n		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

#### Reflective tape

Figure	Description 1)	Model name	Part no.
	Reflective tape "Diamond Grade", self-adhesive, customizable size by sheet, $74.9\ \text{cm}\ \text{x}$ 91.4 cm	REF-DG-K	4019634

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Customizable length by sheet. Width max. 74.9 cm, length max. 91.4 cm.

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

<sup>→</sup> For additional accessories, please see page L-861



# W24-2 for use in Category 2G explosive environments (gas)













The W24-2Ex features a rugged metal housing which ensures reliability in harsh industrial conditions. Special electronics allows longer sensing range despite the

limited factors of the norms for Category 2G (ATEX, explosive environments). The necessary switching amplifiers are also available.

#### At a glance

- Classification: EX II 2G Ex ia op is IIC T4 according to Directive 94/9/EC (ATEX)
- · Corresponds to Category 2G
- Output type: EN 60947-5-6 (NAMUR)
- M12 or terminal chamber connection: 90° rotatable
- · Durable metal housing
- · Precise background suppression

## **Your benefits**

- The W24-2Ex features a rugged metal housing that has been IP 69K tested which ensures reliability in harsh industrial conditions
- · Special electronics allows longer sensing range despite the limited factors of the norms for Category 2G (ATEX, explosive environments)
- Flexible installation due to 90° rotatable connector









#### **Additional information**

/ total to little little to little t
Detailed technical data H-603
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-608

→ www.mysick.com/en/W24-2\_Ex

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## **Detailed technical data**

#### **Features**

	WT24-2 Ex	WL24-2 Ex
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor
Detection principle	Background suppression	-
Dimensions (W x H x D)	27 mm x 87.5 mm x 65 mm	
Housing design (light emission)	Rectangular	
Sensing range max.	40 mm 2,000 mm <sup>1)</sup>	0 m 22 m <sup>2)</sup>
Sensing range	100 mm 2,000 mm <sup>1)</sup>	0 mm 15 mm <sup>2)</sup>
Type of light	Infrared light	Visible red light
Light source 3)	LED	
Light spot size (distance)	Ø 50 mm (2,000 mm)	Ø 250 mm (15 m)
Adjustment	Potentiometer	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

	WT24-2 Ex	WL24-2 Ex	
Supply voltage 1)	5 V DC 15.5 V DC		
Ripple <sup>2)</sup>	< 0.4 V <sub>pp</sub>		
Output type	NAMUR		
Switching mode	Light switching		
Response time 3)	≤ 10 ms		
Switching frequency 4)	50 Hz		
Connection type	Terminals with gland $^{5)}\!/\!$ Male connector, M12 $^{5)}$ (depending on type)		
Circuit protection	A 6), C 7)		
Protection class 8)	II		
Weight	330 g		
Polarisation filter	V		
Housing material	Zinc diecast		
Optics material	Glass		
Enclosure rating	IP 67		
EC Approval Certificate	PTB 03 ATEX 2105	PTB 08 ATEX 2029	
ATEX marking	II 2G Ex ia op is IIC T4 according to directive 94,	/9/EG (ATEX)	
Hazardous area category	2G		
Input voltage U <sub>i</sub> max. <sup>9)</sup>	≤ 15.5 V		
Input power P <sub>i</sub> max. 9)	≤ 100 mW		
Input current I <sub>i</sub> max. <sup>9)</sup>	≤ 53 mA		
Internal capacitance C <sub>i</sub> max. <sup>9)</sup>	80 nF		
Internal inductance L <sub>i</sub> max. <sup>9)</sup>	ОμΗ		
Ambient operating temperature	-20 °C +60 °C		
Ambient storage temperature	-25 °C +70 °C		

 $<sup>^{</sup>m 1)}$  Limit values, supply with switching amplifier EN2Ex (internal resistor approx. 1 kOhm)



<sup>2)</sup> PL80A

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25  $^{\circ}$  C.

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

 $<sup>^{\</sup>scriptscriptstyle{(3)}}$  Signal transit time with resistive load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  With light/dark ratio 1:1.

<sup>5)</sup> Connection rotable by 90°.

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

<sup>&</sup>lt;sup>8)</sup> Reference voltage: 50 V DC.

<sup>&</sup>lt;sup>9)</sup> For connection to a sperately certified intrinsically safe circuit only.

# **Ordering information**

Other models available at www.mysick.com/en/W24-2\_Ex

### WT24-2 Ex

Sensor principle: photoelectric proximity sensor

• Output type: NAMUR

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Connection	Connection diagram	Туре	Part no.
40 mm 2,000 mm	Ø 50 mm (2 000 mm)	Terminal connection with M16 gland	Cd-050	WT24-2X200	1041910
	2,000 mm)	Connector M12, 4-pin	Cd-122	WT24-2X400	1040722

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### WL24-2 Ex

• Sensor principle: photoelectric retro-reflective sensor

• Output type: NAMUR


Sensing range max. <sup>1)</sup>	Light spot size (distance)	Connection	Connection diagram	Туре	Part no.
0 m 22 m	Ø 250 mm (15 m)	Terminal connection with M16 gland	Cd-050	WL24-2X230	1026036
0 III 22 III	Ø 250 mm (15 m)	Connector M12, 4-pin	Cd-122	WL24-2X430	1026037

<sup>1)</sup> PL80A.

# **Dimensional drawings**

Dimensions in mm (inch)


#### WT24-2 EX





- ① Alignment sight
- ② LED signal strength indicator
- $\ensuremath{\mathfrak{G}}$  Standard direction of the material being detected
- ④ Center of optical axis, sender
- ⑤ Centre of optical axis, receiver (close range)
- **©** Centre of optical axis, receiver (far range)
- $\ensuremath{\mathfrak{D}}$  M5 threaded mounting hole, 6 mm deep
- ${\small \textbf{8} \ \text{M5} \ \text{threaded mounting hole, through-hole}}$
- 9 M16 screw fixing and plug rotatable by 90°



### WL24-2 EX








- ① Alignment sight
- ② LED signal strength indicator
- 3 Center of optical axis, sender
- ④ Center of optical axis, receiver
- ⑤ M5 threaded mounting hole, 6 mm deep
- **⑥** M5 threaded mounting hole, through-hole
- 7 M16 screw fixing rotatable by 90°


# **Adjustments**

### WT24-2 EX



- ② LED signal strength indicator
- 10 Sensing range adjustment

### WL24-2 EX




- ② LED signal strength indicator
- 8 Sensitivity adjustment



## **Characteristic curves**


#### Black-white shift

#### WT24-2 EX



#### Operating reserve


#### WL24-2



- ① PL80A
- ② PL50A
- ③ PL40A
- 4 PL30A ⑤ PL20A
- 6 Reflective tape Diamond Grade
- ⑦ C110A


# **Bar diagrams**

## WT24-2



- Sensing range
- \*) Lower bound of detection area depending on the adjusted sensing distance (see blind zone curve)
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### WL24-2



Sensing range

Sensing range max.

- ① PL80A
- ② PL50A
- ③ PL40A
- 4 PL30A
- ⑤ PL20A
- **6** Reflective tape Diamond Grade
- ⑦ C110A



# **Connection diagram**

# Cd-050 Cd-122 +8,2 V 4 not connected



## **Recommended accessories**

## Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting bracket, small	BEF-WK-W24	4027532
	Stainless steel (1.4301)	Mounting bracket	BEF-WN-W24	2015248

### Alignment aids

Figure	Description	Model name	Part no.
	Adapter for alignment aid AR60	Adapter AR60 for W24-2	4032976

#### Others

Figure	Supply voltage	Output function	Approvals	Model name	Part no.
	AC/DC 24 V 230 V, 1.3 W	2 channels with invertible SPDT relay	II (1) G [Ex ia] IIC II (1) D [Ex iaD] II (3) G Ex nAC [ia] IIC T4 X	EN2-2EX-1	6041096
	DC 19.2 V 30 V, 1 W	2 channels with invertible NO relay	II (1) GD [Ex ia] IIC, IIB II (3) G Ex nAC II T4 X	EN2-2EX-3	6041095

### Universal bar clamp systems



## Device protection (mechanical)

### **Cooling elements**

Figure	Description	Model name	Part no.
	Water cooling plate	BEF-KP-W24	2015071



### Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Aluminum (ano- dised)	Dust protection tube, air-purged	OBS-W24	2015069
	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240
	Aluminum (ano- dised)	Weather hood	OBW-W24	2015070
ME !	Aluminum (ano- dised)	Weather hood	WSG1-01	1018470

## Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

<sup>→</sup> For additional accessories, please see page L-861













The WT27L-2 Laser photoelectric sensor is ideal for precisely detecting small objects from long distances. These sensors feature crosstalk immunity, background suppression and a laser light source.

## At a glance

- 2 mm diameter light spot at a distance of 400 mm
- · Precise adjustable background suppression
- · Visible red laser LED
- · Sensing range adjustment via potentiometer
- UL approval

### Your benefits

· Precise detection of very small parts up to a distance of 400 mm due to 2 mm light spot

- Highly visible red laser provides quick and easy alignment
- Durable design provides high resistance to vibration



## **Additional information**

Detailed technical data
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-614

→ www.mysick.com/en/W27-2\_Laser

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## **Detailed technical data**

#### **Features**

Sensor principle	Photoelectric proximity sensor
Detection principle	Background suppression
Dimensions (W x H x D)	24.6 mm x 80 mm x 53.5 mm
Housing design (light emission)	Rectangular
Sensing range max. 1)	100 mm 800 mm
Sensing range	100 mm 800 mm
Type of light	Visible red light
Light source 2)	Laser
Light spot size (distance)	Ø 2 mm (400 mm)
Laser class 3)	1/2 (depending on type)
Adjustment	Potentiometer

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### Mechanics/electronics

10 V DC 30 V DC
≤ 5 %
≤ 35 mA
PNP/NPN (depending on type)
Complementary
Light/dark-switching
≤ 100 mA
< 25 ms <sup>4)</sup> < 500 µs <sup>4)</sup> (depending on type)
50 Hz
1,000 Hz
Male connector
A <sup>6)</sup> , C <sup>7)</sup> , D <sup>8)</sup>
II
100 g
ABS
IP 67
-10 °C +45 °C
-10 °C +75 °C

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.



 $<sup>^{2)}</sup>$  Average service life 50,000 h at T  $_{\!A}$  = +25  $^{\circ}$  C.

<sup>&</sup>lt;sup>3)</sup> (EN 60825-1), low power. Eyes normally protected by averting reaction and eyelid closing reflex.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

<sup>8)</sup> D = outputs overcurrent and short-circuit protected.

<sup>9)</sup> Reference voltage: 50 V DC.

## **Ordering information**

Other models available at www.mysick.com/en/W27-2\_Laser

## WT27-2 Laser

- Sensor principle: photoelectric proximity sensor
- Light spot size (distance): Ø 2 mm (400 mm)
- Connection: Connector M12, 4-pin


Sensing range max. 1)	Laser class	Response time <sup>2)</sup>	Switching frequen- cy <sup>3)</sup>	Output type	Connection diagram	Туре	Part no.
100 mm 800 mm	1	< 25 ms	50 Hz	PNP	Cd-083	WT27K-2F430	1059239
	2	< F00	1 000 11-	PNP	Cd-083	WT27L-2F430	1016019
	2 < 500 μs		1,000 Hz	NPN	Cd-083	WT27L-2N430	1026165

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## **Dimensional drawings**

Dimensions in mm (inch)


- ① Standard direction
- ② LED signal strength indicator
- 3 Optical axis sender
- 4 Optical axis, receiver
- ⑤ Mounting hole, Ø 5.2 mm
- 6 Sensing range adjustment: potentiometer





## **Adjustments**


#### Potentiometer




<sup>&</sup>lt;sup>2)</sup> Signal transit time with resistive load.

<sup>3)</sup> With light/dark ratio 1:1.

## **Characteristic curves**



## **Bar diagrams**



- Sensing range
- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

## **Connection diagram**

## Cd-083

$$\begin{array}{c|cccc} & & & & & & & & & \\ & & & & & & & & \\ & & & & & & & \\ & & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & \\ & & & \\ & \\ & & \\ & \\ & \\ & \\ & & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ & \\ &$$



## **Recommended accessories**

## Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
		Mounting bracket with hinged arm	BEF-WN-MULTI	2064469
	Steel, zinc coated	Mounting bracket	BEF-WN-W23	2019085
		Mounting bracket with hinged arm	BEF-WN-W27	2009122

## Plug connectors and cables

## Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12 4-nin angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

## Alignment aids

Figure	Description	Model name	Part no.
	Laser alignment aid for various sensors, laser class 2 (IEC 60825): Never look into the beam.	AR60	1015741

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N04 for universal clamp bracket	BEF-KHS-N04	2051610

## Device protection (mechanical)

## Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective housing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601
13	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240

→ For additional accessories, please see page L-861

















## **Additional information**

Detailed technical dataH-617
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-628



## **Product description**

The W27 family is designed for harsh industrial environments where it copes easily with heavy vibrations, shocks and extreme temperature fluctuations. The photoelectric proximity sensor is a leader in its class, especially through its reliable detection at long ranges. A sensor with PinPoint LED or a laser photoelectric proximity sensor is available for detection of small targets. The retro-reflective and through-beam versions reduce downtime due to high operating reserves. A diverse range of features further enhance application-specific functionality including, Teach or potentiometer adjustment, time delays, front lens heating, ASi, and universal voltage DC or AC/DC.

## At a glance

- · Intense visible red emitter LED with consistent light spot for PinPoint versions
- Long sensing ranges with IR LED achieve up to 2500 mm
- Precise background suppression for detection of multi-colored objects
- Universal DC or DC/AC supply voltage
- Operating temperature: -40 °C -+60 °C

#### Your benefits

- · Quick and easy commissioning due to a highly visible red PinPoint LED
- PinPoint technology can replace laser photoelectric proximity sensors in some applications. No laser safety regulations and a longer operating life due to PinPoint technology
- Resistant to ambient light, optical reflections, and crosstalk from other photoelectric devices
- · Less contamination due to high operating reserves, reducing downtime
- · Resistant to vibrations, reducing downtime
- · Operation in harsh environments with temperatures as low as -40 °C
- · Quick and easy configuration

#### www.mysick.com/en/W27-3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## **Detailed technical data**

## **Features**

		DC			AC/DC	
	WTB27-3	WL27-3	WSE27-3	WTB27-3	WL27-3	WSE27-3
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Standard optics	-	Background suppression	Standard optics	-
Dimensions (W x H x D)	24.6 mm x 80.	6 mm x 54 mm				
Housing design (light emission)	Rectangular					
Sensing range max.	30 mm 2,000 mm <sup>1)</sup> (depending on type)	0.1 m 19 m <sup>2)</sup> (depending on type)	0 m 35 m	30 mm 1,600 mm <sup>1)</sup> (depending on type)	0.1 m 15 m <sup>2)</sup>	0 m 35 m
Sensing range	100 mm 2,000 mm (depending on type)	0.1 m 14 m <sup>2)</sup> (depending on type)	0 m 25 m	100 mm 1,600 mm (depending on type)	0.1 m 11 m <sup>2)</sup>	0 m 25 m
Type of light	Infrared light/v	isible red light (d	epending on typ	e)		
Light source	LED 3)/PinPoint	LED 3) (dependi	ng on type)			
Wave length						
Infrared light	880 nm		-	880 nm	_	
Visible red light	660 nm		645 nm	660 nm		645 nm
Adjustment	Potentiometer Double teach- in button (depending on type)	Potentiometer				
Time type	Switch on delay/Time delay off/Switch on delay and time delay off					
Delay time	Adjustable via to 0.02 s 0.5 s/	time delay select /0.5 s 10 s	or switch:	Adjustable via time delay selector switch: 0.5 s 10 s		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	DC				AC/DC	
	WTB27-3	WL27-3	WSE27-3	WTB27-3	WL27-3	WSE27-3
Supply voltage	10 V DC 30 V DC <sup>1)</sup>	24 V AC/DC 240 V AC/ DC <sup>2)</sup>	10 V DC 30 V DC <sup>1)</sup>	24 V AC/DC 240 V AC/ DC <sup>2)</sup>	10 V DC 30 V DC <sup>1)</sup>	24 V AC/DC 240 V AC/ DC <sup>2)</sup>
Ripple 3)	≤ 5 V <sub>SS</sub>			-		
Current consumption	≤ 35 mA ≤ 5	5 mA <sup>4)</sup>				
Current consumption, sender	-		35 mA 50 mA <sup>4)</sup>	-		
Current consumption, receiver	-		20 mA <sup>4)</sup> 35 mA <sup>4)</sup>	-		
Power consumption	-			≤ 2,5 VA	≤ 2,5 VA	≤ 5,5 VA
Output type	PNP / NPN (de	epending on type	)	Relay, electrica Relay, galvanica (depending on	ally isolated <sup>6)</sup>	Relay, galvanically isolated <sup>6)</sup>
Output function	Complementary			Change-over co	ntacts	
Switching mode	Light/dark-switching / Light switching (depending on type)			Light/dark-switching <sup>5)</sup> /Light switching <sup>6)</sup> (depending on type)		
Switching mode selector	-			Selectable via t	ime delay selec	tor switch



<sup>2)</sup> PL80A

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	DC			AC/DC			
	WTB27-3	WL27-3	WSE27-3	WTB27-3	WL27-3	WSE27-3	
Signal voltage PNP HIGH/LOW	Approx. V <sub>S</sub> - 2.5 V / 0 V			-			
Signal voltage NPN HIGH/LOW	Approx. V <sub>S</sub> / < 2	2.5 V		_			
Output current I <sub>max.</sub>	≤ 100 mA			-			
Switching current (switching voltage)	-			3 A (250 V AC) 0.11 A (250 V			
Response time	$\leq$ 1.5 ms $^{7)}$ $\leq$ 1.9 ms $^{8)}$ (depending on type)	$\leq$ 500 $\mu$ s <sup>7)</sup> $\leq$ 2.5 ms <sup>7)</sup> (depending on type)	≤ 500 µs <sup>7)</sup>	≤ 10 ms			
Switching frequency	350 Hz <sup>9), 10)</sup>	1,000 Hz <sup>9)</sup> ± 200 Hz <sup>9)</sup> (depending on type)	1,000 Hz <sup>9)</sup>	10 Hz <sup>9)</sup>			
Angle of reception	-		Approx. 3°	-		Approx. 3°	
Connection type		Male connector, M12 <sup>11)</sup> (depend		Male connector Q6/Cable, 2 m <sup>11)</sup> (depending on type)			
Circuit protection	A <sup>12)</sup> , B <sup>13)</sup> , C <sup>14)</sup>			A <sup>12)</sup> , C <sup>14)</sup>			
Protection class	15)			<sup>16)</sup>			
Weight							
Connector M12	100 g		200 g	-			
Connector Q6	100 g		200 g	120 g		240 g	
Cable	180 g/300 g (depending on type)	180 g	200 g/360 g (depending on type)	180 g		-	
Cable with connector	120 g		-	-			
Polarisation filter	-	√/- (depending on type)	-		•	-	
Front screen heating	-/✔ (dependir	ng on type)					
Housing material	ABS						
Optics material	PMMA						
Enclosure rating	IP 65, IP 66, IP 67, IP 69K (depending on type)			IP 65, IP 66, IP 65, IP 67 IP 67(depending on type)  IP 65, IP 67 IP 65, IP 67 IP 65, IP 67 IP 65			
Usage category	-			AC-15, DC-13,	according to EN	60947-1	
Test input sender off	TE to $V_{\rm S}$ / TE to	0 V (depending	on type)	-			
Ambient operating temperature	-40 °C +60 °C			-40 °C +60	°C 17)		
Ambient storage temperature	-40 °C +75 °C						



<sup>&</sup>lt;sup>2)</sup> +- 10 %.



 $<sup>^{\</sup>rm 3)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>4)</sup> Without load.

<sup>&</sup>lt;sup>5)</sup> Provide suitable spark suppression for inductive or capacitive loads. Relay contacts are separated from the power supply by a basic isolation of 3 mm. Depending on the application, additional isolation might have to be applied in the user's circuit.

<sup>&</sup>lt;sup>6)</sup> Provide suitable spark suppression for inductive or capacitive loads.

<sup>7)</sup> Signal transit time with resistive load.

<sup>8)</sup> Signal transit time with resistive load in switching mode. Different values possible in COM2 mode.

<sup>9)</sup> With light/dark ratio 1:1.

 $<sup>^{10)}</sup>$  With light/dark ratio 1.1 in switching mode. Different values possible in COM2 mode.

 $<sup>^{11)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{12)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

 $<sup>^{13)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>14)</sup> C = interference suppression.

<sup>15)</sup> Reference voltage: 50 V DC.

<sup>&</sup>lt;sup>16)</sup> Reference voltage: 250 V AC.

<sup>&</sup>lt;sup>17)</sup> UL: 0 °C ... +60 °C.

## **Ordering information**

Other models available at www.mysick.com/en/W27-3

## WTB27-3, DC, infrared light

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Type of light: infrared light

• Switching mode: light/dark-switching

Sensing range max. 1)	Light spot size (dis- tance)	Out- put type	Adjustment	Connection	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.				
				Cable, 4-wire, 2 m	-	-	Cd-094	WTB27-3P1111	1027752				
				Cable, 4-wire, 5 m	-	-	Cd-094	WTB27-3P1211	1028065				
					-	-	Cd-083	WTB27-3P2411	1025994				
			Potentiometer	Connector M12, 4-pin	-	~	Cd-083	WTB27-3F2411	1027753				
		•			~	-	Cd-083	WTB27-3P2421	1027754				
				Connector Q6, 6-pin, DC-coding	-	~	Cd-178	WTB27-3F2611	1027756				
30 mm 1,600 mm	Ø 25 mm (800 mm)								Cable with connector M12, 4-pin, 270 mm	-	-	Cd-083	WTB27-3P3411
_, -,	(,		Double teach-	Cable, 4-wire, 2 m	-	-	Cd-094	WTB27-3P1113	1027759				
			in button	Connector M12, 4-pin	-	-	Cd-083	WTB27-3P2413	1027760				
				Cable, 4-wire, 2 m	-	-	Cd-094	WTB27-3N1111	1044855				
			Potentiometer	Connector M12, 4-pin	-	~	Cd-083	WTB27-3E2411	1027755				
		NPN		Connector Q6, 6-pin, DC-coding	-	~	Cd-178	WTB27-3E2611	1027757				
				Double teach- in button	Connector M12, 4-pin	-	-	Cd-083	WTB27-3N2413	1027761			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WTB27-3, DC, visible red light

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Type of light: visible red light
- Switching mode: light/dark-switching
- Front screen heating: -

Sensing range max. 1)	Light spot size (dis- tance)	Out- put type	Adjustment	Connection	Time functions	Con- nection diagram	Туре	Part no.			
				Connector M12, 4-pin	-	Cd-083	WTB27-3P2441	1027744			
			Potentiometer	Connector Q6, 6-pin, DC-coding	<b>✓</b>	Cd-178	WTB27-3F2641	1027746			
30 mm 1,100 mm	Ø 15 mm (500 mm)		PNP	PNP	PNP		Cable with connector M12, 4-pin, 270 mm, PVC	-	Cd-083	WTB27-3P3441	1029082
_,	(,							Double teach- in button	Connector M12, 4-pin	-	Cd-083
		NPN	Potentiometer	Connector Q6, 6-pin, DC-coding	V	Cd-178	WTB27-3E2641	1027747			
		Ø 12 mm PNP	Potentiometer	Connector M12, 4-pin	-	Cd-083	WTB27-3P2461	1044163			
	Ø 12 mm (800 mm)		Potentiometer	Cable with connector M12, 4-pin	-	Cd-083	WTB27-3P3461	1048546			
	(500 11111)	NPN	Potentiometer	Cable, 4-wire, 2 m, PVC	-	Cd-094	WTB27-3N1161	1051644			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



## WL27-3, DC, visible red light

• Sensor principle: photoelectric retro-reflective sensor

• Type of light: visible red light

Sensing range max. 1)	Light spot size (dis- tance)	Out- put type	Switch- ing mode	Adjustment	Connection	Time func- tions	Con- nection diagram	Туре	Part no.											
					Cable, 4-wire, 2 m	-	Cd-094	WL27-3P1131	1027768											
					Commontos MAC A min		04 000	WL27-3P2431	1027982											
				Potentiom-	Connector M12, 4-pin	_	Cd-083	WL27-3P2451	1027770											
			Light/	eter	Cable with connector M12, 4-pin, 270 mm	-	Cd-083	WL27-3P3431	1029081											
0.1 m	Ø 220 mm (10 m)	PNP	dark- switching		Connector Q6, 6-pin, DC-cod- ing	•	Cd-178	WL27-3F2631	1027772											
15 m				-	Connector M12 4 nin		Cd-083	WL27-3P2430	1027769											
					Connector M12, 4-pin	_	Ca-083	WL27-3P2450	1027771											
		PNIP	NPN	NPN	NPN	NPN	NPN	NPN	NPN	NPN	NPN					Connector M12, 4-pin	-	Cd-101	WL27-3K2430	1028069
																Light switching	-	Connector M12, 4-pin	-	Cd-104
												Light/ dark- switching	Potentiom- eter	Connector Q6, 6-pin, DC-cod- ing	•	Cd-178	WL27-3E2631	1027773		
0.1 m 19 m	Ø 60 mm		Light/	+	Cable with connector M12, 4-pin, 270 mm	-	Cd-083	WL27-3P3460	1047955											
	(6 m)		PNP dark- switching	Dotontion		Connector M12, 4-pin	-	Cd-083	WL27-3P2461	1044166										

<sup>1)</sup> PL80A.

## WL27-3, DC, detecting objects wrapped in film

• Sensor principle: photoelectric retro-reflective sensor

• Type of light: visible red light

Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Output type		Con- nection diagram	Туре	Part no.
0.1 m 4.3 m <sup>1)</sup>	Ø 90 mm (4 m)	PNP	Connector M12, 4-pin	Cd-083	WL27-3P2430S01	1028057
0.1 m 3 m <sup>2)</sup>	Ø 30 mm (3 m)	PNP	Connector M12, 4-pin	Cd-083	WL27-3P2460S14	1047908

<sup>&</sup>lt;sup>1)</sup> PL80A.

## WSE27-3, DC, infrared light

Sensor principle: through-beam photoelectric sensor

• Switching mode: light/dark-switching

Sensing range max.	Light spot size (dis- tance)		Adjustment	Connection	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.
0 m	Ø 3.7 m	PNP	_	Cable, 4-wire, 3 m, PVC	-	-	Cd-088	WSE27-3P1710	1028059
35 m	(25 m)	PINP	_	Connector M12, 4-pin	-	-	Cd-072	WSE27-3P2410	1048199



<sup>&</sup>lt;sup>2)</sup> PL20A.

## WSE27-3, DC, visible red light

- Sensor principle: through-beam photoelectric sensor
- Switching mode: light/dark-switching

Sensing range max.	Light spot size (dis- tance)	Out- put type	Adjustment	Connection	Front screen heating	Time func- tions	Con- nection diagram	Туре	Part no.																
				Connector M12, 4-pin	-	-	Cd-072	WSE27-3P2430	1027790																
			-	Connector W12, 4-pin	~	-	Cd-072	WSE27-3P2450	1027791																
0 m	Ø 600 mm		Potentiometer	Connector Q6, 6-pin, DC-coding	-	~	Cd-143	WSE27-3F2631	1027792																
35 m	(25 m)																			Cable, 4-wire, 2 m, PVC	-	-	Cd-088	WSE27-3N1130	1047803
				-	Connector M12, 4-pin	-	-	Cd-072	WSE27-3N2430	1028072															
		Potentiometer	Connector Q6, 6-pin, DC-coding	-	~	Cd-143	WSE27-3E2631	1027793																	

## WTB27-3, AC/DC

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Output type: relay

Adjustment: potentiometer

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (dis- tance)	Switching mode	Connection	Time func- tions	Con- nection diagram	Туре	Part no.
Infrared	30 mm	Ø 25 mm	Light/dark-switching 2)	Connector Q6, 6-pin, AC/ UC-coding	~	Cd-181	WTB27-3R2611	1027763
light	1,600 mm	(800 mm)	Light switching 3)	Cable, 5-wire, 2 m	-	Cd-161	WTB27-3S1511	1027762
Visible	30 mm	Ø 15 mm	Light/dark-switching 2)	Connector Q6, 6-pin, AC/ UC-coding	•	Cd-181	WTB27-3R2641	1027750
red light	1,100 mm	(500 mm)	Light switching 3)	Cable, 5-wire, 2 m	-	Cd-161	WTB27-3S1541	1027749

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WL27-3, AC/DC

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

Type of light: visible red light

Output type: relay

· Adjustment: potentiometer

Sensing range max. 1)	Light spot size (dis- tance)	Switching mode	Connection	Time func- tions	Con- nection diagram	Туре	Part no.
0.1 m 15 m	Ø 220 mm	Light/dark-switching 2)	Connector Q6, 6-pin, AC/ UC-coding	•	Cd-181	WL27-3R2631	1027776
	(10 mm)	Light switching 3)	Cable, 5-wire, 2 m, PVC	-	Cd-161	WL27-3S1531	1027775

<sup>1)</sup> PL80A.



<sup>&</sup>lt;sup>2)</sup> Provide suitable spark suppression for inductive or capacitive loads. Relay contacts are separated from the power supply by a basic isolation of 3 mm. Depending on the application, additional isolation might have to be applied in the user's circuit.

<sup>&</sup>lt;sup>3)</sup> Provide suitable spark suppression for inductive or capacitive loads.

<sup>&</sup>lt;sup>21</sup> Provide suitable spark suppression for inductive or capacitive loads. Relay contacts are separated from the power supply by a basic isolation of 3 mm. Depending on the application, additional isolation might have to be applied in the user's circuit.

 $<sup>^{\</sup>scriptsize\textrm{3)}}$  Provide suitable spark suppression for inductive or capacitive loads.

## WSE27-3, AC/DC

• Sensor principle: through-beam photoelectric sensor

• Type of light: visible red light

• Output type: relay

• Adjustment: potentiometer


Sensing range max.	Light spot size (dis- tance)	Switching mode	Connection	Time func- tions	Con- nection diagram	Туре	Part no.
0 m 35 m	Ø 600 mm (25 mm)	Light/dark-switching 1)	Connector Q6, 6-pin, AC/ UC-coding	•	Cd-159	WSE27-3R2631	1027795

<sup>&</sup>lt;sup>1)</sup> Provide suitable spark suppression for inductive or capacitive loads. Relay contacts are separated from the power supply by a basic isolation of 3 mm. Depending on the application, additional isolation might have to be applied in the user's circuit.

## **Dimensional drawings**


Dimensions in mm (inch)

#### WTB27-3, potentiometer



- ① Standard direction of the material being detected
- 2 Optical axis, sender
- 3 Optical axis, receiver
- 4 Mounting hole ø 5.2 mm
- ⑤ Status indicator LED green: power on
- ⑥ Status indicator LED, yellow: Status of received light beam
- 7 Sensing range adjustment: potentiometer


#### WTB27-3, double teach-in button



- ① Standard direction of the material being detected
- 2 Optical axis, sender
- 3 Optical axis, receiver
- 4 Mounting hole ø 5.2 mm
- ⑤ Status indicator LED green: power on
- Status indicator LED, yellow: Status of received light beam
- 7 Sensing range adjustment: double teach button




#### WTB27-3, potentiometer, time functions




- ① Standard direction of the material being detected
- 2 Optical axis, sender
- 3 Optical axis, receiver
- 4 Mounting hole ø 5.2 mm
- ⑤ Status indicator LED green: power on
- 6 Status indicator LED, yellow: Status of received light beam
- 7 Sensing range adjustment: potentiometer
- Time control
- 9 Time delay selector switch


## WL27-3, WSE27-3



- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Mounting hole ø 5.2 mm
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam








- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Mounting hole ø 5.2 mm
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam
- 6 Sensitivity control (10 revolutions)




#### WL27-3, WSE27-3, potentiometer, time functions



- ① Optical axis sender
- 2 Optical axis, receiver
- 3 Mounting hole ø 5.2 mm
- Status indicator LED green: power on
- § Status indicator LED, yellow: Status of received light beam
- 6 Sensitivity control (10 revolutions)
- 7 Time control
- Time delay selector switch


## **Adjustments**

#### Potentiometer




# ① Potentiometer

#### **Double teach-in button**




 $\ensuremath{\ensuremath{\mathbb{T}}}$  Double teach-in button

# Potentiometer, time functions



- ① Potentiometer
- ② Time control
- 3 Time delay selector switch

# Potentiometer, time functions, light-/dark-switch




- ① Potentiometer
- 2 Time control
- 3 Time delay selector switch



## **Characteristic curves**


#### Black-white shift

#### WTB27-3, infrared




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

## WTB27-3, PinPoint LED



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### WTB27-3, red light




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission




## Operating reserve

#### WL27-3




- ① PL80A
- ③ PL40A
- ⑤ PL20A
- 7 Reflective tape Diamond Grade

#### WSE27-3



## **Bar diagrams**

## WTB27-3, infrared



0 200 400 600 800 1000 1200 1400 1600 (7.87)(15.75)(23.62)(31.50)(39.37)(47.24)(55.12)(62.99)


Distance in mm (inch)



Sensing range

- 1 Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission


#### WTB27-3, red light



Sensing range


- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

## WTB27-3, PinPoint LED



- Sensing range
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

## WL27-3




Sensing range

Sensing range max.

- ① PL80A
- ② PL50A
- 3 PL40A
- 4 PL30A
- ⑤ PL20A
- 6 C110A
- 7 Reflective tape Diamond Grade

#### WSE27-3



Sensing range


Sensing range typ. max.

## **Connection diagram**

#### Cd-072

- ${\bf 1}\!\!{\rm Sender}$
- ② Receiver


#### Cd-088



- ① Sender
- 2 Receiver

#### Cd-083

#### Cd-094







#### Cd-101

# $\begin{array}{c|c} - & & \\ \hline & & \\$

#### Cd-104




#### Cd-143




- ① Sender
- 2 Receiver


#### Cd-159



## Cd-161




#### Cd-178



# Sender Receiver

## Cd-181



## **Recommended accessories**

## Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Steel zine seeted	Mounting hypothet with hinged arm	BEF-WN-MULTI	2064469
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W27	2009122

## Plug connectors and cables

## Connecting cable (female connector-open)

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connect- ing cable	Cable material	Enclosure rating	Model name	Part no.
			2 m, 4-wire	PVC	IP 67	DOL-1204-G02M	6009382
100	Female connector,		5 m, 4-wire	PVC	IP 67	DOL-1204-G05M	6009866
	M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-G02MC	6025900
180			5 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-G05MC	6025901
//	Female connector, M12, 4-pin, angled,	Cable, open conductor heads	2 m, 4-wire	PVC	IP 67	DOL-1204-L02M	6027945
1 2	with 3 LEDs		5 m, 4-wire	PVC	IP 67	DOL-1204-L05M	6027944
			2 m, 4-wire	PVC	IP 67	DOL-1204-W02M	6009383
	Female connector, M12, 4-pin, angled	Cable open con	5 m, 4-wire	PVC	IP 67	DOL-1204-W05M	6009867
		Cable, open con- ductor heads	2 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-W02MC	6025903
19			5 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-W05MC	6025904

## Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	РВТ	IP 67	DOS-1204-W	6007303



## Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	STE-1204-W	6022084

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
ð	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

## Device protection (mechanical)

## Protective housing/tubes

Figure	Material	Description	Model name	Part no.
1	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601
St	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240

## Reflectors

## Angular



Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.
	Reflective tape "Diamond Grade", self-adhesive, customizable size by sheet, 74.9 cm x 91.4 cm $^{\rm 1)}$	REF-DG-K	4019634
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Customizable length by sheet. Width max. 74.9 cm, length max. 91.4 cm.

## Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

<sup>→</sup> For additional accessories, please see page L-861

















## **Additional information**

/ total till of the till of th
Detailed technical dataH-633
Ordering information
Dimensional drawings
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-638

## **Product description**

The W27 family is designed for harsh industrial environments where it copes easily with heavy vibrations, shocks and extreme temperature fluctuations. The W27-3 Ex photoelectric sensor meets category 3G/3D (ATEX) requirements for use in explosive environments. These sensors are enclosed in a rugged metal

housing that provides users with a readyto-install solution that complies with all its aspects. For, besides limit values for temperature, performance or UV resistance, the standard also prescribes a specific mechanical stability that conventional sensors do not meet.

## At a glance

- Classification: EX II 3G EX nA op is IIB T4 Gc X, EX II 3D EX tc IIIB T135°C Dc IP67 X according to Directive 94/9/ EC (ATEX)
- Corresponds to category 3D/3G
- · Conform to standards and ready-to-install: Sensor and additional protective housing (stainless steel 1.4301)
- · Long sensing range with IR LED
- High level of operating reserve
- · Resistant to ambient light, optical reflections, and crosstalk from other photoelectric devices

## Your benefits

- · Ready-to-install sensors including rugged metal housing conform with the 3G/3D category for explosive zones (ATEX)
- · Resistant to ambient light, optical reflections, and immune to crosstalk from other photoelectric devices, reducing false detection
- · Long sensing range with high operating reserve
- Resistant to vibrations, reducing downtime
- · Withstands harsh environments with temperatures between -20 °C -+50 °C

#### www.mysick.com/en/W27-3\_Ex

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



## **Detailed technical data**

## **Features**

	WT27-3 Ex	WL27-3 Ex	WSE27-3 Ex
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Standard optics	-
Dimensions (W x H x D)	31.4 mm x 112.3 mm x 70.4 m	nm	
Housing design (light emission)	Rectangular		
Sensing range max.	30 mm 1,600 mm <sup>1)</sup>	0.1 m 15 m <sup>2)</sup>	0 m 35 m
Sensing range	100 mm 1,600 mm	0.1 m 11 m <sup>2)</sup>	0 m 25 m
Type of light	Infrared light	Visible red light	
Light source 3)	LED		
Light spot size (distance)	Ø 25 mm (800 mm)	Ø 220 mm (10 m)	Ø 600 mm (25 m)
Angle of dispersion	-	Approx. 1.5°	
Wave length	880 nm	660 nm	645 nm
Adjustment	Potentiometer		-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

	WT27-3 Ex	WL27-3 Ex	WSE27-3 Ex
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>		
Current consumption 3)	≤ 40 mA	≤ 30 mA	35 mA
Current consumption, sender 3)	-		35 mA
Current consumption, receiver 3)	-		20 mA
Output type	PNP		
Output function	Complementary		
Switching mode	Light/dark-switching		
Signal voltage PNP HIGH/LOW	Approx. $V_S - 2.5 V / 0 V$		
Output current I <sub>max.</sub>	≤ 100 mA		
Response time 4)	≤ 1.5 ms	≤ 500 µs	
Switching frequency 5)	350 Hz	1,000 Hz	
Angle of reception	-		Approx. 3°
Connection type	Cable, 10 m <sup>6)</sup> Cable with connector, M12 (depending on type)		
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , C <sup>9)</sup>		
Protection class 10)	II		
Weight	750 g		1,500 g
Polarisation filter	-	✓	-
Housing material			
Sensor	ABS		
Protection housing	Stainless steel V2A (1.4301)		
Optics material	PMMA		
Enclosure rating	IP 67		



 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	WT27-3 Ex	WL27-3 Ex	WSE27-3 Ex		
ATEX marking	EX II 3G EX nA op is IIB T4 Gc X/	EX II 3D EX to IIIB T135°C Do			
Hazardous area category	3D, 3G				
Ambient operating temperature	-20 °C +50 °C				
Ambient storage temperature	-40 °C +75 °C				

<sup>&</sup>lt;sup>1)</sup> Limit values, operation in short-circuit protected network max. 8 A.

## **Ordering information**

Other models available at www.mysick.com/en/W27-3\_Ex

#### WT27-3 Ex

• Sensor principle: photoelectric proximity sensor

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.
30 mm 1,600 mm	Ø 25 mm (800 mm)	PNP	Cable, 4-wire, 10 m	Cd-094	WTB27X-3P1811	1027988

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WL27-3 Ex

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.
0.1 m 15 m	Ø 220 mm (10 mm)	DND	Cable, 4-wire, 10 m, PVC	Cd-094	WL27X-3P1831	1027989
0.1 111 15 111	0.1 m 15 m Ø 220 mm (10 mm)	PNP	Cable with connector M12, 4-pin	Cd-094	WL27X-3P3431	1029955

<sup>1)</sup> PL80A.

## WSE27-3 Ex

• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Туре	Part no.
0 m 35 m	Ø 600 mm (25 m)	PNP	Cable, 4-wire, 10 m	Cd-088	WSE27X-3P1830	1027991



 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  Do not bend below 0  $^{\circ}\text{C.}$ 

 $<sup>^{7)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.


<sup>9)</sup> C = interference suppression.

<sup>10)</sup> Reference voltage: 50 V DC.

## **Dimensional drawings**


Dimensions in mm (inch)

#### **WTB27-3 EX**



- ① Standard direction
- 2 Optical axis, sender
- 3 Optical axis, receiver
- 4 Mounting hole,  $\varnothing$  5.2 mm
- ⑤ Status indicator LED green: power on
- **6** Status indicator LED, yellow: Status of received light beam
- $\ensuremath{{\ensuremath{\mathcal{T}}}}$  Sensing range adjustment: potentiometer


## **WL27-3 EX**




- ① Optical axis, sender
- ② Optical axis, receiver
- 3 Mounting hole, Ø 5.2 mm
- Sensitivity adjustment
- ⑤ Status indicator LED, yellow: Status of received light beam



## **WSE27-3 EX**






- ① Optical axis, sender
- 2 Optical axis, receiver
- 3 Mounting hole ø 5.2 mm
- 4 Status indicator LED green: power on
- ⑤ Status indicator LED, yellow: Status of received light beam


## **Adjustments**

## WTB27-3 Ex



Sensing range adjustment: potentiometer

## WL27-3 Ex




© Sensitivity adjustment: potentiometer

## **Characteristic curves**

#### Black-white shift


#### **WTB27-3 EX**



- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission


## Operating reserve

#### **WL27-3 EX**



- ① PL80A
- 3 PL40A5 PL20A
- Reflective tape Diamond Grade


## **WSE27-3 EX**





## **Bar diagrams**

#### **WTB27-3 EX**




0 200 400 600 800 1000 1200 1400 1600 (7.87)(15.75)(23.62)(31.50)(39.37)(47.24)(55.12)(62.99)

Distance in mm (inch)

Sensing range

- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### **WL27-3 EX**




Sensing range

Sensing range max.

- ① PL80A
- ② PL50A
- ③ PL40A
- 4 PL30A
- ⑤ PL20A
- **6** C110A
- 7 Reflective tape Diamond Grade

#### **WSE27-3 Ex**




Sensing range

Sensing range typ. max.


## **Connection diagram**

#### Cd-088



- ① Sender
- ② Receiver

## Cd-094



## **Recommended accessories**

## Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
55			BEF-WN-MULTI	2064469
	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W27	2009122

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
Ø	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

## Device protection (mechanical)

## Protective housing/tubes

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (protective hous- ing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W27	2039601
12	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240

## Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861









## **Product description**

The W250 family integrates both DC and universal AC/DC versions into one compact housing. Both cable and rotatable M12 connector versions enhance this sensor's integration flexibility. In addition, an easy-to-read sensing range indicator aids users during adjustment. Operating mode (light/dark) is selectable via a control cable, which reduces the number of device variants.

## At a glance

- Highly visible red light spot thanks to the Bright Light LED
- · Potentiometer for adjusting sening
- Operating mode (light/dark) selectable via control wire
- Cable or rotatable M12 connector
- Versions for 10 30 V DC or 24 240 V DC/ 24 - 240 V AC voltage supply in compact design
- · Stainless steel mounting bracket BEF-W250 included in delivery

## Your benefits

- Mounting bracket is included to ease installation
- · Visible red Bright Light LED for simpler alignment of the sensors
- Cable or rotatable M12 connector provide installation flexibility
- Operating mode (light/dark) is selectable via a control cable to reduce the number of device variants
- · Variants with DC voltage and universal AC/DC voltage in the same housing provide increased flexibility



## **Additional information**

Detailed technical data...........H-641 Dimensional drawings ..........H-644 Recommended accessories . . . . H-652

→ www.mysick.com/en/W250-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more





## **Detailed technical data**

## **Features**

		DC			AC/DC	
	WTB250-2	WL250-2	WSE250-2	WTB250-2	WL250-2	WSE250-2
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background suppression	Standard optics	-	Background suppression	Standard optics	-
Dimensions (W x H x D)	20 mm x 65 m	m x 43.9 mm				
Housing design (light emission)	Rectangular					
Sensing range max.	$100 \text{ mm} \dots$ $1,000 \text{ mm}^{1)}$ (depending on type)	0.01 m 15 m <sup>2)</sup>	0 m 50 m	$100 \ \text{mm} \dots$ $1,000 \ \text{mm}^{1)}$ (depending on type)	0.01 m 15 m <sup>2)</sup>	0 m 50 m
Sensing range	100 mm 1,000 mm <sup>1)</sup> (depending on type)	0.01 m 13 m <sup>2)</sup>	0 m 40 m	$100 \text{ mm} \dots$ $1,000 \text{ mm}^{1)}$ (depending on type)	0.01 m 13 m <sup>2)</sup>	0 m 40 m
Type of light	Visible red light					
Light source 3)	BrightLight LED	)				
Angle of dispersion	Approx. 3° Approx. 2° Approx. 3° Approx. 2°					
Adjustment 4)	Potentiometer,	2 turns				

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## Mechanics/electronics

		DC			AC/DC	
	WTB250-2	WL250-2	WSE250-2	WTB250-2	WL250-2	WSE250-2
Supply voltage	10 V DC 30 V	V DC <sup>1)</sup>		24 V DC 240 V DC <sup>2)</sup> 24 V AC/DC 240 V AC/DC <sup>2)</sup>		
Ripple 3)	≤ 5 V <sub>pp</sub>			-		
Current consumption	≤ 35 mA	≤ 20 mA	-	-		
Current consumption, sender	-		20 mA <sup>3)</sup>	-		
Current consumption, receiver	-		20 mA <sup>3)</sup>	-		
Power consumption	-			≤ 5 VA		-
Power consumption, sender	-					≤ 3,5 VA
Power consumption, receiver	_					≤ 3,5 VA
Output type	PNP, open colle (depending on	ector/NPN, open type)	collector	Relay, electrically isolated <sup>5)</sup>		
Output function	-			Change-over cont	acts	
Switching mode	<b>.</b>	ching/Light swit L/D control wire	_	Light switching 5)		
Output current I <sub>max.</sub>	≤ 100 mA			-		
Switching current (switching voltage)	-			3 A (240 V AC)/3	A (30 V DC)	
Response time	≤ 3 ms <sup>6)</sup>			≤ 15 ms		
Switching frequency 7)	160 Hz	1,000 Hz		33 Hz		
Angle of reception	-		20°	-		20°
Connection type	Cable <sup>8)</sup> /Male connector, M12 <sup>9)</sup> (depending on type)		Cable 8)			
Circuit protection	A $^{10)}$ , B $^{11)}$ , C $^{12)}$ ,	D 13)		A <sup>10)</sup> , C <sup>12)</sup>		



<sup>2)</sup> PI 80A

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

<sup>&</sup>lt;sup>4)</sup> With position indicator.

		DC			AC/DC	
	WTB250-2	WL250-2	WSE250-2	WTB250-2	WL250-2	WSE250-2
Protection class	Ш			II <sup>14)</sup>		
Overvoltage category	-			2		
Weight						
Cable	150 g		300 g	330 g		660 g
Connector	40 g		80 g	-		
Polarisation filter	-	✓	-		✓	-
Housing material	ABS					
Optics material	PMMA					
Enclosure rating	IP 67					
Items supplied	BEF-W250 mounting bracket	Reflector P250, BEF-W250 mounting bracket	BEF-W250 mod	unting bracket	Reflector P250, BEF-W250 mounting bracket	BEF-W250 mounting bracket
Usage category	-			AC-15, DC-13,	according to EN	60947-1
EMC <sup>15)</sup>	EN 60947-5-2					
Ambient operating temperature	-25 °C +55	°C				
Ambient storage temperature	-40 °C +70	°C				

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

## **Ordering information**

Other models available at www.mysick.com/en/W250-2



Sensor principle: photoelectric proximity sensor

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP	Light/dowleavitabing	Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2P1131	6044674
100 mm 300 mm	Ø 30 mm	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-087	WTB250-2P2431	6044675
100 11111 300 11111	(300 mm)	NPN	Light (dork awitahing	Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2N1131	6044672
		NPN	Light/dark-switching	Connector M12, 4-pin	Cd-087	WTB250-2N2431	6044673
				Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2P1141	6044680
		PNP	Light/dark-switching	Cable, 4-wire, 5 m, PVC	Cd-089	WTB250-2P1241	6044681
150 mm 500 mm	Ø 30 mm	PINP		Connector M12, 4-pin	Cd-087	WTB250-2P2441	6044682
150 11111 500 11111	(500 mm)		Light switching	Connector M12, 4-pin	Cd-066	WTB250-2F2441	6044685
		NPN	Light (dork awitahing	Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2N1141	6044678
			Light/dark-switching	Connector M12, 4-pin	Cd-087	WTB250-2N2441	6044679

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

<sup>&</sup>lt;sup>2)</sup> ±10 %.

 $<sup>^{3)}</sup>$  May not exceed or fall short of  $V_{\rm s}$  tolerances.

<sup>4)</sup> Without load.

<sup>&</sup>lt;sup>5)</sup> Provide suitable spark suppression for inductive or capacitive loads.

 $<sup>^{\</sup>rm 6)}$  Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Do not bend below 0 °C.

<sup>9) 90 °</sup> rotatable.

 $<sup>^{10)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{12)}</sup>$  C = interference suppression.

<sup>&</sup>lt;sup>13)</sup> D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>rm 14)}$  Reference voltage: 250 V AC.

<sup>15)</sup> The AC/DC devices meet the interference suppression requirements for industrial use (interference suppression class A). When used in residential areas it can cause interference.

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2P1151	6044690
		PNP	Light/dark-switching	Cable, 4-wire, 5 m, PVC	Cd-089	WTB250-2P1251	6044691
200 mm 1,000 mm	Ø 35 mm			Connector M12, 4-pin	Cd-087	WTB250-2P2451	6044690 6044691 6044692
200 111111 1,000 111111	(1,000 mm)			Cable, 4-wire, 2 m, PVC	Cd-089	WTB250-2N1151	6044686
		NPN	Light/dark-switching	Cable, 5-wire, 5 m, PVC	Cd-089	WTB250-2N1251	6044687
				Connector M12, 4-pin	Cd-087	WTB250-2N2451	6044689

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WL250-2, DC

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Cable, 4-wire, 2 m, PVC	Cd-089	WL250-2P1131	6044697
		PNP	Light/dark-switching	Cable, 4-wire, 5 m, PVC	Cd-089	WL250-2P1231	6044698
0.01 m 15 m <sup>1)</sup>	Ø 260 mm	PINP		Connector M12, 4-pin	Cd-087	WL250-2P2431	6044699
0.01 m 12 m <sup>2)</sup>	(8 m)		Light switching	Connector M12, 4-pin	Cd-067	WL250-2F2431	6044702
		NPN	Light/dark-switching	Cable, 4-wire, 2 m, PVC	Cd-089	WL250-2N1131	6044695
		INPIN	Light/ dark-switching	Connector M12, 4-pin	Cd-087	WL250-2N2431	6044696

<sup>1)</sup> PL80A.

## WSE250-2, DC

• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Cable, 4-wire, 2 m, PVC	Cd-058	WSE250-2P1131	6044703
		PNP	Light/dark-switching	Cable, 4-wire, 5 m, PVC	Cd-058	WSE250-2P1231	6044704
0 m 50 m	Ø 0.6 m (20 m)	PNP		Connector M12, 4-pin	Cd-060	WSE250-2P2431	6044705
0 III 50 III	Ø 0.6 III (20 III)		Light switching	Connector M12, 4-pin	Cd-071	WSE250-2F2431	6044706
		NPN	Light/dark-switching	Cable, 4-wire, 2 m, PVC	Cd-058	WSE250-2N1131	6044709
		INPIN	Lighty dark-Switching	Connector M12, 4-pin	Cd-060	WSE250-2N2431	6044711

## WTB250-2, AC/DC

• Sensor principle: photoelectric proximity sensor

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode <sup>2)</sup>	Connection	Connection diagram	Model name	Part no.
100 mm 300 mm	Ø 30 mm (300 mm)	Relay	Light switching	Cable, 5-wire, 2 m, PVC	Cd-163	WTB250-2R1531	6044676
				Cable, 5-wire, 5 m, PVC	Cd-163	WTB250-2R1631	6044677
150 mm 500 mm	Ø 30 mm (500 mm)	Relay	Light switching	Cable, 5-wire, 2 m, PVC	Cd-163	WTB250-2R1541	6044683
				Cable, 5-wire, 5 m, PVC	Cd-163	WTB250-2R1641	6044684
200 mm 1,000 mm	Ø 35 mm (1,000 mm)	Relay	Light switching	Cable, 5-wire, 2 m, PVC	Cd-163	WTB250-2R1551	6044693
				Cable, 5-wire, 5 m, PVC	Cd-163	WTB250-2R1651	6044694

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)



<sup>&</sup>lt;sup>2)</sup> P250.

 $<sup>^{\</sup>rm 2)}$  Provide suitable spark suppression for inductive or capacitive loads.

## WL250-2, AC/DC

• Sensor principle: photoelectric retro-reflective sensor

Sensing range max.	Light spot size (distance)	Output type	Switching mode <sup>2)</sup>	Connection	Connection diagram	Model name	Part no.
0.01 m 15 m <sup>1)</sup> Ø 260 mm 0.01 m 12 m <sup>2)</sup> (8 m)	Ø 260 mm	Delev	Light assitables	Cable, 5-wire, 2 m, PVC	Cd-229	WL250-2R1531	6044700
	Relay	Light switching	Cable, 5-wire, 5 m, PVC	Cd-229	WL250-2R1631	6044701	

<sup>1)</sup> PL80A.

## WSE250-2, AC/DC

• Sensor principle: through-beam photoelectric sensor


Sensing range max.	Light spot size (distance)	Output type	Switching mode <sup>2)</sup>	Connection	Connection diagram	Model name	Part no.
0 m 50 m	Ø 0.6 m (20 m)	Relay	Light switching	Cable, 5-wire, 2 m, PVC	Cd-228	WSE250-2R1531	6044707
				Cable, 5-wire, 5 m, PVC	Cd-228	WSE250-2R1631	6044708

 $<sup>^{\</sup>rm 2)}$  Provide suitable spark suppression for inductive or capacitive loads.

## **Dimensional drawings**


Dimensions in mm (inch)

#### WTB250-2, DC, cable



- ① Standard direction of the material being detected
- 2 Axis of sender
- 3 Axis of receiver
- ④ Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- ⑤ Connection cable






<sup>&</sup>lt;sup>2)</sup> P250.


<sup>&</sup>lt;sup>2)</sup> Provide suitable spark suppression for inductive or capacitive loads.

#### WTB250-2, DC, connector





- 39 (1.73) 39 (1.54) (1.02) (1.03)
- $\ensuremath{\textcircled{1}}$  Standard direction of the material being detected
- 2 Axis of sender
- 3 Axis of receiver
- 4 Mounting hole  $\varnothing$  4.2 mm, for M4 hexagon nut on both sides
- (§) Connector M12, 4-pin: Connector position rotatable by 90° (V>H); V: Vertical final position; H: Horizontal final position, can be locked with slider

## WL250-2, DC, cable




- ① Reception axis
- 2 Axis of sender
- $\ensuremath{\mathfrak{G}}$  Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- 4 Connection cable








#### WL250-2, DC, connector





- 24.7 (0.97)
- 43.9 (1.73) 1.8 20 (0.79) 39 (1.54) 3 36 (1.42) 1 65 (2.56) 2 23.6 (0.93) 4 36.3 (1.43)
- ① Reception axis
- 2 Axis of sender
- $\ensuremath{\mathfrak{J}}$  Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- $\ensuremath{\textcircled{4}}$  Connector M12, 4-pin: Connector position rotatable by 90  $^\circ$  (V>H); V: Vertical final position; H: Horizontal final position, can be locked with

## WSE250-2, DC, cable




- ① Center of the optical axis, sender (WS 250), receiver (WE 250)
- 2 Mounting hole  $\emptyset$  4.2 mm, for M4 hexagon nut on both sides
- ③ Connection cable







#### WSE250-2, DC, connector




- ① Center of the optical axis, sender (WS 250), receiver (WE 250)
- ② Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- ③ Connector M12, 4-pin: Connector position rotatable by 90° (V>H); V: Vertical final position; H: Horizontal final position, can be locked with slider






#### WTB250-2, AC/DC, cable




- ① Standard direction of the material being detected
- 2 Axis of sender
- 3 Axis of receiver
- 4 Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- ⑤ Connection cable




### WL250-2, AC/DC, cable




- ① Reception axis
- 2 Axis of sender
- $\ensuremath{\mathfrak{G}}$  Mounting hole ø 4.2 mm, for M4 hexagon nut on both sides
- 4 Connection cable







### WSE250-2, AC/DC, cable



- $\ensuremath{\textcircled{1}}$  Center of the optical axis, sender (WS 250), receiver (WE 250)
- 3 Connection cable









# **Adjustments**

### WTB250-2



- 6 LED indicator green: Stability indicator
- ② Status indicator LED, yellow: Status of received light beam
- 8 Sensing range adjustment: potentiometer
- $\ensuremath{\mathfrak{D}}$  Position indicator for sensitivity setting (270 °)

### WL250-2, WSE250-2, Sender




- ⑤ LED indicator green: Stability indicator
- 6 Status indicator LED, yellow: Status of received light beam
- 7 Sensitivity adjustment: potentiometer
- ® Position indicator for sensitivity setting (270°)

# **Characteristic curves**

### Black-white shift

# WTB250-2, 300 mm


% of sensing range



- ① Sensing range on black, background white
- ② Sensing range on gray, background white
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, background white

### WTB250-2, 500 mm

% of sensing range




- $\ensuremath{\mathbbm{1}}$  Sensing range on black, background white
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, background white
- 3 Sensing range on white, background white



### WTB250-2, 1000 mm

% of sensing range




- ① Sensing range on black, background white
- ② Sensing range on gray, background white
- 3 Sensing range on white, background white

# Operating reserve


### WL250-2


Function reserve



### WSE250-2

Operating reserve






- 2 Reflector type P205
- 3 Reflector type PL50A, PL40A, PL30A, PL31A
- 4 Reflector type PL20A




# **Bar diagrams**

### WTB250-2, 300 mm




- Sensing range
- ① Sensing range on black, background white
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, background white
- 3 Sensing range on white, background white

#### WTB250-2, 1000 mm



- Sensing range
- ① Sensing range on black, background white
- 2 Sensing range on gray, background white
- 3 Sensing range on white, background white


### WSE250-2



Sensing range


Sensing range max.

### WTB250-2, 500 mm



- Sensing range
- ① Sensing range on black, background white
- 2 Sensing range on gray, background white
- 3 Sensing range on white, background white

#### WL250-2




Sensing range

Sensing range max.

- ① Reflector type PL80A, C110A
- ② Reflector type P205
- 3 Reflector type PL50A, PL40A, PL30A, PL31A
- 4 Reflector type PL20A
- ⑤ Reflective tape Diamond Grade (100 mm x 100 mm/3.94 inch x 3.94 inch)


# **Connection diagram**

### Cd-058



- ① Sender
- 2 Receiver

### Cd-060



- ① Sender
- ② Receiver

### Cd-066

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
 & \text{wht} & 2 \\
 & \text{blu} & 3 \\
 & & \text{-(M)}
\end{array}$$

### Cd-067

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
 & \text{wht} & 2 \\
 & \text{blu} & 3 \\
 & \text{blk} & 4 \\
 & Q
\end{array}$$


### Cd-071

$$\begin{array}{c|c} & \begin{array}{c|c} & & \\ & & \end{array} & \begin{array}{c|c} & & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & & \end{array} & \begin{array}{c|c} & \\ & & \\ & \end{array} & \begin{array}{c|c} & \\ & & \\ & \end{array} & \begin{array}{c|c} & \\ & & \\ & \end{array} & \begin{array}{c|c} & \\ & & \\ & \end{array} & \begin{array}{c|c} & \\ & \\ & \end{array} & \begin{array}{$$


### Cd-087

$$\begin{array}{c|c}
 & \text{brn} & 1 \\
 & \text{wht} & 2 \\
 & \text{blu} & 3 \\
 & \text{loc} & \text{OM}
\end{array}$$


#### Cd-089




#### Cd-163




#### Cd-228





- ① Sender
- ② Receiver

### Cd-229



# Recommended accessories

# Mounting brackets/plates




Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Mounting bracket	BEF-W250	5305850

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
.\		Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	Female connector, M12, 4-pin, straight		5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
/ · · · ·			10 m, 4-wire	IP 67	DOL-1204-G10M	6010543
	Female connector, M12, 4-pin, angled	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
			5 m, 4-wire	IP 67	DOL-1204-W05M	6009867
			10 m, 4-wire	IP 67	DOL-1204-W10M	6010541

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO2 for universal clamp bracket	BEF-KHS-N02	2051608

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861





tor



# **Product description**

The W280-2 consists of three high-performance sensor types - energetic photoelectric proximity sensor, photoelectric retro-reflective sensor and through-beam photoelectric sensor. The AC/DC devices (-2Hxxxx) are compliant with EN 61000-6-3 (electromagnetic interference for "residential, commercial and light-industrial environments") which makes the sensor especially suitable for

door and gates areas. In other branches the fast install kit provides a rotatable M12 connector, cable or screw terminal connection which offer a quick and easy setup even in space-restricted conditions. Devices with potentiometer and light/dark switching provide application flexibility. In addition, these sensors are available in DC and AC/DC versions.

# At a glance

- · Highly visible red light spot thanks to the BrightLight LED
- Potentiometer for adjusting sensing range
- Light/dark switching (DC devices only)
- Rotatable connector, cable connection or terminal chamber
- Versions for 10 30 V DC or 24 -240 V DC/AC voltage supply
- AC/DC (-2Hxxxx) devices are compliant with EN61000-6-3 (electromagnetic interference for "residential, commercial and light-industrial environments")
- Stainless steel mounting bracket and P250 reflector (for WL280 only) are included in delivery

# Your benefits

- · Simple and fast commissioning with the highly visible light spot of the BrightLight LED
- Simple operation via potentiometer
- Light/dark switching provides application flexibility
- · All necessary mounting and operating accessories are included in delivery, enabling quick and easy setup: since mounting bracket (stainless steel 1.4301) is included in delivery scope
- DC devices and AC/DC devices available in the same housing, allowing electrical flexibility
- · Less contamination due to high operating reserves, reducing downtime

# ( (

### **Additional information**

Detailed technical data...........H-655 Recommended accessories . . . . H-663

### www.mysick.com/en/W280-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

	DC				AC/DC	
	WTE280-2	WL280-2	WSE280-2	WTE280-2	WL280-2	WSE280-2
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Energetic	Standard optics	-	Energetic	Standard optics	-
Dimensions (W x H x D)	23.5 mm x 74.	5 mm x 63 mm				
Housing design (light emission)	Rectangular					
Sensing range max.	10 mm 2,000 mm <sup>1)</sup>	0.01 m 15 m <sup>2)</sup>	0 m 60 m	10 mm 2,000 mm <sup>1)</sup>	0.01 m 15 m <sup>2)</sup>	0 m 60 m
Sensing range	10 mm 1,500 mm	0.01 m 13 m <sup>2)</sup>	0 m 50 m	10 mm 1,500 mm	0.01 m 13 m <sup>2)</sup>	0 m 50 m
Type of light	Visible red light  BrightLight LED					
Light source 3)						
Adjustment	Potentiometer					

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

		DC			AC/DC	
	WTE280-2	WL280-2	WSE280-2	WTE280-2	WL280-2	WSE280-2
Supply voltage	10 V DC 30 V	/ DC <sup>1)</sup>		24 V DC 240 24 V AC 240		
Ripple <sup>3)</sup>	≤ 5 V <sub>pp</sub>		≤ 5 V <sub>pp</sub>	-		
Current consumption	≤ 20 mA		-			
Current consumption, sender	-		≤ 20 mA	-		
Current consumption, receiver	-		≤ 20 mA <sup>4)</sup>	-		
Power consumption	-			≤ 5 VA		-
Power consumption, sender	-					≤ 3,5 VA
Power consumption, receiver	-					≤ 3,5 VA
Output type	PNP, open collector/NPN, open collector (depending on type)			Relay, electrica	lly isolated 5)	
Output function	-	-		Change-over contacts		
Switching mode	Light/dark-swit (selectable via	ching light/dark rotary	/ switch)	Light switching	5)	
Output current I <sub>max.</sub>	100 mA			-		
Switching current (switching voltage)	-			3 A (240 V AC)	/3 A (30 V DC)	
Response time	$\leq$ 0.5 ms $^{6)}$			≤ 15 ms		
Switching frequency 7)	1,000 Hz			33 Hz		
Connection type	Cable 8)/Cable	gland (dependin	g on type)			
Circuit protection	A $^{9)}$ , B $^{10)}$ , C $^{11)}$ ,	D <sup>12)</sup>		A $^{9)}$ , C $^{11)}$		
Protection class	III					<sup>13)</sup>
Overvoltage category	-			2/3 (depending	g on type)	
Weight	150 g		300 g	150 g		300 g
Polarisation filter	-	<b>✓</b>	-		<b>/</b>	-
Interference emission	_			EN 61000-6-3	(only -2Hxxxx) 1	4)
	ABS					



<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

		DC			AC/DC	
	WTE280-2	WL280-2	WSE280-2	WTE280-2	WL280-2	WSE280-2
Optics material	PMMA					
Enclosure rating	IP 66, IP 67					
Items supplied	Mounting bracket BEF-W280	Mounting bracket BEF-W280, Reflector P250	Mounting bracket BEF-W280		Mounting bracket BEF-W280, Reflector P250	Mounting bracket BEF-W280
Usage category	-			AC-15, DC-13,	according to EN	60947-1
EMC <sup>15)</sup>	EN 60947-5-2					
Ambient operating temperature	-25 °C +55 °C -40 °C +70 °C					
Ambient storage temperature						

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W280-2

# WTE280-2, DC

• Sensor principle: photoelectric proximity sensor

• Switching mode: light/dark-switching

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	mm 2,000 mm Ø 45 mm (1,500 mm)	PNP	Cable, 3-wire, 2 m	Cd-043	WTE280-2P1131	6044726
			Connector M12, 4-pin	Cd-068	WTE280-2P2431	6044728
10 mm 2 000 mm			Cable gland	Cd-207	WTE280-2P4331	6044724
10 11111 2,000 111111		NPN	Cable, 3-wire, 2 m	Cd-043	WTE280-2N1131	6044727
			Connector M12, 4-pin	Cd-068	WTE280-2N2431	6044729
			Cable gland	Cd-207	WTE280-2N4331	6044725

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WL280-2, DC

• Sensor principle: photoelectric retro-reflective sensor

Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
			Cable, 3-wire, 2 m	Cd-043	WL280-2P1131	6044734
	Ø 260 mm (8 m)	PNP	Connector M12, 4-pin	Cd-068	WL280-2P2431	6044736
0.01 m 15 m <sup>1)</sup>			Cable gland	Cd-207	WL280-2P4331	6044732
0.01 m 12 m <sup>2)</sup>		NPN	Cable, 3-wire, 2 m	Cd-043	WL280-2N1131	6044735
			Connector M12, 4-pin	Cd-068	WL280-2N2431	6044737
			Cable gland	Cd-207	WL280-2N4331	6044733

<sup>1)</sup> PL80A.

H-656



<sup>&</sup>lt;sup>2)</sup> ±10 %.

 $<sup>^{\</sup>rm 3)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>4)</sup> Without load.

<sup>&</sup>lt;sup>5)</sup> Provide suitable spark suppression for inductive or capacitive loads.

<sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

<sup>8)</sup> Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

 $<sup>^{10)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> C = interference suppression.

<sup>&</sup>lt;sup>12)</sup> D = outputs overcurrent and short-circuit protected.

<sup>13)</sup> Rated voltage: 250 V AC/DC.

 $<sup>^{14)}</sup>$  In the case of a DC supply (relating to EN 61000-6-3) the length of cable between the supply source and the sensor must be < 30 m.

<sup>15)</sup> The AC/DC devices meet the interference suppression requirements for industrial use (interference suppression class A). When used in residential areas it can cause interference.

<sup>&</sup>lt;sup>2)</sup> P250.

# WSE280-2, DC

- Sensor principle: through-beam photoelectric sensor
- Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
		PNP	Cable, 3-wire, 2 m	Cd-049	WSE280-2P1131	6044743
	Ø 0.6 mm (20 m)		Connector M12, 4-pin	Cd-187	WSE280-2P2431	6044745
0 m 60 m			Cable gland	Cd-190	WSE280-2P4331	6044741
0 111 00 111		NPN	Cable, 3-wire, 2 m	Cd-049	WSE280-2N1131	6044744
			Connector M12, 4-pin	Cd-187	WSE280-2N2431	6044746
			Cable gland	Cd-190	WSE280-2N4331	6044742

# WTE280-2, AC

- Sensor principle: photoelectric proximity sensor
- Switching mode: light switching (provide suitable spark suppression for inductive or capacitive loads.)

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Overvoltage category	Connection diagram	Model name	Part no.
10 mm 2,000 mm	Ø 45 mm (1,500 mm)	Relay	Cable, 5-wire, 2 m	2	Cd-229	WTE280-2H1531	6044731
				3	Cd-163	WTE280-2R1531	6044759
			Cable gland	2	Cd-169	WTE280-2H4331	6044730
				3	Cd-169	WTE280-2R4331	6044758

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# WL280-2, AC

- Sensor principle: photoelectric retro-reflective sensor
- Switching mode: light switching (provide suitable spark suppression for inductive or capacitive loads.)

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Overvoltage category	Connection diagram	Model name	Part no.
	Ø 260 mm (8 m)	Relay	Cable, 5-wire, 2 m	2	Cd-229	WL280-2H1531	6044739
				3	Cd-163	WL280-2R1531	6044761
0.01 m 15 m			Cable, 5-wire, 5 m	2	Cd-229	WL280-2H1631	6044740
			Cable gland	2	Cd-169	WL280-2H4331	6044738
				3	Cd-169	WL280-2R4331	6044760

<sup>1)</sup> PL80A.

# WSE280-2, AC

- Sensor principle: through-beam photoelectric sensor
- Switching mode: light switching (provide suitable spark suppression for inductive or capacitive loads.)


Sensing range max.	Light spot size (distance)	Output type	Connection	Overvoltage category	Connection diagram	Model name	Part no.	
		) Relay	Cable, 5-wire, 2 m	Cable E wire 2 m	2	Cd-228	WSE280-2H1531	6044748
	Ø 0.6 mm (20 m)		Cable, 5-wire, 2 m	3	Cd-228	WSE280-2R1531	6044763	
0 m 60 m			Cable, 5-wire, 5 m	2	Cd-228	WSE280-2H1631	6044749	
			Cable gland	2	Cd-227	WSE280-2H4331	6044747	
				3	Cd-227	WSE280-2R4331	6044762	



# **Dimensional drawings**


Dimensions in mm (inch)


# WTE280-2, WL280-2, DC





- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Cable entry gland 3/8" for cable diameter 6 to 8 mm
- 4 Mounting hole, Ø 4.3 mm
- $\mbox{\fontfamily{\fontfamil}{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamily{\fontfamil}{\fontfamily{\fontfamily{\fontfamil}{\fontfamily{\fontfamil}{\fontfamil$
- **6** Cable, 2 m, 3-pin, Ø 3,8 mm

# WSE280-2, DC














- ② Cable entry gland 3/8" for cable diameter 6 to 8 mm
- 3 Mounting hole, Ø 4.3 mm
- ① Connector M12, 4-pin, 90° rotatable, can be locked with slider
- ⑤ Cable, 2 m, 3-pin, Ø 3,8 mm



### WTE280-2, WL280-2, AC/DC










- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- $\ensuremath{\mathfrak{3}}$  Cable entry gland 3/8" for cable diameter 6 to 8 mm
- 4 Mounting hole, Ø 4.3 mm
- ⑤ Cable, 2 m, 5-wire, Ø 6,3 mm

# WSE280-2, AC/DC








- ① Centre of optical axis, sender and receiver
- 2 Cable entry gland 3/8" for cable diameter 6 to 8 mm
- 4 Cable, 2 m, 5-wire, Ø 6,3 mm




# **Adjustments**

# WTE280-2P/-2N, DC, WSE280-2P/-2N, DC



- 7 LED indicator green: Stability indicator
- ® Status indicator LED, yellow: Status of received light beam
- Sensing range/Sensitivity adjustment: potentiometer
- 10 Light/dark selector

# WTE280-2, AC/DC, WL280-2H/-2R, WSE280-2H/-2R




- 6 LED indicator green: Stability indicator
- Tstatus indicator LED, yellow: Status of received light beam
- ® Sensing range/Sensitivity adjustment: potentiometer

# **Characteristic curves**

### Black-white shift

### WTE280-2




- 1 Sensing range on black, 6 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission



# Operating reserve


#### WL280-2

Function reserve




- ① Reflector type PL80A, C110A
- 2 Reflector type P205
- 3 Reflector type PL50A, PL40A, PL30A, PL31A
- 4 Reflector type PL20A
- ⑤ Reflective tape Diamond Grade (100 mm x 100 mm/3.94 inch x 3.94 inch)

#### WSE280-2




# **Bar diagrams**

# WTE280-2




- ① Sensing range on black, 6 % remission
- ② Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

### WL280-2



- Sensing range
- Sensing range max.
- ① Reflector type PL80A, C110A
- 2 Reflector type P205
- ③ Reflector type PL50A, PL40A, PL30A, PL31A
- Reflector type PL20A
- ⑤ Reflective tape Diamond Grade (100 mm x 100 mm/3.94 inch x 3.94 inch)

### WSE280-2






# **Connection diagram**

### Cd-043




#### Cd-049




- ① Sender
- 2 Receiver


### Cd-068




### Cd-163



### Cd-169




#### Cd-187




- ① Sender
- ② Receiver

### Cd-190





- ① Sender
- 2 Receiver

### Cd-207




# Cd-227






- ① Sender
- ② Receiver


### Cd-228





- ① Sender
- 2 Receiver

### Cd-229



# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel V2A (1.4301)	Mounting bracket	BEF-W280	5313885

# Plug connectors and cables

# Connecting cable (female connector-open)

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connect- ing cable	Cable material	Enclosure rating	Model name	Part no.
			2 m, 4-wire	PVC	IP 67	DOL-1204-G02M	6009382
	Female connector,	Cable open con	5 m, 4-wire	PVC	IP 67	DOL-1204-G05M	6009866
	M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-G02MC	6025900
100			5 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-G05MC	6025901
			2 m, 4-wire	PVC	IP 67	DOL-1204-W02M	6009383
	Female connector,	Cable, open con-	5 m, 4-wire	PVC	IP 67	DOL-1204-W05M	6009867
	M12, 4-pin, angled	ductor heads	2 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-W02MC	6025903
19			5 m, 4-wire	PUR, halo- gen-free	IP 65, IP 68, IP 69K	DOL-1204-W05MC	6025904

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	DOS-1204-W	6007303



# Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type terminals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type terminals	PBT	IP 67	STE-1204-W	6022084

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
3		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
-		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861













# **Product description**

The powerful photoelectric proximity sensor W280L-2 Long Range is characterized by its maximum sensing range of up to 4 m combined with extremely simple operation. The sensing range can be further extended to 18 m with the WLT280L-2 Long Range reflector version. The option of 2 independant switching outputs allows feedback of low and high detection points. Setup is easy through an intuitive sensing range adjustment

potentiometer and indicator LED for each switching output. A visible red class 1 laser light ensures that the alignment is quick and precise. An integrated protective system in the W280L-2 Long Range prevents adverse effects caused by reflections in the background, for example, resulting from reflective metal surfaces, windows and warning vests. Additionally, the W280L-2 Long Range ignores crosstalk from an adjacent sensor.

# At a glance

- WTT280L-2: sensing range up to 4 m
- WLT280L-2: sensing range up to
- Complete background suppression: very small black/white shift, insensitive against reflections from the background (e.g. shiny metal, window, safety vest)
- Visible red class 1 laser light
- Version 1: with 1 x switching output and light/dark switch, version 2: with 2 x switching outputs and light/dark switch
- · Disable laser by wire
- · Reliable detection also in very fast production processes thanks to the switching frequency of 1000 Hz

# Your benefits

- · Reliable target detection with difficult target colors, angles and color transitions (black/white shift)
- One sensor with two outputs and two status LEDs improves application flexibility and reduces the number of sensors needed
- · Quick and easy comissioning with sensing range adjustment potentiometers and status LED - one for each
- · Quick and easy alignment with a red class 1 laser light
- Rotatable connector and light/dark switch for mounting and installation flexibility

# **(** € **(**

### **Additional information**

Detailed technical dataH-667
Ordering information
Dimensional drawing
Adjustments
Bar diagrams
Connection diagram
Recommended accessories H-670

### → www.mysick.com/en/W280L-2\_Long\_Range

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

### **Features**

	WTT280L-2 Long Range	WLT280L-2 Long Range
Sensor principle	Photoelectric proximity sensor	
Detection principle	Background suppression	
Dimensions (W x H x D)	23.5 mm x 76 mm x 55.8 mm	
Housing design (light emission)	Rectangular	
Sensing range max.	200 mm 4,000 mm <sup>1)</sup> 200 mm 3,000 mm <sup>2)</sup>	200 mm 18,000 mm <sup>3)</sup>
Sensing range	-	200 mm 18,000 mm
Type of light	Visible red light	
Light source 4)	Laser	
Light spot size (distance)	Ø 12 mm (3 m)	Ø 50 mm (18 m)
Laser class	1 (EN 60825-1:2008-5, IEC 60825-1:2007-03)	
Adjustment	Potentiometer	

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTT280L-2 Long Range	WLT280L-2 Long Range
Supply voltage 1)	10 V DC 30 V DC	
Ripple 2)	≤ 3 V <sub>pp</sub>	
Power consumption 3)	≤ 70 mA	
Output type	PNP, open collector/NPN, open collector 2 x PNP, open collector/ 2 x NPN, open collector (depending on type)	2 x PNP, open collector 2 x NPN, open collector (depending on type)
Switching mode	Light/dark-switching (selectable via light/dark r	otary switch)
Output current I <sub>max.</sub>	≤ 100 mA	
Response time 4)	≤ 0.5 ms	≤ 2 ms
Switching frequency 5)	1,000 Hz	± 250 Hz
Connection type	Cable, 2 m <sup>6)</sup> /Male connector (depending on type	oe)
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , C <sup>9)</sup> , D <sup>10)</sup>	
Protection class	III	
Weight	120 g	
Housing material	ABS	
Optics material	PMMA	
Enclosure rating	IP 67	
Items supplied	Mounting bracket BEF-W280	
EMC <sup>11)</sup>	EN 60947-5-2	
Ambient operating temperature	-10 °C +50 °C	
Ambient storage temperature	-40 °C +70 °C	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.



<sup>&</sup>lt;sup>2)</sup> Objects to be sensed with 6 % reflectivity (based on black)

<sup>3)</sup> Reflector P250, PL80A.

 $<sup>^{4)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}\,\</sup>mathrm{A}=\mathrm{V}_{\mathrm{S}}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>8)</sup> B = output reverse-polarity protected.

<sup>&</sup>lt;sup>9)</sup> C = interference suppression.

 $<sup>^{10)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>11)</sup> The devices meet the interference suppression requirements for industrial use (interference suppression class A). When used in residential areas it can cause interference.

# **Ordering information**

Other models available at www.mysick.com/en/W280L-2\_Long\_Range

# WTT280L-2 Long Range

• Sensor principle: photoelectric proximity sensor

• Voltage type: DC

• Switching mode: light/dark-switching

Sensing range max.	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
	Ø 12 mm (3 m)	PNP	Cable, 5-wire, 2 m, PVC	Cd-209	WTT280L-2P1531	6048065
		PINP	Connector M12, 5-pin	Cd-210	WTT280L-2P2531	6048061
		NPN	Cable, 5-wire, 2 m, PVC	Cd-209	WTT280L-2N1531	6048067
200 mm 4,000 mm <sup>1)</sup>			Connector M12, 5-pin	Cd-210	WTT280L-2N2531	6048063
200 mm 3,000 mm <sup>2)</sup>		2 x PNP	Cable, 5-wire, 2 m, PVC	Cd-208	WTT280L-2P1536	6048066
			Connector M12, 5-pin	Cd-211	WTT280L-2P2536	6048062
		2 x NPN	Cable, 5-wire, 2 m, PVC	Cd-208	WTT280L-2N1536	6048068
			Connector M12, 5-pin	Cd-211	WTT280L-2N2536	6048064

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# WLT280L-2 Long Range

• Sensor principle: photoelectric proximity sensor

• Voltage type: DC

• Switching mode: light/dark-switching

Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.
		2 x PNP	Cable, 5-wire, 2 m, PVC	Cd-208	WLT280L-2P1536	6048071
200 mm 18,000 mm	Ø 50 mm (18 m)	Z X PINP	Connector M12, 5-pin	Cd-211	WLT280L-2P2536	6048069
	0 20 min (18 m)	2 x NPN	Cable, 5-wire, 2 m, PVC	Cd-208	WLT280L-2N1536	6048072
			Connector M12, 5-pin	Cd-211	WLT280L-2N2536	6048070


<sup>1)</sup> Reflector P250, PL80A.



 $<sup>^{2)}</sup>$  Objects to be sensed with 6 % reflectivity (based on black)

# **Dimensional drawing**

Dimensions in mm (inch)




- ① Center of optical axis, receiver
- 2 Center of optical axis, sender
- 3 Mounting hole, Ø 4.3 mm
- Connector M12, 5-pin, rotatable by 90°
- ⑤ Cable, 2 m, 5-wire, Ø 3.8 mm

# Н


# **Adjustments**

### WTT280L-2xxxx1



- © LED indicator green: Stability indicator
- 7 Status indicator LED, yellow: Status of received light beam
- Sensing range adjustment: potentiometer
- 1 Light/dark selector


### WxT280L-2xxxx6



- 6 LED indicator green: Stability indicator
- $\ensuremath{{\ensuremath{\bigcirc}}}$  Status indicator LED, yellow: Status of received light beam (switching output 1)
- ® Status indicator LED, yellow: Status of received light beam (switching output 2)
- Sensing range adjustment: potentiometer for switching output 1
- ${\bf @}$  Sensing range adjustment: potentiometer for switching output 2
- 1 Light/dark selector

# **Bar diagrams**

### Bar diagram photoelectric proximity sensors



Sensing range max.

- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

# **Connection diagram**

Cd-208	Cd-209	Cd-210	Cd-211
—————————————————————————————————————		brn 1 + (L+)	brn 1 + (L+)
→ blk Q1	→ blk   Q1	$\rightarrow blk \stackrel{!}{\downarrow} 4$ Q <sub>1</sub>	$\rightarrow$ blk $\frac{4}{9}$ Q <sub>1</sub>
<u>blu</u> - (M)	<u>blu i</u> - (M)	<u>blu i 3</u> - (M)	<u>blu i 3</u> - (M)
→ wht Q <sub>2</sub>	→ wht Not connected	→ wht 2 Not connected	$\rightarrow$ wht $\frac{2}{2}$ Q <sub>2</sub>
→ gre ! MF	→ gre ! MF	gre! 5	<u>gre ! 5</u> MF
i	i	i	

# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Stainless steel V2A (1.4301)	Mounting bracket	BEF-W280	5313885

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
11	Female connector,	Cable, open con-	2 m, 5-wire	IP 67	DOL-1205-G02M	6008899
1.00	M12, 5-pin, straight	ductor heads	5 m, 5-wire	IP 67	DOL-1205-G05M	6009868

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate NO4 for universal clamp bracket	BEF-KHS-N04	2051610

# Reflectors

### Angular

Figure	Material	Description	Model name	Part no.
	DAMAMA (ADC	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, Ø 23 mm	P25F-1	5319385
	PMMA/ABS	Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm	P41F	5315128
2		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
2		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
Ø		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060

# Reflective tape

Figure	Description	Model name	Part no.
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030

→ For additional accessories, please see page L-861









applications



# **Product description**

The W2000 sensor family offers advanced features with application flexibility and long sensing ranges. Designed with an IP 67-rated housing and a watertight front window, the W2000 is ideal for harsh duty applications. The gasketed top cover can be easily opened to provide access to timing functions, sensitivity adjustments, and a light/dark switching mode. The W2000 family also features SICK's custom Application-Specific Integrated Circuit (ASIC). This superior technology eliminates crosstalk interference and provides immunity to ambient lighting. Three LED indicators provide easily identifiable power, signal and status information from any angle. The W2000 through-beam, retro-reflective and energetic proximity variants enable users to chose the version suited for their application needs.

# At a glance

- · Rugged, plastic housing
- · Crosstalk and ambient light immunity
- · Adjustable sensing range
- · Signal strength indicator
- IP 67/NEMA 6 enclosure rating

### Your benefits

 Application-Specific Integrated Circuit (ASIC) technology eliminates crosstalk interference and provides ambient light immunity, which reduces false detection of unwanted targets

- · Rugged IP-67 rated housing withstands harsh duty applications, increasing the sensor lifetime
- · Three LED indicators make it easy to install and troubleshoot
- Versatile mounting brackets and cable options simplify installation









### **Additional information**

Detailed technical data
Ordering information
Dimensional drawing
Adjustments
Characteristic curves
Bar diagrams
Connection diagram
Recommended accessories H-679



For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

		DC			AC/DC	
	WT2000	WL2000	WS/WE2000	WT2000	WL2000	WS/WE2000
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Dimensions (W x H x D)	45 mm x 73.7	mm x 48.6 mm				
Housing design (light emission)	Rectangular					
Sensing range max.	0 m 3.5 m <sup>1)</sup>	0 m 15 m <sup>2)</sup>	0 m 50 m	0 m 3.5 m <sup>1)</sup>	0 m 15 m <sup>2)</sup>	0 m 50 m
Sensing range	0 m 3.5 m <sup>1)</sup>	0 m 15 m <sup>2)</sup>	0 m 50 m	0 m 3.5 m <sup>1)</sup>	0 m 15 m <sup>2)</sup>	0 m 50 m
Type of light	Infrared light	Visible red light	Infrared light		Visible red light	Infrared light
Light source 3)	LED					
Light spot size (distance)	Ø 55 mm (2.5 m)	Ø 320 mm (14	m)	Ø 55 mm (2.5 m)	Ø 320 mm (14 m)	
Angle of dispersion	Approx. 1.3°		1.3°	Approx. 1.3°		1.3°
Wave length						
Infrared light	880 nm					
Visible red light	660 nm					
Time type	Time delay off	<sup>4)</sup> , Switch on dela	ny <sup>5)</sup>			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

		DC			AC/DC	
	WT2000	WL2000	WS/WE2000	WT2000	WL2000	WS/WE2000
Supply voltage 1)	10 V DC 30 V	/ DC		24 V AC/DC	240 V AC/DC	
Ripple <sup>2)</sup>	≤ 5 V			-		
Power consumption 3)	≤ 80 mA			≤ 6 W		
Output type	PNP, NPN			Relay, electrica	lly isolated	
Output function	Complementary, complementary		Change-over contacts			
Switching mode	Light/dark-switching (selectable via light/dark selector)					
Signal voltage PNP HIGH/LOW	Approx. VS - 2.0 V / 0 V		-			
Output current I <sub>max.</sub>	100 mA		-			
Switching current (switching voltage)	-			3 A (265 V)		
Response time 4)	≤ 1 ms			≤ 10 ms		
Switching frequency	500 Hz			10 Hz		
Connection type	Cable, 2 m $^{5)}/$	Male connector	(depending on ty	/pe)		
Circuit protection	A $^{6)}$ , C $^{7)}$ , D $^{8)}$			-		
Protection class 9)	II					
Weight	5.3 oz, 150 g					
Polarisation filter	-	<b>✓</b>	-		<b>✓</b>	-
Alarm output	PNP			-		



<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $T_{\Delta}$  = +25 °C.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Adjustable via Off delay selector switch.

<sup>&</sup>lt;sup>5)</sup> Adjustable via On delay selector switch.

	DC		AC/DC			
	WT2000	WL2000	WS/WE2000	WT2000	WL2000	WS/WE2000
Housing material	Glassfibre reinforced plastic					
Enclosure rating	IP 67, NEMA 6					
Ambient operating temperature	-13 °F 104 °F / -25 °C +40 °C					
Ambient storage temperature	-40 °F 158	°F/-40 °C	+70 °C			

<sup>1)</sup> Limit values.

# **Ordering information**

Other models available at www.mysick.com/en/W2000

# WT2000, DC

Sensor principle: Photoelectric proximity sensor

• Type of light: Infrared light

• Light spot size (distance):  $\emptyset$  2.2 in (8.2 ft) /  $\emptyset$  55 mm (2.5 m)

• Output type: PNP, NPN

• Switching mode: Light/dark-switching

• Alarm output: PNP

Sensing range max. 1)	Time functions	Connection	Connection diagram	Model name	Part no.
		Cable, 5-wire, 2 m, PVC	Cd-142	WT2000-B1102	7023056
0.0 44.5.0	-	Connector M12, 4-pin	Cd-086	WT2000-B4100	7024001
0 ft 11.5 ft 0 m 3.5 m		Connector M12, 5-pin	Cd-154	WT2000-B5100	7023059
0 111 3.3 111	Time delay off <sup>2)</sup> Switch on delay <sup>3)</sup>	Cable, 5-wire, 2 m, PVC	Cd-142	WT2000-B1122	7023058
		Connector M12, 5-pin	Cd-154	WT2000-B5120	7023061

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

### WL2000, DC

• Sensor principle: Photoelectric retro-reflective sensor

• Type of light: visible red light

• Light spot size (distance): Ø 12.5 in (45.9 ft) / Ø 320 mm (14 m)

• Output type: PNP, NPN

• Switching mode: Light/dark-switching

Alarm output: PNP

Sensing range max. 1)	Time functions	Connection	Connection diagram	Model name	Part no.
	-	Cable, 5-wire, 2 m, PVC	Cd-142	WL2000-B1302	7023044
		Connector M12, 4-pin	Cd-086	WL2000-B4300	7024002
0 ft 49 ft 0 m 15 m		Connector M12, 5-pin	Cd-154	WL2000-B5300	7023047
0 111 13 111	Time delay off <sup>2)</sup> Switch on delay <sup>3)</sup>	Cable, 5-wire, 2 m, PVC	Cd-142	WL2000-B1322	7023046
		Connector M12, 5-pin	Cd-154	WL2000-B5320	7023049

<sup>&</sup>lt;sup>1)</sup> PL80A.

H-674



 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> Do not bend below 0 °C.

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> C = interference suppression.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>&</sup>lt;sup>9)</sup> Reference voltage: 50 V DC.

<sup>&</sup>lt;sup>2)</sup> Adjustable via Off delay selector switch.

<sup>3)</sup> Adjustable via On delay selector switch.

<sup>&</sup>lt;sup>2)</sup> Adjustable via Off delay selector switch.

<sup>3)</sup> Adjustable via On delay selector switch.

# WS/WE2000, DC

• Sensor principle: Through-beam photoelectric sensor

• Type of light: Infrared light

• Light spot size (distance): 12.5 in (45.9 ft)  $/ \emptyset$  320 mm (14 m)

• Output type: PNP, NPN

Switching mode: Light/dark-switching

• Alarm output: PNP

Sensing range max.	Time functions	Connection	Connection diagram	Model name	Part no.
	-	Cable, 5-wire, 2 m, PVC	Cd-206	WS/WE2000-B1102	7025964
		Connector M12, 4-pin	Cd-215	WS/WE2000-B4100	7028604
0 ft 164 ft 0 m 50 m		Connector M12, 5-pin	Cd-155	WS/WE2000-B5100	7025965
0 111 30 111	Time delay off <sup>1)</sup> Switch on delay <sup>2)</sup>	Cable, 5-wire, 2 m, PVC	Cd-206	WS/WE2000-B1122	7025966
		Connector M12, 5-pin	Cd-155	WS/WE2000-B5120	7025967

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Adjustable via Off delay selector switch.

# WT2000, AC/DC

• Sensor principle: Photoelectric proximity sensor

• Type of light: Infrared light

• Light spot size (distance): Ø 2.2 in (8.2 ft) / Ø 55 mm (2.5 m)

• Output type: relay

• Switching mode: Light/dark-switching

Sensing range max. 1)	Time functions	Connection	Connection diagram	Model name	Part no.
0 ft 11.5 ft 0 m 3.5 m	-	Cable, 5-wire, 2 m, PVC	Cd-165	WT2000-R1102	7023062
		Mini connector, 5-pin	Cd-171	WT2000-R5100	7023065
	3.5 m Time delay off <sup>2)</sup>	Cable, 5-wire, 2 m, PVC	Cd-165	WT2000-R1122	7023064
	Switch on delay 3)	Mini connector, 5-pin	Cd-171	WT2000-R5120	7023067

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# WL2000, AC/DC

• Sensor principle: Photoelectric retro-reflective sensor

• Type of light: visible red light

Light spot size (distance): Ø 12.5 in (45.9 ft) / Ø 320 mm (14 m)

Output type: relay

• Switching mode: Light/dark-switching

Sensing range max. 1)	Time functions	Connection	Connection diagram	Model name	Part no.
	-	Cable, 5-wire, 2 m, PVC	Cd-165	WL2000-R1302	7023050
0 ft 49 ft		Mini connector, 5-pin	Cd-171	WL2000-R5300	7023053
0 m 15 m	m Time delay off <sup>2)</sup>	Cable, 5-wire, 2 m, PVC	Cd-165	WL2000-R1322	7023052
	Switch on delay 3)	Mini connector, 5-pin	Cd-171	WL2000-R5320	7023055

<sup>1)</sup> PL80A.



 $<sup>^{\</sup>mbox{\tiny 2)}}$  Adjustable via On delay selector switch.

<sup>&</sup>lt;sup>2)</sup> Adjustable via Off delay selector switch.

<sup>3)</sup> Adjustable via On delay selector switch.

<sup>&</sup>lt;sup>2)</sup> Adjustable via Off delay selector switch.

<sup>3)</sup> Adjustable via On delay selector switch.

# WS/WE2000, AC/DC

• Sensor principle: Through-beam photoelectric sensor

• Type of light: Infrared light

• Light spot size (distance): 12.5 in (45.9 ft)  $/ \emptyset$  320 mm (14 m)


• Output type: relay

• Switching mode: Light/dark-switching


Sensing range max.	Time functions	Connection	Connection diagram	Model name	Part no.
0 ft 164 ft 0 m 50 m	-	Cable, 5-wire, 2 m, PVC	Cd-046	WS/WE2000-R1102	7025968
		Mini connector, 5-pin	Cd-172	WS/WE2000-R5100	7025969
	m Time delay off <sup>1)</sup> Switch on delay <sup>2)</sup>	Cable, 5-wire, 2 m, PVC	Cd-046	WS/WE2000-R1122	7025970
		Mini connector, 5-pin	Cd-172	WS/WE2000-R5120	7025971

<sup>1)</sup> Adjustable via Off delay selector switch.

# **Dimensional drawing**



# **Adjustments**



- 7 ON delay selector
- ® ON delay selector
- 9 Light/dark selector

- $\ensuremath{\text{\textcircled{1}}}$  Status indicator LED green: power on
- ② Status indicator LED red: signal strength
- 3 Status indicator LED, yellow: Output active
- $\ensuremath{\textcircled{4}}$  Center of emitter optical axis
- ⑤ Center of receiver optical axis
- 6 Mounting hole ø 0.2 mm x 0.8 mm




<sup>&</sup>lt;sup>2)</sup> Adjustable via On delay selector switch.

# **Characteristic curves**

# Black-white shift


### WT2000






# Operating range

# WL2000




# WS/WE2000





# **Bar diagrams**


### WT2000



Sensing range


- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

# WS/WE2000



Sensing range

### WL2000




Sensing range

- ① PL80A
- ② PL50A
- ③ PL40A
- 4 PL30A
- ⑤ PL20A
- 6 Reflective tape Diamond Grade


# **Connection diagram**

### Cd-046




- ① Sender
- 2 Receiver

### Cd-154




### Cd-155




### Cd-086


Cd-165




### Cd-142




Cd-171





### Cd-215



- ① Sender
- 2 Receiver

# **Recommended accessories**

Plug connectors and cables

### Connecting cable (female connector-open)

• Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Cable length	Model name	Part no.
	Female connector, M12,		2 m	DOL-1204-G02M	6009382
	4-pin, straight	Cable	5 m	DOL-1204-G05M	6009866
	Female connector, M12,	Cable	2 m	DOL-1204-W02M	6009383
	4-pin, angled		5 m	DOL-1204-W05M	6009867



# Reflectors

# Angular

• Description: Rectangular, screw connection

Figure	Material	Dimensions	Model name	Part no.
		47 mm x 47 mm	P250	5304812
		38 mm x 15 mm	PL20A	1012719
B a	PMMA/ABS	56 mm x 28 mm	PL30A	1002314
		37 mm x 56 mm	PL40A	1012720
		80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Dimensions	Model name	Part no.
	Self-adhesive	50 mm x 60 mm	REF-IRF-56	5314244

### Round

Figure	Description	Material	Diameter	Model name	Part no.
	Round, screw connection	PMMA/ABS	80 mm	C110A	5304549







# Cylindrical photoelectric sensors



# A well-rounded package

No tools required: cylindrical sensors are easy to install and ready for operation in no time. With the broadest portfolio on the market, this sensor family offers total versatility. They are equipped with an innovative mounting system, shortbody or standard housings in metal, INOX stainless steel, or plastic, in versions suitable for food and beverage, or with high-precision laser technology. The comprehensive range covers the entire application spectrum of modern photoelectric sensor technology. SICK's cylindrical sensors are simply designed for every area of application.

### Your benefits

- The solution for economical challenges thanks to simple mounting, standardized connection technology and universal use
- Compatible due to standardized design in cylindrical housing, standardized connection system and electrical interfaces
- High operating reserves and access to new solutions due to large sensing ranges and similar system specifications for all variants
- Standard housing made of plastic, metal or stainless steel ensures durability in rough environmental conditions





# Cylindrical photoelectric sensors

	General information       I-684         Product selection       I-686         Product family overview       I-690
•	ELF
8	GR18S
	MH15V
CART .	V18 Laser
OFFICE STATES	V18V
	V180-2
	W15
	<b>Z-Sensor</b>





# Cylindrical photoelectric sensors from SICK: Versatile designs for a wide range of applications

#### **Short**

M18 short housing designs - ideal for universal space-saving solutions



The extremely short design is a feature of sensors from the GR18S product family and the MH15V stainless steel variant. The right-angle versions, in particular, require very little space and are therefore the ideal solution for tight installation spaces.

#### **Standard**

Top performance standard design for universal applications – a cost-effective and well-rounded solution



Adapted to the key requirements of the market, the sensors from the V180-2, V18V, and V18 Laser product families are an extremely cost-effective solution thanks to their standard M18 housing. In addition to plastic and metal housings, a rugged stainless steel variant is also available for use in hygiene and washdown zones.

# **Hybrid**

Flexible and versatile – SICK's hybrid designs combine state-of-the-art industrial design with SICK technology to produce an optimum application solution



Cylindrical photoelectric sensors from the ELF, Z-Sensor and W15 product families are highly versatile thanks a wide range of special housing options. The Z1 and Z2 sensors have an integrated M18 male thread and additional mounting holes. The Z3 sensor can be infinitely aligned in any direction, just like the human eye. The hybrid design of the W15 product family impresses with the flexibility of its mounting options.

# Flexible mounting and application options thanks to a universal and simple M18 mounting hole



In addition to the simple mounting hole of the standard M18 housings, the special "fully flush" mounting allows cylindrical photoelectric sensors to be used in even more areas. These flush-mount housing variants provide superior solutions for all tasks where it is essential that sensor and mounting does not interfere with the target.



Thanks to the short housing designs and "fully flush" mounting, GR18S cylindrical photoelectric sensors can be flush-mounted practically anywhere.



The "fully flush" metal variant was designed specially for the harsh environment of storage and conveyor systems.



Short housings and right-angle designs allow for a high level of installation flexibility, particularly when space is restricted.



The stainless steel variants of the MH15V and V18V cylindrical photoelectric sensors can handle even the most adverse conditions.



Flexible and flush mounting with the flush variant and snap ring allows the sensor to be positioned at the heart of the process and ensures very short mounting times.



The hybrid design of the Z3 cylindrical photoelectric sensor can be infinitely rotated and aligned in any direction.

# Overview of cylindrical photoelectric sensors

Cylindrical photoelec- tric sensors	□ Housing					Sensor principle										
	Mater	ial		Enclos	sure rat	ing	Housi	ng desig	(n							
	Stainless steel	Plastic	Metal	IP 67	IP 68	₩ 69K	Cylindrical, axial	Cylindrical, radial	Hybrid	Photoelectric proximity sensor	Energetic	Background suppression	Photoelectric retro-reflective sensor	Dual lens	Through-beam photoelectric sensor	
ELF																
ELF3		•		•							•					
GR18																
GR18S NEW		•		•							•			•	•	
MH15																
MH15V																
V18																
V18 Laser			•	•			•	•		•	•		•	•	•	
V18V					•											
V180												•				
V180-2		•		•							•					
W15																
W15		•		•					•	•	•					
Z-Sensor																
Z-Sensor		•		•					•	•	•	•	•	•		

					<u> </u>				
Optics/Technology					Special applications				Page
Type of light/	Light sender			Technology					
LED infrared light	LED red light	Red laser light 🔭	PinPoint LED red light	SIRIC®	Hyglenic and washdown zones	Detecting transparent objects	Detecting small objects	Detecting objects wrapped in film	
Ä	9	Re	re Pi	SIS	Hyg waa	Del	Obj	Del	
•	•						•		I-692
			•			•	•		I-698
									I-714
									I-724
	•					•	•		I-732
									I-742
•				•					I-766
									I-776

# Photoelectric proximity sensors

	Maximum sensing range	Dimensions (W x H x D)/ Housing length	Page
ELF	0 mm 155 mm	23.8 mm x 45.4 mm x 33.6 mm	I-692
Z-Sensor	0 mm 155 mm	13.6 mm x 45.2 mm x 31.7 mm	I-776
MH15V	10 mm 350 mm	52.9 mm	I-714
W15	4 mm 350 mm	16.2 mm x 48.5 mm x 31.9 mm	I-766
V18 Laser	0 mm 400 mm	97.7 mm 107.7 mm	I-724
GR18S	3 mm 550 mm	36.1 mm 53.7 mm	I-698
V18V	0 mm 900 mm	83 mm	I-732
V180-2	1 mm 1,100 mm	62.5 mm 84.2 mm	I-742

# Photoelectric retro-reflective sensors

	Maximum sensing range	Dimensions (W x H x D)/ Housing length	Page
ELF	0.1 m 4.8 m	23.8 mm x 45.4 mm x 33.6 mm	I-692
Z-Sensor	0.1 m 4.8 m	13.6 mm x 45.2 mm x 31.7 mm	I-776
MH15V	0.035 m 5 m	52.9 mm	I-714
V18V	0.035 m 5 m	83 mm	I-732
W15	0.035 m 5 m	16.2 mm x 48.5 mm x 31.9 mm	I-766
V180-2	0.05 m 7 m	62.5 mm 84.2 mm	I-742
GR18S	0.03 m 7.2 m	36.1 mm 53.7 mm	I-698
V18 Laser	0.1 m 35 m	97.7 mm 107.7 mm	I-724

# Through-beam photoelectric sensors

	■ Maximum sensing range	Dimensions (W x H x D)/ Housing length	Page
MH15V	0 m 5 m	52.9 mm	I-714
W15	0 m 5 m	16.2 mm x 48.5 mm x 31.9 mm	I-766
GR18S	0 m 15 m	36.1 mm 53.7 mm	I-698
V18V	0 m 20 m	83 mm	I-732
V180-2	0 m 28 m	62.5 mm 84.2 mm	I-742
V18 Laser	0 m 60 m	97.7 mm 107.7 mm	I-724

# **Product family overview**





Hybrid sensor with integrated M18 threads for front and base mounting



Round, short and economically unbeatable



Space-saving photoelectric sensors designed for wash down applications



Low-cost cylindrical M18 Laser photoelectric sensor

Optical axis		Axial/Axial, fully flush	Axial	Axial / radial	
		Radial/Radial, fully flush			
Dimensions (W x H x D)	23.8 mm x 45.4 mm x 33.6 mm	-	-	-	
Sensing range max.					
Photoelectric proximity sensor	0 mm 155 mm	3 mm 550 mm	3 mm 350 mm	0 mm 400 mm	
Photoelectric retro-reflective sensor	0.1 m 4.8 m	0.03 m 7.2 m	0.035 m 5 m	0.1 m 35 m	
Through-beam photoelectric sensor		0 m 15 m	0 m 5 m	0 m 60 m	
Light source	LED	PinPoint LED	PinPoint LED / LED	Laser	
Type of light	Visible red light / Infrared light	Visible red light	Visible red light / Infrared light	Visible red light	
Enclosure rating	IP 67	IP 67	IP 67, IP 68, IP 69K	IP 67	
Housing material	Plastic	Metal/Plastic	Stainless steel	Metal	
At a glance					

- Flush red lens
- Polarization filter
- Clear back cover for highly visible status indication
- 18 mm front and base mount
- Power and status indicator
- Low-cost cylindrical M18 sensor with extra short housing
- Potentiometer for adjustment of switching thresh-
- Five different housing styles
- Variety of plastic and metal housing styles, with straight or right angle optics
- Bright and highly visible PinPoint-LED
- Special flush type, one-piece metal housing
- Highly visible signal indicator LED
- IP 67 rating

- Field-tested resistance to acidic and alkaline cleaning and disinfecting agents
- Corrosion-resistant stainless steel housing 316L, certified by ECOLAB and JohnsonDiversey
- IP 69K-rated housing is resistant to wash down environments
- Available as complete family including proximity, BGS, retro-reflective and through-beam
- 3 mm chemical resistant sensor lens

- Laser emitter LED enclosed in a cylindrical M18 housing
- Laser class 1
- · Fast response time
- Straight or rightangle housing
- Durable metal housing
- IP 67
- Small visible light spot to detect small objects

**Detailed information** 

→I-692

→I-698

→I-714

→ I-724



V18\

Cylindrical photoelectric sensors with foolproof touch-teach for washdown areas



V180-2

Lowest-cost cylindrical photoelectric sensor on the market!



W15

Improve performance and reduce downtime with W15 sensors



7-Senso

Flexible, low-cost presence detection solutions with clear housings

Axial / radial	Axial / radial		
Axiai / Taulai	Axiai / Taulai	-	<del>-</del>
-	16.2 mm x 48.5 mm x 31.9 mm	13.6 mm x 45.2 mm x 31.7 mm	
0 mm 900 mm	1 mm 1.100 mm	4 mm 350 mm	0 mm 155 mm
0,035 m 5 m	0,05 m 7 m	0,035 m 5 m	0,1 m 4,8 m
0 m 20 m	0 m 28 m	0 m 5 m	-
LED	LED	PinPoint LED / LED	LED
Visible red light	Visible red light	Visible red light / Infrared light	Infrared light / visible red light
IP 67	IP 67	IP 66, IP 67, IP 67	IP 67
Metal/Plastic	Metal/Plastic	Plastic	Plastic

- IP 69K-rated cylindrical photoelectric sensors in M18 stainless steel housing
- Resistant to all common cleaning agents and certified by independent institutes
- Extended temperature range: +85° C (long-term), +100°C / 15 min. (shortterm)
- Touch (smart) teach-in adjustment
- All sensor materials, including the housing, LED and lens are resistant to chemicals
- IP 69K and IP 68 according to DIN 40050
- Laser-etched part numbers
- Ecolab & JohnsonDiversey certified for chemical resistance

- Low-cost M18 housing sensor on the market
- Long sensing distances: 100 mm, 400 mm, 800 mm (proximity sensor), 300 mm (proximity sensor with BGS), 6 m (retro-reflective sensor) and 20 m (through-beam sensor)
- Bright power and signal LEDs with 360° visibility
- Wide product portfolio solves a broad range of applications
- High switching frequencies up to 1000 Hz
- Available in a metal housing for applications in harsh environments
- Optical axis selectively axial or radial (90°)

- M18 front mount using plastic nut or snap ring, side assembly with 24.1 mm through holes
- Flush mounting possible using the snap ring
- Transparent back cover
- Best-in-class background suppression and red Pin-Point LED
- High immunity to ambient light
- Highly visible LED indicators

- Economical design with background suppression, retro-reflective or energetic variants available; non-adjustable
- Compact, transparent housing with 360° status indication
- M18 front mount and 24-25.4 mm slotted side through holes compatible with competitor devices
- Spherical eyeball-style housing with 24 mm ball mount allows for infinite adjustability (depending on type)
- Connection system: straight or angled cable outlet (60°) or M12 or M8 connector outlet
- IP 67 enclosure rating for harsh environments

→I-732 →I-742 →I-766 →I-776

Hybrid sensor with integrated M18 threads for front and base mounting







# **Product description**

The industry-proven ELF-3 family of hybrid photoelectric sensors offers basic functions for presence detection applications. These low-cost sensors provide a variety of features that can be optimized for customers to reduce installation and procurement costs. They are ideal for standard, short-range applications, such as conveyor systems, vending machines, packaging lines, or other simple on/off applications. ASIC (application-specific integrated circuit) technology, which is proprietary to SICK, guarantees the best optical performance. ELF-3 sensors are

available in background suppression, energetic and retro-reflective variants. The background suppression variant offers a 50 mm fixed sensing distance. The energetic variant has a 155 mm sensing range and the retro-reflective variant has a 5 m sensing range. A clear back cover provides highly visible power and status indication. These multi-functional sensors are able to integrate optical and electronic elements into different housings. The ELF-3 comes with integrated M18 threads for front and base mounting.

# At a glance

- · Flush red lens
- Polarization filter
- Clear back cover for highly visible status indication
- 18 mm front and base mount
- · Power and status indicator

#### Your benefits

- A wide range of customizable options reduces material and labor costs
- Flush red lens provides an increased sensing range for a broader range of application possibilities
- IP 67-rated housing has a longer service life that stands up to harsh environments, reducing maintenance time and costs
- Highly visible status/power indicator provides quick and easy troubleshooting from a distance
- · M18 front and base mounting ensures quick and easy installation
- · Small sensor footprint easily fits into applications with limited space



# **Additional information**

Detailed technical data I-693
Ordering information I-694
Dimensional drawings I-695
Characteristic curves I-695
Bar diagramsI-696
Connection diagram I-696
Recommended accessories I-697

#### → www.mysick.com/en/ELF3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

#### **Features**

	ET3	EL3	EL4
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sen	nsor
Detection principle	Background suppression / energetic (depending on type)	-	
Dimensions (W x H x D)	23.8 mm x 45.4 mm x 33.6 mm	ı	
Housing design (light emission)	Hybrid		
Thread diameter (housing)	M18		
Sensing range max.	0 mm 155 mm <sup>1)</sup> (depending on type)	0.1 m 4.8 m <sup>2)</sup>	
Sensing range	0 mm 155 mm <sup>1)</sup> (depending on type)	0.1 m 3 m <sup>2)</sup>	
Type of light	Infrared light / visible red light (depending on type)	Visible red light	
Light source 3)	LED		
Wave length			
Infrared light	880 nm	-	
Visible red light	660 nm		
Special feature	Focused optics	-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	ET3	EL3	EL4
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>		
Power consumption 3)	< 20 mA		
Output type	PNP		
Switching mode	Light switching / Dark-switchin	g (depending on type)	
Output current I <sub>max.</sub>	50 mA		
Switching frequency 4)	200 Hz	400 Hz	
Connection type 5)	Cable, 2 m		
Circuit protection	A <sup>6)</sup> , D <sup>7)</sup>		
Protection class 8)	III		
Weight	0.036 kg, 0.08 lbs		
Polarisation filter	-	<b>✓</b>	
Housing material	Glass fiber reinforced ABS plas	tic	
Enclosure rating	IP 67		
Ambient operating temperature	-25 °C +50 °C		
Ambient storage temperature	-40 °C +70 °C		

 $<sup>^{\</sup>scriptsize 1)}$  Limit values.

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $T_A$  = +25  $^{\circ}$ C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_S$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> With light/dark ratio 1:1.

 $<sup>^{5)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{6)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

 $<sup>^{\</sup>scriptscriptstyle{7)}}$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>mbox{\scriptsize 8)}}$  Reference voltage: 50 V DC.

# **Ordering information**

Other models available at www.mysick.com/en/ELF3

# ET3

• Sensor principle: photoelectric proximity sensor

• Output type: PNP

• Connection: cable, 3-wire, 2 m, PVC

Detection principle	Type of light	Sensing range max. 1)	Light spot size (distance)	Switching mode	Connection diagram	Model name	Part no.
Background	Infrared light	0 mm = 50 mm	10.5 mm x 10.5 mm (50 mm)	Light switching	Cd-043	ET3-P3215	1045187
suppression	Infrared light	0 mm 50 mm		Dark-switching	Cd-043	ET3-F3215	1045189
	Visible red light	5 mm 60 mm	8 mm x 8 mm (60 mm)	Light switching	Cd-043	ET3-P2215	1045195
				Dark-switching	Cd-043	ET3-F2215	1045196
Enorgotio		1 mm 100 mm	20 mm x 20 mm (100 mm)	Light switching	Cd-043	ET3-P4215	1045191
Energetic	Infrarad light			Dark-switching	Cd-043	ET3-F4215	1045193
	Infrared light	5 mm 155 mm	31 mm x 31 mm (150 mm)	Light switching	Cd-043	ET3-P5215	1045199
				Dark-switching	Cd-043	ET3-F5215	1045200

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# EL3

• Sensor principle: photoelectric retro-reflective sensor

• Output type: PNP

• Connection: cable, 3-wire, 2 m, PVC

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Switching mode	Connection diagram	Model name	Part no.
Visible and light	0.1 m 4.8 m	125 mm x 125 mm	Light switching	Cd-043	EL3-P2415	1043960
Visible red light	0.1 III 4.8 III	(1 m)	Dark-switching	Cd-043	FI 3-F2415	1043961

<sup>&</sup>lt;sup>1)</sup> PL80A.

### EL4

• Sensor principle: photoelectric retro-reflective sensor

• Output type: PNP

• Connection: cable, 3-wire, 2 m, PVC

Type of light	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Switching mode	Connection diagram	Model name	Part no.
Minible and limbs	0.4 4.0	125 mm x 125 mm	Light switching	Cd-043	EL4-P2415	1044683
Visible red light	0.1 m 4.8 m	(1 m)	Dark-switching	Cd-043	EL4-F2415	1044684


<sup>1)</sup> PL80A.

# **ELF**

# **Dimensional drawings**


Dimensions in mm (inch)






# Ø 24 (0.94) (0.94) M18

EL4






# **Characteristic curves**

#### EL3






- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A
- ⑤ Reflective tape REF-Plus


# **Bar diagrams**

#### ET3, 50 mm




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission

#### ET3, ET4, 100 mm




- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### EL3, EL4




- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A
- 3 Reflective tape REF-Plus

#### ET3, 60 mm



- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


#### ET3, 150 mm



- 1 Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

# **Connection diagram**

# Cd-043



# **Recommended accessories**

# Reflectors

#### Angular

• Description: Rectangular, screw connection

Figure	Material	Dimensions	Model name	Part no.
		47 mm x 47 mm	P250	5304812
		38 mm x 15 mm	PL20A	1012719
	PMMA/ABS	56 mm x 28 mm	PL30A	1002314
		37 mm x 56 mm	PL40A	1012720
		80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Dimensions	Model name	Part no.
	Self-adhesive	50 mm x 60 mm	REF-IRF-56	5314244

#### Round

Figure	Description	Material	Diameter	Model name	Part no.
	Round, screw connection	PMMA/ABS	80 mm	C110A	5304549

→ For additional accessories, please see page L-861















# **Additional information**

Detailed technical data I-699
Ordering information I-700
Dimensional drawings I-703
Characteristic curves I-706
Bar diagramsI-707
Light spot diameter I-708
Response curve I-708
Connection diagram I-709
Recommended accessories I-710

# **Product description**

The GR18S family of photoelectric sensors in cylindrical M18-housings has a special shortened design and offers an optimal price/performance ratio. It can be used universally in many applications thanks to five different housing designs. PinPoint LEDs, plastic and metal housing versions as well as status indicators that

are easily visible from all angles round off the sensor family's features. One highlight is the fully-flush metal variant, which has been especially designed for use in harsh industrial environments found in handling and warehousing systems.

# At a glance

- · Low-cost cylindrical M18 sensor with extra short housing
- Potentiometer for adjustment of switching threshold
- Five different housing styles
- Variety of plastic and metal housing styles, with straight or right angle optics
- Bright and highly visible PinPoint-LED
- Special flush type, one-piece metal housing
- Highly visible signal indicator LED
- IP 67 rating

#### Your benefits

- Space-saving solution due to short housing
- Flexible mounting options due to versatile housing styles
- Potentiometer for adjustment of switching threshold allows detection of transparent objects.
- Easy installation and precise detection due to PinPoint LED
- · Reduced maintenance costs due to high tightening torque of single piece flush metal housing
- · Rugged and reliable with proven SICK technology
- · Highly visible signal indicator LED saves maintenance and commissioning time

#### → www.mysick.com/en/GR18S

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	GRTE18S	GRL18S	GRL18SG	GRSE18S
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-refle	ective sensor	Through-beam photo- electric sensor
Detection principle	Energetic	Standard optics		-
Housing design (light emission)		rlindrical, straight, fully fl lindrical, angled, fully flu		
Sensing range max.	3 mm 550 mm <sup>1)</sup> (depending on type)	0.03 m 7.2 m <sup>2)</sup>		0 m 15 m
Sensing range	5 mm 400 mm <sup>1)</sup> (depending on type)	0.06 m 6 m <sup>2)</sup>		0 m 10 m
Type of light	Visible red light			
Light source 3)	PinPoint LED			
Wave length	650 nm			
Adjustment	Potentiometer, 270 °	-	Potentiometer, 270 °	-
Special feature	-		Detection of transparent objects	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	GRTE18S	GRL18S	GRL18SG	GRSE18S
Supply voltage 1)	10 V DC 30 V DC			
Ripple <sup>2)</sup>	± 5 V <sub>pp</sub>			
Power consumption	≤ 30 mA			
Output type	PNP/NPN (depending	on type)		
Switching mode	Light switching/dark-sw	vitching (depending on t	ype)	
Output current I <sub>max.</sub> 3)	100 mA			
Response time 4)	< 1,000 µs	< 500 µs		
Switching frequency	500 Hz	1,000 Hz		
Connection type	Male connector, M12/0	Cable, 2 m 5) (depending	on type)	
Circuit protection	A $^{6)}$ , B $^{7)}$ , D $^{8)}$			
Protection class	III			
Polarisation filter	-	<b>✓</b>		-
Enclosure rating	IP 67			
Ambient operating temperature 9)	-25 °C +55 °C		$-25~^{\circ}\text{C} \dots +55~^{\circ}\text{C} ^{10)}$	-25 °C +55 °C
Ambient storage temperature	-40 °C +70 °C			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

<sup>2)</sup> PI 80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

 $<sup>^{3)}</sup>$  At Vs > 24 V or ambient temperature > 49 °C,  $\rm I_A$  max = 50 mA.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>&</sup>lt;sup>5)</sup> Do not bend below 0 °C.

 $<sup>^{\</sup>rm 6)}\,{\rm A}={\rm V}_{\rm S}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{8)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>rm 9)}$  At U  $_{\rm v}$  <=24V and I  $_{\rm A}$ <50mA.

<sup>&</sup>lt;sup>10)</sup> Temperature stability after adjustment +/-10 °C.

# **Ordering information**

Other models available at www.mysick.com/en/GR18S

# GRTE18S, metal

• Sensor principle: photoelectric proximity sensor

Detection principle: energetic

• Adjustment: potentiometer, 270 °

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.	
			DND	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2312	1058204	
	3 mm	Ø8mm	PNP	Light Switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-P1312	1058203	
	115 mm	(100 mm)	NPN	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-N2312	1059408	
Axial			INFIN	Light Switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-N1312	1058201	
Axidi			PNP	l i what a control in w	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-P1342	1058205	
	5 mm	Ø 9 mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2342	1058200	
	550 mm	(400 mm)	NPN	Light owitching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-N1342	1058202	
			INPIN	NPN Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-N2342	1059482	
				PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P231Z	1059436
	3 mm	Ø8mm	FINE	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F231Z	1059435	
	115 mm	(100 mm)	(100 mm)	100 mm) NPN	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-N231Z	1059432
Axial, fully			INFIN	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-E231Z	1059409	
flush			PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P234Z	1059487	
	5 mm	Ø9 mm	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F234Z	1059486	
	550 mm	(400 mm)	NPN	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-N234Z	1059484	
			INPIN	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-E234Z	1059483	
	3 mm	Ø8mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P231X	1059440	
Radial,	115 mm	(100 mm)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F231X	1059438	
fully flush	5 mm	Ø 9 mm (400 mm)	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P234X	1059489	
	550 mm (4			Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F234X	1059488	

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033).

# GRTE18S, plastic

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Adjustment: potentiometer, 270 °

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			PNP	Light switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-P1317	1058195
3 mm 115 mm	3 mm	Ø8mm	PNP	Light Switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2317	1058196
	(100 mm)	NIDNI	PN Light switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-N1317	1058194	
		NPN		Connector M12, 3-pin	Cd-045	GRTE18S-N2317	1059378	
		DND	Light assitution	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-P1347	1058197	
	5 mm	Ø 9 mm	PNP	PNP Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2347	1058193
	550 mm	(400 mm)	NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRTE18S-N1347	1058393
					Connector M12, 3-pin	Cd-045	GRTE18S-N2347	1059441
	3 mm	Ø8mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2319	1059407
Dadial	115 mm	(100 mm)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F2319	1059406
Radial	5 mm		PNP	Light switching	Connector M12, 3-pin	Cd-045	GRTE18S-P2349	1059481
	550 mm			Dark-switching	Connector M12, 3-pin	Cd-045	GRTE18S-F2349	1059480

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

# GRL18S, metal

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.				
				Light quitabing	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-P1331	1059542				
			24.12	Light switching	Connector M12, 3-pin	Cd-045	GRL18S-P2331	1058199				
Avial	0.03 m	Ø 175 mm (7 m)	PNP	PNP Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-F1331	1059541				
Axiai	Axial 7.2 m				Connector M12, 3-pin	Cd-045	GRL18S-F2331	1058198				
							NPN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-N1331	1059538
			NPN	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-E1331	1059537				
Axial, fully	0.03 m	Ø 175 mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRL18S-P233Y	1058207				
flush	7.2 m	(7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18S-F233Y	1058206				
Radial,	0.03 m	Ø 175 mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRL18S-P233W	1058210				
fully flush	7.2 m	(7 m)	PINP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18S-F233W	1058209				

<sup>1)</sup> PL80A.

# GRL18S, plastic

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.	
				1141 1114	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-P1336	1059534	
		PNP	Light switching	Connector M12, 3-pin	Cd-045	GRL18S-P2336	1058192		
A: - 1	0.03 m	Ø 175 mm	PNP	David and taking	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-F1336	1059532	
Axial 7.2 m	(7 m)		Dark-switching	Connector M12, 3-pin	Cd-045	GRL18S-F2336	1059533		
				NPN	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-E1336	1059530
			INPIN	Light switching	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-N1336	1059531	
				Light quitables	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-P1338	1059536	
DII-I	0.03 m	Ø 175 mm	PNP	Light switching	Connector M12, 3-pin	Cd-045	GRL18S-P2338	1058212	
Radial	7.2 m	(7 m)		Dayle awitahing	Cable, 3-wire, 2 m, PVC	Cd-044	GRL18S-F1338	1059535	
				Dark-switching	Connector M12, 3-pin	Cd-045	GRL18S-F2338	1058211	

<sup>1)</sup> PL80A.

# GRL18SG, metal, clear material detection

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- $\bullet$  Adjustment: potentiometer, 270  $^\circ$

Housing design	Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
Axial	0.03 m 7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18SG-F2332	1059555
Axial, fully flush	0.03 m 7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18SG-F233Z	1059556
Radial, fully flush	0.03 m 7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18SG-F233X	1059557

<sup>&</sup>lt;sup>1)</sup> PL80A.

# GRL18SG, plastic, clear material detection

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Adjustment: potentiometer, 270 °

Housing design	Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
Axial 0.03 m 7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18SG-F2337	1059553	
	7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Cable, 3-wire, 2 m	Cd-045	GRL18SG-F1337	1062231
Radial	0.03 m 7.2 m	Ø 175 mm (7 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-045	GRL18SG-F2339	1059554

<sup>1)</sup> PL80A.

# GRSE18S, metal

• Sensor principle: through-beam photoelectric sensor

Housing design	Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
Axial 0 m 15 m		PNP	Light switching	Connector M12, 3-pin	Cd-051	GRSE18S-P2331	1059550	
	Ø 250 mm (10 m)		Dark-switching	Connector M12, 3-pin	Cd-051	GRSE18S-F2331	1059549	
		(10 111)	NPN	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-049	GRSE18S-E1331	1059548
Radial, fully flush 0 m 15 m	Ø 250 mm	DND	Light switching	Connector M12, 3-pin	Cd-051	GRSE18S-P233W	1059552	
	0 III 15 M	(10 m)	PNP	Dark-switching	Connector M12, 3-pin	Cd-051	GRSE18S-F233W	1059551

# GRSE18S, plastic


• Sensor principle: through-beam photoelectric sensor


Housing design	Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				1.4	Cable, 3-wire, 2 m, PVC	Cd-049	GRSE18S-P1336	1059545
Axial 0 m 15 m		54.5	Light switching	Connector M12, 3-pin	Cd-051	GRSE18S-P2336	1058215	
	0 m 15 m	Ø 250 mm (10 m)	PNP	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-049	GRSE18S-F1336	1059544
					Connector M12, 3-pin	Cd-051	GRSE18S-F2336	1058214
			NPN	Dark-switching	Cable, 3-wire, 2 m, PVC	Cd-049	GRSE18S-E1336	1059543
Dodial	0 m 15 m	Ø 250 mm	PNP	Light switching	Connector M12, 3-pin	Cd-051	GRSE18S-P2338	1059547
Radial 0	0111 15111	(10 m)		Dark-switching	Connector M12, 3-pin	Cd-051	GRSE18S-F2338	1059546

# **Dimensional drawings**

Dimensions in mm (inch)


#### **GRTE18S**, metal, connector, axial






- ① Connector M12, 3-pin
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Sensitivity control; Potentiometer 270°
- 6 Fastening nuts (2 x); 24 mm hex, metal


#### GRTE18S, metal, cable, axial






- ① Connection cable 2 m
- ② Threaded mounting hole M18 x 1
- ③ LED indicator yellow
- 4 LED indicator green
- S Sensitivity control; Potentiometer 270°
- 6 Fastening nuts (2 x); 24 mm hex, metal


# GRTE18S, metal, connector, axial, fully flush






- ① Connector M12, 3-pin
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- 5 Sensitivity control; Potentiometer 270°
- 6 Fastening nut; 24 mm hex, metal

# $\textbf{GRTE18S},\,\textbf{metal},\,\textbf{connector},\,\textbf{radial},\,\textbf{fully}\,\,\textbf{flush}$




- ① Connector M12, 3-pin
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- Sensitivity control; Potentiometer 270°
- 6 Fastening nut; 24 mm hex, metal

#### GRTE18S, plastic, cable, axial




- ① Connection cable 2 m
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- Sensitivity control; Potentiometer 270°
- 6 Fastening nut; 22 mm hex, plastic
- 7 Mounting ring

#### **GRTE18S**, plastic, connector, axial




- ① Connector M12, 3-pin
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Sensitivity control; Potentiometer 270°
- **6** Fastening nut; 22 mm hex, plastic
- 7 Mounting ring


#### GRTE18S, plastic, connector, radial



- ① Connector M12, 3-pin
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- LED indicator green
- S Sensitivity control; Potentiometer 270°
- 6 Fastening nut; 22 mm hex, plastic


# GRL18S, GRSE18S, metal, cable, axial






- ① Connection cable 2 m
- ${f 2}$  Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Dummy plug
- 6 Fastening nuts (2 x); 24 mm hex, metal


# GRL18S, GRSE18S, metal, connector, axial






- ① Connector M12, 3-pin
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Dummy plug
- 6 Fastening nuts (2 x); 24 mm hex, metal

#### GRL18S, GRSE18S, metal, connector, axial, fully flush




- ① Connector M12, 3-pin
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Dummy plug
- 6 Fastening nut; 24 mm hex, metal

#### GRL18S, GRSE18S, metal, connector, radial, fully flush




- ① Connector M12, 3-pin
- ② Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Dummy plug
- 6 Fastening nut; 24 mm hex, metal

#### GRL18S, GRSE18S, plastic, cable, axial




- ① Connection cable 2 m
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Fastening nut; 22 mm hex, plastic
- **6** Mounting ring

#### GRL18S, GRSE18S, plastic, connector, axial




- ① Connector M12, 3-pin
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- (5) Fastening nut; 22 mm hex, plastic
- 6 Mounting ring

#### GRL18S, GRSE18S, plastic, cable, radial



- ① Connection cable 2 m
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Fastening nut; 22 mm hex, plastic

#### GRL18S, GRSE18S, plastic, connector, radial




- ① Connector M12, 3-pin
- 2 Threaded mounting hole M18 x 1
- 3 LED indicator yellow
- 4 LED indicator green
- ⑤ Fastening nut; 22 mm hex, plastic

# **Characteristic curves**

#### Black-white shift


#### **GRTE18S, 115 mm**

#### Operating reserve



Distance in mm (inch)

# **GRTE18S, 550 mm**Operating reserve




- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on black, 6 % remission
- ② Sensing range on gray, 20 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 20 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission

# Operating reserve

#### **GRL18S**

#### Operating reserve




Distance in m (feet)

- ① Reflector type PL80A
- 2 Reflector type PL40A
- 3 Reflector type PL20A
- 4 Reflector type P205
- 3 Reflector type PL22-2
- 6 Reflective tape REF-Plus 3436

#### GRSE18S






Distance in m (feet)

# **Bar diagrams**

# **GRTE18S**, **115** mm




Sensing range

Sensing range max.


- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 20 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### **GRTE18S**, 550 mm



- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on black, 6 % remission
- 2 Sensing range on gray, 20 % remission
- 3 Sensing range on white, 90 % remission

#### **GRL18S**



Sensing range Sensing range max.

① Reflector type PL80A 2 Reflector type PL40A


3 Reflector type PL20A

4 Reflector type P205

3 Reflector type PL22-2


6 Reflective tape REF-Plus 3436

#### GRSE18S




# Light spot diameter


# **GRTE18S**, **115** mm




#### **GRTE18S**, 550 mm



**GRL18S** 




GRSE18S



# Response curve


# **GRTE18S, 115 mm**

Parallel operating range y in mm (inch)



#### **GRTE18S**, 550 mm


Parallel operating range y in mm (inch)



Distance x in mm (inch)


#### GRL18S

Parallel operating range y in mm (inch)



#### **GRSE18S**

Parallel operating range y in mm (inch)



- ① Reflector type PL80A
- 2 Reflector type PL40A
- 3 Reflector type PL20A
- 4 Reflector type P205
- S Reflector type PL22-2
- 6 Reflective tape REF-Plus 3436

# **Connection diagram**


#### Cd-044



#### Cd-045




# Cd-049



- ① Sender
- 2 Receiver

# Cd-051



- ① Sender
- ② Receiver

# **Recommended accessories**

# Plug connectors and cables

# Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Cable, open con- ductor heads	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
			5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
100			10 m, 4-wire	IP 67	DOL-1204-G10M	6010543
	Female connector, M12, 4-pin, angled	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
			5 m, 4-wire	IP 67	DOL-1204-W05M	6009867
	, , , , , ,		10 m, 4-wire	IP 67	DOL-1204-W10M	6010541

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

# Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
The second	Male connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	STE-1204-G	6009932
	Male connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	STE-1204-W	6022084

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
O	Steel, zinc coated	Mounting plate for M18 sensors	BEF-WG-M18	5321870	•	•
6		Mounting bracket, M18 thread	BEF-WN-M18	5308446	•	•

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N06 for universal clamp bracket	BEF-KHS-N06	2051612	•	•

# Other mounting accessories

# Others

Figure	Description	Model name	Part no.	GR18S	GR18SG
T()	Mounting tool for "fully flush" variants	BEF-TO-GR18S	4072132	•	•

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812	•	•
C SHIFFE C		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719	•	•
		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314	•	•
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720	•	•
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865	•	•

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843	-	•
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210	-	•
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636	-	•
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844	-	•
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089	-	•
0	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523	-	•
Ø		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060	-	•

# Reflective tape

Figure	Description	Model name	Part no.	GR18S	GR18SG
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030	-	•
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244	•	•

#### Round

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
	PMMA/ABS	Round, screw connection	C110A	5304549	•	•

# **Special reflectors**

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404	-	•
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403	-	•
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405	-	•

# Terminal and alignment brackets

# **Alignment brackets**

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
0	Plastic	Mounting bracket with ball-and-socket	BEF-WN-M18-ST02	5312973	•	•

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.	GR18S	GR18SG
	Plastic (PA12),	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481	•	•
40	glass-fiber rein- forced	Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482	•	•
0	Plastic (PA12)	Integrated adapter	BEF-WN-MH15-1	4039533	•	•
	Stainless steel	Mounting ring	BEF-WN-MH15-2V	4053358	•	•

<sup>→</sup> For additional accessories, please see page L-861















#### **Additional information**

# **Product description**

The stainless steel housing of the MH15V is specifically designed to operate in very harsh environments that use cleaning methods such as HPLV (High Pressure Low Volume), CIP (Clean-In-Place), and SIP (Sterilize-In-Place). Years of research and collaboration with customers in the food and beverage industry perfected the stainless steel housing design of the MH15V. It is designed to withstand chemical cleaning processes, high humidity, and high-pressure cleaning, all in order to reduce downtime

caused by failing sensors in harsh wash down environments.

The MHTB15V's superior resistance to acidic and alkaline cleaning and disinfecting agents is field tested and certified in independent tests by ECOLAB and Johnson Diversey. The 316L stainless steel housing and 3 mm thick flat sensor lens construction also allow for quick and easy, yet thorough, cleaning. This thorough cleaning reduces the risk of dirt build-up, bacteria growth and process contamination.

### At a glance

- · Field-tested resistance to acidic and alkaline cleaning and disinfecting agents
- Corrosion-resistant stainless steel housing 316L, certified by ECOLAB und JohnsonDiversey
- IP 69K-rated housing is resistant to wash down environments
- · Available as complete family including proximity, BGS, retro-reflective and through-beam
- 3 mm chemical resistant sensor lens

#### Your benefits

- Field-tested, compact, stainless steel IP 69K design of the MH15V reduces downtime and replacement costs
- · 3 mm flat, chemically resistant material of the sensor lens offers a long service life, reducing maintenance time and costs
- Reliable object detection, even in difficult environments reduces miscount and increases machine throughput
- Short M18 housing with flush mounting fits in tight areas, which saves machine space
- · ECOLAB and JohnsonDiversey certified MH15V are suitable for hygienic environments, reducing maintenance costs
- · Innovative stainless steel mounting accessories provide fast and low-cost installation

#### www.mysick.com/en/MH15V

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

#### **Features**

	MHTB15V	MHT15V	MHL15V	MHSE15V
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor
Detection principle	Background suppression	Energetic	Standard optics	-
Housing design (light emission)	Cylindrical, straight			
Housing length	52.9 mm			
Thread diameter (housing)	M18 x 1			
Sensing range max.	3 mm 300 mm <sup>1)</sup>	10 mm 350 mm <sup>1)</sup> (depending on type)	0.035 m 5 m <sup>2)</sup>	0 m 5 m
Sensing range	3 mm 300 mm	10 mm 250 mm (depending on type)	0.035 m 3.5 m <sup>2)</sup>	0 m 3.8 m
Type of light	Visible red light	Infrared light	Visible red light	
Light source 3)	PinPoint LED	LED		
Angle of dispersion	-	Approx. 4.5°	Approx. 1.5°	
Wave length	650 nm	950 nm	650 nm	
Adjustment	Potentiometer, 270 °		-	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	MHTB15V	MHT15V	MHL15V	MHSE15V
Supply voltage 1)	10 V DC 30 V DC			
Ripple <sup>2)</sup>	≤ 5 V <sub>pp</sub>			
Power consumption <sup>3)</sup>	≤ 30 mA			
Output type	PNP/NPN (depending	on type)		
Switching mode	Dark-switching/Light sv	witching (depending on t	ype)	
Signal voltage PNP HIGH/LOW	Uv - (< 2,9 V) / ca. 0 V			
Signal voltage NPN HIGH/LOW	Uv / < 2,9 V			
Output current I <sub>max.</sub>	≤ 100 mA <sup>4)</sup>	≤ 100 mA		
Response time 5)	≤ 0.72 ms	≤ 1.25 ms		≤ 1.4 ms
Switching frequency 6)	700 Hz	400 Hz		350 Hz
Connection type 7)	Male connector, M12			
Circuit protection	A <sup>8)</sup> , C <sup>9)</sup> , D <sup>10)</sup>			
Protection class	III			
Weight	50 g			100 g
Polarisation filter	-	-	<b>✓</b>	-
Housing material	Stainless steel V4A (1.4	4404, 316L)		
Optics material	PMMA			
Enclosure rating	IP 67, IP 68, IP 69K			
Ambient operating temperature 11)12)	-25 °C +55 °C			
Ambient storage temperature	-25 °C +70 °C			

<sup>1)</sup> Limit values.

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25  $^{\circ}$  C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>rm 4)}$  Reduced output current at ambient operating temperatures > 50 °C: IAmax = 50 mA.

 $<sup>^{\</sup>rm 5)}\,{\rm Signal}$  transit time with resistive load.

<sup>6)</sup> With light/dark ratio 1:1.

 $<sup>^{7)}\</sup>mbox{ With gold plated contact pins.}$ 

 $<sup>^{\</sup>rm 8)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>9)</sup> C = interference suppression.

 $<sup>^{\</sup>rm 10)}$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{11)}</sup>$  Use at higher ambient temperatures reduce the sender LED lifetime .

<sup>12) +100 °</sup>C for 15 minutes.

# **Ordering information**

Other models available at www.mysick.com/en/MH15V

#### MHTB15V

• Sensor principle: photoelectric proximity sensor

Detection principle: background suppression

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.	
		PNP	Dark-switching	Connector M12, 4-pin	Cd-066	MHTB15-P3267V	1047160	
3 mm	Ø 7 mm	PINP	Light switching	Connector M12, 4-pin	Cd-066	MHTB15-P3367V	1046537	
300 mm	(100 mm)	(100 mm)	NIDNI	Dark-switching	Connector M12, 4-pin	Cd-066	MHTB15-N3267V	1047159
		NPN	Light switching	Connector M12, 4-pin	Cd-066	MHTB15-N3367V	1046536	

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### MHT15V

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.				
		PNP	Dark-switching	Connector M12, 4-pin	Cd-066	MHT15-P3217V	1043805				
10 mm	Ø 20 mm	PNP	Light switching	Connector M12, 4-pin	Cd-066	MHT15-P3317V	1043806				
100 mm	(100 mm)	(100 mm)	(100 mm)	(100 mm)	(100 mm)	NPN	Dark-switching	Connector M12, 4-pin	Cd-066	MHT15-N3217V	1043803
		INPIN	Light switching	Connector M12, 4-pin	Cd-066	MHT15-N3317V	1043804				
		PNP	Dark-switching	Connector M12, 4-pin	Cd-066	MHT15-P3247V	1043810				
10 mm	Ø 50 mm	PNP	Light switching	Connector M12, 4-pin	Cd-066	MHT15-P3347V	1043811				
350 mm	(350 mm)	NIDNI	Dark-switching	Connector M12, 4-pin	Cd-066	MHT15-N3247V	1043808				
		NPN	Light switching	Connector M12, 4-pin	Cd-066	MHT15-N3347V	1043809				

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# MHL15V

• Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.		
		PNP	Dark-switching	Connector M12, 4-pin	Cd-066	MHL15-P3236V	1043814		
0.035 m 5 m	(3.5 m)	PINP	Light switching	Connector M12, 4-pin	Cd-066	MHL15-P3336V	1043815		
0.035 111 5 111		(3.5 m)	(3.5 m)	NPN	Dark-switching	Connector M12, 4-pin	Cd-066	MHL15-N3236V	1043812
		INPIN	Light switching	Connector M12, 4-pin	Cd-066	MHL15-N3336V	1043813		

<sup>1)</sup> PL80A.

#### MHSE15V


• Sensor principle: through-beam photoelectric sensor

Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP	Dark-switching	Connector M12, 4-pin	Cd-057	MHSE15-P3236V	1043818
0 m 5 m	Ø 65 mm (4 m)	NPN	Light switching	Connector M12, 4-pin	Cd-057	MHSE15-P3336V	1043819
0 111 5 111	Ø 65 mm (4 m)		Dark-switching	Connector M12, 4-pin	Cd-057	MHSE15-N3236V	1043816
			Light switching	Connector M12, 4-pin	Cd-057	MHSE15-N3336V	1043817

# **Dimensional drawings**


Dimensions in mm (inch)

#### MHTB15V




- ① Connector M12, 4-pin
- ② Sensing range adjustment: potentiometer, 270°
- $\ensuremath{\mathfrak{G}}$  Status indicator LED, yellow: Status of received light beam
- 4 Optical axis, sender
- ⑤ Optical axis, receiver
- **6** Standard direction of the material being detected

#### MHT15V




- ① Connector M12, 4-pin
- ② Sensitivity adjustment 270  $^{\circ}$
- 4 Optical axis, sender
- ⑤ Optical axis, receiver

#### MHL15V



- ① Connector M12, 4-pin
- 3 Optical axis, sender
- 4 Optical axis, receiver

#### MHSE15V




- ① Connector M12, 4-pin
- 3 Optical axis, sender
- 4 Optical axis, receiver

# **Characteristic curves**


# Black-white shift

#### MHTB15V




- ① Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on white, 90 % remission

#### MHT15V, 100 mm



- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{J}}$  Sensing range on white, 90 % remission


#### MHT15V, 350 mm



- $\ensuremath{\textcircled{1}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on white, 90 % remission


# Operating reserve

# MHL15V




- ① PL80A
- ② P250
- 4 PL50A, PL40A
- 6 PL20A

# MHSE15V




# **Bar diagrams**

#### MHTB15V




- Sensing range Sensing range max.
- ① Sensing range on black, 6 % remission 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### MHT15V, 350 mm




- Sensing range Sensing range max.
- ① Sensing range on gray, 18 % remission ② Sensing range on white, 90 % remission

#### MHT15V, 100 mm



- Sensing range Sensing range max.
- ① Sensing range on black, 6 % remission 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

#### MHL15V



Sensing range Sensing range max.

① PL80A

⑤ PL30A, PL31A

② P250

@ PL20A

3 C110A

⑦ P250 CHEM

4 PL50A, PL40A

**8** PL20 CHEM

# MHSE15V



Sensing range

Sensing range max.

# **Connection diagram**

#### Cd-057

- ① Sender
- 2 Receiver

# Cd-066

# **Recommended accessories**

# Mounting brackets/plates

# **Mounting plates**

Figure	Material	Description	Model name	Part no.
	Chairless at al	Mounting plate for M18 housing	BEF-WG-M18N	5320948
40	Stainless steel	Mounting bracket	BEF-WN-M18N	5320947

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N06N for universal clamp bracket, M18	BEF-KHS-N06N	2051622

# Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	riastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

## Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

# Terminal and alignment brackets

#### **Alignment brackets**

Figure	Material	Description	Model name	Part no.
0	Plastic	Mounting bracket with ball-and-socket	BEF-WN-M18-ST02	5312973

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Plastic (PA12),	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481
glass-fiber rein- forced		Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482
	Stainless steel	Mounting ring	BEF-WN-MH15-2V	4053358

→ For additional accessories, please see page L-861











# **Additional information**

Detailed technical data I-725
Ordering information I-726
Dimensional drawings I-727
Characteristic curves I-727
Bar diagramsI-728
Light spot diameter
Connection diagram I-729
Recommended accessories I-730

# **Product description**

The V18 Laser family of photoelectric sensors offers modern laser technology with a small, highly visible light spot that detects small parts and offers precise sensing. These laser class 1 sensors provide long sensing distances and short response times.

Yellow and green indicator LEDs ensure easy mounting, commissioning, adjustment and maintenance. Sensitivity can be set in several ways - either manually via a teach-in pushbutton or electronically using control input C.

### At a glance

- Laser emitter LED enclosed in a cylindrical M18 housing
- Laser class 1
- · Fast response time
- Straight or right-angle housing
- · Durable metal housing
- IP 67
- Small visible light spot to detect small objects

## **Your benefits**

- Lowest-cost laser sensor in M18 cylindrical housing saves installation costs
- Time-saving installation and alignment with highly visible light spot
- Laser class 1 does not require increased safety measures or markings, reducing installation costs
- Fast response time ensures reliable object detection at high speeds and increases machine throughput

#### → www.mysick.com/en/V18\_Laser

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	VTE18L	VL18L	VSE18L
Sensor principle	Photoelectric proximity sensor	Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Energetic	Standard optics	-
Housing design (light emission)	Cylindrical, straight; cylindrical,	angled (depending on type)	
Housing length	97.7 mm/107.7 mm (dependi	ng on type)	
Thread diameter (housing)	M18 x 1		
Sensing range max.			
Axial	0 mm 400 mm <sup>1)</sup>	0.1 m 35 m <sup>2)</sup>	0 m 60 m
Radial	2 mm 250 mm <sup>1)</sup>	0.1 m 35 m <sup>2)</sup>	0 m 60 m
Sensing range			
Axial	5 mm 300 mm	0.1 m 30 m <sup>2)</sup>	0 m 50 m
Radial	5 mm 200 mm	0.1 m 30 m <sup>2)</sup>	0 m 50 m
Focus 3)		-	
Type of light	Visible red light		
Light source 4)	Laser		
Angle of dispersion	-	0.04°	0.06°
Wave length	650 nm		
Laser class	1 (IEC 60825-1)		
Adjustment	Cable, Single teach-in button		Potentiometer, 270 °

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	VTE18L	VL18L	VSE18L
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	≤ 10 %		
Power consumption 3)	≤ 30 mA	≤ 20 mA	≤ 25 mA
Output type	PNP/NPN (depending on type)		
Switching mode	Light/dark-switching		
Switching mode selector	Selectable via control input C		Selectable via L/D control wire
Output current I <sub>max.</sub>	≤ 100 mA		
Response time 4)	≤ 0.625 ms		≤ 0.5 ms
Switching frequency 5)	800 Hz		1,000 Hz
Angle of reception	-		0.08°
Connection type	Male connector, M12		
Circuit protection	A <sup>6)</sup> , B <sup>7)</sup> , C <sup>8)</sup> , D <sup>9)</sup>		
Protection class	III		
Weight	60 g		120 g
Polarisation filter	-	<b>✓</b>	-
Housing material	Nickel-plated brass/PC		
Optics material	PC with protective glass pane		

<sup>&</sup>lt;sup>2)</sup> P250F.

 $<sup>^{\</sup>scriptsize{\rm 3)}}$  Focused, focus at 100 mm.

 $<sup>^{4)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	VTE18L	VL18L	VSE18L
Enclosure rating	IP 67		
Test input sender off	-		"Test" to 0V
Ambient operating temperature	-15 °C +55 °C		
Ambient storage temperature	-25 °C +70 °C		

<sup>1)</sup> Limit values.

# **Ordering information**

Other models available at www.mysick.com/en/V18\_Laser

#### VTE18L

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

Adjustment: cable, single teach-in button

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
Axial	0 mm	Ø8mm	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-099	VTE18L-4P324	6027418
Axidi	400 mm (300 mm)	(300 mm)	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-099	VTE18L-4N324	6027420
Padial	Radial 2 mm Ø 5 mm 250 mm (200 mm	Ø 5 mm	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-099	VTE18L-4P344	6027422
Naulai		(200 mm)	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-099	VTE18L-4N344	6027424

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### VL18L

Sensor principle: photoelectric retro-reflective sensor

• Detection principle: standard optics

• Adjustment: cable, single teach-in button

Housing design	Sensing range max. <sup>1)</sup>	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.			
		Ø 9 mm	Ø 9 mm (35 mm)	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-099	VL18L-4P324	6027430		
Axial	Axial 0.1 m 35 m ~							PINP	Light switching	Connector M12, 4-pin	Cd-066
		(55)	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-099	VL18L-4N324	6027432			
Dadial	dial 0.4 25	0 9 mm (35 mm)	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-099	VL18L-4P344	6027434			
Radial 0.1 m 35 m	(35 mm)		NPN	Light/dark-switching	Connector M12, 4-pin	Cd-099	VL18L-4N344	6027436			

<sup>&</sup>lt;sup>1)</sup> P250F.

#### VSE18L

• Sensor principle: through-beam photoelectric sensor

• Adjustment: potentiometer, 270 °

Housing design	Sensing range max.	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
Avial	0 m 60 m	Ø 40 mm	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-219	VSE18L-4P324	6027931
Axidi	Axial 0 m 60 m (50 r	(50 mm)	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-219	VSE18L-4N324	6027933
Dodial	- dial 0 00	Ø 40 mm	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-219	VSE18L-4P344	6027935
Radial 0 m 60 m	(50 mm)	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-219	VSE18L-4N344	6027937	

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Without load.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

 $<sup>^{6)}</sup>$  A =  $V_s$  connections reverse-polarity protected.


<sup>&</sup>lt;sup>7)</sup> B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>8)</sup> C = interference suppression.<sup>9)</sup> D = outputs overcurrent and short-circuit protected.

# **Dimensional drawings**


Dimensions in mm (inch)

#### **Axial**



- ① Connector M12, 4-pin
- ② Sensitivity setting; single teach-in button
- $\ensuremath{\mathfrak{G}}$  Green LED indicator:  $\ensuremath{\mathrm{V}}_{\ensuremath{\mathrm{S}}}$  supply voltage feed
- 4 Yellow LED indicator:- lights continuously: Reception signal> reserve factor 2-blinks: Reception signal< reserve factor 2 but > switching threshold 1
- ⑤ Fastening nuts (2 x); width across 24, metal(included with delivery)

#### Radial




- ① Connector M12, 4-pin
- ② Sensitivity setting; single teach-in button
- 3 Green LED indicator: V<sub>S</sub> supply voltage feed
- ④ Yellow LED indicator:- lights continuously: Reception signal > reserve factor 2blinks: Reception signal < reserve factor 2 but > switching threshold 1
- ⑤ Fastening nuts (2 x); width across 24, metal(included with delivery)


## **Characteristic curves**

#### Black-white shift

#### VTE18L, axial




#### VTE18L, radial




## Operating reserve

#### VL18L




- ① P250F
- ③ PL80A
- 4 P250
- 7 Reflective tape Diamond Grade


#### VSE18L



# **Bar diagrams**

#### VTE18L






Sensing range max.


- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission

# VSE18L

Sensing range




#### VL18L




- Sensing range
- Sensing range max.
- ① P250F
- ② PL10F
- 3 PL80A
- 4 P250
- ⑤ C110A
- 6 PL20F
- ? Reflective tape Diamond Grade

# **Light spot diameter**

## VL18L



#### VSE18L




# **Connection diagram**

# Cd-066

## Cd-099

#### Cd-219



- ① Sender
- 2 Receiver

# **Recommended accessories**

# Mounting brackets/plates

#### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
0	Steel, zinc coated	Mounting plate for M18 sensors	BEF-WG-M18	5321870
90	Steel, Zinc coated	Mounting bracket, M18 thread	BEF-WN-M18	5308446

# Plug connectors and cables

## Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867

#### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M12, 4-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-1204-G	6007302
	Female connector, M12, 4-pin, angled	Screw-type termi- nals	PBT	IP 67	DOS-1204-W	6007303

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N06 for universal clamp bracket	BEF-KHS-N06	2051612

#### Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
	DAMAMA /ADC	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Fine triple, screw connection, suitable for laser sensors, 47 mm x 47 mm	P250F	5308843
		Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
9		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523

#### Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

# Terminal and alignment brackets

## **Alignment brackets**

Figure	Material	Description	Model name	Part no.
0	Plastic	Mounting bracket with ball-and-socket	BEF-WN-M18-ST02	5312973

#### **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Plastic (PA12),	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481
RO.	glass-fiber rein- forced	Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482

<sup>→</sup> For additional accessories, please see page L-861

Cylindrical photoelectric sensors with foolproof touch-teach for washdown areas













### **Additional information**

Detailed technical data I-73
Ordering information I-73
Dimensional drawings I-73
Characteristic curves I-73
Bar diagramsI-73
Connection diagram I-73
Recommended accessories I-73

# **Product description**

The V18V has a chemical and pressure cleaning resistant housing for wash down applications and includes patented touch (smart) teach for foolproof operation. These sensors are field-tested and are able to stand up to harsh environments. The sensors offer ease of use in wash down areas due to corrosion resistant and food grade materials, a

wide sensing range and an extended temperature range.

The V18V sensors are certified by ECO-LAB and JohnsonDiversey. Their IP 69K enclosure rating makes them ideal for applications in the food and beverage, pharmaceutical and packaging industries.

## At a glance

- IP 69K-rated cylindrical photoelectric sensors in M18 stainless steel housing
- Resistant to all common cleaning agents and certified by independent institutes
- Extended temperature range: +85° C (long-term), +100°C / 15 min. (shortterm)
- Touch (smart) teach-in adjustment
- · All sensor materials, including the housing, LED and lens are resistant to chemicals
- . IP 69K and IP 68 according to DIN 40050
- · Laser-etched part numbers
- · Ecolab & JohnsonDiversey certified for chemical resistance

### Your benefits

- Simple, time-saving design ensures easy mounting, alignment and replacement
- IP 69K-rated stainless steel housing has a long service life that withstands wash down environments, reducing maintenance time and costs
- Unique touch-teach feature and lock/ unlock functionality allow users to control who can change the sensor setting, which reduces the chances of disturbing a proven process and saves commissioning and maintenance time
- Laser-etched part numbers ensures the part numbers will not be washed off, saving maintenance time

#### www.mysick.com/en/V18V

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	VTB18V	VTF18V	VTE18V	VL18V	VS/VE18V	
Sensor principle	Photoelectric proxi	Photoelectric proximity sensor			Through-beam photoelectric sensor	
Detection principle	Background sup- pression	Energetic		Standard optics	-	
Housing design (light emission)	Cylindrical, straigh	t				
Housing length	83 mm					
Thread diameter (housing)	M18 x 1					
Sensing range max.	0 mm 140 mm <sup>1)</sup>	0 mm 110 mm <sup>1)</sup>	0 mm 900 mm <sup>1)</sup> (depending on type)	0.035 m 5 m <sup>2)</sup> (depending on type)	0 m 20 m	
Sensing range	0 mm 130 mm	5 mm 100 mm	5 mm 800 mm (de- pending on type)	0.035 m 4.5 m <sup>2)</sup> (depending on type)	0 m 18 m	
Type of light	Visible red light		Infrared light	Visible red light	Infrared light	
Light source 3)	LED	LED				
Wave length	660 nm	660 nm 880 nm		660 nm	880 nm	
Adjustment	Single teach-in but	tton		-		

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	VTB18V	VTF18V	VTE18V	VL18V	VS/VE18V
Supply voltage 1)	10 V DC 30 V D	C			
Ripple <sup>2)</sup>	≤ 10 %				
Power consumption 3)	≤ 50 mA	≤ 35 mA			-
Power consumption, sender	-				35 mA <sup>3)</sup>
Power consumption, receiver	-				40 mA <sup>3)</sup>
Output type	PNP, open collecto	or/NPN, open collec	tor (depending on t	ype)	
Switching mode	Light/dark-switchi	ng (selectable via L	/D control wire)		
Signal voltage PNP HIGH/LOW	Approx. VS - 2.0 V	// 0 V			
Signal voltage NPN HIGH/LOW	Approx. VS / < 2.0	V			
Output current I <sub>max.</sub>	≤ 100 mA				
Response time 4)	≤ 0.5 ms	≤ 1 ms			≤ 2 ms
Switching frequency 5)	1,000 Hz	500 Hz	± 500 Hz	500 Hz	250 Hz
Angle of reception	-				8°
Attenuation along light beam	-			≥ 20 %	
Attenuation difference along light beam	-			≥ 15 %	-
Attenuation difference of object	-			≥ 7.5 %	
Connection type <sup>6)</sup>	Male connector, M	112			
Circuit protection	A <sup>7)</sup> , B <sup>8)</sup> , C <sup>9)</sup> , D <sup>10)</sup>				
Protection class	III				
Weight	120 g				240 g
Polarisation filter	-			-/ ✔ (depending on type)	-
Housing material	Stainless steel V4	A (1.4404, 316L)			

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>rm 3)}$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

	VTB18V	VTF18V	VTE18V	VL18V	VS/VE18V
Optics material	Plan, PPS (Grilamic	)		Plan, PPS (Grilamid), Plan, PMMA, surface hardened and te- mered (depend- ing on type)	Plan, PPS (Grilamid)
Enclosure rating <sup>11)</sup>	IP 67, IP 68, IP 69				
Test input sender off	-				"Test" to 0V
Ambient operating temperature	-25 °C +80 °C	2)			
Ambient storage temperature	-40 °C +80 °C				

<sup>1)</sup> Limit values.

# **Ordering information**

Other models available at www.mysick.com/en/V18V

#### VTB18V

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

Sensing range max. 1)	Light spot size (distance)	Adjustment	Output type	Connection diagram	Model name	Part no.
0 110	Ø 15 mans (120 mans)	Single teach-in	PNP	Cd-087	VTB18-4P1240V	6035493
0 mm 140 mm	Ø 15 mm (130 mm)	button	NPN	Cd-087	VTB18-4N1240V	6035494

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### VTF18V

- Sensor principle: photoelectric proximity sensor
- Detection principle: energetic
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

	Sensing range max. 1)	Light spot size (distance)	Adjustment	Output type	Connection diagram	Model name	Part no.
	0 mm 110 mm	Ø 45 mm (400 mm)	Single teach-in	PNP	Cd-087	VTF18-4P1240V	6035487
		Ø 15 mm (100 mm)	button	NPN	Cd-087	VTF18-4N1240V	6035488

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

#### VTE18V

- Sensor principle: photoelectric proximity sensor
- Detection principle: energetic
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

Sensing range max. 1)	Light spot size (distance)	Adjustment	Output type	Connection diagram	Model name	Part no.
0 70 70 450 70 70	50 mm Ø 60 mm (400 mm) Single teach-in button	PNP	Cd-087	VTE18-4P4240V	6035489	
0 mm 450 mm		button	NPN	Cd-087	VTE18-4N4240V	6035490
0 mm 900 mm	Ø 100 mm (800 mm)	Single teach-in button	PNP	Cd-087	VTE18-4P8240V	6035491
			NPN	Cd-087	VTE18-4N8240V	6035492

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{S}$  tolerances.

<sup>3)</sup> Without load, at VS 30 V DC.

<sup>4)</sup> Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> With gold plated contact pins, PPS with FDA certificate.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>8)</sup> B = interference suppression.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{10)}</sup>$  D = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>11)</sup> With correct mounted IP 69K connector.

<sup>12) +100 °</sup>C at max 15 minutes.

#### VL18V, clear material detection

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

Sensing range max. 1)	Light spot size (distance)	Output type	Connection diagram	Model name	Part no.	
0.005 4.5	Ø CO mana (4 ma)	PNP	Cd-087	VL18-4P2240V	6035497	
0.035 m 4.5 m	Ø 60 mm (1 m)	NPN	Cd-087	VL18-4N2240V	6035498	

<sup>1)</sup> PL80A.

#### VL18V

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

Sensing range max. 1)	Light spot size (distance)	Output type	Connection diagram	Model name	Part no.
0.4 5	(4.500	PNP	Cd-087	VL18-4P3140V	6035495
0.1 m 5 m	Ø 200 mm (4.5 m)	NPN	Cd-087	VL18-4N3140V	6035496

<sup>1)</sup> PL80A.

## VS/VE18V


- Sensor principle: through-beam photoelectric sensor
- Switching mode: light/dark-switching
- Connection: connector M12, 4-pin PPS (Griamid)

Sensing range max.	Light spot size (distance)	Output type	Connection diagram	Model name	Part no.
0 m 20 m	Ø COO (4.5)	PNP	Cd-219	VS/VE18-4P3140V	6035499
	Ø 600 mm (15 m)	NPN	Cd-219	VS/VE18-4N3140V	6035500

# **Dimensional drawings**


Dimensions in mm (inch)

#### VTB18V




- ① Connector M12, 4-pin
- $\hbox{ \ensuremath{@} 2 Sensing range adjustment: Touch-Teach-In}$
- $\ensuremath{\mathfrak{G}}$  Status indicator LED, green: signalizing Touch-Teach-in
- ④ Status indicator LED, yellow: Status of received light beam
- ⑤ Fastening nuts (2 x); width across 24, stainless steel
- **6** Standard direction of the material being detected

#### VL18V, VSE18V



- ① Connector M12, 4-pin
- 2 Yellow LED indicator:
  - lights continuously: Reception signal> reserve factor 2
  - blinks: Reception signal < reserve factor 2 but > switching threshold 1
- 3 Fastening nuts (2 x); width across 24, stainless steel

#### VTF18V, VTE18V




- ① Connector M12, 4-pin
- 2 Sensing range adjustment: Touch-Teach-In
- ③ Status indicator LED, green: signalizing Touch-Teach-in
- 4 Yellow LED indicator:
  - lights continuously: Reception signal> reserve factor 2
  - blinks: Reception signal < reserve factor 2 but > switching threshold 1  $\,$
- ⑤ Fastening nuts (2 x); width across 24, stainless steel

# **Characteristic curves**


#### Black-white shift

#### VTB18V




- ① Sensing range on black, 6 % remission
- $\ensuremath{\mathfrak{D}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on white, 90 % remission

#### VTF18V



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission


#### VTE18V, 450 mm



- 1 Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission


## Operating reserve

#### VL18V, clear material detection




① PL80A

#### VTE18V, 900 mm




- ① Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission

#### VL18V




- ① PL80A
- ② C110A
- ⑤ P250 CHEM

#### VS/VE18V



## **Bar diagrams**

#### VTF18V




- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission

#### VTE18V, 900 mm




- ① Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission

## VS/VE18V




#### VTE18V, 450 mm



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission

#### VL18V




- Sensing range Sensing range max.
- ① PL80A
- ② C110A
- $\ensuremath{\mathfrak{G}} \ensuremath{\operatorname{Reflective}} \ensuremath{\operatorname{tape}} \ensuremath{\operatorname{Diamond}} \ensuremath{\operatorname{Grade}}$

# **Connection diagram**

#### Cd-087



#### Cd-219



- ① Sender
- 2 Receiver

# **Recommended accessories**

# Mounting brackets/plates

## **Mounting plates**

Figure	Material	Description	Model name	Part no.
	Stainless steel	Mounting plate for M18 housing	BEF-WG-M18N	5320948
40	Starriess steer	Mounting bracket	BEF-WN-M18N	5320947

## Plug connectors and cables

#### Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
11	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
1	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

## Universal bar clamp systems

Figure	Material	Description	Model name	Part no.	
6	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N06N for universal clamp bracket, M18	BEF-KHS-N06N	2051622	

## Reflectors

## Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	riastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## **Special reflectors**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm		PL40B-CHEM	5326088
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

# Terminal and alignment brackets

## **Alignment brackets**

Figure	Material	Description	Model name	Part no.
0	Plastic	Mounting bracket with ball-and-socket	BEF-WN-M18-ST02	5312973

## **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Plastic (PA12),	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481 2051482
401	glass-fiber rein- forced	Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482
	Stainless steel	Mounting ring	BEF-WN-MH15-2V	4053358

<sup>→</sup> For additional accessories, please see page L-861











## **Additional information**

Detailed technical data I-743
Ordering information I-745
Dimensional drawings I-751
Adjustments I-756
Characteristic curves I-757
Bar diagramsI-760
Light spot diameter I-761
Connection diagram I-762
Recommended accessories I-762

# **Product description**

The V180-2 sensors are designed to provide the longest sensing range for proximity sensors. These low-cost cylindrical sensors are easy to use, easy to install and maintain saving installation time and maintenance costs. The V180-2 is available in either a plastic or metal housing. The bright red LED makes these sensors easy to align and set up, offering time-saving installation. Plus,

the indication LEDs provide continuous signal strength information for quick and simple troubleshooting.

The V180-2 provides an economical solution for universal applications, such as product detection and machine positioning in packaging, general manufacturing automation, material handling and warehousing systems.

### At a glance

- Low-cost M18 housing sensor on the market
- Long sensing distances: 100 mm, 400 mm, 800 mm (proximity sensor), 300 mm (proximity sensor with BGS), 6 m (retro-reflective sensor) and 20 m (through-beam sensor)
- Bright power and signal LEDs with 360° visibility
- Wide product portfolio solves a broad range of applications
- High switching frequencies up to 1000 Hz
- Available in a metal housing for applications in harsh environments
- Optical axis selectively axial or radial (90°)

#### Your benefits

- Low-cost M18 cylindrical sensor on the market reduces installation costs
- Bright red sender LED simplifies alignment and saves installation time
- Bright power and signal LEDs with 360° visibility offer quick and simple troubleshooting, reducing maintenance time and costs
- The flat and smooth lens reduces the collection of dust and dirt, ensuring safe operation with less maintenance and fewer costs

#### → www.mysick.com/en/V180-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

## **Features**

	VTB180-2	VTF180-2	VTE180-2	VL180-2	VSE180-2
Sensor principle	Photoelectric prox	Photoelectric proximity sensor		Photoelectric retro-reflective sensor	Through-beam photoelectric sensor
Detection principle	Background sup- pression	Background blanking	Background blanking/ener- getic (depending on type)	Standard optics	-
Housing design (light emission)	Axial	Axial/radial (depe	nding on type)		
Thread diameter (housing)	M18 x 1				
Sensing range max.					
Axia	10 mm 350 mm <sup>1)</sup>	1 mm 140 mm <sup>1)</sup>	$1 \text{ mm}$ $1,100 \text{ mm}^{-1}$ (depending on type)	0.05 m 7 m <sup>2)</sup>	0 m 28 m
Radia	-	1 mm 130 mm <sup>1)</sup>	1 mm 900 mm <sup>1)</sup> (depending on type)	0.05 m 5.5 m <sup>2)</sup>	0 m 25 m
Sensing range					
Axia	30 mm 200 mm <sup>1)</sup>	1 mm 100 mm <sup>1)</sup>	1 mm 800 mm <sup>1)</sup> (depending on type)	0.05 m 6 m <sup>2)</sup>	0 m 20 m
Radia	-	1 mm 100 mm <sup>1)</sup>	1 mm 650 mm <sup>1)</sup> (depending on type)	0.05 m 4.5 m <sup>2)</sup>	0 m 19 m
Focus	-	<b>✓</b> 3)4)	-		
Type of light	Visible red light				
Light source 5)	LED				
Wave length	632 nm	m 645 nm			
Adjustment	Potentiometer, 4 turns	neter, Potentiometer, 270 °			Potentiometer, 270 ° <sup>6)</sup>

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	VTB180-2	VTF180-2	VTE180-2	VL180-2	VSE180-2	
Supply voltage 1)	10 V DC 30 V DC					
Ripple <sup>2)</sup>	± 10 %					
Current consumption 3)	≤ 35 mA	≤ 30 mA			-	
Current consumption, sender	-				20 mA <sup>3)</sup>	
Current consumption, receiver	-				15 mA <sup>3)</sup>	
Output type	PNP, open collector <sup>4)</sup> /NPN, open collector <sup>5)</sup> (depending on type)					
Switching mode	Light-switching 4)/o	dark-switching/Light	/dark-switching 5) (d	depending on type)		
Switching mode selector	Selectable via L/D	electable via L/D control wire				
Signal voltage PNP HIGH/LOW	Approx. V <sub>S</sub> - 1.8 V / 0 V					
Signal voltage NPN HIGH/LOW	Approx. $V_S / < 1.8$	V				
Output current I <sub>max.</sub>	≤ 100 mA					
Response time 6)	≤ 1 ms ≤ 0.5 ms					
Switching frequency 7)	≤ 500 Hz 1,000 Hz					

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{\</sup>scriptscriptstyle{(3)}}$  Focused approx. 7 mm at 60 mm distance.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Focused, focus approx. 7 mm at 60 mm .

 $<sup>^{5)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

<sup>6)</sup> Receiver.

	VTB180-2	VTF180-2	VTE180-2	VL180-2	VSE180-2
Connection type	Cable, 2 m 8)/Male connector, M12 (depending on type)				
Circuit protection	A $^{9)}$ , B $^{10)}$ , D $^{11)}$				
Protection class	III				
Weight					
Plastic, cable	62 g				124 g
Plastic, connector	18 g				36 g
Metal, cable	95 g				190 g
Metal, connector	47 g				94 g
Polarisation filter	-			V	-
Housing material					
Plastic	PBT/PC				
Metal	Nickel-plated brass	and PC			
Optics material	PMMA				
Enclosure rating	IP 67				
Items supplied	Fastening nuts (2 x	()		Reflector P250, fastening nuts (2 x), Reflector P250 (depend- ing on type)	Fastening nuts (4 x)
Ambient operating temperature	-25 °C +55 °C				
Ambient storage temperature	-40 °C +70 °C				

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

#### Selection aid

Sensor principle	Sensing range max.	Housing material	Model name	Page
	10 mm 350 mm	Metal	VTB180-2, metal	I-745
	10 111111 550 111111	Plastic	VTB180-2, plastic	I-745
	1 mm 140 mm	Metal	VTF180-2, metal	I-746
Photoclostric provimity concor	1 11111 140 11111	Plastic	VTF180-2, plastic	I-746
Filotoelectric proximity sensor	1 mm 500 mm	Metal	VTE180-2, metal, mid range	I-747
	1 mm 500 mm	Plastic	VTE180-2, plastic, mid range	I-747
	1 mm 1100 mm	Metal	VTE180-2, Metal, long range	I-748
		Plastic	VTE180-2, plastic, long range	I-748
Dhata alastria ratra raflectiva canaar	0.05 m 7 m	Metal	VL180-2, metal	I-749
Photoelectric retro-reflective sensor	0,05 III 7 III	Plastic	VL180-2, plastic	I-749
Through beam photoglostric conser	0 m 28 m	Metal	VSE180-2, metal	I-750
Photoelectric proximity sensor  Photoelectric retro-reflective sensor  Through-beam photoelectric sensor	0 111 20 111	Plastic	VSE180-2, plastic	I-750

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Control wire open: dark-switching D.ON.

 $<sup>^{\</sup>rm 5)}$  Control wire open: light-switching L.ON.

<sup>&</sup>lt;sup>6)</sup> Signal transit time with resistive load.

<sup>7)</sup> With light/dark ratio 1:1.

 $<sup>^{8)}</sup>$  Do not bend below 0 °C.

 $<sup>^{9)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>10)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{11)}</sup>$  D = outputs overcurrent and short-circuit protected.

# **Ordering information**

Other models available at www.mysick.com/en/V180-2

## VTB180-2, metal

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Adjustment: potentiometer, 4 turns

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light (dork owitching 2)	Cable, 4-wire 2 m	Cd-089	VTB180-2P41112	6043869
			PNP	Light/dark-switching 2)	Connector M12, 4-pin	Cd-087	VTB180-2P42412	6043870
10 mm 350 mm	Ø 15 mm (300 mm)	Axial	xial	Light switching	Connector M12, 4-pin	Cd-066	VTB180-2F32412	6044019
	,		NIDNI	Light (doub out to bing 3)	Cable, 4-wire 2 m	Cd-089	VTB180-2N41112	6043867
			NPN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTB180-2N42412	6043868

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# VTB180-2, plastic

• Sensor principle: photoelectric proximity sensor

• Detection principle: background suppression

• Adjustment: potentiometer, 4 turns

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				1:4.71 1	Cable, 4-wire 2 m	Cd-089	VTB180-2P41117	6043873
			PNP	Light/dark-switching 1)	Connector M12, 4-pin	Cd-087	VTB180-2P42417	6043874
10 mm 350 mm	Ø 15 mm (300 mm)	Axial		Light switching	Connector M12, 4-pin	Cd-066	VTB180-2F32417	6044020
(30	(,		NPN	Light/dark-switching <sup>2)</sup>	Cable, 4-wire 2 m	Cd-089	VTB180-2N41117	6043871
	(300 mm)				Connector M12, 4-pin	Cd-087	VTB180-2N42417	6043872

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

<sup>1)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>2)</sup> Control wire open: light-switching L.ON.

<sup>1)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>2)</sup> Control wire open: light-switching L.ON.

# VTF180-2, metal

• Sensor principle: photoelectric proximity sensor

• Detection principle: background blanking

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light (doub out to bing 2)	Cable, 4-wire 2 m	Cd-089	VTF180-2P41114	6043805
			PNP	Light/dark-switching <sup>2)</sup>	Connector M12, 4-pin	Cd-087	VTF180-2P42414	6043806
	Ø 8 mm (100 mm)	Radial		Light switching	Connector M12, 3-pin	Cd-066	VTF180-2F32414	6044023
	,		NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTF180-2N41114	6043803
			INFIN	Lighty dank Switching	Connector M12, 4-pin	Cd-087	VTF180-2N42414	6043804
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTF180-2P41112	6041802
			PNP	Light/dark-switching -/	Connector M12, 4-pin	Cd-087	VTF180-2P42412	6041803
1 mm 140 mm	Ø 8 mm (100 mm)	Axial		Light switching	Connector M12, 3-pin	Cd-066	VTF180-2F32412	6044021
	, ,		NPN	Light (dark cwitching 3)	Cable, 4-wire 2 m	Cd-089	VTF180-2N41112	6041799
			INPIN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTF180-2N42412	6041801

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## VTF180-2, plastic

• Sensor principle: photoelectric proximity sensor

Detection principle: background blanking

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light/dark-switching <sup>2)</sup>	Cable, 4-wire 2 m	Cd-089	VTF180-2P41119	6043810
			PNP	Light/dark-switching -/	Connector M12, 4-pin	Cd-087	VTF180-2P42419	6043811
1 mm 130 mm	Ø 8 mm (100 mm)	Radial		Light switching	Connector M12, 4-pin	Cd-066	VTF180-2F32419	6044024
			NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTF180-2N41119	6043807
			INFIN	Lighty dank owntoning	Connector M12, 4-pin	Cd-087	VTF180-2N42419	6043808
				Light (dark awitching 2)	Cable, 4-wire 2 m	Cd-089	VTF180-2P41117	6037479
			PNP	Light/dark-switching <sup>2)</sup>	Connector M12, 4-pin	Cd-087	VTF180-2P42417	6037480
1 mm 140 mm	Ø 8 mm (100 mm)	Axial		Light switching	Connector M12, 3-pin	Cd-066	VTF180-2F32417	6044022
110 111111	,		NPN	Light (dark awitching 3)	Cable, 4-wire 2 m	Cd-089	VTF180-2N41117	6037477
			INPIN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTF180-2N42417	6037478

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

<sup>&</sup>lt;sup>2)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

# VTE180-2, metal, mid range

- Sensor principle: photoelectric proximity sensor
- Detection principle: background blanking
- Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light (dark awitching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41142	6041806
			PNP	Light/dark-switching <sup>2)</sup>	Connector M12, 4-pin	Cd-087	VTE180-2P42442	6041807
1 mm 500 mm	Ø 20 mm (400 mm)	Axial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2F32342	2442 6041807 2342 6042576 1142 6041805 1144 6043814 2444 6043815 2444 6043812
	, ,		NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41142	6041804
			INFIN	Lighty dark Switching	Connector M12, 4-pin	Cd-087	VTE180-2N42442	6041805
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41144	6043814
			PNP	Lighty dark-switching	Connector M12, 4-pin	Cd-087	VTE180-2P42444	6043815
1 mm 450 mm	Ø 20 mm (400 mm)	Radial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2F32444	6044025
	,		NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41144	6043812
			INPIN	Light/dark-Switching	Connector M12, 4-pin	Cd-087	VTE180-2N42444	6043813

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## VTE180-2, plastic, mid range

- Sensor principle: photoelectric proximity sensor
- Detection principle: background blanking
- Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light/dark-switching <sup>2)</sup>	Cable, 4-wire 2 m	Cd-089	VTE180-2P41147	6037483
			PNP	Light/dark-switching -/	Connector M12, 4-pin	Cd-087	VTE180-2P42447	6037484
1 mm 500 mm	Ø 20 mm (400 mm)	Axial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2P32447	6043946
	, ,		NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41147	6037481
			INFIN	Lighty dank Switching	Connector M12, 4-pin	Cd-087	VTE180-2N42447	6037482
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41149	6043818
			PNP	Lighty dark-switching -/	Connector M12, 4-pin	Cd-087	VTE180-2P42449	6043819
1 mm 450 mm	Ø 20 mm (400 mm)	Radial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2F32449	6044026
.00	,		NDN	Light (dark awitching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41149	6043816
	(400 mm) Ø 20 mm		NPN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTE180-2N42449	6043817

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

 $<sup>^{\</sup>rm 2)}$  Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

# VTE180-2, metal, long range

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light (doub out to bing 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41182	6041810
			PNP	Light/dark-switching <sup>2)</sup>	Connector M12, 4-pin	Cd-087	VTE180-2P42482	6041811
	Ø 30 mm (800 mm)	Axial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2P32482	6043945
	,		NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41182	6041808
			INFIN	Lighty dank Switching	Connector M12, 4-pin	Cd-087	VTE180-2N42482	6041809
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41184	6043822
			PNP	Light/dark-switching -/	Connector M12, 4-pin	Cd-087	VTE180-2P42484	6043823
1 mm 900 mm	Ø 30 mm (800 mm)	Radial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2F32484	6044028
	, ,		NPN	Light (dark cwitching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41184	6043820
			INPIN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTE180-2N42484	6043821

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## VTE180-2, plastic, long range

• Sensor principle: photoelectric proximity sensor

• Detection principle: energetic

• Adjustment: potentiometer, 270 °

Sensing range max. <sup>1)</sup>	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41189	6043826
			PNP	Lighty dark-switching	Connector M12, 4-pin	Cd-087	VTE180-2P42489	6043827
	Ø 30 mm (800 mm)	Radial		Light switching	Connector M12, 3-pin	Cd-066	VTE180-2F32489	6044029
			NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41189	6043824
			INFIN	Lighty dank Switching	Connector M12, 4-pin	Cd-087	VTE180-2N42489	6043825
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VTE180-2P41187	6037487
			PNP	Light/dark-switching -/	Connector M12, 4-pin	Cd-087	VTE180-2P42487	6037488
1 mm 1,100 mm	Ø 30 mm (800 mm)	Axial		Light switching 2)	Connector M12, 3-pin	Cd-066	VTE180-2F32487	6044027
1,100 111111	,		NPN	Light (dark awitching 3)	Cable, 4-wire 2 m	Cd-089	VTE180-2N41187	6037485
			INPIN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VTE180-2N42487	6037486

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

<sup>&</sup>lt;sup>2)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

# VL180-2, metal

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
				Light switching	Connector M12, 4-pin	Cd-066	VL180-2F32331	6043458
			PNP	Light (dork owitching 2)	Cable, 4-wire 2 m	Cd-089	VL180-2P41131	6041818
	Ø 400 mm	Axial	PINP	Light/dark-switching 2)	Connector M12, 4-pin	Cd-087	VL180-2P42431	6041819
0.05 m 7 m	(6 m)	Axiai		Dark-switching	Connector M12, 4-pin	Cd-066	VL180-2P32431	6044030
			NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VL180-2N41131	6041816
			INPIN	Lighty dark-switching 47	Connector M12, 4-pin	Cd-087	VL180-2N42431	6041817
				Light (dark awitching 2)	Cable, 4-wire 2 m	Cd-089	VL180-2P41133	6043832
0.05 m 5.5 m	Ø 270 mm	Radial	PNP	Light/dark-switching 2)	Connector M12, 4-pin	Cd-087	VL180-2P42433	6043834
	(4 m)	naulai		Dark-switching	Connector M12, 3-pin	Cd-066	VL180-2P32433	6044032
			NPN	Light/dark-switching 3)	Connector M12, 4-pin	Cd-087	VL180-2N42433	6043830

<sup>&</sup>lt;sup>1)</sup> PL80A.

## VL180-2, plastic

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Adjustment: potentiometer, 270 °

Sensing range max. 1)	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			PNP	Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VL180-2P41136	6037495
0.05 m 7 m	Ø 400 mm	Axial	FINE	Lighty dark-switching	Connector M12, 4-pin	Cd-087	VL180-2P42436	6037496
	(6 m)	Axiai	NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VL180-2N41136	6037493
			INFIN	Lighty dark-switching	Connector M12, 4-pin	Cd-087	VL180-2N42436	6037494
				Light/dark-switching 2)	Cable, 4-wire 2 m	Cd-089	VL180-2P41138	6043837
			PNP	Lighty dark-switching	Connector M12, 4-pin	Cd-087	VL180-2P42438	6043838
0.05 m 5.5 m	Ø 270 mm (4 m)	Radial		Dark-switching	Connector M12, 3-pin	Cd-066	VL180-2P32438	6044033
0.0			NPN	Light/dark-switching 3)	Cable, 4-wire 2 m	Cd-089	VL180-2N41138	6043835
			INFIN	Lighty dark-Switching	Connector M12, 4-pin	Cd-087	VL180-2N42438	6043836

<sup>1)</sup> PL80A.

<sup>&</sup>lt;sup>2)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>3)</sup> Control wire open: light-switching L.ON.

 $<sup>^{\</sup>rm 2)}$  Control wire open: dark-switching D.ON.

 $<sup>^{\</sup>scriptscriptstyle{(3)}}$  Control wire open: light-switching L.ON.

# VSE180-2, metal

- Sensor principle: through-beam photoelectric sensor
- Adjustment: potentiometer, 270 ° (Receiver.)

Sensing range max.	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			PNP	Light/dark-switching 1)	Cable, 4-wire 2 m	Cd-058	VSE180-2P41132	6041822
0 m 28 m	Ø 1,100 mm	Avial	PINP	Light/dark-switching -	Connector M12, 4-pin	Cd-060	VSE180-2P42432	6041823
	(20 m)	Axial	NPN	Light/dark-switching <sup>2)</sup>	Cable, 4-wire 2 m	Cd-058	VSE180-2N41132	6041820
			INPIN	Light/dark-switching -/	Connector M12, 4-pin	Cd-060	VSE180-2N42432	6041821
				Light (doub out to bing 1)	Cable, 4-wire 2 m	Cd-058	VSE180-2P41134	6043849
			PNP	Light/dark-switching 1)	Connector M12, 4-pin	Cd-060	VSE180-2P42434	6043850
0 m 25 m	Ø 1,100 mm (20 m)	Radial		Dark-switching	Connector M12, 3-pin	Cd-057	VSE180-2P32434	6044036
	, ,		NIDNI	Light (doub out to bing 2)	Cable, 4-wire 2 m	Cd-058	VSE180-2N41134	6043847
			NPN	Light/dark-switching <sup>2)</sup>	Connector M12, 4-pin	Cd-060	VSE180-2N42434	6043848

<sup>1)</sup> Control wire open: dark-switching D.ON.

## VSE180-2, plastic

- Sensor principle: through-beam photoelectric sensor
- Adjustment: potentiometer, 270 ° (Receiver.)

Sensing range max.	Light spot size (distance)	Optical axis	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			PNP	Light (doub, puritable per 1)	Cable, 4-wire 2 m	Cd-058	VSE180-2P41137	6037499
0 m 28 m	Ø 1,100 mm	Avial	PNP	Light/dark-switching 1)	Connector M12, 4-pin	Cd-060	VSE180-2P42437	6037500
	(20 m)	Axial	NIDNI	Light (doubt out to bing 2)	Cable, 4-wire 2 m	Cd-058	VSE180-2N41137	6037497
			NPN	Light/dark-switching 2)	Connector M12, 4-pin	Cd-060	VSE180-2N42437	6037498
				Light (doub out to bing 1)	Cable, 4-wire 2 m	Cd-058	VSE180-2P41139	6043853
			PNP	Light/dark-switching 1)	Connector M12, 4-pin	Cd-060	VSE180-2P42439	6043854
0 m 25 m	Ø 1,100 mm (20 m)	Radial		Dark-switching	Connector M12, 3-pin	Cd-057	VSE180-2P32439	6044037
	, ,		NIDNI	Light (doubt out to bing 2)	Cable, 4-wire 2 m	Cd-058	VSE180-2N41139	6043851
			NPN	Light/dark-switching 2)	Connector M12, 4-pin	Cd-060	VSE180-2N42439	6043852

<sup>1)</sup> Control wire open: dark-switching D.ON.

<sup>&</sup>lt;sup>2)</sup> Control wire open: light-switching L.ON.


 $<sup>^{\</sup>rm 2)}$  Control wire open: light-switching L.ON.

# **Dimensional drawings**

Dimensions in mm (inch)


#### VTF180-2, VTE180-2, VTB180-2, metal, axial


## 62.5 (2.46) 2 (0.08) 60.5 (2.38) 56.8 (2.24) 41.8 (1.65) 24 34 (1.34) 2 (0.08) (0.94)Ø 16.6 (0.65) 4 (0.16)69.8 (2.75) 9.3 60.5 (2.38) (0.37)



- ① Connector M12, 4-pin
- ② Connection cable 2 m
- 3 Sensitivity adjustment 270°
- 4 LED indicator orange: switching output active
- ⑤ LED indicator green: strength indicator
- 7 Fastening nuts (2 x); 24 mm hex, metal


#### VTF180-2, VTE180-2, VTB180-2, plastic, axial






- ① Connector M12, 4-pin
- 2 Connection cable 2 m
- 3 Sensitivity control (potentiometer, 270°)
- 4 LED indicator orange: switching output active
- ⑤ LED indicator green: strength indicator
- 6 Fastening nuts (2 x); width across 22, PC

#### VTF180-2, VTE180-2, metal, radial




- ① Connector M12, 3-pin / Connector M12, 3-pin
- ② Connection cable 2 m
- 4 LED indicator orange: switching output active
- \$ LED indicator green, stability indicator: LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 7 Metal housing, fastening nuts (2 x); width across 24


#### VTF180-2, VTE180-2, plastic, radial



- ① Connector M12
- ② Connection cable 2 m
- $\ensuremath{\mathfrak{3}}$  Sensitivity control; Potentiometer 270  $^\circ$
- 4 LED indicator orange: switching output active
- $\c$  LED indicator green, stability indicator: LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 6 Fastening nuts (2 x); width across 22, PC


#### VL180-2, metal, axial






- ① Connector M12, 4-pin
- 2 Connection cable 2 m
- $\ensuremath{\mathfrak{3}}$  Sensitivity adjustment 270°
- $\ensuremath{\textcircled{4}}$  LED indicator orange: switching output active
- ⑤ LED indicator green: strength indicator
- 7 Fastening nuts (2 x); 24 mm hex, metal


#### VL180-2, metal, radial






- ① Connector M12, 3-pin / Connector M12, 3-pin
- ② Connection cable 2 m
- 3 Sensitivity control; Potentiometer 270°
- 4 LED indicator orange: switching output active
- \$ LED indicator green, stability indicator: LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 7 Metal housing, fastening nuts (2 x); width across 24


#### VL180-2, plastic, axial






- ① Connector M12, 4-pin
- 2 Connection cable 2 m
- 3 Sensitivity control (potentiometer, 270°)
- ④ LED indicator orange: switching output active
- ⑤ LED indicator green: strength indicator
- 6 Fastening nuts (2 x); width across 22, PC

#### VL180-2, plastic, radial




- ① Connector M12
- 2 Connection cable 2 m
- ③ Sensitivity control; Potentiometer 270°
- 4 LED indicator orange: switching output active
- $\$  LED indicator green, stability indicator: LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 6 Fastening nuts (2 x); width across 22, PC

#### VSE180-2, metal, axial




- ① Connector M12, 4-pin
- ② Connection cable 2 m
- 3 Sensitivity adjustment 270°
- $\ensuremath{\mathfrak{A}}$  LED indicator orange: switching output active
- 7 Fastening nuts (2 x); 24 mm hex, metal

#### VSE180-2, metal, radial




- ① Connector M12, 3-pin / Connector M12, 3-pin
- 2 Connection cable 2 m
- $\ensuremath{\ensuremath{\mathfrak{3}}}$  Sensitivity control; Potentiometer 270° (only VE)
- 4 LED indicator orange: switching output active (only VE)
- \$ LED indicator green, stability indicator (only VE): LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 7 Metal housing, fastening nuts (2 x); width across 24

## VSE180-2, plastic, axial




- ① Connector M12, 4-pin
- ② Connection cable 2 m
- 3 Sensitivity adjustment 270°
- $\textcircled{4} \ \mathsf{LED} \ \mathsf{indicator} \ \mathsf{orange}$
- $\ensuremath{\mathfrak{D}}$  LED indicator green: strength indicator
- 6 Fastening nuts (2 x); width across 22, PC

## VSE180-2, plastic, radial



- ① Connector M12
- 2 Connection cable 2 m
- $\ensuremath{\mathfrak{J}}$  Sensitivity control; Potentiometer 270  $^\circ$  (only VE)
- 4 LED indicator orange: switching output active (only VE)
- $\$  LED indicator green, stability indicator (only VE): LED lights continuously = light reception < 0.9/> 1.1; LED off = light reception > 0.9 / < 1.1
- 6 Fastening nuts (2 x); width across 22, PC

# **Adjustments**




- 3 Sensitivity adjustment 270°
- 4 LED indicator orange: switching output active
- 3 LED indicator green

## **Characteristic curves**

## Black-white shift


## VTB180-2, 350 mm

% of sensing range




- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission

## VTF180-2, 130 mm, radial




- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission

# VTF180-2, 140 mm, axial




- ① Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission

## VTE180-2, 450 mm, radial




- $\ensuremath{\textcircled{1}}$  Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on black, 6 % remission

## VTE180-2, 500 mm, axial




- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{3}}$  Sensing range on black, 6 % remission

#### VTE180-2, 900 mm, radial



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission


## VTE180-2, 1.100 mm, axial



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{G}}$  Sensing range on black, 6 % remission


# Operating reserve

## VL180-2, 7 m, axial




- ① PL80A
- ② P250, PL40A, PL50A, C110A
- ③ PL30A, PL31A
- 4 PL20A
- ⑤ P45
- 6 Reflective tape Diamond Grade

## VSE180-2, 28 m, axial




## VL180-2, 5.5 m, axial




- ① PL80A
- ② P250, PL40A, PL50A, C110A
- ③ PL30A, PL31A
- 4 PL20A
- ⑤ P45
- 6 Reflective tape Diamond Grade

## VSE180-2, 25 m, radial



# **Bar diagrams**

## VTB180-2, 350 mm




Sensing range

Sensing range max.


- $\ensuremath{\text{\textcircled{$1$}}}$  Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

## VTF180-2, 130 mm, radial




- ① Sensing range on white, 90 % remission ② Sensing range on gray, 18 % remission

## VTE180-2, 450 mm, radial



- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission

#### VTE180-2, 900 mm, radial




Sensing range

Sensing range max.


- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

## VTF180-2, 140 mm, axial




- ① Sensing range on white, 90 % remission
- ② Sensing range on gray, 18 % remission

#### VTE180-2, 500 mm, axial



- Sensing range Sensing range max.
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission


#### VTE180-2, 1.100 mm, axial



Sensing range

Sensing range max.

#### VL180-2, 7 m, axial




Sensing range

Sensing range max.


- ① PL80A
- ② P250, PL40A, PL50A, C110A
- ③ PL30A, PL31A
- 4 PL20A
- ⑤ P45
- 6 Reflective tape Diamond Grade

#### VSE180-2, 28 m, axial



Sensing range Sensing range typ. max.

#### VL180-2, 5.5 m, radial




Sensing range

Sensing range max.

- ① PL80A
- ② P250, PL40A, PL50A, C110A
- ③ PL30A, PL31A
- 4 PL20A
- (5) P45
- 6 Reflective tape Diamond Grade


#### VSE180-2, 25 m, radial




Sensing range

# **Light spot diameter**


## VTB180-2




#### VTF180-2




VTE180-2, 400 mm, 500 mm




## VTE180-2, 900 mm, 1.100 mm



#### VL180-2




#### VSE180-2, 28 m, axial




# **Connection diagram**

## Cd-057




- ① Sender
- ② Receiver

## Cd-058



- ① Sender
- 2 Receiver

#### Cd-060



- ① Sender
- 2 Receiver

#### Cd-066

# brn 1 + (L+) wht 2 not connected blu 3 - (M) blk 4 Q

#### Cd-087

#### Cd-089

# **Recommended accessories**

## Mounting brackets/plates

## **Mounting plates**

Figure	Material	Description	Model name	Part no.
	Ctainless steel	Mounting plate for M18 housing	BEF-WG-M18N	5320948
96	Stainless steel	Mounting bracket	BEF-WN-M18N	5320947

# Plug connectors and cables

# Connecting cable (female connector-open)

- Cable material: PVC
- Connector material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.
//	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-1204-G02MN	6028128
1 60	M12, 4-pin, straight	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-G05MN	6028130
	Female connector,	Cable, open con-	2 m, 4-wire	IP 67, IP 69K	DOL-1204-W02MN	6028129
1	M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67, IP 69K	DOL-1204-W05MN	6028131

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N06N for universal clamp bracket, M18	BEF-KHS-N06N	2051622

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097
	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

## Fine triple reflectors

Figure	Material	Description	Model name	Part no.
	Plastic	Fine triple, chemically resistant, screw connection, 18 mm x 18 mm	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

# **Special reflectors**

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405

# Terminal and alignment brackets

# **Alignment brackets**

Figure	Material	Description	Model name	Part no.
0	Plastic	Mounting bracket with ball-and-socket	BEF-WN-M18-ST02	5312973

## **Terminal brackets**

Figure	Material	Description	Model name	Part no.
	Plastic (PA12),	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481
401	glass-fiber rein- forced	Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482
	Stainless steel	Mounting ring	BEF-WN-MH15-2V	4053358

→ For additional accessories, please see page L-861

Improve performance and reduce downtime with W15 sensors











# **Additional information**

Detailed technical data I-7	67
Ordering information 1-7	68
Dimensional drawings I-7	70
Characteristic curves 1-7	71
Bar diagramsI-7	72
Connection diagram 1-7	73
Recommended accessories I-7	74

# **Product description**

The high-performance W15 photoelectric sensor family is flexible and versatile, combining a modern industrial design with SICK technology for an optimum application solution.

These sensors use SICK's third generation custom ASIC that incorporates OES3 technology to provide exceptional background suppression at an extended range. The W15 series includes four different sensing modes, including the

WTB15, WTE15, WL15 and WSE15 to provide a complete product offering. An attractive feature of this series is its flexible mounting options. The W15 fea-

tures 18 mm front mount and side mount through holes. The M18 front mount enables the sensor to be flush mounted with a snap ring, which prevents the disruption of product flow in conveyor systems.

# At a glance

- M18 front mount using plastic nut or snap ring, side assembly with 24.1 mm through holes
- · Flush mounting possible using the snap ring
- Transparent back cover
- Best-in-class background suppression and red PinPoint LED
- · High immunity to ambient light
- · Highly visible LED indicators

# Your benefits

- Completely compatible with many competitor models, making it easy install and commission
- · Flush mounting reduces setup time and prevents obstructions to material flow on conveyor systems
- Clearly visible LED indicators reduce setup time and simplify troubleshooting
- · Reliable detection due to best-inclass background suppression that ignores stray background reflections, detects multi-colored/shiny objects and provides high immunity to ambient light
- · Customer-specific options reduce material and labor costs

## → www.mysick.com/en/W15

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

	WTB15	WTE15	WL15	WSE15
Sensor principle	Photoelectric proximity	sensor	Photoelectric retro- reflective sensor	Through-beam photo- electric sensor
Detection principle	Background suppression	Energetic	Standard optics	-
Dimensions (W x H x D)	16.2 mm x 48.5 mm x	31.9 mm		
Housing design (light emission)	Hybrid			
Thread diameter (housing)	M18 x 1			
Sensing range max.	4 mm 200 mm <sup>1)</sup>	10 mm 350 mm <sup>1)</sup>	$0.035~m$ 5 m $^{2)}$	0 m 5 m
Sensing range	15 mm 200 mm	10 mm 250 mm	0.035 m 3.5 m	0 m 3.8 m
Type of light	Visible red light	Infrared light	Visible red light	
Light source 3)	PinPoint LED	LED		
Light spot size (distance)	Ø 7 mm (50 mm)	Ø 50 mm (350 mm)	Ø 140 mm (3.5 m)	160 mm (4 m)
Angle of dispersion	-	4.5°	1.5°	
Wave length	650 nm	950 nm	650 nm	
Adjustment	Potentiometer, 5 turns		-	
Time type	-		Time delay off / adjustable via time control (depending on type)	-
Delay time	-		0 s 2 s (depending on type)	-

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	WTB15	WTE15	WL15	WSE15
Supply voltage 1)	10 V DC 30 V DC			
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>	≤ 5 V <sub>pp</sub>		
Power consumption 3)	≤ 30 mA			
Output type	PNP, NPN, PNP/NPN (d	epending on type)		
Output function	Complementary			-
Switching mode	Light/dark-switching;/L	ight switching/Dark-swit	ching (depending on type	e)
Output current I <sub>max.</sub>	≤ 100 mA			
Response time 4)	< 0.5 ms	≤ 1.25 ms		≤ 1.4 ms
Switching frequency 5)	1,000 Hz	400 Hz		350 Hz
Connection type	Male connector/Cable, (depending on type)	2 m <sup>6)</sup>		
Circuit protection	A $^{7)}$ , B $^{8)}$ , D $^{9)}$			
Protection class <sup>10)</sup>	II			
Weight	10 g / 20 g (depending	ng on type)		20 g / 40 g (depending on type)
Polarisation filter	-		<b>✓</b>	-
Housing material	ABS			
Optics material	PMMA			

<sup>&</sup>lt;sup>2)</sup> PL80A.

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25 °C.

	WTB15	WTE15	WL15	WSE15		
Enclosure rating	IP 66, IP 67	IP 67				
Items supplied	Snap-ring and M18 nut					
Ambient operating temperature	-40 °C +60 °C	-25 °C +55 °C				
Ambient storage temperature	-40 °C +75 °C	-25 °C +70 °C				

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Limit values, operation in short-circuit protected network max. 8 A.

# **Ordering information**

Other models available at www.mysick.com/en/W15

## **WTB15**

- Sensor principle: photoelectric proximity sensor
- Detection principle: background suppression
- Adjustment: potentiometer, 5 turns

Sensing range max. 1)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
	PNP	Light/dark quitabing	Connector M12, 4-pin	Cd-083	WTB15-P2431	1044305
	PNP	Light/dark-switching	Cable, 4-wire 2 m PUR	Cd-094	WTB15-P1131	1046284
	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-083	WTB15-N2431	1044306
4 mm 200 mm			Cable, 4-wire 2 m PUR	Cd-094	WTB15-N1131	1046283
4 111111 200 111111		•	Connector M12, 4-pin	Cd-086	WTB15-B2431	1043326
	PNP, NPN		Cable, 4-wire 2 m PUR	Cd-096	WTB15-B1131	1046282
			Connector M12, 4-pin	Cd-086	WTB15-A2431	1043325
			Cable, 4-wire 2 m PUR	Cd-096	WTB15-A1131	1046281

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

## WTE15

- Sensor principle: photoelectric proximity sensor
- Detection principle: energetic
- Adjustment: potentiometer, 5 turns

Sensing range max. 1)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
	PNP	Light/dark quitabing	Connector M12, 4-pin	Cd-083	WTE15-P2411	1043314
	PINP	Light/dark-switching	Cable, 4-wire 2 m PUR	Cd-094	WTE15-P1111	1046148
	NPN	Light/dark-switching	Connector M12, 4-pin	Cd-083	WTE15-N2411	1043313
10 mm 350 mm	INPIN		Cable, 4-wire 2 m PUR	Cd-094	WTE15-N1111	1046147
10 11111 550 11111		Light switching, PNP, NPN Dark-switching	Connector M12, 4-pin	Cd-086	WTE15-B2411	1043317
	PNP, NPN		Cable, 4-wire 2 m PUR	Cd-096	WTE15-B1111	1046278
			Connector M12, 4-pin	Cd-086	WTE15-A2411	1043316
			Cable, 4-wire 2 m PUR	Cd-096	WTE15-A1111	1046277

 $<sup>^{1)}</sup>$  Object with 90 % reflectance (referred to standard white, DIN 5033)

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>8)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{9)}</sup>$  D = outputs overcurrent and short-circuit protected.

<sup>10)</sup> Reference voltage: 50 V DC.

# **WL15**

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics

Sensing range max. 1)	Output type	Switching mode	Time functions	Connection	Connection diagram	Model name	Part no.
				Connector M12, 4-pin	Cd-083	WL15-P2430	1043321
	PNP	Light/dark-	-	Cable, 4-wire 2 m PUR	Cd-094	WL15-P1130	1044303
	PNP	switching	Time delay off ?)	Connector M12, 4-pin	Cd-083	WL15-F2433	1043319
			Time delay off 2)	Cable, 4-wire 2 m PUR	Cd-094	WL15-F1133	1046150
	NPN	Light/dark- switching		Connector M12, 4-pin	Cd-083	WL15-N2430	1043320
0.035 m 5 m			_	Cable, 4-wire 2 m PUR	Cd-094	WL15-N1130	1044304
0.035 111 5 111			Time delay off <sup>2)</sup>	Connector M12, 4-pin	Cd-083	WL15-E2433	1043318
				Cable, 4-wire 2 m PUR	Cd-094	WL15-E1133	1046149
		Light switching,		Connector M12, 4-pin	Cd-086	WL15-B2430	1043324
	PNP, NPN	Light switching,	_	Cable, 4-wire 2 m PUR	Cd-096	WL15-B1130	1046280
		Dark-switching- Dark-switching		Connector M12, 4-pin	Cd-086	WL15-A2430	1043323
			_	Cable, 4-wire 2 m PUR	Cd-096	WL15-A1130	1046279

<sup>1)</sup> PL80A.

# WL15, detecting objects wrapped in film

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics

Sensing range max. 1)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0.035 m 5 m	PNP	Light/dark-switching	Connector M12, 4-pin	Cd-083	WL15-P2430S01	1054623

<sup>1)</sup> PL80A.

# WSE15

Sensor principle: through-beam photoelectric sensor


Sensing range max.	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
0 m 5 m	PNP, NPN	Light switching, Light switching, Dark-switching Dark-switching	Connector M12, 4-pin	Cd-215	WSE15-B2430	1043328
			Cable, 4-wire 2 m PUR	Cd-218	WSE15-B1130	1046286
			Connector M12, 4-pin	Cd-215	WSE15-A2430	1043327
			Cable, 4-wire 2 m PUR	Cd-218	WSE15-A1130	1046285

<sup>&</sup>lt;sup>2)</sup> Adjustable via time control.

# **Dimensional drawings**


Dimensions in mm (inch)

## **WTE15, WTB15**




- ① Optical axis receiver
- 2 Optical axis sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Connector M12, 4-pin
- ⑤ Potentiometer
- **6** LED indicator green: power; yellow: output

# WL15, WSE15, without time functions



- ① Optical axis, receiver
- 2 Optical axis, sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Connector M12, 4-pin
- ⑤ LED indicator green: power; yellow: output

## WL15, WSE15, with time functions




- ① Optical axis receiver
- 2 Optical axis sender
- 3 Mounting hole, Ø 3.2 mm
- 4 Connector M12, 4-pin
- ⑤ Time control
- 6 LED indicator green: power; yellow: output

# **Characteristic curves**


## Black-white shift

# **WTB15**



- 1 Sensing range on black, 6 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\mathfrak{B}}$  Sensing range on white, 90 % remission


## **WTE15**



- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on gray, 18 % remission
- $\ensuremath{\text{\textcircled{2}}}$  Sensing range on white, 90 % remission


# Operating reserve

#### **WL15**




- ① PL80A
- ⑤ PL30A, PL31A
- ② P250
- 6 PL20A
- 3 C110A
- 7 Reflective tape REF-Plus
- 4 PL50A, PL40A

## **WSE15**



# **Bar diagrams**


#### **WTB15**



- Sensing range
- Sensing range max.
- ① Sensing range on black, 6 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on white, 90 % remission


# **WTE15**

**WSE15** 



- ① Sensing range on gray, 18 % remission
- ② Sensing range on white, 90 % remission

# **WL15**



Sensing range

7 Reflective tape REF-Plus

- ① PL80A ② P250
- ⑤ PL30A, PL31A
- 6 PL20A
- 3 C110A 4 PL50A, PL40A
- Sensing range max.

#### 0 (3.28)(6.56)(9.84) (13.12) (16.40) (19.69) Distance in m (feet)

Sensing range

Sensing range typ. max.

# **Connection diagram**

# Cd-083

# $\begin{array}{c|c} & & \\ & & \\ \hline & & \\ \hline$

# Cd-086




## Cd-094



## Cd-096





## Cd-215



- ① Sender
- 2 Receiver

## Cd-218





- ① Sender
- ② Receiver

# **Recommended accessories**

# Mounting brackets/plates

## **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Steel, zinc coated	Mounting plate for M18 sensors	BEF-WG-M18	5321870
0		Mounting bracket, M18 thread	BEF-WN-M18	5308446

# Plug connectors and cables

# Connecting cable (female connector-open)

• Cable material: PVC

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Connecting cable	Enclosure rating	Model name	Part no.	
	Female connector, M12, 4-pin, straight	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-G02M	6009382
		ductor heads	5 m, 4-wire	IP 67	DOL-1204-G05M	6009866	
	Female connector,	Female connector,	Cable, open con-	2 m, 4-wire	IP 67	DOL-1204-W02M	6009383
M12, 4-pin, angled	ductor heads	5 m, 4-wire	IP 67	DOL-1204-W05M	6009867		

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N06 for universal clamp bracket	BEF-KHS-N06	2051612

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
B a	PMMA/ABS	Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

<sup>→</sup> For additional accessories, please see page L-861







The Z photoelectric sensor is a low-cost sensor for standard applications in conveyor lines, packaging machines, bin controls and hands-free systems. The sensor's transparent housing provides 360° status indication and has a straight cable outlet for easy connection. The Z1 and Z2 are offered in many differ-

ent sensing ranges and are available in three variants: retro-reflective, background suppression and energetic. The eyeball-shaped housing of the Z3 allows for infinite adjustability and the indicator LED to be seen from 360° around the device.

# At a glance

- Economical design with background suppression, retro-reflective or energetic variants available; nonadjustable
- Compact, transparent housing with 360° status indication
- M18 front mount and 24-25.4 mm slotted side through holes compatible with competitor devices
- Spherical eyeball-style housing with 24 mm ball mount allows for infinite adjustability (depending on type)
- Connection system: straight or angled cable outlet (60°) or M12 or M8 connector outlet
- IP 67 enclosure rating for harsh environments

# Your benefits

- High performance at a low cost
- Clear housing provides highly visible 360° of status indication, which simplifies troubleshooting
- Simple and unique mounting options lower installation costs
- Small size fits applications with limited space
- Customization options reduce material and labor costs
- Compatibility with competitor products for easy integration into existing systems



# **Additional information**

Detailed technical data I-777
Ordering information I-778
Dimensional drawings I-780
Characteristic curves I-781
Bar diagramsI-781
Connection diagram I-782
Recommended accessories I-782

#### → www.mysick.com/en/Z-Sensor

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more.



# **Detailed technical data**

## **Features**

	ZT1	ZT2	ZL1	ZL2	ZL3	
Sensor principle	Photoelectric proxim	nity sensor	Photoelectric retro-	reflective sensor		
Detection principle	Background suppres getic (depending on	•	Standard optics			
Dimensions (W x H x D)	13.6 mm x 41.9 mm x 31.7 mm 13.6 mm x 45.2 mm x 31.7 mm 13.6 mm x 34.8 mm x 21.9 mm (depending on type)					
Housing design (light emission)	Hybrid					
Thread diameter (housing)	M18 x 1				-	
Sensing range max.	0 mm 155 mm <sup>1)</sup> type)	(depending on	0.1 m 4.8 m <sup>2)</sup>			
Sensing range	0 mm 155 mm (c type)	depending on	0.1 m 3 m <sup>2)</sup>			
Type of light	Infrared light		Visible red light			
Light source 3)	LED					
Wave length	880 nm		660 nm			

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033)

# Mechanics/electronics

	ZT1	ZT2	ZL1	ZL2	ZL3
Supply voltage 1)	10 V DC 30 V D	С			
Ripple <sup>2)</sup>	< 5 V <sub>pp</sub>				
Power consumption <sup>3)</sup>	< 20 mA				
Output type	PNP/NPN (depen	ding on type)	PNP	PNP/NPN (depen	ding on type)
Switching mode	Light switching / [	Dark-switching (d	depending on type)		
Output current I <sub>max.</sub>	50 mA				
Switching frequency 4)	200 Hz		400 Hz		
Connection type	Cable with connect Cable with connect Cable, 2 m <sup>5)</sup> (depending on typ	etor, M12, 150 m			
Circuit protection	A <sup>6)</sup> , D <sup>7)</sup>				
Protection class 8)	III				
Polarisation filter	-		V		
Housing material	Glass fiber reinfore	ced ABS plastic			
Enclosure rating	IP 67				
Items supplied	Mounting nut M18	3			-
Ambient operating temperature	-25 °C +50 °C	;			
Ambient storage temperature	-40 °C +70 °C	;			

<sup>1)</sup> Limit values.

<sup>2)</sup> PL80A

 $<sup>^{3)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25 °C.

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>&</sup>lt;sup>4)</sup> With light/dark ratio 1:1.

 $<sup>^{5)}</sup>$  Do not bend below 0  $^{\circ}\text{C}.$ 

 $<sup>^{\</sup>rm 6)}$  A =  $\rm V_{\rm S}$  connections reverse-polarity protected.

 $<sup>^{7)}\,</sup>D$  = outputs overcurrent and short-circuit protected.

<sup>8)</sup> Reference voltage: 50 V DC.

# **Ordering information**

Other models available at www.mysick.com/en/Z-Sensor

# ZT1

• Sensor principle: photoelectric proximity sensor

Type of light: infrared lightSwitching mode: light switching

Detection principle	Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.	
				Cable with connector M8, 4-pin 150 mm	Cd-067	ZT1-P3231	1045595	
Background	Background 0 mm suppression 50 mm	10.5 mm	PNP	Cable with connector M12, 4-pin 150 mm	Cd-067	ZT1-P3221	1045579	
suppression		(50 mm)		Cable, 3-wire 2 m PVC	Cd-043	ZT1-P3215	1045563	
			NPN	Cable, 3-wire 2 m PVC	Cd-043	ZT1-N3215	1045562	
	1 mm	20 mm (100 mm)	20 mm	PNP	Cable with connector M12, 4-pin 150 mm	Cd-067	ZT1-P4221	1045583
	100 mm		PNP	Cable, 3-wire 2 m PVC	Cd-043	ZT1-P4215	1045567	
Energetic			PNP	Cable with connector M8, 4-pin 150 mm	Cd-067	ZT1-P5231	1045591	
	5 mm 155 mm	31 mm (100 mm)		Cable with connector M12, 4-pin 150 mm	Cd-067	ZT1-P5221	1045575	
				Cable, 3-wire 2 m PVC	Cd-043	ZT1-P5215	1045559	

 $<sup>^{\</sup>rm 1)}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

# ZT2

Sensor principle: photoelectric proximity sensor

Type of light: infrared lightSwitching mode: light switching

Detection principle	Sensing range max. 1)	Light spot size (distance)	Output type	Connection	Connection diagram	Model name	Part no.								
				Connector M8, 4-pin	Cd-067	ZT2-P3238	1045489								
Background	0 mm	10.5 mm	PNP	Connector M12, 4-pin	Cd-067	ZT2-P3228	1045473								
suppression	50 mm (50 mm	(50 mm)		Cable, 3-wire 2 m PVC	Cd-043	ZT2-P3215	1045408								
											NPN	Cable, 3-wire 2 m PVC	Cd-043	ZT2-N3215	1045407
	1 mm		20 mm	20 mm	PNP	Connector M8, 4-pin	Cd-067	ZT2-P4238	1045493						
Energotic	100 mm		PNP	Connector M12, 4-pin	Cd-067	ZT2-P4228	1045477								
Energetic	5 mm	31 mm	PNP	Connector M8, 4-pin	Cd-067	ZT2-P5238	1045485								
	155 mm	155 mm (100 mm)	PNP	Connector M12, 4-pin	Cd-067	ZT2-P5228	1045469								

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Object with 90 % reflectance (referred to standard white, DIN 5033).

# ZL1

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Type of light: visible red light

Sensing range max. 1)	Light spot size (distance)	Output type	Switching Connection mode		Connection diagram	Model name	Part no.
		mm (1 m) PNP	Light switching	Cable with connector M8, 4-pin 150 mm	Cd-067	ZL1-P2431	1045505
				ching Cable with connector M12, 4-pin 150 mm		ZL1-P2421	1045501
0.1 m	10F mans (1 ms)			Cable, 3-wire 2 m PVC	Cd-043	ZL1-P2415	1045497
4.8 m	125 11111 (1 111)		Dark-switching	Cable with connector M8, 4-pin 150 mm	Cd-067	ZL1-F2431	1045506
				Cable with connector M12, 4-pin 150 mm	Cd-067	ZL1-F2421	1045502
				Cable, 3-wire 2 m PVC	Cd-043	ZL1-F2415	1045498

<sup>&</sup>lt;sup>1)</sup> PL80A.

# ZL2

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Type of light: visible red light

Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
			Cable, 3-wire 2 m PVC	Cd-043	ZL2-F2415	1045389	
		n (1 m)	Dark-switching	Connector M8, 4-pin	Cd-067	ZL2-F2438	1045385
0.1 m 4.8 m	125 mm (1 m)			Connector M12, 4-pin	Cd-067	ZL2-F2428	1045371
			Dark-switching	Cable, 3-wire 2 m PVC	Cd-043	ZL2-E2415	1045390
				Connector M12, 4-pin	Cd-067	ZL2-E2428	1045372

<sup>1)</sup> PL80A.

# ZL3

- Sensor principle: photoelectric retro-reflective sensor
- Detection principle: standard optics
- Type of light: visible red light


Sensing range max. 1)	Light spot size (distance)	Output type	Switching mode	Connection	Connection diagram	Model name	Part no.
		PNP	Dark-switching	Cable with connector M8, 4-pin 150 mm	Cd-067	ZL3-F2431	1045539
				Dark-switching Cable with connector M12, 4-pin 150 mm		Cd-067	ZL3-F2421
0.1 m	125 mm (1 m)			Cable, 3-wire 2 m PVC	Cd-043	ZL3-F2415	1045531
4.8 m	125 mm (1 m)		Light switching	Cable, 3-wire 2 m PVC	Cd-043	ZL3-P2415	1045530
		NDN	NPN Dark-switching	Cable with connector M8, 4-pin 150 mm	Cd-067	ZL3-E2431	1045540
		NPN		Cable with connector M12, 4-pin 150 mm	Cd-067	ZL3-E2421	1045536

<sup>1)</sup> PL80A.


# **Dimensional drawings**

Dimensions in mm (inch)


**ZT1**, **ZL1** 




ZT2, ZL2, Connector M8, 4-pin




ZT2, ZL2, Connector M12, 4-pin



ZT2, ZL2, cable




ZL3



## **Characteristic curves**

# Operating reserve


## **ZL1**, **ZL2**, **ZL3**



- ① PL80A
- ② P250
- 3 PL40A
- 4 PL20A
- (5) Reflective tape REF-Plus


# **Bar diagrams**

## ZT1, 50 mm




- Sensing range
- Sensing range max.
- $\ensuremath{\text{\textcircled{1}}}$  Sensing range on white, 90 % remission
- $\ensuremath{\text{@}}$  Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

## ZT1, 155 mm




- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- ③ Sensing range on black, 6 % remission

## ZT1, 100 mm



- Sensing range
- Sensing range max.
- ① Sensing range on white, 90 % remission
- 2 Sensing range on gray, 18 % remission
- 3 Sensing range on black, 6 % remission

# **ZL1**, **ZL2**, **ZL3**




- Sensing range
- Sensing range max.
- ① PL80A
- ② P250
- ③ PL40A
- 4 PL20A
- 3 Reflective tape REF-Plus

# **Connection diagram**

# Cd-043

## Cd-067



$$\begin{array}{c|c} & & \\ \hline & \text{brn} & \frac{1}{2} & + \text{(L+)} \\ \hline & \text{wht} & \frac{2}{2} & \text{not connected} \\ \hline & \text{blu} & \frac{3}{2} & - \text{(M)} \\ \hline & & \text{blk} & \frac{4}{2} & \text{Q} \\ \end{array}$$

# **Recommended accessories**

# Mounting brackets/plates

# **Mounting brackets**

Figure	Material	Description	Model name	Part no.
	Ctaal sine acatad	Mounting plate for M18 sensors	BEF-WG-M18	5321870
90	Steel, zinc coated	Mounting bracket, M18 thread	BEF-WN-M18	5308446

# Plug connectors and cables

# Connecting cable (female connector-open)

Cable material: PVC

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Enclosure rating	Model name	Part no.		
//	Female connector, M8, 4-pin, straight	Female connector,	Female connector, Cable, open	Cable, open con-	2 m, 4-wire	PVC	IP 67, IP 69K	DOL-0804-G02M	6009870
		ductor heads	5 m, 4-wire	PVC	IP 67, IP 69K	DOL-0804-G05M	6009872		
	Female connector, M12, 4-pin, straight	Cable, open con-	2 m, 4-wire	TPU	IP 67	DOL-1204-G02M	6009382		
100		ductor heads	5 m, 4-wire	TPU	IP 67	DOL-1204-G05M	6009866		

# Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type termi- nals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078

# Universal bar clamp systems

Figure	Material	Description	Model name	Part no.
6	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N06 for universal clamp bracket	BEF-KHS-N06	2051612

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
, n		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
-		Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244

## Round

Figure	Material	Description	Model name	Part no.
	PMMA/ABS	Round, screw connection	C110A	5304549

→ For additional accessories, please see page L-861

# Fiber-optic sensors and fibers



# Fits flexibly into the narrowest corners

When installation space is extremely limited or the objects to be detected are tiny, fiber-optic sensors are the ideal solution. If it is necessary for even higher requirements to be fulfilled, such as sensing range, temperature resistance, material durability or a flexible mounting process, the intelligent combination of sensors and fiber-optic cables can provide the perfect solution. A wide range of fiber-optic cables with application-specific optical heads ensure that every need is met.

## Your benefits

- Reliable and accurate detection of the smallest objects thanks to innovative, microcontroller-supported electronics
- Immune to EMC, high temperatures or chemicals, as the electronic evaluation system is fitted separately from the fiber-optic cable head
- Space-saving mounting even in confined spaces
- Multiple setting options permit solutions for practically any application
- Light weight, suitable for use on a robot arm
- Universal application possibilities due to diversity of fiber-optic cables






# Fiber-optic sensors and fibers


General information
WLL170-2
WLL180T
LL3



# The versatile WLL170-2




Easy to operate fiber-optic sensor. Simple adjustment via potentiometer or teach-in button.



The devices are optimized for the individual applications:

- Standard applications
- High speed applications (50 µs)
- Easy contrast detection with green LED emitter

# The high-performance WLL180T



The world's fastest fiber-optic sensor in its class with a 16  $\mu$ s response time. It reliably detects up to 31,250 workpieces per second.



Even sensing ranges of up to 20 m can be achieved with the WLL180T and the corresponding fiber. The powerful light beam penetrates particles in the air. Workpieces are detected even under difficult conditions, such as dust, mist or spray.



The plug/socket design means installation on a mounting rail is extremely easy



The copy function simplifies commissioning. All settings are copied to the other bus devices at the touch of a button.



- Easy reading guaranteed: The 7-segment display can be turned upside down in difficult installation conditions
- Up to 16 devices can be synchronized in bus mode.
   This prevents mutual interference (anti-interference) in the case of closely mounted fiber-optic heads.

- All connected WLL180T sensors can be individually set on the device or via the relevant teach-in cable. If all devices should be taught-in simultaneously, this can be done via bus coupling with a single teach-in cable.
- ASC for maintenance-free operation: If, for example, the light intensity is reduced by dust, this is detected and the switching threshold compensates accordingly.
   The switching threshold is automatically recalibrated after the optics are cleaned.
- Adjustable hysteresis: The hysteresis can be adjusted from 1% to 40%. This enables flexible settings for detection of complex objects.
- Anti-blooming function to prevent overload.

# **Product family overview**







## WLL170-2

Versatility for standard applications


## Technical data overview

Housing material	Plastic	
Type of light	Visible red light / Green light	
Enclosure rating	IP 66	
Response time	≤ 0.25 ms, ≤ 50 µs	
Switching mode	Light/dark-switching	
Indication	LED	

## At a glance

- Rapid response time (50 μs)
- Switching threshold adjustment via potentiometer, or teach-in via button or cable
- Four different teach-in modes
- Simple installation
- Red or green LED emitter

Detailed information → J-790



8015327/2014-02-08 Subject to change without notice









# **Additional information**

Detailed technical dataJ-791
Ordering information
Dimensional drawings J-793
Adjustments J-794
Connection diagram J-795
Function diagram J-795
Recommended accessoriesJ-795

# **Product description**

The WLL170-2 fiber-optic photoelectric sensor family features a standard operating system that is especially suitable for basic applications, but can be used when rapid response times are crucial. There are several variants. The WLL170(T) version is optimized for a number of key applications, such as detection of very small objects, colored marks, or transparent objects. The WLL170T-2 is a teach-in version where the switching threshold can be set either automatically by pressing a button or via a cable. In contrast, the WLL170-2 has a manual switching threshold adjustment via a potentiometer. Both models are available in a high-speed version with a switching frequency of 10 kHz for extremely fast response times. For optimum detection of color contrasts, you can choose between devices with a red or green LED emitter. Detection tasks are handled securely and reliably using the LL3 series of fiber-optic cables.

# At a glance

- Rapid response time (50 µs)
- Switching threshold adjustment via potentiometer, or teach-in via button or cable
- · Four different teach-in modes
- · Simple installation
- · Red or green LED emitter

## Your benefits

- Reliable, rapid process detection
- Low installation costs due to short commissioning time
- Flexible teach-in modes allow the sensor to be customized according to the specific application
- · Emitted light ideal for color or contrast detection
- Easy programming via simple potentiometer and switch adjustment

## www.mysick.com/en/WLL170-2

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



# **Detailed technical data**

# **Features**

	WLL170-2	WLL170T-2	
Sensor principle	Fiber-optic photoelectric sensor		
Dimensions (W x H x D)	10.5 mm x 35.5 mm x 83.7 mm		
Housing design (light emission)	Rectangular		
Sensing range max.	0 mm 4,000 mm, through-beam system $^{1)}$ (depending on type)	0 mm 3,500 mm, through-beam system $^{\scriptscriptstyle (1)}$ (depending on type)	
Sensing range	0 mm 160 mm, proximity system <sup>2)</sup> 0 mm 700 mm, through-beam system <sup>3)</sup> (depending on type)	0 mm 160 mm, proximity system <sup>2)</sup> 0 700 mm, through-beam system <sup>3)</sup> (depending on type)	
Type of light	Visible red light/Green light (depending on type)		
Light source 4)	LED		
Wave length			
Visible red light	660 nm		
Green light	520 nm	525 nm	
Teach-in	Potentiometer, 10-turn 5)	Teach-in-button, cable	
Time type	Off-delayed		
Delay time	Selectable by sliding switch: ≤ 40 ms		
Indication	LED		

<sup>1)</sup> LL3-TB02 and tip adapter LL3-TA01.

# Mechanics/electronics

	WLL170-2	WLL170T-2	
Supply voltage 1)	10 V DC 30 V DC		
Ripple <sup>2)</sup>	10 %		
Power consumption 3)	≤ 30 mA		
Output type	PNP, open collector/NPN, open collector (depending on type)		
Switching mode	Light/dark-switching (selectable via light/dark selector)		
Output current I <sub>max.</sub>	≤ 100 mA		
Response time	$\leq$ 0.25 ms <sup>4)</sup> $\leq$ 50 $\mu$ s <sup>4)</sup> (depending on type)		
Switching frequency 5)			
Response time ≤ 0,25 ms <sup>4)</sup>	2,000 Hz		
Response time ≤ 50 µs <sup>4)</sup>	10,000 Hz		
Connection type	Cable, 2 m $^{6}$ /Male connector, M8 (depending or	n type)	
Circuit protection	A $^{7)}$ , B $^{8)}$ , C $^{9)}$ , D $^{10)}$		
Protection class	III		

 $<sup>^{2)}</sup>$  Objects to be sensed with 90% reflectivity (based on DIN 5033 white standard). Sensing range depends on fiber-optic cable.

<sup>&</sup>lt;sup>3)</sup> LL3-tB01.

 $<sup>^{\</sup>rm 4)}$  Average service life of 100,000 h at T  $_{\! A}$  = +25 °C.

<sup>&</sup>lt;sup>5)</sup> Scale 270°.

	WLL170-2	WLL170T-2
Housing material	ABS/PC	ABS
Enclosure rating 11)	IP 66	
Ambient operating temperature	-25 °C +55 °C	
Ambient storage temperature	-40 °C +70 °C	

<sup>1)</sup> Limit values.

### **Ordering information**

Other models available at www.mysick.com/en/WLL170-2

### WLL170-2

• Adjustment: Potentiometer, 10-turn (Scale 270°.)

Type of light	Response time	Sensing range max. <sup>1)</sup>	Switching mode	Connection	Connection diagram	Model name	Part no.												
				Cable, 3-wire, 2 m	Cd-043	WLL170-2P132	6029511												
		0 mm	PNP	Male connector, M8, 3-pin	Cd-045	WLL170-2P330	6029513												
Visible red	≤ 0.25 ms	4,000 mm,		Male connector, M8, 4-pin	Cd-066	WLL170-2P430	6029514												
light	≤ 0.25 ms	through-beam		Cable, 3-wire, 2 m	Cd-043	WLL170-2N132	6029515												
		system	NPN	Male connector, M8, 3-pin	Cd-045	WLL170-2N330	6029517												
				Male connector, M8, 4-pin	Cd-066	WLL170-2N430	6029518												
				Cable, 3-wire, 2 m	Cd-043	WLL170-2P192	6029519												
		0 mm	PNP	Male connector, M8, 3-pin	Cd-045	WLL170-2P390	6029521												
Green light	≤ 0.25 ms	1,700 mm, through-beam system								Male connector, M8, 4-pin	Cd-066	WLL170-2P490	6029522						
Green light	2 0.25 1115			Cable, 3-wire, 2 m	Cd-043	WLL170-2N192	6029523												
			System	system	system	System	System	system	system	System	system	system	system	NPN	NPN	Male connector, M8, 3-pin	Cd-045	WLL170-2N390	6029525
															Male connector, M8, 4-pin	Cd-066	WLL170-2N490	6029526	
				Cable, 3-wire, 2 m	Cd-043	WLL170-2P162	6029527												
		0 mm	PNP	Male connector, M8, 3-pin	Cd-045	WLL170-2P360	6029529												
Visible red	< <b>5</b> 0 uo	1 600 mm		Male connector, M8, 4-pin	Cd-066	WLL170-2P460	6029530												
light	J	through-beam		Cable, 3-wire, 2 m	Cd-043	WLL170-2N162	6029531												
		system	NPN	Male connector, M8, 3-pin	Cd-045	WLL170-2N360	6029533												
				Male connector, M8, 4-pin	Cd-066	WLL170-2N460	6029534												

 $<sup>^{\</sup>mbox{\tiny 1)}}$  LL3-TB02 and tip adapter LL3-TA01.

J-792

 $<sup>^{2)}</sup>$  May not exceed or fall short of  $V_{\rm S}$  tolerances.

<sup>&</sup>lt;sup>3)</sup> Without load.

 $<sup>^{\</sup>mbox{\tiny 4)}}$  Signal transit time with resistive load.

<sup>5)</sup> With light/dark ratio 1:1.

<sup>&</sup>lt;sup>6)</sup> Do not bend below 0 °C.

 $<sup>^{7)}</sup>$  A =  $V_S$  connections reverse-polarity protected.

 $<sup>^{8)}</sup>$  B = inputs and output reverse-polarity protected.

<sup>&</sup>lt;sup>9)</sup> C = interference suppression.

 $<sup>^{10)}</sup>$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{11)}</sup>$  With correctly attached fibre-optic cable LL3 and closed protection hood.


### WLL170T-2

Type of light	Response time	Sensing range max. <sup>1)</sup>	Switching mode	Adjustment	Connection	Con- nection diagram	Model name	Part no.													
				Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2P132	6033948													
		0 mm	PNP	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2P430	6033950													
Visible	≤ 0.25 ms	3,500 mm,		Teach-in button	Male connector, M8, 3-pin	Cd-045	WLL170T-2P330	6033949													
red light	≤ 0.25 ms	through- beam		Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2N132	6033951													
		system	NPN	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2N430	6033953													
				Teach-in button	Male connector, M8, 3-pin	Cd-045	WLL170T-2N330	6033952													
						Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2P192	6033954											
		0 mm	PNP	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2P490	6033956													
Green	≤ 0.25 ms	1,600 mm,	1,600 mm, through-						Teach-in button	Male connector, M8, 3-pin	Cd-045	WLL170T-2P390	6033955								
light	≥ 0.25 IIIS	beam system	beam	beam	beam	beam	beam	beam		J	Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2N192	6033957						
									NPN	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2N490	6033959							
				Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2P162	6033963													
		0 mm	PNP	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2P460	6033965													
Visible	≤ 50 µs	1,500 mm, µs through- beam		Teach-in button	Male connector, M8, 3-pin	Cd-045	WLL170T-2P360	6033964													
red light	≥ 50 µS			Teach-in button,	Cable, 4-wire, 2 m	Cd-093	WLL170T-2N162	6033960													
		system	NPN	Cable	Male connector, M8, 4-pin	Cd-092	WLL170T-2N460	6033962													
				Teach-in button	Male connector, M8, 3-pin	Cd-045	WLL170T-2N360	6033961													

<sup>1)</sup> LL3-TB02 and tip adapter LL3-TA01.

### **Dimensional drawings**


### WLL170-2



Dimensions in mm (inch)

- ① Sender LED, installation of LL3 fibre-optic cable (sender fibre)
- ② Receiver, installation of LL3 fibre optic cable (receiver fibre)
- ③ Protective hood, can be raised at both ends
- Mounting bracket, included
- ⑤ Connection


### WLL170T-2



- ① Sender LED, installation of LL3 fibre-optic cable (sender fibre)
- ② Receiver, installation of LL3 fibre optic cable (receiver fibre)
- 3 Protective hood, can be raised at both ends
- 4 Mounting bracket, included
- ⑤ Connection


### **Adjustments**

### WLL170-2



- 6 Indication of correct fibre-optic cable mounting
- 7 LED indicator orange, lights up when switching output is active
- \$ LED signal strength indicator green, lights up, when light received< 0.9 or >1.1 (switching threshold = 1)
- 9 Sensitivity scale 270°
- ® Sensitivity control (10 revolutions)
- $\circledR$  L.ON/ d.ON selection switch. "OFF DLY" (on) / "OFF", 40 ms fixed
- ② Selector switch: "L.ON" ( light-switching) / "D.ON" ( dark-switching)


### WLL170T-2



- **6** Indication of correct fibre-optic cable mounting
- ② LED indicator orange: switching output active
- \$ LED signal strength indicator green, lights up, when light received< 0.9 or >1.1 (switching threshold = 1)
- Teach-in button
- 10 Operating mode selector switch: "SET" (Teach-in mode) / "RUN" (sensor mode)
- @ L.ON/ d.ON selection switch. "OFF DLY" (on) / "OFF", 40 ms fixed
- ${ @ \ \ \, }$  Selector switch: "L.ON" ( light-switching) / "D.ON" ( dark-switching)

### **Connection diagram**

### Cd-043



### Cd-045

### Cd-066

### Cd-092

$$\begin{array}{c|c} & & \\ \hline & \text{brn} & 1 \\ \hline & \text{wht} & 2 \\ \hline & \text{blu} & 3 \\ \hline & & \text{-} (M) \\ \hline & & \text{blk} & 4 \\ \hline & & \text{Q} \\ \end{array}$$

### Cd-093

### **Function diagram**


### WLL170T-2

### ■ WLL170T-2 in sensor mode

Operating mode selector switch in RUN mode (after setting the switching threshold by means of Teach-in.

**Orange LED display:** lights up if supply connection Q is active. Dependent on setting of light/dark-selector switch.

**Green LED display:** lights up if light received is < 0.9 or > 1.1 (based on the switching threshold Q, switching threshold = 1).



### **Recommended accessories**

### Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
3 700	Steel, zinc coated	Mounting bracket	BEF-WLL170	5306574

### Plug connectors and cables

### Connecting cable (female connector-open)

- Cable material: PVC
- Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Model name	Part no.
	Female connector,	Cable, open	2 m, 3-wire	TPU	DOL-0803-G02M	6010785
	M8, 3-pin, straight	conductor heads	5 m, 3-wire	TPU	DOL-0803-G05M	6022009
	Female connector,	Cable, open	2 m, 3-wire	TPU	DOL-0803-W02M	6008489
	M8, 3-pin, angled	conductor heads	5 m, 3-wire	TPU	DOL-0803-W05M	6022010
	Female connector,	Cable, open	2 m, 4-wire	PVC	DOL-0804-G02M	6009870
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	PVC	DOL-0804-G05M	6009872
	Female connector,	Cable, open	2 m, 4-wire	PVC	DOL-0804-W02M	6009871
	M8, 4-pin, angled	conductor heads	5 m, 4-wire	PVC	DOL-0804-W05M	6009873

### Female connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Description	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0803-G	7902077
	Female connector, M8, 3-pin, angled	Pin penetration	PBT	IP 67	DOS-0803-W	7902078
	Female connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	DOS-0804-G	6009974
	Female connector, M8, 4-pin, angled	Pin penetration	PBT	IP 67	DOS-0804-W	6009975

### Male connector (ready to assemble)

Figure	Connection type head A	Connection type head B	Connector material	Description	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	STE-0803-G	6037322
	Male connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	STE-0804-G	6037323

### Other mounting accessories

### Others

Figure	Material	Description	Model name	Part no.
A Property of the second	Stainless steel	Rail end piece for block mounting	BF-EB01-W190	5313011
Manual Ma	Plastic	Cutter for fibers, supplied with LL3, 10 mm x 37 mm x 65 mm	FC	5304141

<sup>→</sup> For additional accessories, please see page L-861













### **Additional information**

Detailed technical data J-799
Ordering information J-800
Dimensional drawings J-801
Adjustments J-802
Connection diagram J-802
Recommended accessories I-803

### **Product description**

The WLL180T fiber-optic photoelectric sensor family provides the world's fastest response time - only 16 µs. In addition, it offers superior sensing distances of up to 20 m and its high light intensity delivers a reliable, high-powered solution - even in difficult ambient conditions, like dust, spray, mist, and water jets. Commissioning is simple - either via the external teach-in input or directly on the unit. Two, four-digit displays provide visualization of all programming

steps, status displays, plus target and actual values through an intuitive menu structure. The WLL180T sensors can be operated either as a stand-alone or in a bus configuration, depending on the requirements. In a bus configuration, several sensors are networked via an internal bus, enabling the settings on one WLL180T to be copied to all other devices on the bus. Fiber-optic amplifier cross-talk is prevented by the sensors' integrated anti-interference logic.

### At a glance

- Selectable response time up to 16 µs
- Sensing range up to 20 m (Throughbeam system); up to 1400 mm (proximity system)
- Bus-compatible with anti-interference
- 2 x 4-digit display
- Adjustable hysteresis
- · Rotatable display screen
- · High-resolution signal processing
- · Programmable time delays

### Your benefits

- Reliable, rapid process detection, even under the most difficult ambient conditions, such as dust, spray or mist
- Easy commissioning and product changeover due to external teach-in
- Cross-talk is eliminated when utilizing bus configuration option
- Quick, easy setup and adjustment due to an intuitive operating menu
- · Flexible parameter adjustment due to high-resolution signal processing. Hysteresis and time delays can be adapted to suit the application, e.g., when detecting tiny or transparent objects
- Easy-to-read display, even under difficult installation conditions

### → www.mysick.com/en/WLL180T

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



### **Detailed technical data**

### **Features**

Sensor principle	Fiber-optic photoelectric sensor
Device type	Stand-alone/Base unit 1)/Expansion unit (depending on type)
Dimensions (W x H x D)	10.5 mm x 34.6 mm x 71.9 mm
Housing design (light emission)	Rectangular
Sensing range max. 2)	0 m 20 m, through-beam system <sup>3)</sup> (depending on type)
Sensing range	0 mm 1,400 mm, proximity system $^{4)}$ 5) 0 18 m, through-beam system $^{3)}$ (depending on type)
Type of light	Visible red light / Infrared light (depending on type)
Light source 6)	LED
Angle of dispersion	Approx. 65°
Wave length	
Visible red light	650 nm
Infrared light	1,450 nm
Teach-in	Menu-controlled
Time type	Without time delay Time delay off Switch on delay ON and OFF delay One shot
Delay time	Programmable: 0 ms 9,999 ms
Indication	Display
Display	LED status display / $2x$ 4-character digital dual displays, Set value (green indicator) and actual value (red indicator) are displayed simultaneously, display of parameters

 $<sup>^{\</sup>scriptscriptstyle 1)}\,\text{Up}$  to 15 expansion units can be connected.

### Mechanics/electronics

Supply voltage 1)	12 V DC 24 V DC
Ripple <sup>2)</sup>	≤ 10 %
Power consumption 3)	≤ 50 mA
Output type	PNP, open collector/NPN, open collector (depending on type)
Switching mode	Light/dark-switching (manually selectable)
Output current I <sub>max.</sub>	≤ 100 mA
Response time 4)	$\leq$ 2 ms, $\leq$ 8 ms, $\leq$ 16 $\mu$ s, $\leq$ 70 $\mu$ s, $\leq$ 250 $\mu$ s
Switching frequency	31.2 kHz, 7.1 kHz, 2 kHz, 250 Hz, 62.5 Hz
Connection type	Cable, 2 m 5/Male connector, M8 (depending on type)
Circuit protection	A <sup>6)</sup> , B <sup>7)</sup> , C <sup>8)</sup> , D <sup>9)</sup>
Protection class	III

 $<sup>^{2)}</sup>$  Sensing range with 8 ms response time. Reduction with shorter response time (see tables LL3/WLL180T)

<sup>3)</sup> LL3-TX01.

<sup>&</sup>lt;sup>4)</sup> Objects to be sensed with 90% reflectivity (based on DIN 5033 white standard). Sensing range with 8 ms response time. Reduction with shorter response time (see tables LL3/WLL180T)

<sup>5)</sup> LL3-DK06

 $<sup>^{6)}</sup>$  Average service life of 100,000 h at  $\rm T_A$  = +25  $^{\circ}\rm C.$ 

Housing material	ABS/PC
Enclosure rating 10)	IP 50
Ambient operating temperature	$-25~^{\circ}\text{C} \dots +55~^{\circ}\text{C}$ $^{11)}$ (depending on type)
Ambient storage temperature	-40 °C +70 °C

<sup>&</sup>lt;sup>1)</sup> +- 10%.

### **Ordering information**

Other models available at www.mysick.com/en/WLL180T

### Stand-alone

• Adjustment: Teach-in buttoncable+/- increment button, manual

Type of light	Sensing range max. 1)	Output type	tput type Connection		Model name	Part no.
		PNP	Cable, 4-wire, 2 m	Cd-136	WLL180T-P432	6039093
Visible and limb	0 m 20 m, through-	PINP	Male connector, M8, 4-pin	Cd-134	WLL180T-P434	6039095
Visible red light	beam system 2)	NIDNI	Cable, 4-wire, 2 m	Cd-136	WLL180T-N432	6039094
		NPN	Male connector, M8, 4-pin	Cd-134	WLL180T-N434	6039096
Infrared light	0 mm 1,000 mm,	PNP	Male connector, M8, 4-pin	Cd-134	WLL180T-P474	6039618
Infrared light	through-beam system 3)	NPN	Male connector, M8, 4-pin	Cd-134	WLL180T-N474	6039619

 $<sup>^{1)}</sup>$  Sensing range with 8 ms response time. Reduction with shorter response time (see tables LL3/WLL180T)

### Base unit

- Type of light: visible red light
- Adjustment: Teach-in button, cable, manual +/- increment button
- Sensing range max.: 0 m ... 20 m, through-beam system (Sensing range with 8 ms response time. Reduction with shorter response time (see tables LL3/WLL180T)) (LL3-TX01.)

Output type	Connection	Connection diagram	Model name	Part no.
	Cable, 4-wire, 2 m	Cd-138	WLL180T-M432	6039097
PNP	Male connector, M8, 3-pin	Cd-045	WLL180T-M333	6042428
	Male connector, M8, 4-pin	Cd-140	WLL180T-M434	6039101
	Cable, 4-wire, 2 m	Cd-138	WLL180T-L432	6039099
NPN	Male connector, M8, 3-pin	Cd-045	WLL180T-L333	6049837
	Male connector, M8, 4-pin	Cd-140	WLL180T-L434	6039103
2 x PNP	Male connector, M8, 4-pin	Cd-213	WLL180T-M634	6050760

 $<sup>^{\</sup>rm 2)}$  May not exceed or fall short of  $\rm V_{\rm S}$  tolerances.

<sup>3)</sup> Without load.

<sup>4)</sup> Selectable.

<sup>&</sup>lt;sup>5)</sup> Do not bend below 0 °C.

 $<sup>^{6)}</sup>$  A =  $V_s$  connections reverse-polarity protected.

<sup>&</sup>lt;sup>7)</sup> B = inputs and output reverse-polarity protected.

 $<sup>^{8)}</sup>$  C = interference suppression.

 $<sup>^{\</sup>rm 9)}$  D = outputs overcurrent and short-circuit protected.

 $<sup>^{\</sup>rm 10)}$  With correctly attached fibre-optic cable LL3 and closed protection hood.

<sup>&</sup>lt;sup>11)</sup> Operating temperature fluctuates according to number of devices connected: 4–8 devices: -25 °C ... +50 °C (output current 50 mA) / 9–16 devices: -25 °C ... +45 °C (output current 20 mA)

<sup>&</sup>lt;sup>2)</sup> LL3-TX01.

<sup>3)</sup> LL3-TW01.


### Expansion unit

- Type of light: visible red light
- Adjustment: Teach-in buttoncable+/- increment button, manual
- Sensing range max.: 0 m ... 20 m, through-beam system (Sensing range with 8 ms response time. Reduction with shorter response time (see tables LL3/WLL180T)) (LL3-TX01.)

Output type	Connection	Connection diagram	Model name	Part no.
	Cable, 2-wire, 2 m	Cd-138	WLL180T-F232	6039098
PNP	Male connector, M8, 3-pin	Cd-045	WLL180T-F333	6042429
	Male connector, M8, 4-pin	Cd-140	WLL180T-F434	6039102
	Cable, 2-wire, 2 m	Cd-138	WLL180T-E232	6039100
NPN	Male connector, M8, 3-pin	Cd-045	WLL180T-E333	6049838
	Male connector, M8, 4-pin	Cd-140	WLL180T-E434	6039104
2 x NPN	Cable, 2-wire, 2 m	Cd-214	WLL180T-E632	6050763


### **Dimensional drawings**

### Stand-alone




- Dimensions in mm (inch)
- ① Sender LED, installation of LL3 fibre-optic cable (sender fibre)
- ② Receiver, installation of LL3 fibre optic cable (receiver fibre)
- ③ Protective hood, can be raised at both ends
- 4 Connection
- ⑤ Mounting bracket, included

### **Base unit**




- ① Sender LED, installation of LL3 fibre-optic cable (sender fibre)
- ② Receiver, installation of LL3 fibre optic cable (receiver fibre)
- ③ Protective hood, can be raised at both ends
- 4 Connection
- ⑤ Mounting bracket, included

### **Extension unit**



- ① Sender LED, installation of LL3 fibre-optic cable (sender fibre)
- 2 Receiver, installation of LL3 fibre optic cable (receiver fibre)
- 3 Protective hood, can be raised at both ends
- 4 Connection
- (5) Mounting bracket, included
- 6 Bus connector

### **Adjustments**



- 3 Locking the fiber-optic cables
- ② LED indicator orange, lights up when switching output is active
- ® Numeric display 2 x 4-digit; green: switching threshold, operating mode; red: actual value, Teach-in and function parameter
- Step-button> (manual switching threshold: higher; or next function parameter)
- 10 Step-button< (manual switching threshold: lower; or previous function parameter)
- 1 Mode/Enter-button
- 12 Teach-in button

### **Connection diagram**


# Cd-045


## Ext. Input

$$\begin{array}{c|c} & & & & \\ & & & & \\ & & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ & & & \\ &$$

Cd-134

### Cd-136






\*) Only base unit

### Cd-140




 $^{*)}$  Only base unit

### Cd-213



### Cd-214



### **Recommended accessories**

### Mounting brackets/plates

### **Mounting brackets**

Figure	Material	Description	Model name	Part no.
(Sh			BEF-WLL170 53	5306574
S. Comments	Steel, zinc coated	Mounting bracket	BEF-WLL180	5325812

### Plug connectors and cables

### Connecting cable (female connector-open)

- Cable material: PVC
- Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Connector material	Model name	Part no.
	Female connector, M8, 3-pin, straight	Cable, open	2 m, 3-wire	TPU	DOL-0803-G02M	6010785
		conductor heads	5 m, 3-wire	TPU	DOL-0803-G05M	6022009
	Female connector, M8, 3-pin, angled	Cable, open	2 m, 3-wire	TPU	DOL-0803-W02M	6008489
1		conductor heads	5 m, 3-wire	TPU	DOL-0803-W05M	6022010
	Female connector,	Cable, open	2 m, 4-wire	PVC	DOL-0804-G02M	6009870
	M8, 4-pin, straight	conductor heads	5 m, 4-wire	PVC	DOL-0804-G05M	6009872
	Female connector	Cable, open	2 m, 4-wire	PVC	DOL-0804-W02M	6009871
Female connector, M8, 4-pin, angled	conductor heads	5 m, 4-wire	PVC	DOL-0804-W05M	6009873	

### Other mounting accessories

### Others

Figure	Material	Description	Model name	Part no.
A Property of the Parks	Stainless steel	Rail end piece for block mounting	BF-EB01-W190	5313011
THE REAL PROPERTY OF THE PARTY	Plastic	Cutter for fibers, supplied with LL3, 10 mm x 37 mm x 65 mm	FC	5304141

→ For additional accessories, please see page L-861







### **Product description**

For any application-oriented sensor solution, a suitable fiber-optic cable must be chosen. At SICK, the broad range of fiberoptic cables made from plastic and glass fibers permits optimal automation solutions. This applies in particular to tasks for which the fiber-optic cable requires application-specific adaption, where flexible cable installation is crucial, where high temperatures prevail, or a particular material compatibility is important. While the fibers of plastic fiber-optic cables are characterized, among other things, by

the smallest of bend radii and maximum flexibility, and can also be shortened to any length, the glass fiber-optic cables are more chemically resistant and suitable for a higher temperature range. The wide variety of end sleeve options or individual special sleeves enable virtually any installation possibility. Depending on the application, the fiber-optic cable's protective cladding can be made from plastic, metal, or Teflon for exposure to aggressive chemicals.

### At a glance

- · Very large selection of plastic and glass fiber-optic cables.
- · Fiber-optic cables resistant to chemicals and high temperature
- · Threaded and smooth sleeves, bands of light (array), 90° reflection versions available
- Focused optics
- Proximity and through-beam versions available
- · Plastic, protective metal or Teflon sheathing available

### Your benefits

- Very large selection of fiber-optic cables with plastic and glass fibers, giving users more application flex-
- Resistant to damage caused by mechanical and chemical stress, as well as high temperatures
- Standard and customer-specific types
- Simple installation saves time
- · For detection of objects, surfaces, leading edges, and fluid levels

### $\epsilon$

### **Additional information**

Ordering information........... J-806 Dimensional drawings ..... J-833 Recommended accessories ..... I-855

### www.mysick.com/en/LL3

For more information, just enter the link or scan the QR code and get direct access to technical data, CAD design models, operating instructions, software, application examples and much more



### Selection chart

Detection principle	Category	Ordering information (page)	Dimensional drawing (page)
	Threaded sleeve	J-806	J-833
	Smooth sleeve	J-808	J-835
	90° deflection	J-809	J-836
	Flat type	J-810	J-836
Proximity system	Long end sleeve	J-812	J-839
	Area detection	J-814	J-841
	Heat-resistant	J-815	J-842
1-7	Resistant to oil/chemicals	J-815	J-842
	LCDs/transparent objects/semiconductors	J-816	J-843
	Retro-reflective	J-816	J-843
	Liquid level	J-817	J-844
	Tip adapters	J-832	J-855
	Threaded sleeve	J-818	J-845
	Smooth sleeve	J-819	J-846
	90° deflection	J-820	J-847
Through-beam system	Flat type	J-821	J-848
Tillough-beath system	Long end sleeve	J-823	J-850
	Area detection	J-824	J-851
i-J	Heat-resistant	J-825	J-852
	LCDs/transparent objects/semiconductors	J-826	J-854
	Resistant to oil/chemicals	J-827	J-854
	Liquid level	J-827	J-855
	Tip adapters	J-828	J-855

### **Ordering information**

Other models available at www.mysick.com/en/LL3



### Threaded sleeve

• Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
(M3)		≥ 0.02 mm	10 mm		14 mm <sup>1)</sup> 49 mm <sup>2)</sup> 99 mm <sup>3)</sup> 190 mm <sup>4)</sup> 210 mm <sup>5)</sup>	60 mm <sup>6)</sup> 27 mm <sup>7)</sup> 17 mm <sup>8)</sup>	LL3-DJ01	5325989
(m)	1,000 mm	2 0.02 11111	10 111111	-	38 mm <sup>1)</sup> 120 mm <sup>2)</sup> 230 mm <sup>3)</sup> 460 mm <sup>4)</sup> 490 mm <sup>5)</sup>	110 mm <sup>6)</sup> 50 mm <sup>7)</sup> 30 mm <sup>8)</sup>	LL3-DJ02	5325992
		≥ 0.015 mm	4 mm	V	18 mm <sup>1)</sup> 50 mm <sup>2)</sup> 90 mm <sup>3)</sup> 200 mm <sup>4)</sup> 370 mm <sup>5)</sup>	22 mm <sup>6)</sup> 9 mm <sup>7)</sup> 3 mm <sup>8)</sup>	LL3-DR02	5308079
<b>™</b> ≥ ×			4 mm	V	18 mm <sup>1)</sup> 60 mm <sup>2)</sup> 100 mm <sup>3)</sup> 220 mm <sup>4)</sup> 360 mm <sup>5)</sup>	37 mm <sup>6)</sup> 11 mm <sup>7)</sup> 5 mm <sup>8)</sup>	LL3-DR06	5308082
			45	V	18 mm <sup>1)</sup> 55 mm <sup>2)</sup> 95 mm <sup>3)</sup> 190 mm <sup>4)</sup> 360 mm <sup>5)</sup>	47 mm <sup>6)</sup> 17 mm <sup>7)</sup> 7 mm <sup>8)</sup>	LL3-DS06	5308073
(ma)	0.000	. 0.045	15 mm		40 mm <sup>1)</sup> 130 mm <sup>2)</sup> 200 mm <sup>3)</sup> 350 mm <sup>4)</sup> 600 mm <sup>5)</sup>	75 mm <sup>6)</sup> 22 mm <sup>7)</sup> 11 mm <sup>8)</sup>	LL3-DT01	5308076
(Me)	2,000 mm	≥ 0.015 mm			90 mm <sup>1)</sup> 280 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,350 mm <sup>5)</sup>	160 mm <sup>6)</sup> 62 mm <sup>7)</sup> 37 mm <sup>8)</sup>	LL3-DB01	5308074
(Me)			25 mm	V	90 mm <sup>1)</sup> 300 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,350 mm <sup>5)</sup>	160 mm <sup>6)</sup> 62 mm <sup>7)</sup> 37 mm <sup>8)</sup>	LL3-DB03	5313021
(Ma)					90 mm <sup>1)</sup> 280 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,350 mm <sup>5)</sup>	90 mm <sup>6)</sup> 55 mm <sup>7)</sup> 50 mm <sup>8)</sup>	LL3-DB04	5325990

 $<sup>^{\</sup>scriptscriptstyle 1)}$  Operating mode: 16  $\mu s.$ 

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s.$ 

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Operating mode: 250  $\mu s.$ 

<sup>4)</sup> Operating mode: 2 ms.

<sup>&</sup>lt;sup>5)</sup> Operating mode: 8 ms.

 $<sup>^{6)}</sup>$  Red light: 250  $\mu$ s.  $^{7)}$  High speed: 50  $\mu$ s.  $^{8)}$  Green light: 250  $\mu$ s.

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
M6			25 mm	V	100 mm <sup>1)</sup> 300 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,400 mm <sup>5)</sup>	165 mm <sup>6)</sup> 65 mm <sup>7)</sup> 37 mm <sup>8)</sup>	LL3-DK06	5313019
		≥ 0.015 mm	2 mm	V	90 mm <sup>1)</sup> 300 mm <sup>2)</sup> 500 mm <sup>3)</sup>	115 mm <sup>6)</sup>	LL3-DK66	5313024
MB Z		2 0.010 111111	2 111111	•	900 mm <sup>4)</sup> 1,400 mm <sup>5)</sup>	27 mm <sup>8)</sup>	LL3-DK67	5313025
			4 mm	V	90 mm <sup>1)</sup> 280 mm <sup>2)</sup> 450 mm <sup>3)</sup> 880 mm <sup>4)</sup> 1,350 mm <sup>5)</sup>	135 mm <sup>6)</sup> 50 mm <sup>7)</sup> 20 mm <sup>8)</sup>	LL3-DR01	5308078
	2,000 mm		4 mm	V	8 mm <sup>1)</sup> 25 mm <sup>2)</sup> 46 mm <sup>3)</sup> 90 mm <sup>4)</sup> 98 mm <sup>5)</sup>	22 mm <sup>6)</sup> 9 mm <sup>7)</sup> 6 mm <sup>8)</sup>	LL3-DR08	5326037
			45	-	14 mm <sup>1)</sup> 45 mm <sup>2)</sup> 75 mm <sup>3)</sup> 135 mm <sup>4)</sup> 200 mm <sup>5)</sup>	17 mm <sup>6)</sup> 7 mm <sup>7)</sup> 3 mm <sup>8)</sup>	LL3-DK21	5313023
(M4)		≥ 0.02 mm	15 mm	V	40 mm <sup>1)</sup> 130 mm <sup>2)</sup> 200 mm <sup>3)</sup> 350 mm <sup>4)</sup> 600 mm <sup>5)</sup>	72 mm <sup>6)</sup> 22 mm <sup>7)</sup> 11 mm <sup>8)</sup>	LL3-DM02	5308077
(M3)			25	V	27 mm <sup>1)</sup> 88 mm <sup>2)</sup> 165 mm <sup>3)</sup> 330 mm <sup>4)</sup> 350 mm <sup>5)</sup>	65 mm <sup>6)</sup> 30 mm <sup>7)</sup> 20 mm <sup>8)</sup>	LL3-DB07	5325988
MA		25 mm	V	75 mm <sup>1)</sup> 255 mm <sup>2)</sup> 420 mm <sup>3)</sup> 800 mm <sup>4)</sup> 1,300 mm <sup>5)</sup>	165 mm <sup>6)</sup> 65 mm <sup>7)</sup> 37 mm <sup>8)</sup>	LL3-DM01	5308071	
<sup>1)</sup> Operating mode: 16) Red light: 250 μs.		erating mode: 70 ed: 50 µs.	μs. <sup>3)</sup> Opera Green light: 250	ting mode: 250 μ μs.		ng mode: 2 ms.	<sup>5)</sup> Operating mode: 8 ms	ò.

<sup>→</sup> For dimensional drawings, please see page J-833



• Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
2 1	1,000 mm	≥ 0.015 mm	4 mm	-	20 mm <sup>1)</sup> 70 mm <sup>2)</sup> 110 mm <sup>3)</sup> 220 mm <sup>4)</sup> 360 mm <sup>5)</sup>	25 mm <sup>6)</sup> 9 mm <sup>7)</sup> 3 mm <sup>8)</sup>	LL3-DR04	5308081
		≥ 0.02 mm	10 mm	-	3 mm <sup>2)</sup> 14 mm <sup>3)</sup> 29 mm <sup>4)</sup> 31 mm <sup>5)</sup>	3.5 mm <sup>6)</sup>	LL3-DP01	5325998
2			2 mm	V	65 mm <sup>1)</sup> 200 mm <sup>2)</sup> 350 mm <sup>3)</sup> 650 mm <sup>4)</sup> 1,000 mm <sup>5)</sup>	115 mm <sup>6)</sup> 47 mm <sup>7)</sup> 27 mm <sup>8)</sup>	LL3-DK4Z	5313026
<b>2 X</b>		> 0.015 mm	4 mm	V	30 mm <sup>1)</sup> 85 mm <sup>2)</sup> 140 mm <sup>3)</sup> 300 mm <sup>4)</sup> 600 mm <sup>5)</sup>	37 mm <sup>6)</sup> 13 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DR03	5308080
		≥ 0.015 mm	15 mm	V	18 mm <sup>1)</sup> 55 mm <sup>2)</sup> 95 mm <sup>3)</sup> 190 mm <sup>4)</sup> 360 mm <sup>5)</sup>	47 mm <sup>6)</sup> 17 mm <sup>7)</sup> 7 mm <sup>8)</sup>	LL3-DT03	5308072
	2,000 mm		25 mm	V	100 mm <sup>1)</sup> 300 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,400 mm <sup>5)</sup>	165 mm <sup>6)</sup> 65 mm <sup>7)</sup> 37 mm <sup>8)</sup>	LL3-DK04	5313020
			1 mm	V	4 mm <sup>1)</sup> 13 mm <sup>2)</sup> 27 mm <sup>3)</sup> 55 mm <sup>4)</sup> 59 mm <sup>5)</sup>	11 mm <sup>6)</sup> 5 mm <sup>7)</sup>	LL3-DR12	5326001
	≥ 0.02 mm	≥ 0.02 mm	2 mm	V	22 mm <sup>1)</sup> 74 mm <sup>2)</sup> 140 mm <sup>3)</sup> 280 mm <sup>4)</sup> 300 mm <sup>5)</sup>	65 mm <sup>6)</sup> 30 mm <sup>7)</sup> 20 mm <sup>8)</sup>	LL3-DR11	5326000
		25 mm	V	70 mm <sup>1)</sup> 220 mm <sup>2)</sup> 360 mm <sup>3)</sup> 720 mm <sup>4)</sup> 770 mm <sup>5)</sup>	170 mm <sup>6)</sup> 75 mm <sup>7)</sup> 60 mm <sup>8)</sup>	LL3-DB10	5325999	

<sup>→</sup> For dimensional drawings, please see page J-835

7) High speed: 50 μs.

8) Green light: 250 µs.

<sup>6)</sup> Red light: 250 μs.



### 90° deflection

• Detection principle: Proximity system

• Length: 2,000 mm

• Fiber-optic cable cuttable: 🗸

Figure	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
		2 mm	20 mm <sup>1)</sup> 110 mm <sup>2)</sup> 180 mm <sup>3)</sup> 400 mm <sup>4)</sup> 650 mm <sup>5)</sup>	16 mm <sup>6)</sup> 12 mm <sup>7)</sup> 12 mm <sup>8)</sup>	LL3-DV07	5322551
	≥ 0.015 mm	0.5	25 mm <sup>1)</sup> 110 mm <sup>2)</sup> 185 mm <sup>3)</sup> 400 mm <sup>4)</sup> 650 mm <sup>5)</sup>	47 mm <sup>6)</sup> 17 mm <sup>7)</sup> 17 mm <sup>8)</sup>	LL3-DV05	5322549
		25 mm	30 mm <sup>1)</sup> 130 mm <sup>2)</sup> 210 mm <sup>3)</sup> 450 mm <sup>4)</sup> 800 mm <sup>5)</sup>	47 mm <sup>6)</sup> 12 mm <sup>7)</sup> 12 mm <sup>8)</sup>	LL3-DV06	5322550
	≥ 0.02 mm	25 mm	47 mm <sup>1)</sup> 165 mm <sup>2)</sup> 285 mm <sup>3)</sup> 575 mm <sup>4)</sup> 610 mm <sup>5)</sup>	110 mm <sup>6)</sup> 55 mm <sup>7)</sup> 30 mm <sup>8)</sup>	LL3-DB09	5325991
1) Operating mode:	16 µs. <sup>2)</sup> Operating m	node: 70 µs. 3) Opera	ating mode: 250 µs. 4	Operating mode: 2 ms.	5) Operating mode: 8 m	S.

<sup>→</sup> For dimensional drawings, please see page J-836

 $^{6)}$  Red light: 250  $\mu s.$   $^{7)}$  High speed: 50  $\mu s.$   $^{8)}$  Green light: 250  $\mu s.$ 



• Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
2		≥ 0.01 mm	1 mm	V	13 mm <sup>1)</sup> 48 mm <sup>2)</sup> 86 mm <sup>3)</sup> 170 mm <sup>4)</sup> 180 mm <sup>5)</sup>	35 mm <sup>6)</sup> 15 mm <sup>7)</sup> 12 mm <sup>8)</sup>	LL3-DE02	5324497
2	1,000 mm	≥ 0.16 mm	1 mm	V	11 mm <sup>1)</sup> 38 mm <sup>2)</sup> 78 mm <sup>3)</sup> 150 mm <sup>4)</sup> 160 mm <sup>5)</sup>	35 mm <sup>6)</sup> 8 mm <sup>7)</sup>	LL3-DE01	5325285
10		≥ 0.3 mm	1 mm	V	2 mm <sup>1)</sup> 4 mm <sup>2)</sup> 6 mm <sup>3)</sup> 9 mm <sup>4)</sup> 10 mm <sup>5)</sup>	4.5 mm <sup>6)</sup> 2.5 mm <sup>7)</sup> 2.5 mm <sup>8)</sup>	LL3-DC08	5326029
<b>20</b> ×		-	4 mm	V	15 mm <sup>1)</sup> 22 mm <sup>2)</sup> 23 mm <sup>3)</sup> 25 mm <sup>4)</sup> 25 mm <sup>5)</sup>	15 mm <sup>6)</sup> 15 mm <sup>7)</sup> 10 mm <sup>8)</sup>	LL3-DC06	5326017
2		> 0.01	4		12 mm <sup>1)</sup> 25 mm <sup>2)</sup> 37 mm <sup>3)</sup> 75 mm <sup>4)</sup> 90 mm <sup>5)</sup>	30 mm <sup>6)</sup> 10 mm <sup>7)</sup> 5 mm <sup>8)</sup>	LL3-DC47	5324268
2	2 000	≥ 0.01 mm	1 mm	V	35 mm <sup>1)</sup> 45 mm <sup>2)</sup> 55 mm <sup>3)</sup> 250 mm <sup>4)</sup> 330 mm <sup>5)</sup>	50 mm <sup>6)</sup> 35 mm <sup>7)</sup> 10 mm <sup>8)</sup>	LL3-DC57	5324269
00	2,000 mm		10 mm	V	8 mm <sup>1)</sup> 10 mm <sup>2)</sup> 11 mm <sup>3)</sup> 13 mm <sup>4)</sup> 17 mm <sup>5)</sup>	8 mm <sup>6)</sup> 8 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DC09	5326028
J. a. glass		≥ 0.02 mm	0.5	-	5 mm <sup>1)</sup> 10 mm <sup>2)</sup> 19 mm <sup>3)</sup> 37 mm <sup>4)</sup> 43 mm <sup>5)</sup>	7 mm <sup>6)</sup> 10.5 mm <sup>7)</sup> 9 mm <sup>8)</sup>	LL3-DH06	5326026
S of			25 mm	V	5 mm <sup>1)</sup> 11 mm <sup>2)</sup> 22 mm <sup>3)</sup> 30 mm <sup>4)</sup> 38 mm <sup>5)</sup>	11 mm <sup>6)</sup> 15.5 mm <sup>7)</sup> 9.3 mm <sup>8)</sup>	LL3-DH08	5326025

 $<sup>^{\</sup>scriptscriptstyle 1)}$  Operating mode: 16  $\mu$ s.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

 $<sup>^{\</sup>scriptscriptstyle 3)}$  Operating mode: 250  $\mu s.$ 

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs.

 $<sup>^{7)}</sup>$  High speed: 50  $\mu$ s.


<sup>8)</sup> Green light: 250 µs.

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
					45 mm <sup>1)</sup> 130 mm <sup>2)</sup> 250 mm <sup>3)</sup> 510 mm <sup>4)</sup> 550 mm <sup>5)</sup>	110 mm <sup>6)</sup> 43 mm <sup>7)</sup> 31 mm <sup>8)</sup>	LL3-DE03	5325986
	2,000 mm	≥ 0.03 mm	1 mm	V	50 mm <sup>1)</sup> 130 mm <sup>2)</sup> 250 mm <sup>3)</sup> 500 mm <sup>4)</sup> 540 mm <sup>5)</sup>	110 mm <sup>6)</sup> 50 mm <sup>7)</sup> 35 mm <sup>8)</sup>	LL3-DE04	5325987
20	2,000 111111				110 mm <sup>1)</sup> 345 mm <sup>2)</sup> 560 mm <sup>3)</sup> 1,100 mm <sup>4)</sup> 1,190 mm <sup>5)</sup>	300 mm <sup>6)</sup> 120 mm <sup>7)</sup> 80 mm <sup>8)</sup>	LL3-DR09	5325528
00		≥ 0.06 mm	10 mm	V	8 mm <sup>1)</sup> 12 mm <sup>2)</sup> 14 mm <sup>3)</sup> 16 mm <sup>4)</sup> 18 mm <sup>5)</sup>	10 mm <sup>6)</sup> 8 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DC07	5326019
		-	4 mm	V	18 mm <sup>1)</sup> 31 mm <sup>2)</sup> 34 mm <sup>3)</sup> 38 mm <sup>4)</sup> 38 mm <sup>5)</sup>	20 mm <sup>6)</sup> 20 mm <sup>7)</sup> 15 mm <sup>8)</sup>	LL3-DC04	5326018
0.00	3,000 mm	> 0.00 yyyy	05		11 mm <sup>1)</sup> 18 mm <sup>2)</sup> 21 mm <sup>3)</sup> 24 mm <sup>4)</sup> 26 mm <sup>5)</sup>	18 mm <sup>6)</sup> 18 mm <sup>7)</sup> 15 mm <sup>8)</sup>	LL3-DH10	5326023
0.00 N 10000		≥ 0.02 mm	25 mm	-	19 mm <sup>1)</sup> 29 mm <sup>2)</sup> 34 mm <sup>3)</sup> 39 mm <sup>4)</sup> 42 mm <sup>5)</sup>	24 mm <sup>6)</sup> 24 mm <sup>7)</sup> 24 mm <sup>8)</sup>	LL3-DH11	5326024
80	4,000 mm	≥ 0.3 mm	25 mm	V	60 mm <sup>1)</sup> 75 mm <sup>2)</sup> 85 mm <sup>3)</sup> 150 mm <sup>4)</sup> 280 mm <sup>5)</sup>	80 mm <sup>6)</sup> 60 mm <sup>7)</sup> 60 mm <sup>8)</sup>	LL3-DC03	5326020

 $<sup>^{\</sup>scriptscriptstyle 1)}$  Operating mode: 16  $\mu s$ .  $^{2)}$  Operating mode: 70  $\mu s$ .  $^{3)}$  Operating mode: 250  $\mu s$ . 4) Operating mode: 2 ms. <sup>5)</sup> Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs. <sup>7)</sup> High speed: 50 μs. <sup>8)</sup> Green light: 250 μs.

<sup>→</sup> For dimensional drawings, please see page J-836



• Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
2 %				V	10 mm <sup>1)</sup> 30 mm <sup>2)</sup> 60 mm <sup>3)</sup> 140 mm <sup>4)</sup> 225 mm <sup>5)</sup>	9 mm <sup>6)</sup> 4 mm <sup>7)</sup> 2 mm <sup>8)</sup>	LL3-DT02	5308085
2 %	500 mm	≥ 0.015 mm	4 mm		13 mm <sup>1)</sup> 45 mm <sup>2)</sup> 80 mm <sup>3)</sup> 140 mm <sup>4)</sup> 280 mm <sup>5)</sup>	9 mm <sup>6)</sup> 4 mm <sup>7)</sup> 2 mm <sup>8)</sup>	LL3-DT04	5308086
				-	10 mm <sup>1)</sup> 30 mm <sup>2)</sup> 60 mm <sup>3)</sup> 140 mm <sup>4)</sup> 225 mm <sup>5)</sup>	12 mm <sup>6)</sup> 4 mm <sup>7)</sup> 2 mm <sup>8)</sup>	LL3-DR05	5308087
		≥ 0.015 mm	25 mm	-	5 mm <sup>1)</sup> 15 mm <sup>2)</sup> 35 mm <sup>3)</sup> 65 mm <sup>4)</sup> 120 mm <sup>5)</sup>	7 mm <sup>6)</sup> 3 mm <sup>7)</sup>	LL3-DR07	5326007
	1,000 mm				8 mm <sup>1)</sup> 25 mm <sup>2)</sup> 52 mm <sup>3)</sup> 100 mm <sup>4)</sup> 110 mm <sup>5)</sup>	22 mm <sup>6)</sup> 6 mm <sup>7)</sup> 6 mm <sup>8)</sup>	LL3-DB05	5326002
glass W		≥ 0.02 mm	25 mm	-	55 mm <sup>1)</sup> 220 mm <sup>2)</sup> 580 mm <sup>3)</sup> 1,170 mm <sup>4)</sup> 1,240 mm <sup>5)</sup>	220 mm <sup>6)</sup> 90 mm <sup>7)</sup> 70 mm <sup>8)</sup>	LL3-DH05	5326021
20			2 mm	V	90 mm <sup>1)</sup> 300 mm <sup>2)</sup> 500 mm <sup>3)</sup> 900 mm <sup>4)</sup> 1,400 mm <sup>5)</sup>	115 mm <sup>6)</sup> 47 mm <sup>7)</sup> 27 mm <sup>8)</sup>	LL3-DK63Z	5313027
				V	10 mm <sup>1)</sup> 28 mm <sup>2)</sup> 45 mm <sup>3)</sup> 93 mm <sup>4)</sup> 170 mm <sup>5)</sup>	47 mm <sup>6)</sup> 17 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DK43	5313030
	2,000 mm	mm ≥ 0.015 mm	15 mm		10 mm <sup>1)</sup> 25 mm <sup>2)</sup> 45 mm <sup>3)</sup> 90 mm <sup>4)</sup> 170 mm <sup>5)</sup>	50 mm <sup>6)</sup> 17 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DM03	5308084
					10 mm <sup>1)</sup> 28 mm <sup>2)</sup> 45 mm <sup>3)</sup> 95 mm <sup>4)</sup> 170 mm <sup>5)</sup>	50 mm <sup>6)</sup> 17 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DT05	5313028

 $<sup>^{1)}</sup>$  Operating mode: 16  $\mu$ s. <sup>2)</sup> Operating mode: 70 µs.  $^{3)}$  Operating mode: 250  $\mu s$ .

 $^{6)}$  Red light: 250  $\mu s.$ 7) High speed: 50 μs. 8) Green light: 250 µs.

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
<u>.</u>		≥ 0.015 mm	15 mm	V	10 mm <sup>1)</sup> 35 mm <sup>2)</sup> 70 mm <sup>3)</sup> 125 mm <sup>4)</sup> 290 mm <sup>5)</sup>	16 mm <sup>6)</sup> 3 mm <sup>7)</sup> 3 mm <sup>8)</sup>	LL3-DV02	5308089
		2 0.013 11111	25 mm	V	100 mm <sup>1)</sup> 350 mm <sup>2)</sup> 580 mm <sup>3)</sup> 850 mm <sup>4)</sup> 1,300 mm <sup>5)</sup>	170 mm <sup>6)</sup> 67 mm <sup>7)</sup> 42 mm <sup>8)</sup>	LL3-DB02	5308083
			1 mm	V	12 mm <sup>1)</sup> 40 mm <sup>2)</sup> 77 mm <sup>3)</sup> 150 mm <sup>4)</sup> 160 mm <sup>5)</sup>	35 mm <sup>6)</sup> 15 mm <sup>7)</sup> 9 mm <sup>8)</sup>	LL3-DR10	5326005
		> 0.02 mm		V	60 mm <sup>1)</sup> 210 mm <sup>2)</sup> 360 mm <sup>3)</sup> 700 mm <sup>4)</sup> 760 mm <sup>5)</sup>	150 mm <sup>6)</sup> 60 mm <sup>7)</sup> 40 mm <sup>8)</sup>	LL3-DB06	5326006
	2,000 mm	≥ 0.02 mm	25 mm		17 mm <sup>1)</sup> 55 mm <sup>2)</sup> 107 mm <sup>3)</sup> 200 mm <sup>4)</sup> 220 mm <sup>5)</sup>	45 mm <sup>6)</sup> 18 mm <sup>7)</sup> 13 mm <sup>8)</sup>	LL3-DB08	5326004
O. S. Silans				-	65 mm <sup>1)</sup> 225 mm <sup>2)</sup> 500 mm <sup>3)</sup> 1,000 mm <sup>4)</sup> 1,060 mm <sup>5)</sup>	350 mm <sup>6)</sup> 120 mm <sup>7)</sup> 90 mm <sup>8)</sup>	LL3-DH04	5326022
		≥ 0.025 mm	25 mm	V	35 mm <sup>1)</sup> 135 mm <sup>2)</sup> 170 mm <sup>3)</sup> 290 mm <sup>4)</sup> 320 mm <sup>5)</sup>	95 mm <sup>6)</sup> 41 mm <sup>7)</sup> 27 mm <sup>8)</sup>	LL3-DK33	5313031
		≥ 0.025 mm	25 mm	į	40 mm <sup>1)</sup> 135 mm <sup>2)</sup> 180 mm <sup>3)</sup> 270 mm <sup>4)</sup> 330 mm <sup>5)</sup>	95 mm <sup>6)</sup> 41 mm <sup>7)</sup> 22 mm <sup>8)</sup>	LL3-DV01	5308088
					35 mm <sup>1)</sup> 135 mm <sup>2)</sup> 170 mm <sup>3)</sup> 290 mm <sup>4)</sup> 320 mm <sup>5)</sup>	95 mm <sup>6)</sup> 41 mm <sup>7)</sup> 22 mm <sup>8)</sup>	LL3-DV03	5308090
<sup>1)</sup> Operating mode:	16 µs. <sup>2)</sup> Op	erating mode: 70		ting mode: 250 μ		ng mode: 2 ms.	5) Operating mode: 8 m	5.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs.  $^{7)}$  High speed: 50  $\mu$ s.

<sup>&</sup>lt;sup>8)</sup> Green light: 250 μs.

<sup>→</sup> For dimensional drawings, please see page J-839



### Area detection

• Detection principle: Proximity system

• Length: 2,000 mm

• Minimal object diameter: ≥ 0.02 mm • Minimum bend radius: 25 mm

Fiber-optic cable cuttable: 

✓

Figure	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
	65 mm <sup>1)</sup> 240 mm <sup>2)</sup> 320 mm <sup>3)</sup> 650 mm <sup>4)</sup> 690 mm <sup>5)</sup>	-	LL3-DZ01	5326013
	57 mm <sup>1)</sup> 190 mm <sup>2)</sup> 310 mm <sup>3)</sup> 630 mm <sup>4)</sup> 670 mm <sup>5)</sup>	150 mm <sup>6)</sup> 70 mm <sup>7)</sup> 50 mm <sup>8)</sup>	LL3-DZ02	5326014
	50 mm <sup>1)</sup> 160 mm <sup>2)</sup> 280 mm <sup>3)</sup> 450 mm <sup>4)</sup> 590 mm <sup>5)</sup>	110 mm <sup>6)</sup> 55 mm <sup>7)</sup> 35 mm <sup>8)</sup>	LL3-DZ03	5326015

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Operating mode: 16  $\mu s.$ 

→ For dimensional drawings, please see page J-841

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

 $<sup>^{3)}</sup>$  Operating mode: 250  $\mu$ s.

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

 $<sup>^{\</sup>rm 6)}$  Red light: 250  $\mu s.$ 

 $<sup>^{7)}\,\</sup>text{High}$  speed: 50  $\mu\text{s}.$ 

<sup>8)</sup> Green light: 250 µs.



### Heat-resistant

### • Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
Sinso W					65 mm <sup>1)</sup> 260 mm <sup>2)</sup> 670 mm <sup>3)</sup> 1,340 mm <sup>4)</sup> 1,430 mm <sup>5)</sup>	220 mm <sup>6)</sup> 100 mm <sup>7)</sup> 70 mm <sup>8)</sup>	LL3-DH07	5326031
	1,000 mm	≥ 0.02 mm	25 mm	-	20 mm <sup>1)</sup> 50 mm <sup>2)</sup> 95 mm <sup>3)</sup> 150 mm <sup>4)</sup> 400 mm <sup>5)</sup>	-	LL3-DW01	5315234
MO TOOL		≥ 0.015 mm	25 mm	V	70 mm <sup>1)</sup> 230 mm <sup>2)</sup> 350 mm <sup>3)</sup> 600 mm <sup>4)</sup> 1,000 mm <sup>5)</sup>	125 mm <sup>6)</sup> 45 mm <sup>7)</sup> 8 mm <sup>8)</sup>	LL3-DH02	5308092
	2,000 mm	2 0.013 11111	35 mm	V	120 mm <sup>1)</sup> 350 mm <sup>2)</sup> 600 mm <sup>3)</sup> 980 mm <sup>4)</sup> 1,500 mm <sup>5)</sup>	220 mm <sup>6)</sup> 95 mm <sup>7)</sup> 45 mm <sup>8)</sup>	LL3-DH01	5308091
Class W	2,000 111111	≥ 0.02 mm	25 mm	-	55 mm <sup>1)</sup> 220 mm <sup>2)</sup> 490 mm <sup>3)</sup> 990 mm <sup>4)</sup> 1,050 mm <sup>5)</sup>	170 mm <sup>6)</sup> 80 mm <sup>7)</sup> 50 mm <sup>8)</sup>	LL3-DH03	5324787
9.00E		2 U.U2 IIIII	23 111111	V	70 mm <sup>1)</sup> 230 mm <sup>2)</sup> 370 mm <sup>3)</sup> 750 mm <sup>4)</sup> 800 mm <sup>5)</sup>	220 mm <sup>6)</sup> 90 mm <sup>7)</sup> 70 mm <sup>8)</sup>	LL3-DH09	5326030
<sup>1)</sup> Operating mode: <sup>6)</sup> Red light: 250 μs		erating mode: 70 ed: 50 µs.	μs. <sup>3)</sup> Opera Green light: 250	ting mode: 250 μ μs.	s. <sup>4)</sup> Operatir	ng mode: 2 ms.	<sup>5)</sup> Operating mode: 8 ms	ò.

<sup>→</sup> For dimensional drawings, please see page J-842



### Resistant to oil/chemicals

### Detection principle: Proximity system

Figure	Length	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
	2,000 mm	≥ 0.02 mm	60 mm	100 mm <sup>1)</sup> 180 mm <sup>2)</sup> 200 mm <sup>3)</sup> 150 mm <sup>4)</sup> 280 mm <sup>5)</sup>	50 mm <sup>6)</sup> 27 mm <sup>7)</sup> 12 mm <sup>8)</sup>	LL3-DY01	5308093
1) Operating mode:	16 us. 2) Operat	ting mode: 70 us.	3) Operating mode	: 250 us. 4) Ope	rating mode: 2 ms.	5) Operating mode: 8 mg	S.

 $<sup>^{1)}</sup>$  Operating mode: 16 µs.  $^{2)}$  Operating mode: 70 µs.  $^{3)}$  Operating  $^{6)}$  Red light: 250 µs.  $^{7)}$  High speed: 50 µs.  $^{8)}$  Green light: 250 µs.

<sup>→</sup> For dimensional drawings, please see page J-842



### LCDs/transparent objects/semiconductors

- Detection principle: Proximity system
- Fiber-optic cable cuttable: 

  ✓

Figure	Length	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
	2,000 mm	≥ 0.02 mm	<b>1</b> 0 mm	6 mm <sup>1)</sup> 6 mm <sup>2)</sup> 6 mm <sup>3)</sup> 10 mm <sup>4)</sup> 15 mm <sup>5)</sup>	7 mm <sup>6)</sup> 7 mm <sup>7)</sup> 6 mm <sup>8)</sup>	LL3-DC38	5322472
				4 mm <sup>2)</sup> 4 mm <sup>3)</sup> 4 mm <sup>4)</sup> 4 mm <sup>5)</sup>	5 mm <sup>6)</sup> 4 mm <sup>7)</sup> 4 mm <sup>8)</sup>	LL3-DC39	5322513
	3,000 mm	≥ 25 mm	25 mm	18 mm <sup>1)</sup> 29 mm <sup>2)</sup> 35 mm <sup>3)</sup> 40 mm <sup>4)</sup> 43 mm <sup>5)</sup>	22 mm <sup>6)</sup> 22 mm <sup>7)</sup> 25 mm <sup>8)</sup>	LL3-DC05	5326016

 $<sup>^{\</sup>mbox{\tiny 1)}}$  Operating mode: 16  $\mu s.$ 

### → For dimensional drawings, please see page J-843



### Retro-reflective

- Detection principle: Proximity system
- Length: 2,000 mm
- Fiber-optic cable cuttable: 

  ✓

Figure	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
	2000	40	105 mm <sup>1)</sup> 190 mm <sup>2)</sup> 230 mm <sup>3)</sup> 460 mm <sup>4)</sup> 490 mm <sup>5)</sup>	220 mm <sup>6)</sup> 80 mm <sup>7)</sup> 65 mm <sup>8)</sup>	LL3-RB01	5326010
	≥ 0.06 mm	10 mm	100 mm <sup>1)</sup> 170 mm <sup>2)</sup> 210 mm <sup>3)</sup> 430 mm <sup>4)</sup> 460 mm <sup>5)</sup>	220 mm <sup>6)</sup> 80 mm <sup>7)</sup> 65 mm <sup>8)</sup>	LL3-RB02	5326011
	≥ 0.12 mm	10 mm	80 mm <sup>1)</sup> 200 mm <sup>2)</sup> 310 mm <sup>3)</sup> 620 mm <sup>4)</sup> 660 mm <sup>5)</sup>	-	LL3-RG01	5326012
	≥ 0.3 mm	1 mm	290 mm <sup>1)</sup> 580 mm <sup>2)</sup> 720 mm <sup>3)</sup> 1,450 mm <sup>4)</sup> 1,550 mm <sup>5)</sup>	650 mm <sup>6)</sup> 250 mm <sup>7)</sup> 180 mm <sup>8)</sup>	LL3-RR01	5326008

<sup>&</sup>lt;sup>1)</sup> Operating mode: 16 μs.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

 $<sup>^{\</sup>scriptscriptstyle (3)}$  Operating mode: 250  $\mu s$ .

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

 $<sup>^{6)}</sup>$  Red light: 250  $\mu s.$ 

 $<sup>^{7)}\,\</sup>text{High}$  speed: 50  $\mu\text{s}.$ 

<sup>&</sup>lt;sup>8)</sup> Green light: 250 μs.

<sup>&</sup>lt;sup>2)</sup> Operating mode: 70 µs.

<sup>&</sup>lt;sup>3)</sup> Operating mode: 250 µs.

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250  $\mu$ s. <sup>7)</sup> High speed: 50  $\mu$ s.

<sup>8)</sup> Green light: 250 µs.

<sup>→</sup> For dimensional drawings, please see page J-843



### Liquid level

• Detection principle: Proximity system

Figure	Length	Minimum bend radius	Fiber-optic cable cuttable	Model name	Part no.
				LL3-DF04	5326035
		10 mm	<b>,</b>	LL3-DF05	5326034
	2,000 mm	10 111111	•	LL3-DF07	5326033
		30 mm	~	LL3-DF02-S01	5321924
	5,000 mm	20 mm	V	LL3-DW02	5325608

<sup>→</sup> For dimensional drawings, please see page J-844



### Threaded sleeve

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
M4)	1,000 mm	≥ 0.05 mm	10 mm	-	145 mm <sup>1)</sup> 460 mm <sup>2)</sup> 830 mm <sup>3)</sup> 1,600 mm <sup>4)</sup> 1,770 mm <sup>5)</sup>	40 mm <sup>6)</sup> 120 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TJ01	5325915
M3 2 X		≥ 0.1 mm	4 mm	V	60 mm <sup>1)</sup> 175 mm <sup>2)</sup> 330 mm <sup>3)</sup> 750 mm <sup>4)</sup> 1,100 mm <sup>5)</sup>	115 mm <sup>6)</sup> 38 mm <sup>7)</sup> 23 mm <sup>8)</sup>	LL3-TR02	5308053
M3		2 0.1 111111	15 mm	~	55 mm <sup>1)</sup> 175 mm <sup>2)</sup> 300 mm <sup>3)</sup> 700 mm <sup>4)</sup> 1,100 mm <sup>5)</sup>	125 mm <sup>6)</sup> 45 mm <sup>7)</sup> 30 mm <sup>8)</sup>	LL3-TM02	5308069
M4 2			2 mm	~	220 mm <sup>1)</sup> 650 mm <sup>2)</sup> 1,200 mm <sup>3)</sup> 2,750 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	370 mm <sup>6)</sup> 125 mm <sup>7)</sup> 120 mm <sup>8)</sup>	LL3-TK77	5313035
M4)	2,000 mm	≥ 0.2 mm	25 mm	V	225 mm <sup>1)</sup> 650 mm <sup>2)</sup> 1,200 mm <sup>3)</sup> 2,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	470 mm <sup>6)</sup> 165 mm <sup>7)</sup> 135 mm <sup>8)</sup>	LL3-TB02	5308048
мз			25		220 mm <sup>1)</sup> 680 mm <sup>2)</sup> 1,200 mm <sup>3)</sup> 2,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	470 mm <sup>6)</sup> 165 mm <sup>7)</sup> 135 mm <sup>8)</sup>	LL3-TM01	5308068
M4 2 ×		≥ 0.3 mm	4 mm	V	200 mm <sup>1)</sup> 600 mm <sup>2)</sup> 1,000 mm <sup>3)</sup> 2,400 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	340 mm <sup>6)</sup> 125 mm <sup>7)</sup> 125 mm <sup>8)</sup>	LL3-TR01	5308052
M4		≥ 0.5 mm	30 mm	V	300 mm <sup>1)</sup> 950 mm <sup>2)</sup> 1,700 mm <sup>3)</sup> 3,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	720 mm <sup>6)</sup> 315 mm <sup>7)</sup> 280 mm <sup>8)</sup>	LL3-TB01	5308050
114	10,000 mm	≥ 0.4 mm	25 mm	V	6,600 mm <sup>1)</sup> 19,500 mm <sup>2)</sup> 19,500 mm <sup>3)</sup> 19,500 mm <sup>4)</sup>	19,500 mm <sup>6)</sup> 7,500 mm <sup>7)</sup> 6,000 mm <sup>8)</sup>	LL3-TB08	5325917
	20,000 mm	≥ 0.5 mm	25 mm	V	2,000 mm <sup>1)</sup> 7,500 mm <sup>2)</sup> 13,500 mm <sup>3)</sup> 27,000 mm <sup>4)</sup> 40,000 mm <sup>5)</sup>	3,000 mm <sup>6)</sup> 1,300 mm <sup>7)</sup> 1,200 mm <sup>8)</sup>	LL3-TX02	5325046

 $<sup>^{1)}</sup>$  Operating mode: 16  $\mu$ s.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

 $<sup>^{3)}</sup>$  Operating mode: 250  $\mu$ s.

<sup>4)</sup> Operating mode: 2 ms.

<sup>&</sup>lt;sup>5)</sup> Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs.

 $<sup>^{7)}</sup>$  High speed: 50  $\mu s$ .

<sup>8)</sup> Green light: 250 µs.



### Smooth sleeve

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
X	500 mm	≥ 0.02 mm	4 mm	-	5 mm <sup>1)</sup> 17 mm <sup>2)</sup> 28 mm <sup>3)</sup> 56 mm <sup>4)</sup> 60 mm <sup>5)</sup>	12 mm <sup>6)</sup> 5 mm <sup>7)</sup> 5 mm <sup>8)</sup>	LL3-TR04	532591
X	4.000	≥ 0.1 mm	4 mm	V	60 mm <sup>1)</sup> 175 mm <sup>2)</sup> 330 mm <sup>3)</sup> 750 mm <sup>4)</sup> 1,100 mm <sup>5)</sup>	115 mm <sup>6)</sup> 38 mm <sup>7)</sup> 23 mm <sup>8)</sup>	LL3-TR03	530805
	1,000 mm	≥ 10 mm	10 mm	V	6 mm <sup>1)</sup> 19 mm <sup>2)</sup> 38 mm <sup>3)</sup> 74 mm <sup>4)</sup> 130 mm <sup>5)</sup>	18 mm <sup>6)</sup> 7 mm <sup>7)</sup> 11 mm <sup>8)</sup>	LL3-TH06	532592
2		≥ 0.02 mm	1 mm	V	13 mm <sup>1)</sup> 50 mm <sup>2)</sup> 85 mm <sup>3)</sup> 170 mm <sup>4)</sup> 180 mm <sup>5)</sup>	25 mm <sup>6)</sup> 12 mm <sup>7)</sup> 12 mm <sup>8)</sup>	LL3-TG05	532592
		- 0.02 mm	1	·	380 mm <sup>1)</sup> 1,220 mm <sup>2)</sup> 2,000 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	800 mm <sup>6)</sup> 250 mm <sup>7)</sup> 250 mm <sup>8)</sup>	LL3-TR10	532592
<b>O</b> .		≥ 0.03 mm	25 mm	V	180 mm <sup>1)</sup> 540 mm <sup>2)</sup> 890 mm <sup>3)</sup> 1,700 mm <sup>4)</sup> 1,900 mm <sup>5)</sup>	400 mm <sup>6)</sup> 190 mm <sup>7)</sup> 200 mm <sup>8)</sup>	LL3-TB07	532591
	2,000 mm	≥ 0.05 mm	25 mm	V	590 mm <sup>1)</sup> 1,790 mm <sup>2)</sup> 2,400 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,100 mm <sup>6)</sup> 600 mm <sup>7)</sup> 500 mm <sup>8)</sup>	LL3-TV08	532592
		≥ 0.1 mm	15 mm	V	55 mm <sup>1)</sup> 175 mm <sup>2)</sup> 300 mm <sup>3)</sup> 700 mm <sup>4)</sup> 1,100 mm <sup>5)</sup>	125 mm <sup>6)</sup> 45 mm <sup>7)</sup> 30 mm <sup>8)</sup>	LL3-TM03	530807
		≥ 0.2 mm	2 mm	V	220 mm <sup>1)</sup> 650 mm <sup>2)</sup> 1,200 mm <sup>3)</sup> 2,750 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	370 mm <sup>6)</sup> 125 mm <sup>7)</sup> 120 mm <sup>8)</sup>	LL3-TK05	531303
		≥ 0.5 mm	30 mm	V	275 mm <sup>1)</sup> 1,000 mm <sup>2)</sup> 1,800 mm <sup>3)</sup> 3,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	720 mm <sup>6)</sup> 315 mm <sup>7)</sup> 280 mm <sup>8)</sup>	LL3-TS07	530804

<sup>&</sup>lt;sup>1)</sup> Operating mode: 16 μs.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

<sup>&</sup>lt;sup>3)</sup> Operating mode: 250 µs.

<sup>4)</sup> Operating mode: 2 ms.

 $<sup>^{5)}</sup>$  Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs.

 $<sup>^{7)}</sup>$  High speed: 50  $\mu$ s.  $^{8)}$  Green light: 250  $\mu$ s.

<sup>→</sup> For dimensional drawings, please see page J-846



Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
200		≥ 0.04 mm	1 mm	V	360 mm <sup>1)</sup> 1,200 mm <sup>2)</sup> 2,200 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	900 mm <sup>6)</sup> 500 mm <sup>7)</sup> 450 mm <sup>8)</sup>	LL3-TR09	5325985
		≥ 0.05 mm	25 mm	V	150 mm <sup>1)</sup> 480 mm <sup>2)</sup> 770 mm <sup>3)</sup> 1,500 mm <sup>4)</sup> 1,600 mm <sup>5)</sup>	400 mm <sup>6)</sup> 170 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TB06	5325916
		≥ 0.06 mm	1 mm	V	160 mm <sup>1)</sup> 480 mm <sup>2)</sup> 800 mm <sup>3)</sup> 1,600 mm <sup>4)</sup> 1,700 mm <sup>5)</sup>	350 mm <sup>6)</sup> 170 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TR08	5325984
glass		≥ 0.1 mm	50 mm	-	18 mm <sup>1)</sup> 30 mm <sup>2)</sup> 120 mm <sup>3)</sup> 220 mm <sup>4)</sup> 420 mm <sup>5)</sup>	23 mm <sup>6)</sup> 23 mm <sup>7)</sup>	LL3-TH07	5325977
glass	2,000 mm	≥ 0.16 mm	25 mm	V	90 mm <sup>1)</sup> 290 mm <sup>2)</sup> 480 mm <sup>3)</sup>	170 mm <sup>6)</sup> 75 mm <sup>7)</sup>	LL3-TH15	532597
Signature of the signat		2 0.10 111111	23 111111	•	970 mm <sup>4)</sup> 1,000 mm <sup>5)</sup>	110 mm <sup>8)</sup>	LL3-TH16	532597
14)			05		350 mm <sup>1)</sup> 750 mm <sup>2)</sup> 1,800 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	400 mm <sup>6)</sup> 170 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TV05	532254
		≥ 0.4 mm	25 mm	V	180 mm <sup>1)</sup> 550 mm <sup>2)</sup> 900 mm <sup>3)</sup> 2,100 mm <sup>4)</sup> 3,500 mm <sup>5)</sup>	350 mm <sup>6)</sup> 150 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TV06	532254
14) 2			2 mm	V	340 mm <sup>1)</sup> 1,000 mm <sup>2)</sup> 1,800 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	290 mm <sup>6)</sup> 150 mm <sup>7)</sup> 150 mm <sup>8)</sup>	LL3-TV07	532254
	3,000 mm	≥ 0.3 mm	20 mm	V	460 mm <sup>1)</sup> 1,400 mm <sup>2)</sup> 2,500 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,000 mm <sup>6)</sup> 350 mm <sup>7)</sup> 450 mm <sup>8)</sup>	LL3-TY03	532598

<sup>&</sup>lt;sup>3)</sup> Operating mode: 250 µs.

 $<sup>^{6)}</sup>$  Red light: 250 μs.  $^{7)}$  High speed: 50 μs.  $^{8)}$  Green light: 250 μs.



### Flat type

- Detection principle: Through-beam system
- Fiber-optic cable cuttable: 🗸

Figure	Length	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
2	4 000	≥ 0.08 mm	m 1 mm	120 mm <sup>1)</sup> 350 mm <sup>2)</sup> 620 mm <sup>3)</sup> 1,250 mm <sup>4)</sup> 1,330 mm <sup>5)</sup>	250 mm <sup>6)</sup> 120 mm <sup>7)</sup> 120 mm <sup>8)</sup>	LL3-TE01	5325807
2	1,000 mm	2 0.06 111111		40 mm <sup>1)</sup> 140 mm <sup>2)</sup> 220 mm <sup>3)</sup> 450 mm <sup>4)</sup> 480 mm <sup>5)</sup>	130 mm <sup>6)</sup> 60 mm <sup>7)</sup> 50 mm <sup>8)</sup>	LL3-TE02	5325910
2			1 mm	150 mm <sup>1)</sup> 440 mm <sup>2)</sup> 700 mm <sup>3)</sup> 1,400 mm <sup>4)</sup> 1,490 mm <sup>5)</sup>	320 mm <sup>6)</sup> 160 mm <sup>7)</sup> 120 mm <sup>8)</sup>	LL3-TE04	5325911
2	2 000 mm	≥ 0.03 mm	4 mm	150 mm <sup>1)</sup> 460 mm <sup>2)</sup> 840 mm <sup>3)</sup> 1,680 mm <sup>4)</sup> 1,780 mm <sup>5)</sup>	350 mm <sup>6)</sup> 140 mm <sup>7)</sup> 240 mm <sup>8)</sup>	LL3-TE05	5325914
2 %	2,000 mm	≥ 0.03 mm		360 mm <sup>1)</sup> 1,300 mm <sup>2)</sup> 2,300 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,200 mm <sup>6)</sup> 500 mm <sup>7)</sup> 750 mm <sup>8)</sup>	LL3-TR05	5325808
ZX				560 mm <sup>1)</sup> 1,600 mm <sup>2)</sup> 2,200 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,200 mm <sup>6)</sup> 500 mm <sup>7)</sup> 750 mm <sup>8)</sup>	LL3-TR06	5325912

<sup>&</sup>lt;sup>1)</sup> Operating mode: 16 µs. <sup>2)</sup> Operating

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s.$   $^{3)}$  Operating mode: 250  $\mu s.$ 

<sup>4)</sup> Operating mode: 2 ms.

<sup>&</sup>lt;sup>5)</sup> Operating mode: 8 ms.

 $<sup>^{7)}</sup>$  High speed: 50  $\mu s.$ 

<sup>8)</sup> Green light: 250 µs.

Figure	Length	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.	
2		≥ 0.04 mm	1 mm	250 mm <sup>1)</sup> 730 mm <sup>2)</sup> 1,280 mm <sup>3)</sup> 2,560 mm <sup>4)</sup> 2,730 mm <sup>5)</sup>	600 mm <sup>6)</sup> 300 mm <sup>7)</sup> 400 mm <sup>8)</sup>	LL3-TR13	5325909	
2	0.000	≥ 0.05 mm	1 mm	600 mm <sup>1)</sup> 1,400 mm <sup>2)</sup> 2,300 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,400 mm <sup>6)</sup> 650 mm <sup>7)</sup> 600 mm <sup>8)</sup>	LL3-TR12	5325907	
2	2,000 mm		≥ 0.08 mm	1	590 mm <sup>1)</sup> 1,500 mm <sup>2)</sup> 2,200 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,800 mm <sup>6)</sup> 800 mm <sup>7)</sup> 750 mm <sup>8)</sup>	LL3-TR11	5325906
		2 0.08 MM	1 mm	190 mm <sup>1)</sup> 580 mm <sup>2)</sup> 980 mm <sup>3)</sup> 1,970 mm <sup>4)</sup> 2,100 mm <sup>5)</sup>	500 mm <sup>6)</sup> 250 mm <sup>7)</sup> 200 mm <sup>8)</sup>	LL3-TE03	5325908	

<sup>&</sup>lt;sup>1)</sup> Operating mode: 16 μs.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

 $<sup>^{3)}</sup>$  Operating mode: 250  $\mu$ s.

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

<sup>&</sup>lt;sup>6)</sup> Red light: 250 μs.

<sup>&</sup>lt;sup>7)</sup> High speed: 50 μs.

<sup>&</sup>lt;sup>8)</sup> Green light: 250 μs.

<sup>→</sup> For dimensional drawings, please see page J-848




Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
70	500 mm	≥ 0.02 mm	5 mm	-	2 mm <sup>1)</sup> 8 mm <sup>2)</sup> 14 mm <sup>3)</sup> 28 mm <sup>4)</sup> 30 mm <sup>5)</sup>	5 mm <sup>6)</sup> 3 mm <sup>7)</sup> 3 mm <sup>8)</sup>	LL3-TP01	5325925
		≥ 0.03 mm	25 mm	V	50 mm <sup>1)</sup> 140 mm <sup>2)</sup> 250 mm <sup>3)</sup> 500 mm <sup>4)</sup> 530 mm <sup>5)</sup>	120 mm <sup>6)</sup> 60 mm <sup>7)</sup> 60 mm <sup>8)</sup>	LL3-TB05	5325924
		≥ 0.1 mm 15 mm			10 mm <sup>1)</sup> 30 mm <sup>2)</sup> 60 mm <sup>3)</sup> 140 mm <sup>4)</sup> 200 mm <sup>5)</sup>	32 mm <sup>6)</sup> 13 mm <sup>7)</sup> 5 mm <sup>8)</sup>	LL3-TT01	5308057
			15 mm	V	30 mm <sup>1)</sup> 130 mm <sup>2)</sup> 77 mm <sup>6)</sup>	LL3-TV02	5308059	
					250 mm <sup>3)</sup> 550 mm <sup>4)</sup> 800 mm <sup>5)</sup>	27 mm <sup>7)</sup> 16 mm <sup>8)</sup>	LL3-TV04	5308060
	2,000 mm ≥ 0.2 mm		QE yayı		240 mm <sup>1)</sup> 700 mm <sup>2)</sup> 1,400 mm <sup>3)</sup> 2,500 mm <sup>4)</sup> 2,900 mm <sup>5)</sup>	470 mm <sup>6)</sup> 165 mm <sup>7)</sup> 132 mm <sup>8)</sup>	LL3-TB03	5308056
		> 0.2 mm			180 mm <sup>1)</sup> 600 mm <sup>2)</sup> 1,100 mm <sup>3)</sup> 2,500 mm <sup>4)</sup> 3,300 mm <sup>5)</sup>	2,050 mm <sup>6)</sup> 950 mm <sup>7)</sup> 850 mm <sup>8)</sup>	LL3-TK16	5313038
		25 mm	V	170 mm <sup>1)</sup> 500 mm <sup>2)</sup> 1,000 mm <sup>3)</sup> 2,300 mm <sup>4)</sup> 3,000 mm <sup>5)</sup>	355 mm <sup>6)</sup> 125 mm <sup>7)</sup> 115 mm <sup>8)</sup>	LL3-TS08	5308061	
					120 mm <sup>1)</sup> 400 mm <sup>2)</sup> 800 mm <sup>3)</sup> 1,800 mm <sup>4)</sup> 2,750 mm <sup>5)</sup>	325 mm <sup>6)</sup> 115 mm <sup>7)</sup> 87 mm <sup>8)</sup>	LL3-TV01	5308058
		≥ 0.5 mm	25 mm	V	170 mm <sup>1)</sup> 550 mm <sup>2)</sup> 1,000 mm <sup>3)</sup> 2,300 mm <sup>4)</sup> 3,000 mm <sup>5)</sup>	1,800 mm <sup>6)</sup> 840 mm <sup>7)</sup> 760 mm <sup>8)</sup>	LL3-TS12	5308062

 $<sup>^{\</sup>scriptscriptstyle{1)}}$  Operating mode: 16  $\mu s.$ 

<sup>&</sup>lt;sup>2)</sup> Operating mode: 70 µs.

<sup>&</sup>lt;sup>3)</sup> Operating mode: 250 µs.

<sup>4)</sup> Operating mode: 2 ms.

<sup>5)</sup> Operating mode: 8 ms.

 $<sup>^{6)}</sup>$  Red light: 250 µs.  $^{7)}$  High speed: 50 µs.  $^{8)}$  Green light: 250 µs.



• Detection principle: Through-beam system

• Length: 2,000 mm

Fiber-optic cable cuttable: 

✓

Figure	Minimal object	Minimum bend	Sensing range with	Sensing range with	Model name	Part no.
	diameter	radius	WLL180	WLL170		
2		1 mm	1,300 mm <sup>1)</sup> 2,500 mm <sup>2)</sup> 3,000 mm <sup>3)</sup> 3,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,000 mm <sup>6)</sup> 1,000 mm <sup>7)</sup> 800 mm <sup>8)</sup>	LL3-TZ09	5326598
	≥ 0.25 mm	10 mm	1,700 mm <sup>1)</sup> 2,500 mm <sup>2)</sup> 3,000 mm <sup>3)</sup> 3,500 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,800 mm <sup>6)</sup> 1,200 mm <sup>7)</sup> 800 mm <sup>8)</sup>	LL3-TZ10	5326599
	≥ 0.4 mm	2 mm	3,000 mm <sup>1)</sup> 4,000 mm <sup>2)</sup> 4,000 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	4,000 mm <sup>6)</sup> 1,300 mm <sup>7)</sup> 1,600 mm <sup>8)</sup>	LL3-TS40	5323971
			150 mm <sup>1)</sup> 450 mm <sup>2)</sup> 740 mm <sup>3)</sup> 1,400 mm <sup>4)</sup> 1,500 mm <sup>5)</sup>	350 mm <sup>6)</sup> 150 mm <sup>7)</sup> 250 mm <sup>8)</sup>	LL3-TZ05	5325937
	≥ 0.45 mm	25 mm	150 mm <sup>1)</sup> 480 mm <sup>2)</sup> 790 mm <sup>3)</sup> 1,500 mm <sup>4)</sup> 1,600 mm <sup>5)</sup>	350 mm <sup>6)</sup> 150 mm <sup>7)</sup> 250 mm <sup>8)</sup>	LL3-TZ06	5325938
	≥ 0.5 mm	25 mm	130 mm <sup>1)</sup> 400 mm <sup>2)</sup> 800 mm <sup>3)</sup> 2,000 mm <sup>4)</sup> 3,500 mm <sup>5)</sup>	335 mm <sup>6)</sup> 125 mm <sup>7)</sup> 90 mm <sup>8)</sup>	LL3-TS14	5313039
1) Operating mode:	≥ 1 mm	25 mm	130 mm <sup>1)</sup> 400 mm <sup>2)</sup> 800 mm <sup>3)</sup> 2,000 mm <sup>4)</sup> 3,500 mm <sup>5)</sup>	335 mm <sup>6)</sup> 125 mm <sup>7)</sup> 90 mm <sup>8)</sup>	LL3-TS10	5308063

¹) Operating mode: 16 µs. <sup>7)</sup> High speed: 50 µs. <sup>6)</sup> Red light: 250 μs.

8) Green light: 250 µs.

 $<sup>^{2)}</sup>$  Operating mode: 70  $\mu s$ .

<sup>&</sup>lt;sup>3)</sup> Operating mode: 250 µs.

<sup>&</sup>lt;sup>4)</sup> Operating mode: 2 ms.

 $<sup>^{5)}</sup>$  Operating mode: 8 ms.

<sup>→</sup> For dimensional drawings, please see page J-851



### Heat-resistant

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.	
2000 Sass		≥ 0.02 mm	10 mm	-	50 mm <sup>1)</sup> 180 mm <sup>2)</sup> 300 mm <sup>3)</sup> 600 mm <sup>4)</sup> 640 mm <sup>5)</sup>	130 mm <sup>6)</sup> 50 mm <sup>7)</sup> 80 mm <sup>8)</sup>	LL3-TH10	5325970	
F S S S S S S S S S S S S S S S S S S S	1,000 mm	00 mm	25 mm		130 mm <sup>1)</sup> 400 mm <sup>2)</sup> 700 mm <sup>3)</sup> 1,400 mm <sup>4)</sup> 1,500 mm <sup>5)</sup>	320 mm <sup>6)</sup> 130 mm <sup>7)</sup> 200 mm <sup>8)</sup>	LL3-TH11	5325971	
		≥ 0.04 mm	23 111111	-	80 mm <sup>1)</sup> 230 mm <sup>2)</sup> 350 mm <sup>3)</sup> 560 mm <sup>4)</sup> 980 mm <sup>5)</sup>	-	LL3-TW01	5315233	
Elass W		≥ 0.04 mm	25 mm		150 mm <sup>1)</sup> 480 mm <sup>2)</sup> 790 mm <sup>3)</sup> 1,500 mm <sup>4)</sup> 1,600 mm <sup>5)</sup>	350 mm <sup>6)</sup> 140 mm <sup>7)</sup> 240 mm <sup>8)</sup>	LL3-TH08	5325978	
glass W			2 0.04 111111	25 111111	-	140 mm <sup>1)</sup> 460 mm <sup>2)</sup> 700 mm <sup>3)</sup> 1,400 mm <sup>4)</sup> 1,500 mm <sup>5)</sup>	350 mm <sup>6)</sup> 140 mm <sup>7)</sup> 240 mm <sup>8)</sup>	LL3-TH09	5325979
Class Class			≥ 0.06 mm	25 mm	V	230 mm <sup>1)</sup> 690 mm <sup>2)</sup> 1,100 mm <sup>3)</sup> 2,300 mm <sup>4)</sup> 2,400 mm <sup>5)</sup>	600 mm <sup>6)</sup> 250 mm <sup>7)</sup> 400 mm <sup>8)</sup>	LL3-TH17	5325967
Slass W	2,000 mm	2,000 mm		V	100 mm <sup>1)</sup> 330 mm <sup>2)</sup> 570 mm <sup>3)</sup>	250 mm <sup>6)</sup>	LL3-TH12	5325972	
A ? glass		≥ 0.12 mm	25 mm		1,100 mm <sup>4)</sup> 1,200 mm <sup>5)</sup>	100 mm <sup>7)</sup> 170 mm <sup>8)</sup>	LL3-TH13	5325973 5325974	
O M TO MAD			≥ 0.2 mm	25 mm	V	55 mm <sup>1)</sup> 180 mm <sup>2)</sup> 320 mm <sup>3)</sup> 680 mm <sup>4)</sup> 1,000 mm <sup>5)</sup>	305 mm <sup>6)</sup> 125 mm <sup>7)</sup> 50 mm <sup>8)</sup>	LL3-TH01	5308064
5.08H		≥ 0.5 mm	35 mm	V	230 mm <sup>1)</sup> 700 mm <sup>2)</sup> 1,300 mm <sup>3)</sup> 2,700 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	620 mm <sup>6)</sup> 255 mm <sup>7)</sup> 125 mm <sup>8)</sup>	LL3-TH02	5308065	

 $<sup>^{6)}</sup>$  Red light: 250  $\mu s.$ 

 $<sup>^{7)}</sup>$  High speed: 50  $\mu s.$ 

<sup>8)</sup> Green light: 250 μs.

<sup>→</sup> For dimensional drawings, please see page J-852



### LCDs/transparent objects/semiconductors

- Detection principle: Through-beam system
- Length: 2,000 mm
- Fiber-optic cable cuttable: 

  ✓

Figure	Minimal object diameter	Minimum bend radius	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.
	≥ 0.02 mm	10 mm	100 mm <sup>1)</sup> 290 mm <sup>2)</sup> 500 mm <sup>3)</sup> 1,000 mm <sup>4)</sup> 1,100 mm <sup>5)</sup>	250 mm <sup>6)</sup> 120 mm <sup>7)</sup> 120 mm <sup>8)</sup>	LL3-TG04	5324499
		10 mm	220 mm <sup>1)</sup> 760 mm <sup>2)</sup> 1,500 mm <sup>3)</sup> 2,900 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	625 mm <sup>6)</sup> 400 mm <sup>7)</sup> 300 mm <sup>8)</sup>	LL3-TS22M	5325968
	≥ 0.05 mm	25 mm	390 mm <sup>1)</sup> 1,300 mm <sup>2)</sup> 2,600 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	850 mm <sup>6)</sup> 500 mm <sup>7)</sup> 400 mm <sup>8)</sup>	LL3-TS22	5325944
	≥ 0.06 mm	1 mm	580 mm <sup>1)</sup> 1,670 mm <sup>2)</sup> 2,400 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	1,100 mm <sup>6)</sup> 450 mm <sup>7)</sup> 700 mm <sup>8)</sup>	LL3-TG02	5325943
		25 mm	880 mm <sup>1)</sup> 2,300 mm <sup>2)</sup> 3,500 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,500 mm <sup>6)</sup> 1,300 mm <sup>7)</sup> 1,600 mm <sup>8)</sup>	LL3-TG01	5325940
			570 mm <sup>1)</sup> 1,980 mm <sup>2)</sup> 2,400 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup> ating mode: 250 µs.	1,000 mm <sup>6)</sup> 450 mm <sup>7)</sup> 700 mm <sup>8)</sup>	LL3-TG03 <sup>5)</sup> Operating mode: 8 m	5325942

 $^{8)}$  Green light: 250  $\mu s.$ 

 $<sup>^{\</sup>rm 6)}$  Red light: 250  $\mu s.$  $^{7)}\,High$  speed: 50  $\mu s.$ 

<sup>→</sup> For dimensional drawings, please see page J-854



### Resistant to oil/chemicals

• Detection principle: Through-beam system

Figure	Length	Minimal object diameter	Minimum bend radius	Fiber-optic cable cut- table	Sensing range with WLL180	Sensing range with WLL170	Model name	Part no.		
	2,000 mm			≥ 0.3 mm	60 mm		400 mm <sup>1)</sup> 1,200 mm <sup>2)</sup> 2,100 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,000 mm <sup>6)</sup> 415 mm <sup>7)</sup> 390 mm <sup>8)</sup>	LL3-TY01	5308066
			60 mm	-	300 mm <sup>1)</sup> 1,000 mm <sup>2)</sup> 1,300 mm <sup>3)</sup> 3,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	620 mm <sup>6)</sup> 225 mm <sup>7)</sup> 210 mm <sup>8)</sup>	LL3-TY02	5308067		
		≥ 4 mm	25 mm	V	850 mm <sup>1)</sup> 2,700 mm <sup>2)</sup> 3,000 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,200 mm <sup>6)</sup> 800 mm <sup>7)</sup> 1,300 mm <sup>8)</sup>	LL3-TY05	5325980		
4	2,500 mm	≥ 0.3 mm	30 mm	V	740 mm <sup>1)</sup> 2,400 mm <sup>2)</sup> 3,000 mm <sup>3)</sup> 4,000 mm <sup>4)</sup> 4,000 mm <sup>5)</sup>	2,200 mm <sup>6)</sup> 800 mm <sup>7)</sup> 1,300 mm <sup>8)</sup>	LL3-TY04	5325981		

 $<sup>^{6)}</sup>$  Red light: 250  $\mu s.$   $^{7)}$  High speed: 50  $\mu s.$   $^{8)}$  Green light: 250  $\mu s.$ 

<sup>→</sup> For dimensional drawings, please see page J-854



### Liquid level

• Detection principle: Through-beam system

Figure	Length	Minimum bend radius	Model name	Part no.
	2,000 mm	20 mm	LL3-TF01	5324242

→ For dimensional drawings, please see page J-855



# Tip adapters through-beam system

# Suitable for amplifier WLL170-2

Figure	Tempera-			LL model name/s	L model name/sensing range (mm)					
	ture	LL3-TB01	LL3-TB01-10	LL3-TB01-30	LL3-TB02	LL3-TB06	LL3-TH01			
	-40 °C - +100 °C	3000 <sup>1)</sup> 1200 <sup>2)</sup> 1100 <sup>3)</sup>	1800 ¹) 700 ²) 600 ³)	1000 <sup>1)</sup> 400 <sup>2)</sup> 200 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1200 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1200 <sup>3)</sup>	3500 ¹) 1400 ²) 1200 ³)			
	-40 °C - +100 °C	3000 <sup>1)</sup> 1200 <sup>2)</sup> 800 <sup>3)</sup>	1800 <sup>1)</sup> 700 <sup>2)</sup> 500 <sup>3)</sup>	1000 <sup>1)</sup> 400 <sup>2)</sup> 200 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 ¹) 1400 ²) 1000 ³)			
	-40 °C - +70 °C	600 <sup>1)</sup> 230 <sup>2)</sup> 100 <sup>3)</sup>	360 ¹) 130 ²)	200 ¹) 80 ²)	600 ¹) 230 ²) 100 ³)	-	-			
	-40 °C - +350 °C	3500 ¹) 1400 ²) 1000 ³)	2100 <sup>1)</sup> 850 <sup>2)</sup> 600 <sup>3)</sup>	1200 <sup>1)</sup> 500 <sup>2)</sup> 200 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>			
	-60 °C - +350 °C	3500 ¹) 1400 ²) 1000 ³)	2100 <sup>1)</sup> 850 <sup>2)</sup> 600 <sup>3)</sup>	1200 <sup>1)</sup> 500 <sup>2)</sup> 200 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>			
	-60 °C - +300 °C	500 ¹) 200 ²)	300 ¹) 100 ²)	180 <sup>1)</sup> 70 <sup>2)</sup>	500 ¹) 200 ²) 80 ³)	-	400 <sup>1)</sup> 150 <sup>2)</sup>			

 $<sup>^{1)}</sup>$  Red light: 250  $\mu s^{-2)}$  Highspeed: 50  $\mu s^{-3)}$  Green light: 250  $\mu s$  Mounting material included.

#### Suitable for amplifier WLL180T

Figure	Tempera-	LL model name/sensing range (mm)										
	ture	LL3-TB01	LL3-TB01-10	LL3-TB01-30	LL3-TB02	LL3-TB06	LL3-TH01					
	-40 °C -	800 <sup>1)</sup> 2500 <sup>2)</sup> 4000 <sup>3)</sup>	720 <sup>1)</sup> 2250 <sup>2)</sup> 3600 <sup>3)</sup>	570 <sup>1)</sup> 1800 <sup>2)</sup> 2880 <sup>3)</sup>	1800 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>	1500 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>	500 <sup>1)</sup> 1400 <sup>2)</sup> 2500 <sup>3)</sup>					
	+100 °C	4000 <sup>4)</sup> 4000 <sup>5)</sup>	3600 <sup>4)</sup> 3600 <sup>5)</sup>	2880 <sup>4)</sup> 2880 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>					
	-40 °C -	800 ¹) 2500 ²) 4000 ³)	720 <sup>1)</sup> 2250 <sup>2)</sup> 3600 <sup>3)</sup>	570 ¹) 1800 ²) 2880 ³)	1800 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>	1500 ¹) 4000 ²) 4000 ³)	500 <sup>1)</sup> 1400 <sup>2)</sup> 2500 <sup>3)</sup>					
	+100 °C	4000 <sup>4)</sup> 4000 <sup>5)</sup>	3600 <sup>4)</sup> 3600 <sup>5)</sup> 180 <sup>1)</sup>	2880 <sup>4)</sup> 2880 <sup>5)</sup> 150 <sup>1)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>					
	-40 °C -	650 <sup>2)</sup> 1200 <sup>3)</sup>	180 <sup>1)</sup> 585 <sup>2)</sup> 1080 <sup>3)</sup>	150¹) 460²) 860³)	1000 <sup>2)</sup> 1800 <sup>3)</sup>	_	_					
	+70 °C	2500 <sup>4)</sup> 3600 <sup>5)</sup>	2250 <sup>4)</sup> 3240 <sup>5)</sup>	1800 <sup>4)</sup> 2600 <sup>5)</sup>	3500 <sup>4)</sup> 4000 <sup>5)</sup>							
	-40 °C -	360 <sup>1)</sup> 2000 <sup>2)</sup> 4000 <sup>3)</sup>	324 <sup>1)</sup> 1800 <sup>2)</sup> 3600 <sup>3)</sup>	260 <sup>1)</sup> 1440 <sup>2)</sup> 2880 <sup>3)</sup>	1200 ¹) 4000 ²) 4000 ³)	1200 ¹) 4000 ²) 4000 ³)	1200 ¹) 2000 ²) 4000 ³)					
	+350 °C	4000 <sup>4)</sup> 4000 <sup>5)</sup>	3600 <sup>4)</sup> 3600 <sup>5)</sup>	2880 <sup>4)</sup> 2880 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>					
	-60 °C	4000 ¹) 4000 ²) 4000 ³)	3600 <sup>1)</sup> 3600 <sup>2)</sup> 3600 <sup>3)</sup>	2880 <sup>1)</sup> 2880 <sup>2)</sup> 2880 <sup>3)</sup>	4000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>	4000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>	4000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup>					
	+350 °C	4000 <sup>4)</sup> 4000 <sup>5)</sup>	3600 <sup>4)</sup> 3600 <sup>5)</sup>	2880 <sup>4)</sup> 2880 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>	4000 <sup>4)</sup> 4000 <sup>5)</sup>					

 $<sup>^{3)}</sup>$  Operating mode: 16  $\mu s$   $^{2)}$  Operating mode: 70  $\mu s$   $^{3)}$  Operating mode: 250  $\mu s$   $^{4)}$  Operating mode: 2 ms  $^{5)}$  Operating mode: 8 ms Mounting material included.

	Model name	Part no.					
LL3-TH08	LL3-TH10	LL3-TH11	LL3-TJ01	LL3-TK77	LL3-TR01		
-	-	-	1500 ¹) 600 ²) 400 ³)	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1200 <sup>3)</sup>	3000 <sup>1)</sup> 1200 <sup>2)</sup> 1000 <sup>3)</sup>	LL3-TA01	5308128
-	-	-	1500 <sup>1)</sup> 600 <sup>2)</sup> 400 <sup>3)</sup>	3500 <sup>1)</sup> 1400 <sup>2)</sup> 1100 <sup>3)</sup>	3000 <sup>1)</sup> 1200 <sup>2)</sup> 1100 <sup>3)</sup>	LL3-TA01S	5326461
-	-	-	500 ¹) 200 ²)	600 ¹) 230 ²)	500 <sup>1)</sup> 200 <sup>2)</sup>	LL3-TA02	5308129
2100 <sup>1)</sup> 850 <sup>2)</sup> 500 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 300 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 300 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 300 <sup>3)</sup>	_ 1400	2500 <sup>1)</sup> 1000 <sup>2)</sup> 700 <sup>3)</sup>	LL3-TA03	5326462
3500 <sup>1)</sup> 1400 <sup>2)</sup> 1000 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 300 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 250 <sup>3)</sup>	1500 <sup>1)</sup> 600 <sup>2)</sup> 250 <sup>3)</sup>		3500 <sup>1)</sup> 1400 <sup>2)</sup> 1100 <sup>3)</sup>	LL3-TAO4	5326463
350 <sup>1)</sup> 140 <sup>2)</sup>	300 <sup>1)</sup> 120 <sup>2)</sup>	350 <sup>1)</sup> 140 <sup>2)</sup>	400 <sup>1)</sup> 160 <sup>2)</sup>	400 <sup>1)</sup> 160 <sup>2)</sup>	350 <sup>1)</sup> 140 <sup>2)</sup>	LL3-TA05	5326464

	Model name	Part no.					
LL3-TH08	LL3-TH10	LL3-TH11	LL3-TJ01	LL3-TK77	LL3-TR01		
-	-	-	750 ¹) 2000 ²) 2000 ³) 2000 ⁴) 2000 ⁵)	2000 ¹) 4000 ²) 4000 ³) 4000 ⁴) 4000 ⁵)	1800 ¹) 4000 ²) 4000 ³) 4000 ⁴) 4000 ⁵)	LL3-TA01	5308128
-	-	-	650 <sup>1)</sup> 2000 <sup>2)</sup> 2000 <sup>3)</sup> 2000 <sup>4)</sup> 2000 <sup>5)</sup>	2000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup> 4000 <sup>4)</sup> 4000 <sup>5)</sup>	1800 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup> 4000 <sup>4)</sup> 4000 <sup>5)</sup>	LL3-TA01S	5326461
-	-	-	200 <sup>1)</sup> 600 <sup>2)</sup> 950 <sup>3)</sup> 1900 <sup>4)</sup> 4000 <sup>5)</sup>	950 <sup>2)</sup> 1800 <sup>3)</sup> 3500 <sup>4)</sup> 4000 <sup>5)</sup>	200 ¹) 900 ²) 1500 ³) 3300 ⁴) 4000 ⁵)	LL3-TA02	5308129
800 ¹) 2000 ²) 4000 ³) 4000 ⁴) 4000 ⁵)	750¹) 2000²) 2000³) 2000⁴) 2000⁴)	1000 ¹) 2000 ²) 2000 ³) 2000 ⁴) 2000 ⁵)	600 <sup>1)</sup> 2000 <sup>2)</sup> 2000 <sup>3)</sup> 2000 <sup>4)</sup> 2000 <sup>5)</sup>	600 ¹) 2000 ²) 4000 ³) 4000 ⁴) 4000 ⁵)	800 ¹) 2000²) 4000 ³) 4000 ⁴) 4000 ⁵)	LL3-TA03	5326462
4000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup> 4000 <sup>4)</sup> 4000 <sup>5)</sup>	2000 <sup>1)</sup> 2000 <sup>2)</sup> 2000 <sup>3)</sup> 2000 <sup>4)</sup> 2000 <sup>5)</sup>	2000 <sup>1)</sup> 2000 <sup>2)</sup> 2000 <sup>3)</sup> 2000 <sup>4)</sup> 2000 <sup>5)</sup>	2000 <sup>1)</sup> 2000 <sup>2)</sup> 2000 <sup>3)</sup> 2000 <sup>4)</sup> 2000 <sup>5)</sup>	4000 ¹) 4000 ²) 4000 ³) 4000 ⁴) 4000 ⁵)	4000 <sup>1)</sup> 4000 <sup>2)</sup> 4000 <sup>3)</sup> 4000 <sup>4)</sup> 4000 <sup>5)</sup>	LL3-TAO4	5326463

Figure	Tempera-				LL model name/sensing range (mm)								
	ture	LL3-TB01		LL3-TB01-10		LL3	LL3-TB01-30		LL3-TB02		LL3-TB06		L3-TH01
		•	2501)		2251)	•	1801)	•	250 1)			•	160 <sup>1)</sup>
	-60 °C		8002)		7202)		570 <sup>2)</sup>	•	8002)			•	4502)
	-		12003)	_	10803)		8603)		1200 <sup>3)</sup>		-		8003)
	+300 °C		24004)		21604)		17004)		24004)				1500 <sup>4)</sup>
			4000 5)		36005)		28805)		40005)				40005)

 $<sup>^{1)}</sup>$  Operating mode: 16  $\mu s$   $^{2)}$  Operating mode: 70  $\mu s$   $^{3)}$  Operating mode: 250  $\mu s$   $^{4)}$  Operating mode: 2 ms  $^{5)}$  Operating mode: 8 ms Mounting material included.

<sup>→</sup> For dimensional drawings, please see page J-855

LL model name/sensing range (mm)										Model name	Part no.		
LI	L3-TH08	LI	L3-TH10	LI	.3-TH11	L	L3-TJ01	LI	_3-TK77	LI	L3-TR01		
•	170 <sup>1)</sup>	•	1001)	•	150 <sup>1)</sup>	•	2001)	•	2001)	•	160 <sup>1)</sup>		
•	550 <sup>2)</sup>	•	3002)	•	4002)	•	6002)	•	6002)	•	550 <sup>2)</sup>		
	8003)		600 <sup>3)</sup>		7003)		950 <sup>3)</sup>	_	950 <sup>3)</sup>	_	8503)	LL3-TA05	5326464
	16004)		11004)		1400 4)		19004)		19004)		17004)		
	40005)		2000 5)		40005)		40005)		40005)		40005)		



# Tip adapters proximity system

Figure	Temperature	Light spot size			Focal length [mm]	Model name	Part no.	
		LL3-DK21	LL3-DT01	LL3-DM02	[111111]			
	- 40 °C - +70 °C	Ø 0.2 mm	Ø 0.4 mm	-	6	LL3-DA01	5308127	
	- 40 °C - + 70 °C	Ø 1.2 mm	Ø 1.4 mm	-	15	LL3-DA02	5308130	
	- 20 °C - + 60 °C	Ø 0.2 mm	Ø 0.4 mm	-	7	LL3-DA03	5326465	
	- 40 °C - + 70 °C	Ø 0.3 mm	Ø 0.5 mm	-	7,5	LL3-DA04	5326466	
	- 40 °C - + 70 °C	-	-	Ø 0.5 mm	6	LL3-DA05	5326467	
	- 40 °C - + 70 °C	-	-	Ø 0.7 mm - 0.85 mm	~ 20	LL3-DA06	5326468	
	- 40 °C - + 70 °C	-	-	Ø 0.5 mm - 0.8 mm	~ 14	LL3-DA07	5326469	

<sup>→</sup> For dimensional drawings, please see page J-855


# **Dimensional drawings**

Dimensions in mm (inch)

## Threaded sleeve


• Detection principle: Proximity system

#### LL3-DJ01




1) Receiver 2) Sender


# LL3-DR02




#### **LL3-DS06**




## LL3-DB01




#### LL3-DJ02






## LL3-DR06




#### LL3-DT01




1) Sender 2) Receiver


#### LL3-DB03




#### LL3-DB04




## LL3-DK06




## LL3-DK66




## LL3-DK67




#### LL3-DR01




#### LL3-DR08




#### LL3-DK21



#### LL3-DM02




## LL3-DB07



# LL3-DM01







#### Smooth sleeve

• Detection principle: Proximity system


## LL3-DR04




## LL3-DP01




## LL3-DK4Z




## LL3-DR03




## LL3-DT03




#### LL3-DK04



## LL3-DR12




## LL3-DR11



- 1) Receiver
- 2) Sender


#### LL3-DB10



# 90° deflection

• Detection principle: Proximity system

# LL3-DV05, LL3-DV06, LL3-DV07







# Flat type


• Detection principle: Proximity system

## LL3-DE02







# LL3-DB09




## LL3-DE01




#### LL3-DC08




#### LL3-DC06




## LL3-DC47




## LL3-DC09




## LL3-DH08




# LL3-DE04



## LL3-DC57




## LL3-DH06







## LL3-DE03




#### LL3-DR09



# LL3-DC07




# LL3-DH11







# LL3-DC03



# LL3-DC04



## LL3-DH10






# Long end sleeve


• Detection principle: Proximity system

#### LL3-DT02




1) End tip cannot be bent

# LL3-DT04




1) End tip cannot be bent


#### LL3-DR05




## LL3-DR07




## LL3-DB05




#### LL3-DH05




## LL3-DK63Z



#### LL3-DK43




#### LL3-DM03




1) Flexible end tip, do not bend in this area (10 mm), bend radius R10 mm

#### LL3-DV02




## LL3-DR10




1) bendable


#### LL3-DB08



## LL3-DT05




#### LL3-DB02




- Flexible end tip, do not bend in this area (10 mm), bend radius R10 mm
   Sender (marked blue)
   Receiver


## LL3-DB06




#### LL3-DH04




#### LL3-DK33






#### LL3-DV03



## Area detection

• Detection principle: Proximity system

## LL3-DZ01



# LL3-DZ02

LL3-DV01

4.88

Ø 2.7


20

Ø5

2000


15

Ø 2.2 x 2



All dimensions in mm

# LL3-DZ03




All dimensions in mm


#### Heat-resistant


• Detection principle: Proximity system

#### LL3-DH07




# LL3-DW01







## LL3-DH02




#### LL3-DH01



## LL3-DH03




## LL3-DH09



## Resistant to oil/chemicals

• Detection principle: Proximity system


#### LL3-DY01




# LCDs/transparent objects/semiconductors

• Detection principle: Proximity system


# LL3-DC38



# LL3-DC39




#### LL3-DC05




# Retro-reflective

• Detection principle: Proximity system


#### LL3-RB01




## LL3-RB02



# LL3-RG01




# LL3-RR01




# Liquid level

• Detection principle: Proximity system


#### LL3-DF04




#### LL3-DF05




# LL3-DF07



## LL3-DF02-S01




## LL3-DW02




#### Threaded sleeve

• Detection principle: Through-beam system


## LL3-TJ01




## LL3-TR02




# LL3-TM02




# LL3-TK77




## LL3-TB02




#### LL3-TM01




## LL3-TR01




## LL3-TB01



#### LL3-TB08




## LL3-TX02




#### Smooth sleeve

• Detection principle: Through-beam system


# LL3-TR04




# LL3-TR03




# LL3-TH06




# LL3-TG05






1) angle of beam


## LL3-TR10




# LL3-TB07



# LL3-TG03, LL3-TV08




# LL3-TM03



#### LL3-TK05




#### **LL3-TS07**




# 90° deflection

• Detection principle: Through-beam system


## LL3-TR09




#### LL3-TB06




# LL3-TR08




# LL3-TH07




## LL3-TH15



# LL3-TV05




## LL3-TY03




## Flat type

• Detection principle: Through-beam system


## LL3-TE01




## LL3-TH16




# LL3-TV06, LL3-TV07




# LL3-TE02




# LL3-TE04




## LL3-TR05




# LL3-TR13




# LL3-TR11




# LL3-TE05




## LL3-TR06



## LL3-TR12




# LL3-TE03




# Long end sleeve

• Detection principle: Through-beam system


## LL3-TP01




## LL3-TT01




#### LL3-TV04




#### LL3-TK16



#### LL3-TV01




# LL3-TB05




1) bendable

## LL3-TV02




## LL3-TB03




1) Flexible end tip, do not bend in this area (10 mm), bend radius R10 mm

#### **LL3-TS08**



# LL3-TS12




## Area detection

• Detection principle: Through-beam system


## LL3-TZ09






# LL3-TZ10







## LL3-TS40




#### LL3-TZ05




## LL3-TZ06



# LL3-TS14




## LL3-TS10




## Heat-resistant

• Detection principle: Through-beam system


# LL3-TH10




## LL3-TH11




## LL3-TW01




# LL3-TH08




#### LL3-TH09




#### LL3-TH12




# LL3-TH14




#### LL3-TH02




## LL3-TH17



#### LL3-TH13




# LL3-TH01




# LCDs/transparent objects/semiconductors

• Detection principle: Through-beam system


# LL3-TG04




## LL3-TS22M




## LL3-TS22




#### LL3-TG02



#### LL3-TG01




#### LL3-TG03




# Resistant to oil/chemicals

• Detection principle: Through-beam system


## LL3-TY01




#### LL3-TY02



# LL3-TY05




## LL3-TY04



# Liquid level

• Detection principle: Through-beam system


# LL3-TF01




# Tip adapters

• Detection principle: Proximity system

#### LL3-DA01




LL3-DA02




• Detection principle: Through-beam system

#### LL3-TA01



LL3-TA02



# **Recommended accessories**

# Others

Figure	Description	Model name	Part no.
minute in the second	Cutter for fibers, supplied with LL3	FC	5304141

→ For additional accessories, please see page L-861

# Your order, please! Customizable solutions to fit your needs.

If you don't find the photoelectric sensors in the SICK portfolio that meets your requirements, we can develop a sensor based on your specifications that fits your application.





# **Tailored solutions**

The design to implementation of a tailored solution is divided into three areas of expertise and six phases. During each phase of the project, you can rely on our support and expert knowledge - anywhere in the world.



Prototyping

SICK uses the specifications to produce a fully functional prototype sensor.

ized solution.



# **Customizable solutions to fit your needs**

SICK is your innovative, reliable, and expert partner when it comes to assessing and prioritizing all your application requirements. After analyzing the necessary product adjustments, we work with you to define the specifications for your customized solution.

We are happy to use the "building blocks" below to create modified sensor solutions that meet your application description in full:

# Housing


- Form and design
- Dimensions
- Material
- · Integrated assembly concept
- · Protective housing

# Cable

- Length
- Material
- · Special features (e.g., oil resistant)
- Pin assignment

# Connection

- M8
- M12
- Special connectors



# Packaging and kitting

Combination of specific complete solutions (e.g., sensor with special accessories) and packaging units

# **Electronics**

- Switching frequency
- · Switching outputs
- · Setting option (e.g., potentiometer, teach-in, fixed setting)

# On-site mounting

· Customized mounting concept for quick and easy installation of the sensor on site

# **Application-specific optics** and detection

- · Light source
- Focal position
- Special marking
- Special sensing range or sensitivity



A range of other individually tailored modifications are also available.

Please get in touch – your contacts at SICK are happy to advise you.







# Perfect sensor integration made easy

Innovative sensor technology is only one side of the coin when talking about intelligent automation solutions. The picture is completed by matching accessories for professional and cost-effective integration. Whether electrical connection technology or mechanical mounting systems, only the right integrative system products lead to a high quality, highly available application solution. The advantage? Sensors and accessories work in conjunction to offer maximum operational safety.

In addition, the user is able to save additional costs for development, manufacture and procurement. A wide range of accessory components are always available on short-notice – convenient single-source availability in combination with sensors. And in the event that a custom solution is required, SICK is on your side as a reliable and competent partner. Tailored developments and adaptations can be implemented in just a short period of time.



Accessories from SICK – the solution for reliable sensor integration.



# Accessories

(	General information	
ſ	Mounting systems	
F	Reflectors	
(	Connection systems	
(	Other accessories	

General information Accessories

# Mounting systems and connection technology

# Mounting systems



To integrate SICK sensors perfectly into a machine or system, mounting equipment tailored precisely to the sensors is required. Whether fine adjustment to precision equipment or protection against harsh environmental conditions, SICK provides matching designs and products for mounting, alignment, and protection for its sensors. When it comes to special applications, SICK works with the customer to develop tailored and system-specific mounting elements, which are then delivered with the sensor.

# Passive connection technology



A broad portfolio of termination screw male and female connectors allows customized wiring solutions to be implemented. Different lengths and qualities of cable can be combined to suit the application – quickly and smoothly. Connecting cables (with a molded round connector on one end and open at the other end), offer maximum flexibility when wiring sensors.

# Your benefits


- Quick system installation and maintenance thanks to a broad portfolio of simple, practical sensor mounting options that have been tailored to SICK sensors
- Flexible, customized alignment of the sensor to the object being detected using the universal clamp system
- Prevention of sensor damage (e.g., due to mechanical loads) and guarantee of sensor functionality with the aid of SICK sensor protection solutions
- Application-specific solutions are available for mounting, aligning and protecting sensors

## Your benefits


- Operational safety because the connection technology is designed for the sensors
- Reduced costs thanks to high-quality components with long service lives
- Guaranteed productivity thanks to reliable detection
- Terminal screwed connectors with screw connection or push-in connection (M8, angled)
- Broad portfolio of connecting and extension cables with PUR jacket (high resistance to oils, lubricants, and coolants), PVC jacket (good resistance to chemicals for use in dry zones), and for use in hygienic and washdown zones (maximum resistance to chemicals, acids, alkalis, and cleaning agents)

# Reflectors

Reflectors are the indispensable counterpart for each photoelectric retro-reflective sensor. Together they form a reliable functional unit. Reliable detection of objects is only guaranteed, including under critical application conditions, if both components are optimally coordinated with one another.



Standard reflectors versus reflective tape



Standard reflectors from SICK vary according to size, shape, and mounting options. The large selection of different designs guarantees optimal sensor operation at all times and perfect integration of the reflectors into the systems.

Reflective tape is typically brought in when it is not possible to use a standard reflector, for example, due to mounting or space restrictions, or if the application requires a large, uninterrupted reflective surface.

Reflectors and reflective tape for laser sensors



Laser photoelectric retro-reflective sensors are characterized in particular by their large sensing ranges and very small light spots. These characteristics, however, place special requirements on the reflector.

If the reflector's individual triple elements are too large, erroneous reflections may occur, resulting in signal interruptions – particularly if the laser light spot passes over the reflector.

For this reason, SICK provides fine triple reflectors and reflective tape specially designed for laser photoelectric retroreflective sensors that have a particularly small triple structure. This ensures a stable reflection signal.

Reflectors for special applications



Most applications in industrial environments can be adapted to use standard plastic reflectors or reflective tape. However, **special applications** also require special sensors and reflectors. SICK therefore offers a wide range of special solutions:

- · Chemically-resistant reflectors
- Stainless steel reflectors
- Heated reflectors (regulated and unregulated)
- Reflectors for high-temperature use
- Antifog reflectors
- · Fine triple glass reflectors
- Dust-resistant and air-rinsed reflector solutions
- Large, premounted reflector plates
- · And many more ...

# **Mounting systems**

# Mounting brackets/plates

# **Mounting brackets**

Figure	For product family	Material	Description	Model name	Part no.
	<b>G1</b> 0	Steel, zinc coated	Mounting bracket for wall and floor mounting for G10 DC	BEF-G10DC01	2071258
	GIO	Steel, zinc coated	Mounting bracket for wall and floor mounting for G10 AC/DC	BEF-G10UC01	2071259
	W8, W8 Inox, W100, G6	Stainless steel	Mounting bracket for wall mounting	BEF-W100-A	5311520
1	W6, W6 III6X, W100, G6	Steel, zinc coated	Mounting bracket for floor mounting	BEF-W100-B	5311521
	W9M4-3	Steet, zine coated		BEF-W160	5305197
	W250-2	Steel, zinc coated	Mounting bracket	BEF-W250	5305850
	W280-2	Stainless steel V2A (1.4301)	Mounting bracket	BEF-W280	5313885
	W2S-2	Charles in a cash of	Mounting bracket for floor mounting	BEF-W2S-A	4034748
100	W25-2	Steel, zinc coated	Mounting bracket for wall mounting	BEF-W2S-B	4034749
	W4-3		Mounting bracket for wall mounting	BEF-W4-A	2051628
1	W <del>4</del> -3	Stainless steel 1.4571	Mounting bracket for floor mounting	BEF-W4-B	2051630
	GR18, V180-2, V18, W15, Z1, Z2	Steel, zinc coated	Mounting plate for M18 sensors	BEF-WG-M18	5321870
8	W11-2, W12-3		Mounting brooket large	BEF-WG-W12	2013942
	W24-2 Stainles W11-2, W12-3	Stainless steel	Mounting bracket, large	BEF-WG-W24	4026324
		Statiliess Steel	Mounting bracket, small	BEF-WK-W12	2012938
(C)	W24-2			BEF-WK-W24	4027532

Figure	For product family	Material	Description	Model name	Part no.
	R/IR			BEF-WK-WTR	2051786
	WLL170-2	Steel, zinc coated	Mounting bracket	BEF-WLL170	5306574
10	WLL180			BEF-WLL180	5325812
	G6	-	-	BEF-WN-G6	2062909
90	GR18, V180-2, V18, W15, Z1, Z2	Steel, zinc coated	Mounting bracket, M18 thread	BEF-WN-M18	5308446
	W27-3	Steel, zinc coated	Mounting bracket for weather hood	BEF-WN-OBW	2023251
	C110A, P250, PL20A PL30A, PL40A, PL80A	Steel, zinc coated	Universal mounting bracket for reflectors, 85 mm x 90 mm x 35 mm	BEF-WN-REFX	2064574
1	W100-2	Steel, zinc coated	Mounting bracket for floor mounting	BEF-WN-W100-S01	4073866
	W14-2, W18-3		Mounting bracket	BEF-WN-W14	2019084
	W14-2, W10-3	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W18	2009317
	W23-2, W27-3, Reflex Array		Mounting bracket	BEF-WN-W23	2019085
	W24-2	Stainless steel (1.4301)	Mounting bracket	BEF-WN-W24	2015248
	W23-2, W27-3, Reflex Array	Steel, zinc coated	Mounting bracket with hinged arm	BEF-WN-W27	2009122
2	W9-3	Steet, zinc coateu	Mounting bracket	BEF-WN-W9-2	2022855

# Mounting plates

Figure	For product family	Material	Description	Model name	Part no.
0 0	W9-3	PMMA, Brass (Br)	Fastening plate with threaded sleeve M3	BEF-GPM3-W9	4066039
	GR18, V180-2, V18, W15, Z1, Z2	Stainless steel	Mounting plate for M18 housing	BEF-WG-M18N	5320948
40			Mounting bracket	BEF-WN-M18N	5320947
6,6	R/IR	Steel, zinc coated	Mounting bracket	BEF-WN-WTR	2017417

# Masks

Figure	Description	Model name	Part no.
	Slotted mask, transmitter and receiver each have 2 self-adhesive masks	BL-100-10	5314182
20 45 45	Mask card for WS/WE12-3 with 2 self-adhesive masks each for sender and receiver, slot width X: 0.5 mm/1.0 mm/1.5 mm/2.0 mm	BL-12-SKN	4031815
	Mask card, vertical/horizontal slots, slot width: 0.5 mm / 1.0 mm / 1.5 mm / 2.0 mm	BL-9-2	4033253

# Device protection (mechanical)

# **Cooling elements**

Figure	For product family	Description	Model name	Part no.
1	W24-2	Water cooling plate	BEF-KP-W24	2015071

# Protective housings/pipes

Figure	For product family	Material	Description	Model name	Part no.
11	G10	Charl vine control	Weather protection hood for G10	BEF-G10WSG	2071960
	Reflector PL80A	Steel, zinc coated	Weather protection hood for reflectors PL80A, P250, PL40A	BEF-PL80AWSG	2071961
4	W11-2, W12-3			BEF-SG-W12-3	2045175
	W14-2, W18-3	Zinc plated steel (protective housing), Diecast zinc (clamp)	Protective housing for universal clamp	BEF-SG-W14	2058124
1	W27-3, Reflex Array			BEF-SG-W27	2039601
	W4S-3, W8, W100, G6	Stainless steel 1.4571	Safety bracket for floor mounting	BEF-SW-W4S	2051497
	W2S-2, G2	Aluminum (mounting bracket), Steel, chrome- plated (coil)	Protective housing for spiral flex hose	BEF-W2S-C	2033270
	W24-2	Aluminum (anodised)	Dust protection tube, air- purged	OBS-W24	2015069
12	W23-2, W24-2, W27-3, W34, Reflex Array	Steel, zinc coated	Weather hood for universal clamp bracket	OBW-KHS-M01	2023240
	W24-2	Aluminum (anadicad)	Weather hood	OBW-W24	2015070
THE	W24-2	Aluminum (anodised)	weather nood	WSG1-01	1018470

# Terminal and alignment brackets

# **Alignment brackets**

Figure	For product family	Material	Description	Model name	Part no.
	W2S-2	Plastic	Ball clamp bracket	BEF-GH-MINIO1	2023160
0	GR18, V180-2, V18, W15, Z1, Z2	Plastic	Mounting bracket with ball- and-socket	BEF-WN-M18-ST02	5312973

# **Terminal brackets**

Figure	For product family	Material	Description	Model name	Part no.
	W11-2, W12-3	Steel, zinc coated	Double clamp bracket for dovetail mounting	BEF-DKH-W12	2013947
0	GR18, V180-2, V18, W15, Z1, Z2	Plastic	M18 mounting bracket, radial rotation possible, with 4 mm fixing holes	BEF-HA-M18R	5313513
<b>6</b> 5	CD40 MH4EV V400 2 V40	Plastic (PA12), glass-fiber reinforced	Clamping block for round sensors M18, without fixed stop	BEF-KH-M18	2051481
<b>6</b> 5	GR18, MH15V, V180-2, V18		Clamping block for round sensors M18, with fixed stop	BEF-KHF-M18	2051482
	W11-2, W12-3	Steel, zinc coated	Clamping block for dovetail mounting	BEF-KH-W12	2013285
0	GR18, MH15V	Plastic (PA12)	Integrated adapter	BEF-WN-MH15-1	4039533
	MH15V, V180-2, V18	Stainless steel	Mounting ring	BEF-WN-MH15-2V	4053358

# Other mounting accessories

Figure	Description	Model name	Part no.
	Diameter 18 mm x 100 mm for W4S-3 lnox hygiene. Hygienic integration without holes and brackets. Cable runs inside tube	BEF-MR18G-NA	4065853

#### **Others**

Figure	For product family	Material	Description	Model name	Part no.
E()	GR18S, radial, fully flush	-	Mounting tool for "fully flush" variants	BEF-TO-GR18S	4072132
A A	WLL180T	Stainless steel	Rail end piece for block mounting	BF-EB01-W190	5313011
	LL3	-	Cutter for fibers, supplied with LL3, 10 mm x 37 mm x 65 mm	FC	5304141

# Universal bar clamp systems


Figure	Material	Description	Model name	Part no.
		Hygienic design mounting tube with bayonet lock, 14.4 mm x 85.5 mm x 14.4 mm	BEF-HDSBR	4074403
		Hygienic design flange with seal, 40 mm x 12 mm x 40 mm	BEF-HDSF	4072880
		Hygienic design telescopic tube, straight, with bayonet lock without flange, 23 mm x 153 mm x 23 mm	BEF-HDSTRG	2067780
	Hygienic Design, Stainless steel V4A	Hygienic design telescopic tube, straight, with bayonet lock with flange, 40 mm x 165 mm x 40 mm	BEF-HDSTRGF	2067779
	(1.4404, 316L), Silicone (seal)	Hygienic design telescopic tube bended, shorted, with shorted bayonet lock with flange, 40 mm x 97.5 mm x 76 mm	BEF-HDSTRK1WF	2071931
		Hygienic design telescopic tube bended, extended, with extended bayonet lock with flange, 40 mm x 249 mm x 40 mm $^{\circ}$	BEF-HDSTRL1GF	2072047
		Hygienic design telescopic tube, angled, with bayonet lock without flange, 23 mm x 125 mm x 73 mm	BEF-HDSTRW	2067778
		Hygienic design telescopic tube, angled, with bayonet lock with flange, 40 mm x 125 mm x 76 mm	BEF-HDSTRWF	2067777
B	Zinc diecast	Universal bar clamp for mounting bars with 12 mm diameter	BEF-KHS-KH3	5322626
VI)	Stainless steel V2A (1.4301)	Universal clamp bracket for mounting bars with 12 mm diameter	BEF-KHS-KH3N	5322627
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N02 for universal clamp bracket	BEF-KHS-N02	2051608
10	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO2N for universal clamp bracket	BEF-KHS-N02N	2051618
	Zinc plated steel (sheet), Diecast	Plate N03 for universal clamp bracket	BEF-KHS-N03	2051609
	zinc (clamp)	Plate N04 for universal clamp bracket	BEF-KHS-N04	2051610
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO3N for universal clamp bracket	BEF-KHS-NO4N	2051619
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N05 for universal clamp bracket	BEF-KHS-N05	2051611
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate NO4N for universal clamp bracket	BEF-KHS-N05N	2051620
6	Stainless steel 1.4408 (clamp)	Plate N05N for universal clamp bracket, M12	BEF-KHS-N05N	2051621
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N06 for universal clamp bracket	BEF-KHS-N06	2051612
16	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N06N for universal clamp bracket, M18	BEF-KHS-N06N	2051622
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N07 for universal clamp bracket	BEF-KHS-N07	2051613
	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N07N for universal clamp bracket	BEF-KHS-N07N	2051623

Figure	Material	Description	Model name	Part no.
	Zinc plated steel (sheet), Diecast zinc (clamp)	Plate N08 for universal clamp bracket	BEF-KHS-N08	2051607
18	Stainless steel 1.4571 (sheet), Stainless steel 1.4408 (clamp)	Plate N08N for universal clamp bracket	BEF-KHS-N08N	2051616
	Die-cast zinc, Steel, zinc coated	Q-Lock, bar clamp system for G10 and reflector	BEF-KHSQ12R01	2071260
1	Die Gast Zine, Otoo, Zine Goatea	P250	BEF-KHSQ12ZR01	2071262
	Steel, zinc coated	Mounting bar, straight, 200 mm	BEF-MS12G-A	4056054
	Steel, zille coated	Mounting bar, straight, 300 mm	BEF-MS12G-B	4056055
	Stainless steel (1.4571)	Mounting bar, straight, 200 mm	BEF-MS12G-NA	4058914
	Stainless Steer (1.4571)	Mounting bar, straight, 300 mm	BEF-MS12G-NB	4058915
	Steel, zinc coated	Mounting bar, L-shaped, 150 mm x 150 mm	BEF-MS12L-A	4056052
		Mounting bar, L-shaped, 250 x 250 mm	BEF-MS12L-B	4056053
	Stainless steel (1.4571)	Mounting bar, L-shaped, 150 mm x 150 mm	BEF-MS12L-NA	4058912
		Mounting bar, L-shaped, 250 mm x 250 mm	BEF-MS12L-NB	4058913
		Mounting rod, U-shape, bending radius 26 mm, 130 mm	BEF-MS12U	4065437
	Steel, zinc coated	Mounting bar, Z-shaped, 150 mm x 70 mm x 150 mm	BEF-MS12Z-A	4056056
		Mounting bar, Z-shaped, 150 mm x 70 mm x 250 mm	BEF-MS12Z-B	4056057
5		Mounting bar, Z-shaped, 100 mm x 150 mm x 200 mm	BEF-MS12Z-C	4064563
	Stainless steel (1.4571)	Mounting bar, Z-shaped, 150 mm x 70 mm x 150 mm	BEF-MS12Z-NA	4058916
	Otalii1033 31551 (1.401 1)	Mounting bar, Z-shaped, 150 mm x 70 mm x 250 mm	BEF-MS12Z-NB	4058917
0	Aluminum	Bar clamp for bar diameter of 12 mm (fixing the mounting rod)	BEF-RMC-D12	5321878


8015327/2014-02-08 Subject to change without notice


# Dimensional drawings mounting brackets/plates

#### BEF-AP-W9




#### BEF-G10DC01







#### BEF-G10UC01




#### BEF-GPM3-W9







# **BEF-W100-A**




#### BEF-W100-B




#### **BEF-W160**




### **BEF-W250**




#### **BEF-W280**




#### **BEF-W2S-A**




#### BEF-W2S-B




#### BEF-W4-A



#### BEF-W4-B




#### BEF-WG-M18 BEF-WG-M18N




#### BEF-WG-W12

5.3 (0.21)


> 13.1 (0.52)




# BEF-WG-W24




#### BEF-WK-W12




#### **BEF-WK-WTR**




### BEF-WN-M18 BEF-WN-M18N




#### BEF-WK-W24




#### BEF-WLL170 BEF-WLL180




#### **BEF-WN-OBW**




#### **BEF-WN-REFX**








- ① C110A
- ② P250
- ③ PL20A
- 4 PL30A, PL80A
- ⑤ PL40A


#### BEF-WN-W14


















#### BEF-WN-W18







#### BEF-WN-W23







#### BEF-WN-W27






#### BEF-WN-W24






#### BEF-WN-W9-2




#### **BEF-WN-WTR**



# Dimensional drawings Masks

#### BL-100-10




3 pairs included with apertures A, B, C. Self-adhesive backing for easy mounting. Apply stick-on mask to WS100 and WE100 front lens.

For small object detection or increasing indexing accuracy.


Sensing ranges with apertures applied:

- A) Aperture 2.0 mm: Range = 4.0 m
- B) Aperture 1.0 mm: Range = 2.0 m
- C) Aperture 0.5 mm: Range = 1.0 m

# BL-12-SKN




#### BL-9-2





L-877

# Dimensional drawings Device protection (mechanical)


#### BEF-G10WSG








#### BEF-KP-W24




- ① Hose nozzle R1/4"
- ${\ensuremath{ 2}}$  Tapped hole for countersunk screw M5


#### **BEF-PL80AWSG**




#### **BEF-SG-W12-3**




# BEF-SG-W27




#### **BEF-SW-W4S**



#### BEF-W2S-C




#### **OBS-W24**



Alle Maße in mm


OBW-KHS-M01



- ① Sensor
- 2 Base plate with clamp supplied with unit


### **OBW-W24**

2 Running nut channel for M5 nut




 $\ensuremath{\textcircled{1}}$  Fast action screw fitting for hose internal diameter 6mm

# WSG1-01




# Dimensional drawings Terminal and alignment brackets


#### BEF-DKH-W12



#### BEF-HA-M18R BEF-WN-M18-ST02




#### BEF-GH-MINI01



- ① Self-tapping screw Ø 4mm
- 2 System or machine part

#### BEF-KH-M18




① Without fixed stop

#### BEF-KHF-M18


# 


#### BEF-KH-W12




② With fixed stop


#### BEF-WN-MH15-1






#### BEF-WN-MH15-2V







Dimensional drawings Other mounting accessories

#### BEF-MR18G-NA







#### BEF-TO-GR18S



#### BF-EB01-W190




#### FC




- ① Template for bend radius R10 mm, for end sleeve Ø 1.5 mm and Ø 2.5 mm
- 2 Bend radius R5 mm

# Dimensional drawings Universal bar clamp systems


# **BEF-HDSBR**




### **BEF-HDSF**




#### **BEF-HDSTRG**




#### **BEF-HDSTRGF**




#### **BEF-HDSTRK1WF**




#### **BEF-HDSTRL1GF**




# **BEF-HDSTRW**




#### **BEF-HDSTRWF**




#### **BEF-KHS-KH3**



#### **BEF-KHS-KH3N**



#### BEF-KHS-N02 BEF-KHS-N02N





BEF-KHS-N03 BEF-KHS-N04N


BEF-KHS-N04 BEF-KHS-N05N


BEF-KHS-N05 BEF-KHS-N05N

BEF-KHS-N06 BEF-KHS-N06N











BEF-KHS-N07 BEF-KHS-N07N


70 (2.76) 2.5 (0.10) 252 (0.99) 45.7 (1.80)


BEF-KHS-N08 BEF-KHS-N08N




BEF-KHSQ12R01











#### BEF-KHSQ12ZR01




BEF-MS12G-A BEF-MS12G-B BEF-MS12G-NA BEF-MS12G-NB




- ① BEF-MS12G-(N)A: A = 200 mm
- ② BEF-MS12G-(N)B: A = 300 mm






- ① BEF-MS12L-(N)A: A = 200 mm, B = 150 mm
- ② BEF-MS12L-(N)B: A = 250 mm, B = 250 mm

# BEF-MS12Z-A, BEF-MS12Z-B, BEF-MS12Z-C, BEF-MS12Z-NA, BEF-MS12Z-NB



- ① BEF-MS12Z-(N)A: A = 150 mm, B = 70 mm, C = 150 mm
- ② BEF-MS12Z-(N)B: A = 150 mm, B = 70 mm, C = 250 mm

# BEF-RMC-D12



# Reflectors

# Reflectors

# Angular

Figure	Material	Description	Model name	Part no.
		Rectangular, screw connection, 47 mm x 47 mm	P250	5304812
		Rectangular, screw connection, 45 mm x 28 mm	P32	5314001
		Rectangular, screw connection, 25 mm x 21 mm	P40	5313923
2		Rectangular, screw connection, 32 mm x 31 mm	P42	5314825
		Rectangular, screw connection, 31 mm x 8.5 mm	P45A	5320027
		Rectangular, screw connection, 96 mm x 96 mm	PL100	5321625
		Rectangular, self-adhesive, 146 mm x 14 mm	PL150	5315548
		Rectangular, screw connection, 175 mm x 34 mm	PL180E01	1013289
	PMMA/ABS	Rectangular, screw connection, 38 mm x 15 mm	PL20A	1012719
		Rectangular, self-adhesive, 38 mm x 15 mm	PL21A	1015172
8		Rectangular, screw connection, 56 mm x 28 mm	PL30A	1002314
		Rectangular, self-adhesive, 56 mm x 28 mm	PL31A	1002315
		Rectangular, screw connection, 37 mm x 56 mm	PL40A	1012720
, person		Rectangular, screw connection M3, countersunk screw head, 40 mm x 60 mm	PL40B	5320134
		Rectangular, screw connection, wrench size 48 mm	PL50A	1000132
		Rectangular, self-adhesive, wrench size 48 mm	PL51A	1001628
		Rectangular, with M6x14 threaded bolt and locking device, 75 mm x 45 mm	PL72-2	5322723

Figure	Material	Description	Model name	Part no.
-	PMMA/ABS	Rectangular, screw connection, 80 mm x 80 mm	PL80A	1003865
		Rectangular, self-adhesive, 76 mm x 45 mm	PL81	5322795
	Plastic	Chemically resistant, screw connection, 47 mm x 47 mm	P250 CHEM	5321097

# Fine triple reflectors

Figure	Material	Description	Model name	Part no.
		Fine triple, screw connection, suitable for laser sensors, $47\ \text{mm}\ \text{x}\ 47\ \text{mm}$	P250F	5308843
		Fine triple, self-adhesive, suitable for laser sensors, $\emptyset$ 23 mm	P25F-1	5319385
		Reflector with microprismatic reflex tape REF-AC1000, suitable for laser sensors, see alignment note, 23 mm x 23 mm	P41F	5315128
		Fine triple, screw connection, suitable for laser sensors, Wrench size 48 mm	P55F	5313924
	DMMAA /ADC	Fine triple, screw connection, suitable for laser sensors, 18 mm x 18 mm	PL10F	5311210
	PMMA/ABS	Fine triple, planar, suitable for laser sensors, 45 mm x 17 mm	PL15F	5313849
		Fine triple, self-adhesive, suitable for laser sensors, 27 mm x 17 mm	PL18F	5319994
		Fine triple, screw connection, suitable for laser sensors, 38 mm x 16 mm	PL20F	5308844
		Fine triple, screw connection, suitable for laser sensors, 56 mm x 28 mm	PL30F	5326523
		Fine triple, screw connection, suitable for laser sensors, 76 mm x 45 mm	PL81-1F	5325060
and the same of th		Fine triple, chemically resistant, screw connection, $18 \ \text{mm} \ \text{x}$ $18 \ \text{mm}$	PL10F CHEM	5321636
	Plastic	Fine triple, chemically resistant, screw connection, 20 mm x 32 mm $$	PL10FB-CHEM	5327722
		Fine triple, chemically resistant, screw connection, suitable for laser sensors, 16 mm x 38 mm	PL20F-CHEM	5326089

# Reflective tape

Figure	Description	Model name	Part no.
	Self-adhesive, not suitable for photoelectric retro-reflective sensors with polarisation filter, length customisable by roll, 91.4 cm x 4.57 m $^{\circ}$	REF-3290	5301885
	Self-adhesive, not suitable for photoelectric retro-reflective sensors with polarisation filter, dimensions customisable by roll, 91.4 cm x 4.57 m $^{\rm )}$	REF-3290-K	4018696
	With alignment mark, self-adhesive, customizable size by roll, 91.4 cm x 45.7 m $^{\circ}$	REF-3930-K2	2057035
	Self-adhesive, not suitable for photoelectric retro-reflective sensors with polarisation filter, customizable length by roll, $61\text{cm}\text{x}4.57\text{m}^{\text{j}}$	REF-7610-0K4	5600079
	Self-adhesive, not suitable for photoelectric retro-reflective sensors with polarisation filter, customizable size by roll, 61 cm x 4.57 m $^{\circ}$	REF-7610-K	4018617
	Suitable for laser sensors, self-adhesive, sheet, see alignment note, 225 mm x 225 mm	REF-AC1000	5319429
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 28 mm x 28 mm	REF-AC1000-28	4067881
	Suitable for laser sensors, self-adhesive, cut, see alignment note, 56.3 mm x 56.3 mm	REF-AC1000-56	4063030
	Suitable for laser sensors, self-adhesive, cut, 20 pieces per pack, see alignment note, 73 mm x 73 mm	REF-AC1000-73P01	2061557
	Sheet, self-adhesive, not suitable for laser sensors, 225 mm x 225 mm	REF-APM	4025097
	Reflective tape "Diamond Grade", self-adhesive, sheet, 749 mm x 914 mm	REF-DG	5320565
	Reflective tape "Diamond Grade", self-adhesive, customizable size by sheet, 74.9 cm x 91.4 cm $^{\circ}$	REF-DG-K	4019634
	Self-adhesive, 50 mm x 60 mm	REF-IRF-56	5314244
A	Self-adhesive, customizable length by roll, 2.5 cm x 22.8 m	REF-PLUS-25-K	4051184
0	Self-adhesive, customizable length by roll, 5 cm x 22.8 m <sup>)</sup>	REF-PLUS-50-K	4051185
	Roll, self-adhesive, 100 mm x 22.8 m	REF-PLUS-R100	5319915
6	Self-adhesive, customizable length by roll, 10 cm x 22.8 m <sup>)</sup>	REF-PLUS-R100-K	4071461
	Self-adhesive, roll, 25 mm x 22.8 m	REF-PLUS-R25	5319929
0	Self-adhesive, roll, 50 mm x 22.8 m	REF-PLUS-R50	5319981
0	Self-adhesive, customizable length by roll, 7.6 cm x 22.8 m $^{\circ}$	REF-PLUS-R76	4071462
	100 pieces per pack, self-adhesive, 34 mm x 36 mm	REF-Plus-3436	5321337
	Roll, self-adhesive, 7.6 cm x 22.8 m )	REF-Plus-R76	5322215
	100 pieces per pack, red, self-adhesive, 25 mm x 50 mm	REF-Plus-RED-2550	5320285

#### Round

Figure	Material	Description	Model name	Part no.
		Round, screw connection	C110A	5304549
		Round, plugable	C42-1	5313506
		Round, M5x9 threaded bolt	C42-2	5324281
		Round, screw connection	C64A	5325185
(1890):		Reflector, round, M4x8 threaded bolt	P25	5315172
		Round, pluggable	P25-2	5318969
		Round, planar	P34	5313922
	PMMA/ABS	Round, M5x9 threaded bolt	P50-1	5322673
		Round, screw connection, wrench size 48 mm	P55	5318680
		Round, pluggable	PL22-1	1003546
		Round, self-adhesive	PL22-2	1003621
		Round, plugable for metal plates	PL22-3	1004488
		Round, pluggable	PL34-1	5322257


# **Special reflectors**

Figure	Material	Description	Model name	Part no.
	Aluminum (anodized) / glass	Single-triple glass reflector for very high sensing ranges, focus: infinite, screw connection	OP60-00	1000141
<b>,</b>		Single-triple glass reflector for very high sensing ranges, focus: 20 m, screw connection	OP60-20	1000136
		Single-triple glass reflector for high-temperature applications, screw connection	OP61-00	1002627
	HOT Thermoplast	High-temperature reflector, screw connection, 47 mm x 47 mm	P250H	5315124
8	Plastic	Chemically resistant, screw connection, 38 mm x 15 mm	PL20 CHEM	5321089
	PMMA/ABS	Antifog, for prevention of moisture fogging on the reflection area, screw connection, 56 mm x 37 mm	PL40A Antifog	5322011


Figure	Material	Description	Model name	Part no.
	Plastic	Rectangular, screw connection M3, countersunk screw head, chemical resistent, 56 mm x 37 mm	PL40B-CHEM	5326088
	PMMA/ABS	Permanently heated, screw connection, wrench size 48 mm	PL50HK	1011545
		Regulated heated, screw connection; heating ON: T < 15 $^{\circ}$ C, wrench size 48 mm	PL50HS	1009871
	Anodised Aluminium / borosilicate glass	Oil-proof, solvent-resistant, screw connection	PL53A	1000382
	Stainless steel V4A (1.4404, 316L)	Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, D12-adapter shaft, 25 mm x 25 mm	PLH25-D12	2063404
		Stainless steel reflector, hygienic design, chemically resistant, Enclosure rating IP 69K, M12-adapter thread, 25 mm x 25 mm	PLH25-M12	2063403
		Stainless steel reflector, wash-down design, chemically resistant, Enclosure rating IP 69K, screw connection, 14 mm x 14 mm	PLV14-A	2063405
<b>(</b> )	Anodised Aluminium / borosilicate glass	High-temperature reflector, glass, screw connection	SW50	1000131

# **Dimensional drawings Reflectors**


# C110A




#### C42-2



# C42-1




# C64A




**Reflectors** Accessories


P25

#### OP60-00, OP60-20, OP61-00







# P25-2




#### P250




#### **P250 CHEM**




#### P250F




#### P250H




#### P25F-1




P32




P34




#### P40




#### P45A




#### P55




# **PL100**




#### P41F




# P50-1




#### P55F




#### PL150




**Reflectors** Accessories







**Reflectors** Accessories

### PL50HK PL50HS






#### PL51A







#### PL53A




#### PL72-2




# PL80A




# **PL81**



#### PL81-1F




#### PLH25-D12




① Reflective area

#### PLV14-A




 ${\bf \textcircled{1}} \ {\bf Reflective} \ {\bf area}$ 

#### **REF-3290**



① X = 91.4 cm ② Y = 4.57 m


### REF-3290-K REF-AC1000-28 REF-PLUS-R100-K



① X = 91.4 cm

② Y = 4.57 m

#### REF-7610-0K4




1 X = 61 cm

② Y = 4.57 m

Accessories


## REF-7610-K



① X = 61 cm


# ② Y = 4.57 m

#### REF-AC1000-56




① X = 56,3 mm ② Y = 56,3 mm

## REF-AC1000



① X = 225 mm ② Y = 225 mm

## REF-AC1000-73P01




① X = 73 mm

② Y = 73 mm

Accessories Reflectors


## **REF-APM**



① X = 225 mm

# ② Y = 225 mm


#### **REF-DG-K**



① X = 74.9 cm

## ② Y = 91.4 cm


#### **REF-PLUS-25-K REF-PLUS-R25**



① X = 2.5 cm


## ② Y = 22.8 m

## REF-DG



① X = 74.9 cm


#### **REF-IRF-56**



① X = 50 mm

② Y = 60 mm

#### REF-PLUS-R100




① X = 100 mm

② Y = 22.8 m


② Y = 91.4 cm

## **REF-PLUS-R50**



① X = 50 mm ② Y = 22.8 m


## REF-Plus-3436




① X = 34 mm

② Y = 36 mm

## SW50




## REF-PLUS-R76 REF-Plus-R76



① X = 7.6 cm ② Y = 22.8 m

## REF-Plus-RED-2550



① X = 25 mm

② Y = 50 mm

# **Connection systems**

## Modules/gateways

#### **Connection modules**

Figure	Description	Model name	Part no.
View.	$\mbox{I/O}$ box extension with 2 ethernet ports enabling switch functionality, number of logical input: 4, output: 8	I/O box extension, 4 in/8 out	6037654
A.	I/O module to add logical output to the $I/O$ extension box, number of logical output = 8, only usage with accessory $6037654$	I/O extension mod- ule, 8 out	6037750
	I/O extension module to extend the number of digital inputs in combination with I/O box extension. Number of digital inputs: 2, only usage with accessory 6037654	I/O module, 2 extra digital inputs	6039038

## Connecting cable (female connector-open) M8, 3-pin, PP, hygienic systems

- Cable material: PP
- Connector material: PP
- Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
	Female connector, M8, 3-pin, straight		2 m, 3-wire	DOL-0803-G02MN	6033664
		Cable, open conductor	5 m, 3-wire	DOL-0803-G05MN	6033665
Ø @		heads	10 m, 3-wire	DOL-0803-G10MN	6033666
			25 m, 3-wire	DOL-0803-G25MN	6044452
			2 m, 3-wire	DOL-0803-W02MN	6033667
Female connector, M8, 3-pin, angled	Cable, open conductor heads	5 m, 3-wire	DOL-0803-W05MN	6033668	
6	3-pin, angled	noddo	10 m, 3-wire	DOL-0803-W10MN	6033669

## Connecting cable (female connector-open) M8, 3-pin, PUR, halogen-free

- Cable material: PUR, halogen-free
- Connector material: TPU
- Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			1 m, 3-wire	DOL-0803-G01MC	6036455
			2 m, 3-wire	DOL-0803-G02MC	6025888
	Female connector, M8, 3-pin, straight	Cable, open conductor heads	5 m, 3-wire	DOL-0803-G05MC	6025889
	3-pin, straight	nodd	10 m, 3-wire	DOL-0803-G10MC	6025890
			20 m, 3-wire	DOL-0803-G20MC	6036456
			2 m, 3-wire	DOL-0803-W02MC	6025891
	Female connector, M8,	Cable, open conductor	3 m, 3-wire	DOL-0803-W03MC	6038991
3-pin, angled	heads	5 m, 3-wire	DOL-0803-W05MC	6025892	
			10 m, 3-wire	DOL-0803-W10MC	6025893

# Connecting cable (female connector-open) M8, 3-pin, PVC

• Cable material: PVC

• Connector material: TPU

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 3-wire	DOL-0803-G02M	6010785
	Female connector, M8, 3-pin, straight	Cable, open conductor	5 m, 3-wire	DOL-0803-G05M	6022009
		heads	10 m, 3-wire	DOL-0803-G10M	6022011
			15 m, 3-wire	DOL-0803-G15M	6036472
			2 m, 3-wire	DOL-0803-W02M	6008489
	Female connector, M8,	Cable, open conductor	5 m, 3-wire	DOL-0803-W05M	6022010
3-pin, angled	3-pin, angled	heads	10 m, 3-wire	DOL-0803-W10M	6022012
			15 m, 3-wire	DOL-0803-W15M	6036473

## Connecting cable (female connector-open) M8, 4-pin, PP, hygienic systems

• Cable material: PP

• Connector material: PP

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 4-wire	DOL-0804-G02MN	6033670
	Female connector, M8, 4-pin, straight	3, Cable, open conductor heads	5 m, 4-wire	DOL-0804-G05MN	6033671
We so	i pini, otraligite		10 m, 4-wire	DOL-0804-G10MN	6033672
			2 m, 4-wire	DOL-0804-W02MN	6033673
	Female connector, M8, 4-pin, angled	Cable, open conductor heads	5 m, 4-wire	DOL-0804-W05MN	6033674
O OF			10 m, 4-wire	DOL-0804-W10MN	6033675

## Connecting cable (female connector-open) M8, 4-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

• Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Shielding	Connecting cable	Model name	Part no.
				2 m, 4-wire	DOL-0804-G02MC	6025894
				5 m, 4-wire	DOL-0804-G05MC	6025895
			Unshielded	10 m, 4-wire	DOL-0804-G10MC	6025896
18	, , , , , , , , , , , , , , , , , , ,	Cable, open conduc- tor heads	o-	15 m, 4-wire	DOL-0804-G15MC	6038622
	M8, 4-pin, straight	vio, 4-pin, straight tor neads		20 m, 4-wire	DOL-0804-G20MC	6051148
			Shielded	5 m, 4-wire	DOL-0804-G05MAC	6050809
1			Silielded	10 m, 4-wire	DOL-0804-G10MAC	6050808
				2 m, 4-wire	DOL-0804-W02MC	6025897
	Female connector, M8, 4-pin, angled	Cable, open conduc- tor heads	Unshielded	5 m, 4-wire	DOL-0804-W05MC	6025898
/ 2	ivio, 4-pin, angled tor neads	tor rioddo		10 m, 4-wire	DOL-0804-W10MC	6025899

L-904

## Connecting cable (female connector-open) M8, 4-pin, PVC

• Cable material: PVC

Connector material: PVC

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 4-wire	DOL-0804-G02M	6009870
			5 m, 4-wire	DOL-0804-G05M	6009872
			10 m, 4-wire	DOL-0804-G10M	6010754
	Female connector, M8, 4-pin, straight	Cable, open conductor heads	15 m, 4-wire	DOL-0804-G15M	6035232
	+ pin, straight		20 m, 4-wire	DOL-0804-G20M	6029109
			30 m, 4-wire	DOL-0804-G30M	6029110
			50 m, 4-wire	DOL-0804-G50M	6029111
8			2 m, 4-wire	DOL-0804-W02M	6009871
	Female connector, M8, 4-pin, angled	Cable, open conductor heads	5 m, 4-wire	DOL-0804-W05M	6009873
		riedus	10 m, 4-wire	DOL-0804-W10M	6010755

## Connecting cable (female connector-open) M12, 3-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

• Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 3-wire	DOL-1203-G02MC	6039075
	Female connector, M12, 3-pin, straight Cable, open conductor heads	' '	5 m, 3-wire	DOL-1203-G05MC	6039076
100		noddo	10 m, 3-wire	DOL-1203-G10MC	6039077
		Cable, open conductor heads	2 m, 3-wire	DOL-1203-W02MC	6039078
			5 m, 3-wire	DOL-1203-W05MC	6039079
	Female connector, M12, 3-pin, angled		10 m, 3-wire	DOL-1203-W10MC	6036752
5 pin, angled	noddo	15 m, 3-wire	DOL-1203-W15MC	6036753	
		20 m, 3-wire	DOL-1203-W20MC	6036754	

## Connecting cable (female connector-open) M12, 4-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

Figure	Connection type head A	Connection type head B	Shielding	Enclosure rating	Connecting cable	Model name	Part no.
					2 m, 4-wire	DOL-1204-G02MC	6025900
					5 m, 4-wire	DOL-1204-G05MC	6025901
			Unshielded	IP 65, IP 68,	10 m, 4-wire	DOL-1204-G10MC	6025902
1	Female connec-	' ·	able, open conductor	IP 69K	15 m, 4-wire	DOL-1204-G15MC	6034749
	tor, M12, 4-pin, straight	conductor heads			20 m, 4-wire	DOL-1204-G20MC	6034750
					25 m, 4-wire	DOL-1204-G25MC	6034751
1			Shielded	IP 67	5 m, 4-wire	DOL-1204-G05MAC	6038621

Figure	Connection type head A	Connection type head B	Shielding	Enclosure rating	Connecting cable	Model name	Part no.
	Female connector, M12, 4-pin, angled, with 3 LEDs	Cable, open conductor heads	Unshielded	IP 65, IP 68, IP 69K	5 m, 4-wire	DOL-1204-L05MC	6020398
			Unshielded		2 m, 4-wire	DOL-1204-W02MC	6025903
					5 m, 4-wire	DOL-1204-W05MC	6025904
	Female connec-	Cable, open		IP 65, IP 68, IP 69K	10 m, 4-wire	DOL-1204-W10MC	6025905
10	tor, M12, 4-pin, angled	conductor heads			15 m, 4-wire	DOL-1204-W15MC	6034752
					20 m, 4-wire	DOL-1204-W20MC	6034753
					25 m, 4-wire	DOL-1204-W25MC	6034754

## Connecting cable (female connector-open) M12, 4-pin, PVC

Cable material: PVCConnector material: TPUEnclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 4-wire	DOL-1204-G02M	6009382
			5 m, 4-wire	DOL-1204-G05M	6009866
	Female connector, M12, 4-pin, straight	Cable, open conductor heads	10 m, 4-wire	DOL-1204-G10M	6010543
/ 10	r pm, oddigne	noddo	15 m, 4-wire	DOL-1204-G15M	6010753
			20 m, 4-wire	DOL-1204-G20M	6034401
		Cable, open conductor heads	2 m, 4-wire	DOL-1204-L02M	6027945
	Female connector, M12, 4-pin, angled, with 3 LEDs		5 m, 4-wire	DOL-1204-L05M	6027944
<i>M</i> : ••••	i pini, anglea, wan e 2236	noddo	10 m, 4-wire	DOL-1204-L10M	6027946
			2 m, 4-wire	DOL-1204-W02M	6009383
			5 m, 4-wire	DOL-1204-W05M	6009867
	Female connector, M12, 4-pin, angled	Cable, open conductor heads	10 m, 4-wire	DOL-1204-W10M	6010541
	, p.i.i, aligica		15 m, 4-wire	DOL-1204-W15M	6036474
			20 m, 4-wire	DOL-1204-W20M	6033559

## Connecting cable (female connector-open) M12, 4-pin, PVC, hygienic systems

• Cable material: PVC

• Connector material: PVC

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 4-wire	DOL-1204-G02MN	6028128
	Female connector, M12,	Cable, open conductor	5 m, 4-wire	DOL-1204-G05MN	6028130
1 100	4-pin, straight	heads	10 m, 4-wire	DOL-1204-G10MN	6028132
			25 m, 4-wire	DOL-1204-G25MN	6028134
			2 m, 4-wire	DOL-1204-L02MN	6028136
	Female connector, M12,	Cable, open conductor	5 m, 4-wire	DOL-1204-L05MN	6028137
	4-pin, angled, with 3 LEDs	heads	10 m, 4-wire	DOL-1204-L10MN	6028138
			25 m, 4-wire	DOL-1204-L25MN	6028139
			2 m, 4-wire	DOL-1204-W02MN	6028129
	Female connector, M12,	Cable, open conductor	5 m, 4-wire	DOL-1204-W05MN	6028131
	4-pin, angled	heads	10 m, 4-wire	DOL-1204-W10MN	6028133
			25 m, 4-wire	DOL-1204-W25MN	6028135

L-906

## Connecting cable (female connector-open) M12, 5-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

• Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Shielding	Connecting cable	Model name	Part no.
				2 m, 5-wire	DOL-1205-G02MC	6025906
			Unshielded	5 m, 5-wire	DOL-1205-G05MC	6025907
	Female connector,	Cable, open conduc-		10 m, 5-wire	DOL-1205-G10MC	6025908
	M12, 5-pin, straight	tor heads	Shielded	5 m, 5-wire	DOL-1205-G05MAC	6036384
				10 m, 5-wire	DOL-1205-G10MAC	6036385
W				20 m, 5-wire	DOL-1205-G20MAC	6036386
			Unshielded	2 m, 5-wire	DOL-1205-W02MC	6025909
	Female connector, M12, 5-pin, angled	Cable, open conduc- tor heads		5 m, 5-wire	DOL-1205-W05MC	6025910
	witz, o-piii, aligicu			10 m, 5-wire	DOL-1205-W10MC	6025911

## Connecting cable (female connector-open) M12, 5-pin, PVC

Cable material: PVCConnector material: TPUEnclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			2 m, 5-wire	DOL-1205-G02M	6008899
	Female connector, M12,	Cable, open conductor	5 m, 5-wire	DOL-1205-G05M	6009868
5-pin, straight	5-pin, straight	heads	10 m, 5-wire	DOL-1205-G10M	6010544
			15 m, 5-wire	DOL-1205-G15M	6029215
			2 m, 5-wire	DOL-1205-W02M	6008900
	Female connector, M12, 5-pin, angled	Cable, open conductor heads	5 m, 5-wire	DOL-1205-W05M	6009869
10	5-pini, angica		10 m, 5-wire	DOL-1205-W10M	6010542

## Connecting cable (female connector-open) M12, 5-pin, PVC, hygienic systems

• Cable material: PVC

• Connector material: PVC

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
	Female connector, M12, 5-pin, straight		2 m, 5-wire	DOL-1205-G02MN	6028140
		Cable, open conductor	5 m, 5-wire	DOL-1205-G05MN	6028141
		heads	10 m, 5-wire	DOL-1205-G10MN	6028142
			25 m, 5-wire	DOL-1205-G25MN	6028143

## Connecting cable (male connector-open) M12, 4-pin, PUR, halogen-free

- Cable material: PUR, halogen-free
- Connector material: TPU
- Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			0.29 m, 4-wire	STL-1204-G0M3C	6011311
			2 m, 4-wire	STL-1204-G02MC	6028077
	Male connector, M12, 4-pin, straight	Cable, open conductor heads	5 m, 4-wire	STL-1204-G05MC	6048170
	Will, I pin, oddigite		10 m, 4-wire	STL-1204-G10MC	6041750
			15 m, 4-wire	STL-1204-G15MC	6048171
	Male connector,	Cable, open conductor	5 m, 4-wire	STL-1204-W05MC	6037472
M12, 4-pin, angled	heads	15 m, 4-wire	STL-1204-W15MC	6037473	

## Connecting cable (male connector-open) M12, 5-pin

- Cable material: PUR, halogen-free
- Connector material: TPU
- Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
	Male connector,	Cable, open conductor	1 m, 5-wire	STL-1205-G01MC	6037741
1			2 m, 5-wire	STL-1205-G02MC	6051951
Illustration may	M12, 5-pin, straight	heads	5 m, 5-wire	STL-1205-G05MC	6051952
differ			10 m, 5-wire	STL-1205-G10MC	6051953

## Female connector (ready to assemble) M8, 3-pin

- Connector material: PBT
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Model name	Part no.
	Female connector, M8, 3-pin, straight	Screw-type terminals	DOS-0803-G	7902077
O. C.	Female connector, M8, 3-pin, angled	Pin penetration	DOS-0803-W	7902078

## Female connector (ready to assemble) M8, 4-pin

- Connector material: PBT
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Model name	Part no.
	Female connector, M8, 4-pin, straight	Screw-type terminals	DOS-0804-G	6009974
We constitute of the second	Female connector, M8, 4-pin, angled	Pin penetration	DOS-0804-W	6009975

## Female connector (ready to assemble) M12, 4-pin

- Connector material: PBT
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Locking nut material	Model name	Part no.
	Female connector, M12,	Screw-type terminals	CuZn	DOS-1204-G	6007302
<b>1</b>	4-pin, straight	зыем-цуре ценнинаю	Stainless steel	DOS-1204-GN	6028357
	Female connector, M12, 4-pin, angled		CuZn	DOS-1204-W	6007303
		Screw-type terminals	Stainless steel	DOS1204-WN	6028358

## Female connector (ready to assemble) M12, 5-pin

- Connector material: PBT
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Model name	Part no.
	Female connector, M12, 5-pin, straight	Screw-type terminals	DOS-1205-G	6009719
	Female connector, M12, 5-pin, angled	Screw-type terminals	DOS-1205-W	6009720

# Male connector (ready to assemble) M8, 3-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 3-pin, straight	Screw-type terminals	PBT	IP 67	STE-0803-G	6037322

## Male connector (ready to assemble) M8, 4-pin

Figure	Connection type head A	Connection type head B	Connector material	Enclosure rating	Model name	Part no.
	Male connector, M8, 4-pin, straight	Screw-type terminals	PBT	IP 67	STE-0804-G	6037323

## Male connector (ready to assemble) M12, 4-pin

• Connector material: PBT

• Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Locking nut material	Model name	Part no.
M/S	Male connector, M12, 4-pin,	Sarau tyna tarminala	CuZn	STE-1204-G	6009932
	straight	Screw-type terminals	Stainless steel	STE-1204-GN	6028359
	Male connector, M12, 4-pin, angled	Screw-type terminals	CuZn	STE-1204-W	6022084

## Male connector (ready to assemble) M12, 5-pin

• Connector material: PBT

• Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Model name	Part no.
	Male connector, M12, 5-pin, straight	Screw-type terminals	STE-1205-G	6022083
	Male connector, M12, 5-pin, angled	Screw-type terminals	STE-1205-W	6022082

## Connection cable (male connector-female connector) M8, 3-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

• Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
		Male connector, M12, 3-pin, straight	0.6 m, 3-wire	DSL-8203-B0M6C	6025916
	Female connector, M8, 3-pin, angled		2 m, 3-wire	DSL-8203-B02MC	6025917
			5 m, 3-wire	DSL-8203-B05MC	6039185
E. 80	Female connector, M8, 3-pin, straight	Male connector, M12, 3-pin, straight	0.6 m, 3-wire	DSL-8203-G0M6C	6025914
			2 m, 3-wire	DSL-8203-G02MC	6025915
			5 m, 3-wire	DSL-8203-G05MC	6030608

## Connection cable (male connector-female connector) M8, 3-pin, PVC

- Cable material: PVC
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			0.6 m	DSL-8203-G0M6	6022570
Illustration may differ	Female connector, M8, 3-pin, straight	Male connector, M12, 3-pin, straight	2 m	DSL-8203-G02M	6022572

#### Connection cable (male connector-female connector) M8, 4-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

Connector material: TPU

• Enclosure rating: IP 65, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
		Male connector, M8, 4-pin, straight	0.6 m, 4-wire	DSL-0804-G0M6C	6039089
			2 m, 4-wire	DSL-0804-G02MC	6036335
06	Female connector, M8,		5 m, 4-wire	DSL-0804-G05MC	6039090
	4-pin, straight	Male connector, M12, 4-pin, straight	0.6 m, 4-wire	DSL-8204-G0M6C	6025918
			2 m, 4-wire	DSL-8204-G02MC	6025919
			5 m, 4-wire	DSL-8204-G05MC	6039181
Illustration may		Male connector, M12, 4-pin, straight	0.6 m, 4-wire	DSL-8204-B0M6C	6025920
Illustration may differ	Female connector, M8, 4-pin, angled		2 m, 4-wire	DSL-8204-B02MC	6025921
	+-μπ, angleu		5 m, 4-wire	DSL-8204-B05MC	6039182

#### Connection cable (male connector-female connector) M8, 4-pin, PVC

- Cable material: PVC
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			0.6 m, 4-wire	DSL-0804-G0M6	6034664
	Female connector, M8,	Male connector, M8, 4-pin,	1.5 m, 4-wire	DSL-0804-G1M5	6042050
	4-pin, straight	straight	2.5 m, 4-wire	DSL-0804-G2M5	6051282
			3 m, 4-wire	DSL-0804-G03M	6051283
60			0.6 m, 4-wire	DSL-8204-G0M6	6022571
Illustration may			2 m, 4-wire	DSL-8204-G02M	6022573
differ	Male connector, M8, 4-pin, straight	Male connector, M12, 4-pin, straight	5 m, 4-wire	DSL-8204-G05M	6034403
	otrangine	Strugit	10 m, 4-wire	DSL-8204-G10M	6034404
			20 m, 4-wire	DSL-8204-G20M	6034405

## Connection cable (male connector-female connector), M12, 3-pin, PUR, halogen-free

- Cable material: PUR, halogen-free
- Enclosure rating: IP 67

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			0.6 m	DSL-2803-G0M6C	6039183
No. No.	Female connector, M12,	Male connector, M8, 3-pin,	2 m	DSL-2803-G02MC	6039184
Illustration may differ	3-pin, straight	straight	5 m	DSL-2803-G05MC	6028664

## Connection cable (male connector-female connector) M12, 4-pin, PUR, halogen-free

• Cable material: PUR, halogen-free

• Connector material: TPU

• Enclosure rating: IP 67, IP 68, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
	Female connector,	Male connector,	0.6 m, 4-wire	DSL-1203-B0M6C	6025924
	M12, 4-pin, angled	M12, 3-pin, straight	2 m, 4-wire	DSL-1203-B02MC	6025925
			0.6 m, 4-wire	DSL-2804-G0M6C	6037595
		Male connector, M8, 3-pin, straight	2 m, 4-wire	DSL-2804-G02MC	6025924 6025925 6037595 6039180 6039091 6025922 6025923 6025926 6033244 6025927
	Female connector,	me, e pm, edalight	5 m, 4-wire	DSL-2804-G05MC	6039091
No. No.		Male connector, M12, 3-pin, straight	0.6 m, 4-wire	DSL-1203-G0M6C	6025922
W			2 m, 4-wire	DSL-1203-G02MC	6025923
Illustration may differ	M12, 4-pin, straight		0.6 m, 4-wire	DSL-1204-G0M6C	6025926
			1 m, 4-wire	DSL-1204-G01MC	6033244
		Male connector, M12, 4-pin, straight	2 m, 4-wire	DSL-1204-G02MC	6025927
		WIIZ, 4 pill, Straight	5 m, 4-wire	DSL-1204-G05MC	6033245
			10 m, 4-wire	DSL-1204-G10MC	6033698

## Connection cable (male connector-female connector) M12, 4-pin, PVC

• Cable material: PVC

• Connector material: TPU

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
No.	Female connector, M12, 4-pin, straight	Male connector, M12, 4-pin, straight	5 m, 4-wire	DSL-1204-G05M	6022569

## Connection cable (male connector-female connector) M12, 4-pin, PVC, hygienic systems

Cable material: PVC

• Connector material: PVC

• Enclosure rating: IP 67, IP 69K

Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
	Female connector, M12, 4-pin, angled	Male connector, M12, 4-pin, straight	0.6 m, 4-wire	DSL-1204-B0M6N	6028197
			2 m, 4-wire	DSL-1204-B02MN	6028198
<b>% &gt;</b>			5 m, 4-wire	DSL-1204-B05MN	6028199
	Female connector, M12, 4-pin, straight	Male connector, M12, 4-pin, straight	0.6 m, 4-wire	DSL-1204-G0M6N	6028194
100 No.			2 m, 4-wire	DSL-1204-G02MN	6028195
			5 m, 4-wire	DSL-1204-G05MN	6028196

## Connection cable (male connector-female connector) M12, 5-pin, PUR, halogen-free

• Cable material: PUR, halogen-free


• Connector material: TPU

• Enclosure rating: IP 67, IP 68, IP 69K


Figure	Connection type head A	Connection type head B	Connecting cable	Model name	Part no.
			0.6 m, 5-wire	DSL-1205-B0M6C	6029283
			1 m, 5-wire	DSL-1205-B01MC	6029284
		Female connector, M12, 5-pin, angled	1.5 m, 5-wire	DSL-1205-B1M5C	6029286
		WIZ, 5 pm, anglea	2 m, 5-wire	DSL-1205-B02MC	6029287
11			5 m, 5-wire	DSL-1205-B05MC	6029288
	Male connector,		0.6 m, 5-wire	DSL-1205-G0M6C	6025930
	M12, 5-pin, straight		1 m, 5-wire	DSL-1205-G01MC	6029280
Illustration may differ			2 m, 5-wire	DSL-1205-G02MC	6025931
		Female connector, M12, 5-pin, straight	5 m, 5-wire	DSL-1205-G05MC	6029282
		<u></u> , o p, oda.ge	10 m, 5-wire	DSL-1205-G10MC	6038954
			15 m, 5-wire	DSL-1205-G15MC	6038956
			20 m, 5-wire	DSL-1205-G20MC	6038957

## Dimensional drawings Plug connectors and cables


#### DOL-0803-GxxMC




## DOL-0803-GxxMN, DOL-0804-GxxMN




#### DOL-0803-WxxMCW10MC




## DOL-0804-GxxM




#### DOL-0804-WxxM




#### DOL-0803-GxxM




## DOL-0803-WxxM




## DOL-0803-WxxMN, DOL-0804-WxxMN




#### DOL-0804-GxxMC




## DOL-0804-WxxMC




#### DOL-1203-GxxMC




# DOL-1204-GxxM, DOL-1204-GxxMC, DOL-1204-GxxMA, DOL-1204-GxxMN




#### DOL-1204-L02MN




## DOL-1203-WxxMC



## DOL-1204-L02M




## DOL-1204-L05MC




38.3


#### DOL-1204-WxxM




#### DOL-1204-WxxMC




#### DOL-1204-WxxMN




#### DOL-1204-W05MA




## DOL-1205-GxxM




DOL-1205-GxxMC




#### DOL-1205-GxxMN




#### DOL-1205-GxxMAC




#### DOL-1205-WxxM




#### DOL-1205-WxxMC




#### DOS-0803-G




#### DOS-0803-W




#### DOS-0804-G




#### DOS-0804-W




#### DOS-1204-G




#### DOS-1204-W




#### DOS-1205-G




## DSL-0804-G03M DSL-0804-G0M6 DSL-0804-G2M5




#### DSL-1204-B0M6N




## DSL-1204-GxxMN




#### DOS-1205-W




## DSL-0804-G02MC DSL-0804-G05MC DSL-0804-G0M6C




#### DSL-1204-GxxMC




#### DSL-1204-GxxM




#### DSL-1205-GxxMC




#### DSL-2803-GxxMC, DSL-2804-GxxMC




## DSL-8203-GxxMC




#### DSL-8204-BxxMC




#### DSL-1208-G01MAC




#### DSL-8203-BxxMC




## DSL-8203-GxxM




#### DSL-8204-GxxM




#### DSL-8204-GxxMC




#### STE-0803-G




#### STE-0804-G




#### STE-1204-G




#### STE-1204-W




#### STE-1205-G




## STE-1205-W



#### STL-1204-GxxMC



#### STL-1204-WxxMC



# **Other accessories**

# Power supplies

Figure	Output type	Description	Model name	Part no.
	NPN	Cable with receptacle, M12, 4-pin, 0.2 m, IP 65	ACIM1-N2221	1057381
	INPIN	Cable with receptacle, M8, 4-pin, 0.2 m, IP 65	ACIM1-N3221	1057380
	PNP	Cable with receptacle, M12, 4-pin, 0.2 m, IP 65	ACIM1-P2221	1057184
		Cable with receptacle, M8, 4-pin, 0.2 m, IP 65	ACIM1-P3221	1057183

# Switching amplifiers

Figure	Supply voltage	Output function	Approvals	Model name	Part no.
	AC/DC 24 V 230 V, 1.3 W	2 channels with invertible SPDT relay	II (1) G [Ex ia] IIC II (1) D [Ex iaD] II (3) G Ex nAC [ia] IIC T4 X	EN2-2EX-1	6041096
	DC 19.2 V 30 V, 1 W	2 channels with invertible NO relay	II (1) GD [Ex ia] IIC, IIB II (3) G Ex nAC II T4 X	EN2-2EX-3	6041095

## **IO-Link** modules


Figure	Description	Model name	Part no.
	IO-Link V1.1 Class A Port, USB2.0 port, optional external power supply 24V / 1A	SiLink2 Master	1061790
	IO-Link master, IO-Link field module, DC 18 V 30 V, IP 65, IP 67	IOLSHPB-P3104	6032904

Accessories

# **Dimensional drawings other accessories**

## Power supplies


## ACIM1




- ① AC input power, switch output
- $\ensuremath{\mathfrak{D}}$  Status indicator LED green: DC output power present
- ③ Orange LED indicator : DC switch input present
- $\ensuremath{\textcircled{4}}$  DC output power, switch input
- ⑤ Magnet

## Switching amplifiers

#### EN2-2EX-1




#### EN2-2EX-3





#### **IO-Link** modules

## SiLink2 Master



## IOLSHPB-P3104





- ① Bus IN
- ② Bus OUT
- 3 Power supply IN
- 4 Power supply OUT
- ⑤ Port 1...4
- 6 Bus address rotary switch

Model name	Part no.	Page
ACIM1-N2221	1057381	L-921
ACIM1-N3221	1057380	L-921
ACIM1-P2221	1057184	L-921
ACIM1-P3221	1057183	L-921
BEF-DKH-W12	2013947	L-867
BEF-G10DC01	2071258	L-864
BEF-G10UC01	2071259	L-864
BEF-G10WSG	2071960	L-866
BEF-GH-MINIO1	2023160	L-867
BEF-GPM3-W9	4066039	L-865
BEF-HA-M18R	5313513	L-867
BEF-HDSBR	4074403	L-868
BEF-HDSF	4072880	L-868
BEF-HDSTRGF	2067779	L-868
BEF-HDSTRG	2067780	L-868
BEF-HDSTRK1WF	2071931	L-868
BEF-HDSTRL1GF	2072047	L-868
BEF-HDSTRWF	2067777	L-868
BEF-HDSTRW	2067778	L-868
BEF-KH-M18	2051481	L-867
BEF-KH-W12	2013285	L-867
BEF-KHF-M18	2051482	L-867
BEF-KHS-KH3N	5322627	L-868
BEF-KHS-KH3	5322626	L-868
BEF-KHS-N02N	2051618	L-868
BEF-KHS-N02	2051608	L-868
BEF-KHS-N03	2051609	L-868
BEF-KHS-N04N	2051619	L-868
BEF-KHS-N04	2051610	L-868
BEF-KHS-N05N	2051620	L-868
BEF-KHS-N05N	2051621	L-868
BEF-KHS-N05	2051611	L-868
BEF-KHS-N06N	2051622	L-868
BEF-KHS-N06	2051612	L-868
BEF-KHS-N07N	2051623	L-868
BEF-KHS-N07	2051613	L-868
BEF-KHS-N08N	2051616	L-869
BEF-KHS-N08	2051607	L-869
BEF-KHSQ12R01	2071260	L-869
BEF-KHSQ12ZR01	2071262	L-869
BEF-KP-W24	2015071	L-866
BEF-MR18G-NA	4065853	L-867
BEF-MS12G-A	4056054	L-869
BEF-MS12G-B	4056055	L-869
BEF-MS12G-NA	4058914	L-869
BEF-MS12G-NB	4058915	L-869
BEF-MS12L-A	4056052	L-869
BEF-MS12L-B	4056053	L-869
BEF-MS12L-NA	4058912	L-869
BEF-MS12L-NB	4058913	L-869
BEF-MS12U	4065437	L-869
BEF-MS12Z-A	4056056	L-869
BEF-MS12Z-B	4056057	L-869
BEF-MS12Z-C	4064563	L-869
BEF-MS12Z-NA	4058916	L-869
BEF-MS12Z-NB	4058917	L-869
BEF-PL80AWSG	2071961	L-866
BEF-RMC-D12	5321878	L-869

BEF-SG-W12-3 BEF-SG-W14 BEF-SG-W14 DEF-SG-W14 DEF-SG-W14 DEF-SG-W27 DEF-W2132 DEF-W100-A DEF-W2132 DEF-W100-B DEF-W250 DEF-W350 DEF-W3	Model name	Destau	D. di
BEF-SG-W14 2058124 L866 BEF-SG-W27 2039601 L866 BEF-SW-W4S 2051497 L866 BEF-SW-W4S 2051497 L866 BEF-W100-A 5311520 L864 BEF-W100-A 5311520 L864 BEF-W100-B 5311521 L864 BEF-W160 5305197 L864 BEF-W250 5305850 L864 BEF-W250 5305850 L864 BEF-W2S-A 4034748 L864 BEF-W2S-B 4034749 L864 BEF-W2S-B 4034749 L864 BEF-W2S-B 2051630 L864 BEF-W4-A 2051628 L864 BEF-W4-A 2051628 L864 BEF-W4-M18N 5320948 L865 BEF-W6-M18N 5321870 L864 BEF-W6-M18 5321870 L864 BEF-W6-W12 2013942 L864 BEF-W6-W12 2013942 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 5015786 L865 BEF-WK-W16 S325812 L865 BEF-WLL170 5306574 L865 BEF-WLL180 5325812 L865 BEF-WN-G6 2062909 L865 BEF-WN-M18 5329947 L865 BEF-WN-M18 5308446 L865 BEF-WN-M18 530846 L903 BEF-WR-M18 530846 L903 BEF-WR-M18 530846 L90		Part no.	Page
BEF-SG-W27  2039601  BEF-SW-W4S  2051497  BEF-TO-GR18S  BEF-W100-A  BEF-W100-A  BEF-W100-B  BEF-W100-B  BEF-W160  BEF-W250  BEF-W350  BEF-W350  BEF-W350  BEF-W350  BEF-W4-A  BEF-W25C  BEF-W4-A  BEF-W350  BEF-W4-A  BEF-W350  BEF-W4-B  BEF-W350  BEF-W4-B  BEF-W6-M18  BEF-W6-M18  BEF-W6-M18  BEF-W6-W12  BEF-W6-W12  BEF-W6-W24  BEF-W6-W24  BEF-W6-W24  BEF-W7-W24  BEF-W7-W24  BEF-W7-W24  BEF-W7-W12  BEF-W7-W10  BEF-W7-W10  BEF-W1170  BOSOF74  BEF-W1170  BEF-W1180  BEF-W1180  BEF-W1180  BEF-WN-M18-ST02  BEF-WR-M18-M18-M18-M18-M18-M1			
BEF-W-W4S BEF-TO-GR18S BEF-W100-A BEF-W100-B BEF-W100-B BEF-W160 S3011520 L864 BEF-W160 S305197 L864 BEF-W250 S305850 L864 BEF-W250 S305850 L864 BEF-W280 S313885 L864 BEF-W28-A BEF-W28-A BEF-W28-B BEF-W28-B BEF-W28-B BEF-W3-B BEF-W4-A D51628 BEF-W3-B BEF-W4-A D51628 BEF-W3-B BEF-W4-B BEF-W3-B BEF-W3			
BEF-TO-GR18S  BEF-W100-A  BEF-W100-B  BEF-W100-B  BEF-W160  BEF-W160  BEF-W250  BEF-W25-A  BEF-W25-B  BEF-W25-C  BEF-W25-C  BEF-W3-A  BEF-W3-C  BEF-W3-A  BEF-W3-B  BE			
BEF-W100-A  BEF-W100-B  BEF-W160  BEF-W250  BEF-W250  BEF-W280  BEF-W280  BEF-W280  BEF-W28-A  BEF-W28-B  BEF-W28-B  BEF-W28-B  BEF-W38-B  BEF-W38-C  BEF-W38-B  BEF-W38-C  BEF-W38-B  BEF-W6-M18  BEF-W6-M18  BEF-W6-M18  BEF-W6-M18  BEF-W6-M12  BEF-W6-M12  BEF-W8-W24  BEF-W8-W24  BEF-W8-W24  BEF-W8-W24  BEF-W8-W24  BEF-W8-W24  BEF-W8-W12  BEF-W8-W24  BEF-W8-W38-B  BEF-W8-W10  BEF-W8-W11  BEF-W			
BEF-W100-B BEF-W160 BEF-W250 BEF-W250 BEF-W250 BEF-W280 BEF-W280 BEF-W280 BEF-W28-A BEF-W28-A BEF-W28-B BEF-W28-C BEF-W28-C BEF-W4-A BEF-W28-C BEF-W4-B BEF-W4-B BEF-W4-B BEF-W3-C BEF-W3-C BEF-W4-B BEF-W3-C BEF-W4-B BEF-W3-C BEF-W4-C BEF-			
BEF-W160 5305197 L864 BEF-W250 5305850 L864 BEF-W250 5305850 L864 BEF-W280 5313885 L864 BEF-W2S-A 4034748 L864 BEF-W2S-B 4034749 L864 BEF-W2S-B 4034749 L866 BEF-W2S-C 2033270 L866 BEF-W3-C 2033270 L866 BEF-W4-A 2051628 L864 BEF-W4-B 2051630 L864 BEF-W4-B 2051630 L864 BEF-W6-M18N 5320948 L865 BEF-W6-M18 5321870 L864 BEF-W6-M12 2013942 L864 BEF-W6-W12 2013942 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 4026324 L864 BEF-WK-W24 4027532 L864 BEF-WK-W16 5306574 L865 BEF-WLL170 5306574 L865 BEF-WLL170 5306574 L865 BEF-WN-M18-ST02 5312973 L867 BEF-WN-M18-ST02 5312973 L867 BEF-WN-M18 5308446 L865 BEF-WN-W14 4039533 L867 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 L865 BEF-WN-W23 2015248 L865 BEF-WN-W23 2015248 L865 BEF-WN-W24 2015248 L865 BEF-WN-W27 2009122 L865 BEF-WN-W27 2009122 L865 BEF-WN-W27 2009122 L865 BEF-WN-W16 5313011 L867 BEF-WN-W27 2009122 L865 BEF-WN-W17 2009122 L865 BEF-WN-W17 2009122 L865 BEF-WN-W27 2009122 L865 BEF-WN-W17 2009122 L865 BEF-WN-W18 2017417 L865 BEF-WN-W27 2009122 L8666 BL-12-SKN 4031815 L866 BL-12-SKN 4031815 L			
BEF-W250			
BEF-W280 5313885 L864 BEF-W2S-A 4034748 L864 BEF-W2S-B 4034749 L864 BEF-W2S-C 2033270 L866 BEF-W3S-C 2033270 L866 BEF-W4-A 2051628 L864 BEF-W4-B 2051630 L864 BEF-W4-B 2051630 L864 BEF-WG-M18N 5320948 L865 BEF-WG-M18N 5320948 L865 BEF-WG-M12 2013942 L864 BEF-WG-W12 2013942 L864 BEF-WG-W12 2013942 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 3016574 L865 BEF-WLL170 5306574 L865 BEF-WLL180 5325812 L865 BEF-WLL180 5325812 L865 BEF-WN-M18 5320947 L865 BEF-WN-M18 5320947 L865 BEF-WN-M18N 5320947 L865 BEF-WN-M15-1 4039533 L867 BEF-WN-M15-1 4039533 L867 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-2 4053358 L867 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 L865 BEF-WN-W18 2009317 L865 BEF-WN-W18 2009317 L865 BEF-WN-W18 2019085 L865 BEF-WN-W23 2019085 L865 BEF-WN-W24 2015248 L865 BEF-WN-W25 2022855 L865 BEF-WN-W27 2009122 L866 BEF-WN-W27 2009122 L866 BEF-WN-W77 2009122 L866 BEF-WN-W7 2009122			
BEF-W2S-A BEF-W2S-B BEF-W2S-C BEF-W4-A BEF-W2S-C BEF-W4-B BEF-W4-B BEF-W4-B BEF-W4-B BEF-W4-B BEF-W6-M18N BEF-W6-M18N BEF-W6-M18 BEF-W6-M18 BEF-W6-M12 BEF-W6-W24 BEF-W6-W24 BEF-W6-W24 BEF-W6-W12 BEF-W6-W17 BEF-W6-W17 BEF-W6-W17 BEF-W6-W18 BEF-W6-W19 BEF-W7-W19 BEF-W7-W19 BEF-W7-W19 BEF-W7-W19 BEF-W7-W19 BEF-W7-W19 BEF-W7-W19 BEF-W8-W19 BEF			
BEF-W2S-B			
BEF-W2S-C BEF-W4-A BEF-W4-B BEF-W4-B BEF-W4-B BEF-WG-M18N BEF-WG-M18 BEF-WG-M18 BEF-WG-W12 BEF-WG-W12 BEF-WG-W12 BEF-WG-W24 BEF-WG-W24 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W14 BEF-WK-W15 BEF-WK-W16 BEF-WK-W17 BEF-WK-W17 BEF-WK-W17 BEF-WK-W18 BEF-WK-W18 BEF-WK-W19 BEF-WK-W			
BEF-W4-A  BEF-W4-B  BEF-WG-M18N  BEF-WG-M18N  BEF-WG-M18  BEF-WG-M18  BEF-WG-W12  2013942  L864  BEF-WG-W12  2013942  L864  BEF-WG-W12  2013942  L864  BEF-WG-W12  2013938  L864  BEF-WG-W12  BEF-WG-W12  2012938  L864  BEF-WK-W12  2012938  L864  BEF-WK-W12  2012938  L864  BEF-WK-W12  2012938  L865  BEF-WK-W12  BEF-WK-W14  BEF-WK-W24  4027532  L864  BEF-WK-W17  5306574  L865  BEF-WLL170  5306574  L865  BEF-WLL180  5325812  L865  BEF-WN-G6  2062909  L865  BEF-WN-M18-ST02  5312973  L867  BEF-WN-M18N  532947  L865  BEF-WN-M18N  5308446  L865  BEF-WN-M18-1  4039533  L867  BEF-WN-M15-2V  4053358  L867  BEF-WN-BEF-WN-BW  2023251  L865  BEF-WN-BEF-WN-BW  2033251  L865  BEF-WN-W100-S01  4073866  L865  BEF-WN-W14  2019084  L865  BEF-WN-W18  2009317  L865  BEF-WN-W23  2019085  L865  BEF-WN-W24  2015248  L865  BEF-WN-W27  2009122  L865  BEF-WN-W27  2009122  L865  BEF-WN-W27  2009122  L865  BEF-WN-W27  2009122  L865  BEF-WN-W27  2022855  L866  BEF-WN-W7  BURCH-W141  BF-EB01-W190  5313011  L867  BL-10-10  5314182  L866  BL-12-SKN  4031815  L866  BL-12-SKN  4033253  L866  C110A  5304549  L892  C42-1  5313506  L892  C42-1  5313506  L892  C0L-0803-G02MC  6025889  L903  DOL-0803-G02MC  6025889  L903  DOL-0803-G05MN  6033666  L903			
BEF-W4-B BEF-WG-M18N BEF-WG-M18 BEF-WG-M18 BEF-WG-M18 BEF-WG-W12 BEF-WG-W24 BEF-WG-W24 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W14 BEF-WK-W15 BEF-WK-W16 BEF-WK-W17 BEF-WK-W17 BEF-WK-W17 BEF-WK-W18 BEF-WK-WH18 BEF-WK-WBW BEF-WK-WBW BEF-WK-WBW BEF-WK-WBW BEF-WK-W100-SO1 BEF-WK-W14 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W18 BEF-WK-W19 BEF-WK-W18 BEF-WK-W19 BEF-WK-W18 BEF-WK-W18 BEF-WK-W19 BEF			
BEF-WG-M18N			
BEF-WG-M18 BEF-WG-W12 BEF-WG-W24 BEF-WG-W24 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W12 BEF-WK-W14 BEF-WK-W17 BEF-WK-W17 BEF-WL170 BEF-WL180 BEF-WN-G6 BEF-WN-G6 BEF-WN-M18-ST02 BEF-WN-M18 BEF-WN-M18 BEF-WN-M18 BEF-WN-M18 BEF-WN-M18 BEF-WN-M15-1 BEF-WN-M15-1 BEF-WN-M94 BEF-WN-W100-S01 BEF-WN-W14 BEF-WN-W10 BEF-WN-W18 BEF-WN-W100-S01 BEF-WN-W18 BEF-WN-W10 BEF-WN-W16 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W23 BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W17 BEF-WN-W17 BEF-WN-W17 BEF-WN-W19-2 BEF-WN-W19-2 BEF-WN-W10 BEF			
BEF-WG-W12 2013942 L864 BEF-WG-W24 4026324 L864 BEF-WK-W12 2012938 L864 BEF-WK-W12 2012938 L864 BEF-WK-W24 4027532 L864 BEF-WK-WTR 2051786 L865 BEF-WLL170 5306574 L865 BEF-WLL180 5325812 L865 BEF-WN-G6 2062909 L865 BEF-WN-M18-ST02 5312973 L867 BEF-WN-M18 5320947 L865 BEF-WN-M18 5320947 L865 BEF-WN-M18 5308446 L865 BEF-WN-M15-1 4039533 L867 BEF-WN-M15-1 4039533 L867 BEF-WN-MH15-2V 4053358 L867 BEF-WN-BEF X 2064574 L865 BEF-WN-W10-S01 4073866 L865 BEF-WN-W14 2019084 L865 BEF-WN-W18 2009317 L865 BEF-WN-W18 2009317 L865 BEF-WN-W23 2019085 L865 BEF-WN-W24 2015248 L865 BEF-WN-W27 2009122 L865 BEF-WN-W27 2009122 L865 BEF-WN-W17 2017417 L865 BEF-WN-W18 2017417 L865 BEF-WN-W19 5313011 L867 BL-10-10 5314182 L866 BL-12-SKN 4031815 L866 BL-9-2 4033253 L866 BL-9-2 4033253 L866 C110A 5304549 L892 C42-1 5313506 L892 C42-1 5313506 L892 C42-2 5324281 L892 C64A 5325185 L892 DOL-0803-G02MC 6025888 L903 DOL-0803-G02MC 6025889 L903 DOL-0803-G05M 6033665 L903 DOL-0803-G05M 602009 L904 DOL-0803-G05MC 6025890 L903 DOL-0803-G10MC 6025890 L903 DOL-0803-G10MC 6025890 L903			
BEF-WG-W24			
BEF-WK-W12 2012938 L864 BEF-WK-W24 4027532 L864 BEF-WK-W24 4027532 L864 BEF-WK-WTR 2051786 L865 BEF-WLL170 5306574 L865 BEF-WLL180 5325812 L865 BEF-WN-G6 2062909 L865 BEF-WN-M18-ST02 5312973 L867 BEF-WN-M18N 5320947 L865 BEF-WN-M18N 5320947 L865 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-2V 4053358 L867 BEF-WN-BEF-WN-MH15-2V 4053358 L865 BEF-WN-W100-S01 4073866 L865 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 L865 BEF-WN-W23 2019085 L865 BEF-WN-W23 2019085 L865 BEF-WN-W24 2015248 L865 BEF-WN-W27 2009122 L865 BEF-WN-W27 20175248 L865 BEF-WN-W17 2017417 L865 BEF-WN-W18 2017417 L865 BEF-B01-W190 5313011 L867 BL-100-10 5314182 L866 BL-12-SKN 4031815 L866 BL-9-2 4033253 L892 C42-1 5313506 L892 C42-1 5313506 L892 C42-2 5324281 L892 C64A 5325185 L892 D0L-0803-G01MC 6036455 L903 D0L-0803-G02MN 6033664 L903 D0L-0803-G02MN 6033665 L903 D0L-0803-G05M 6022009 L904 D0L-0803-G05MN 6033665 L903 D0L-0803-G05MN 6033666 L903			
BEF-WK-W24 BEF-WK-W24 BEF-WK-W7R 2051786 BEF-WLL170 5306574 L865 BEF-WLL180 5325812 L865 BEF-WLL180 5325812 L865 BEF-WN-G6 2062909 L865 BEF-WN-M18-ST02 5312973 L867 BEF-WN-M18N 5320947 L865 BEF-WN-M18N 5320947 L865 BEF-WN-M18N 5320947 L865 BEF-WN-M18N 5320947 L865 BEF-WN-M18 BEF-WN-M181 5308446 L865 BEF-WN-M185-1 4039533 L867 BEF-WN-WH15-2V 4053358 L867 BEF-WN-WBW 2023251 L865 BEF-WN-WFFX 2064574 L865 BEF-WN-W100-S01 4073866 L865 BEF-WN-W14 2019084 L865 BEF-WN-W14 2019084 BEF-WN-W23 2019085 L865 BEF-WN-W23 2019085 L865 BEF-WN-W27 2009122 L865 BEF-WN-W27 2009122 L865 BEF-WN-W7R PEF-WN-W7R 2017417 L865 BEF-WN-W7R PEF-B01-W190 5313011 L867 BL-100-10 5314182 L866 BL-19-2 4033253 L866 BL-10-2 5325185 L892 C42-1 5313506 L892 C42-1 5313506 L892 C42-2 5324281 L892 C64A 5325185 L892 C0-0803-G02MC 6025888 L903 D0L-0803-G02MC 6025889 L903 D0L-0803-G05MC 6025890 L903 D0L-0803-G10MC 603666 L903			
BEF-WK-WTR BEF-WLL170 BEF-WLL180 BEF-WLL180 BEF-WLL180 BEF-WN-G6 BEF-WN-G6 BEF-WN-M18-ST02 BEF-WN-M18N BEF-WN-M18N BEF-WN-M18N BEF-WN-M18N BEF-WN-M18N BEF-WN-M18N BEF-WN-M15-1 BEF-WN-MH15-1 BEF-WN-MH15-2V BEF-WN-MH15-2V BEF-WN-WBW BEF-WN-W100-S01 BEF-WN-W14 BEF-WN-W14 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W19 BEF-WN-W27 BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W9-2 BEF-WN-W190 BEF-WN-W19	22		
BEF-WLL170			
BEF-WLL180			
BEF-WN-G6 BEF-WN-M18-ST02 BEF-WN-M18-ST02 BEF-WN-M18N  5312973 L-867 BEF-WN-M18N  5320947 L-865 BEF-WN-M18N  5320947 L-865 BEF-WN-M18N  5308446 L-865 BEF-WN-M15-1 4039533 L-867 BEF-WN-M15-2V 4053358 L-867 BEF-WN-M15-2V 4053358 L-867 BEF-WN-M15-2V 4053358 L-865 BEF-WN-BEF-WN-GBW 2023251 L-865 BEF-WN-REFX 2064574 L-865 BEF-WN-W100-S01 4073866 L-865 BEF-WN-W14 2019084 L-865 BEF-WN-W14 2019084 L-865 BEF-WN-W23 2019085 L-865 BEF-WN-W23 2019085 L-865 BEF-WN-W24 2015248 L-865 BEF-WN-W27 2009122 L-865 BEF-WN-W27 2009122 L-865 BEF-WN-W9-2 2022855 L-865 BEF-WN-W1R 2017417 L-865 BF-EB01-W190 5313011 L-867 BL-100-10 5314182 L-866 BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025890 L-903 D0L-0803-G10MC 603666 L-903 D0L-0803-G10MC 603666 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903			
BEF-WN-M18-ST02 BEF-WN-M18N  BEF-WN-M18N  BEF-WN-M18N  BEF-WN-M18  BEF-WN-M15-1  BEF-WN-M15-1  BEF-WN-M15-2V  BEF-WN-M15-2V  BEF-WN-REFX  BEF-WN-REFX  BEF-WN-W100-S01  BEF-WN-W14  BEF-WN-W18  BEF-WN-W18  BEF-WN-W23  BEF-WN-W24  BEF-WN-W24  BEF-WN-W27  BEF-WN-W27  BEF-WN-W17  BEF-WN-W18  BEF-WN-W27  BEF-WN-W10-S01  BEF-WN-W27  BEF-WN-W27  BEF-WN-W27  BEF-WN-W27  BEF-WN-W27  BEF-WN-W3-2  BEF-WN-W3-8  BEF-WN			
BEF-WN-M18N 5320947 L865 BEF-WN-M18 5308446 L865 BEF-WN-M15-1 4039533 L867 BEF-WN-MH15-1 4039533 L867 BEF-WN-MH15-2V 4053358 L867 BEF-WN-OBW 2023251 L865 BEF-WN-REFX 2064574 L865 BEF-WN-W100-S01 4073866 L865 BEF-WN-W14 2019084 L865 BEF-WN-W18 2009317 L865 BEF-WN-W23 2019085 L865 BEF-WN-W24 2015248 L865 BEF-WN-W27 2009122 L865 BEF-WN-W9-2 2022855 L865 BEF-WN-W9-2 2022855 L865 BEF-WN-W190 5313011 L867 BI-100-10 5314182 L866 BL-12-SKN 4031815 L866 BL-9-2 4033253 L866 C110A 5304549 L892 C42-1 5313506 L892 C42-2 5324281 L892 C42-2 5324281 L892 C64A 5325185 L903 D0L-0803-G01MC 6036455 L903 D0L-0803-G02MC 6025888 L903 D0L-0803-G02MC 6025889 L903 D0L-0803-G05MC 6025889 L903 D0L-0803-G05MC 6025889 L903 D0L-0803-G05M 603665 L903 D0L-0803-G05M 6022009 L904 D0L-0803-G10MC 6025890 L903 D0L-0803-G10MN 6033666 L903			
BEF-WN-M18 BEF-WN-MH15-1 BEF-WN-MH15-1 BEF-WN-MH15-2V			
BEF-WN-MH15-1 BEF-WN-MH15-2V BEF-WN-OBW BEF-WN-OBW BEF-WN-REFX BEF-WN-REFX BEF-WN-W100-S01 BEF-WN-W14 BEF-WN-W18 BEF-WN-W23 BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W18 BEF-WN-W18 BEF-WN-W190 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W39-2 BEF-WN-W39-8 BEF-W			
BEF-WN-MH15-2V 4053358 L867 BEF-WN-OBW 2023251 L865 BEF-WN-REFX 2064574 L865 BEF-WN-W100-S01 4073866 L865 BEF-WN-W14 2019084 L865 BEF-WN-W18 2009317 L865 BEF-WN-W23 2019085 L865 BEF-WN-W24 2015248 L865 BEF-WN-W27 2009122 L865 BEF-WN-W9-2 2022855 L865 BEF-WN-W17 2017417 L865 BF-EB01-W190 5313011 L867 BL-100-10 5314182 L866 BL-12-SKN 4031815 L866 BL-9-2 4033253 L866 C110A 5304549 L892 C42-1 5313506 L892 C42-2 5324281 L892 C64A 5325185 L892 C64A 5325185 L892 D0L-0803-G01MC 6036455 L903 D0L-0803-G02MC 6025888 L903 D0L-0803-G05MC 6025889 L903 D0L-0803-G05MC 6025889 L903 D0L-0803-G05MC 6025890 L904 D0L-0803-G10MC 6025890 L903			
BEF-WN-OBW BEF-WN-REFX BEF-WN-REFX BEF-WN-W100-S01 BEF-WN-W14 BEF-WN-W14 BEF-WN-W18 BEF-WN-W23 BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W18 BEF-WN-W100-S01 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W3   BEF-WN-W27 BEF-WN-W3  BEF-WN-W3  BEF-WN-W3  BEF-WN-W3  BEF-WN-W4  BEF-WN-W5  BEF-WN-W6  BEF-WN-W7  BEF-WN-W6  BEF-Wh BEF-W6-BE  BEF-WN-W6  BEF-WN-W6  BEF-WN-W6  BEF-WN-W6  BEF-W0  BEF-W			
BEF-WN-REFX BEF-WN-W100-S01 BEF-WN-W14 BEF-WN-W14 BEF-WN-W18 BEF-WN-W23 BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W9-2 BEF-WN-W18 BEF-WN-W9-2 BEF-WN-W190 BEF-WN-W17 BEF-WN-W18 BEF-WN-W18 BEF-WN-W18 BEF-WN-W27 BEF-WN-W28 BEF-WN-W18 B			
BEF-WN-W100-S01			
BEF-WN-W14 2019084 L-865 BEF-WN-W18 2009317 L-865 BEF-WN-W23 2019085 L-865 BEF-WN-W24 2015248 L-865 BEF-WN-W27 2009122 L-865 BEF-WN-W9-2 2022855 L-865 BEF-WN-WTR 2017417 L-865 BF-EB01-W190 5313011 L-867 BL-100-10 5314182 L-866 BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903			
BEF-WN-W18  BEF-WN-W23  BEF-WN-W24  BEF-WN-W27  BEF-WN-W27  BEF-WN-W9-2  BEF-WN-W9-2  BEF-WN-W18  BEF-WN-W18  BEF-WN-W17  BEF-WN-W18  BEF-WN-W18  BEF-WN-W18  BEF-WN-W190  BI-100-10  BI-100-10  BI-12-SKN  BI-12-SKN  BI-9-2  C110A  C110A  C3304549  L892  C42-1  C42-1  C42-2  5313506  L892  C42-2  C64A  5325185  L892  DOL-0803-G01MC  DOL-0803-G02MC  DOL-0803-G02MC  DOL-0803-G05MC  DOL-0803-G05MC  DOL-0803-G05MC  DOL-0803-G05MN  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MC  DOL-0803-G10MN  D			
BEF-WN-W23 BEF-WN-W24 BEF-WN-W27 BEF-WN-W9-7 BEF-WN-W9-2 BEF-WN-W9-2 BEF-WN-W17 BEF-WN-W17 BEF-WN-W190 BI-100-10 BI-12-SKN BI-9-2 BI-9-3 BI-9-			
BEF-WN-W24 BEF-WN-W27 BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W9-2 BEF-WN-WTR BEF-WN-WTR  BI-100-10 BI-12-SKN BI-9-2 C42-1 C42-2 C5324281 C42-2 C5324281 DOL-0803-G02MC DOL-0803-G05MC DOL-0803-G05MN DOL-0803-G10MC DOL-0803-G10MN DOL-0803-G10M			
BEF-WN-W27 BEF-WN-W9-2 BEF-WN-W9-2 BEF-WN-WTR 2017417 L-865 BF-EB01-W190 5313011 L-867 BL-100-10 5314182 L-866 BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MC 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025890 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903			
BEF-WN-W9-2 2022855 L-865 BEF-WN-WTR 2017417 L-865 BF-EB01-W190 5313011 L-867 BL-100-10 5314182 L-866 BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MC 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025890 L-903 D0L-0803-G05MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903	BEF-WN-W27		
BEF-WN-WTR BF-EB01-W190 BI-100-10 BL-100-10 BL-12-SKN BI-12-SKN BI-9-2 BI-9-3 BI-9-2 BI-9-3 B	BEF-WN-W9-2		
BF-EB01-W190 5313011 L-867 BL-100-10 5314182 L-866 BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6033664 L-903 D0L-0803-G02M 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	BEF-WN-WTR		
BL-100-10 BL-12-SKN BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	BF-EB01-W190		
BL-12-SKN 4031815 L-866 BL-9-2 4033253 L-866 C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6033664 L-903 D0L-0803-G02M 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6033665 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	BL-100-10		
BL-9-2	BL-12-SKN	4031815	
C110A 5304549 L-892 C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G10MC 6025890 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	BL-9-2		
C42-1 5313506 L-892 C42-2 5324281 L-892 C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G05MN 6022009 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	C110A		
C64A 5325185 L-892 D0L-0803-G01MC 6036455 L-903 D0L-0803-G02MC 6025888 L-903 D0L-0803-G02MN 6010785 L-904 D0L-0803-G05MC 6025889 L-903 D0L-0803-G05MN 6033665 L-903 D0L-0803-G05MN 6022009 L-904 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MC 6025890 L-903 D0L-0803-G10MN 6033666 L-903	C42-1	5313506	L-892
DOL-0803-G01MC 6036455 L-903 DOL-0803-G02MC 6025888 L-903 DOL-0803-G02MN 6033664 L-903 DOL-0803-G02M 6010785 L-904 DOL-0803-G05MC 6025889 L-903 DOL-0803-G05MN 6033665 L-903 DOL-0803-G05M 6022009 L-904 DOL-0803-G10MC 6025890 L-903 DOL-0803-G10MN 6033666 L-903	C42-2	5324281	L-892
DOL-0803-G02MC 6025888 L-903 DOL-0803-G02MN 6033664 L-903 DOL-0803-G02M 6010785 L-904 DOL-0803-G05MC 6025889 L-903 DOL-0803-G05MN 6033665 L-903 DOL-0803-G05M 6022009 L-904 DOL-0803-G10MC 6025890 L-903 DOL-0803-G10MN 6033666 L-903	C64A	5325185	L-892
DOL-0803-G02MN       6033664       L-903         DOL-0803-G02M       6010785       L-904         DOL-0803-G05MC       6025889       L-903         DOL-0803-G05MN       6033665       L-903         DOL-0803-G05M       6022009       L-904         DOL-0803-G10MC       6025890       L-903         DOL-0803-G10MN       6033666       L-903	DOL-0803-G01MC	6036455	L-903
DOL-0803-G02M       6010785       L-904         DOL-0803-G05MC       6025889       L-903         DOL-0803-G05MN       6033665       L-903         DOL-0803-G05M       6022009       L-904         DOL-0803-G10MC       6025890       L-903         DOL-0803-G10MN       6033666       L-903	DOL-0803-G02MC	6025888	L-903
DOL-0803-G05MC 6025889 L-903 DOL-0803-G05MN 6033665 L-903 DOL-0803-G05M 6022009 L-904 DOL-0803-G10MC 6025890 L-903 DOL-0803-G10MN 6033666 L-903	DOL-0803-G02MN	6033664	L-903
DOL-0803-G05MN         6033665         L-903           DOL-0803-G05M         6022009         L-904           DOL-0803-G10MC         6025890         L-903           DOL-0803-G10MN         6033666         L-903	DOL-0803-G02M	6010785	L-904
DOL-0803-G05M         6022009         L-904           DOL-0803-G10MC         6025890         L-903           DOL-0803-G10MN         6033666         L-903	DOL-0803-G05MC	6025889	L-903
DOL-0803-G10MC 6025890 L-903 DOL-0803-G10MN 6033666 L-903	DOL-0803-G05MN	6033665	L-903
DOL-0803-G10MN 6033666 L-903	DOL-0803-G05M	6022009	L-904
DOL 0000 0404	DOL-0803-G10MC	6025890	L-903
DOL-0803-G10M 6022011 L-904	DOL-0803-G10MN	6033666	L-903
	DOL-0803-G10M	6022011	L-904

No del mene		
Model name	Part no.	Page
DOL-0803-G15M	6036472	L-904
DOL-0803-G20MC	6036456	L-903
DOL-0803-G25MN	6044452	L-903
DOL-0803-W02MC	6025891	L-903
DOL-0803-W02MN	6033667	L-903
DOL-0803-W02M	6008489	L-904
DOL-0803-W03MC	6038991	L-903
DOL-0803-W05MC	6025892	L-903
DOL-0803-W05MN	6033668	L-903
DOL-0803-W05M	6022010	L-904
DOL-0803-W10MC	6025893	L-903
DOL-0803-W10MN	6033669	L-903
DOL-0803-W10M	6022012	L-904
DOL-0803-W15M	6036473	L-904
DOL-0804-G02MC	6025894	L-904
DOL-0804-G02MN	6033670	L-904
DOL-0804-G02M	6009870	L-905
DOL-0804-G05MAC	6050809	L-904
DOL-0804-G05MC	6025895	L-904
DOL-0804-G05MN	6033671	L-904
DOL-0804-G05M	6009872	L-905
DOL-0804-G10MAC	6050808	L-904
DOL-0804-G10MC	6025896	L-904
DOL-0804-G10MN	6033672	L-904
DOL-0804-G10M	6010754	L-905
DOL-0804-G15MC	6038622	L-904
DOL-0804-G15M	6035232	L-905
DOL-0804-G20MC	6051148	L-904
DOL-0804-G20M	6029109	L-905
DOL-0804-G30M	6029110	L-905
DOL-0804-G50M	6029111	L-905
DOL-0804-W02MC	6025897	L-904
DOL-0804-W02MN	6033673	L-904
DOL-0804-W02M	6009871	L-905
DOL-0804-W05MC	6025898	L-904
DOL-0804-W05MN	6033674	L-904
DOL-0804-W05M	6009873	L-905
DOL-0804-W10MC	6025899	L-904
DOL-0804-W10MN	6033675	L-904
DOL-0804-W10M	6010755	L-905
DOL-1203-G02MC	6039075	L-905
DOL-1203-G05MC	6039076	L-905
DOL-1203-G10MC	6039077	L-905
DOL-1203-W02MC	6039078	L-905
DOL-1203-W05MC	6039079	L-905
DOL-1203-W10MC	6036752	L-905
DOL-1203-W15MC	6036753	L-905
DOL-1203-W20MC	6036754	L-905
DOL-1204-G02MC	6025900	L-905
DOL-1204-G02MN	6028128	L-906
DOL-1204-G02M	6009382	L-906
DOL-1204-G05MAC	6038621	L-905
DOL-1204-G05MC	6025901	L-905
DOL-1204-G05MN	6028130	L-906
DOL-1204-G05M	6009866	L-906
DOL-1204-G10MC	6025902	L-905
DOL-1204-G10MN	6028132	L-906
DOL-1204-G10M	6010543	L-906

Mandalasassa		
Model name	Part no.	Page
DOL-1204-G15MC	6034749	L-905
DOL-1204-G15M	6010753	L-906
DOL-1204-G20MC	6034750	L-905
DOL-1204-G20M	6034401	L-906
DOL-1204-G25MC	6034751	L-905
DOL-1204-G25MN	6028134	L-906
DOL-1204-L02MN	6028136	L-906
DOL-1204-L02M	6027945	L-906
DOL-1204-L05MC	6020398	L-906
DOL-1204-L05MN	6028137	L-906
DOL-1204-L05M	6027944	L-906
DOL-1204-L10MN	6028138	L-906
DOL-1204-L10M	6027946	L-906
DOL-1204-L25MN	6028139	L-906
DOL-1204-W02MC	6025903	L-906
DOL-1204-W02MN	6028129	L-906
DOL-1204-W02M	6009383	L-906
DOL-1204-W05MC	6025904	L-906
DOL-1204-W05MN	6028131	L-906
DOL-1204-W05M	6009867	L-906
DOL-1204-W10MC	6025905	L-906
DOL-1204-W10MN	6028133	L-906
DOL-1204-W10M	6010541	L-906
DOL-1204-W15MC	6034752	L-906
DOL-1204-W15M	6036474	L-906
DOL-1204-W20MC	6034753	L-906
DOL-1204-W20M	6033559	L-906
DOL-1204-W25MC	6034754	L-906
DOL-1204-W25MN	6028135	L-906
DOL-1205-G02MC	6025906	L-907
DOL-1205-G02MN	6028140	L-907
DOL-1205-G02M	6008899	L-907
DOL-1205-G05MAC	6036384	L-907
DOL-1205-G05MC	6025907	L-907
DOL-1205-G05MN	6028141	L-907
DOL-1205-G05M	6009868	L-907
DOL-1205-G10MAC	6036385	L-907
DOL-1205-G10MC	6025908	L-907
DOL-1205-G10MN	6028142	L-907
DOL-1205-G10M	6010544	L-907
DOL-1205-G15M	6029215	L-907
DOL-1205-G20MAC	6036386	L-907
DOL-1205-G25MN	6028143	L-907
DOL-1205-W02MC	6025909	L-907
DOL-1205-W02M	6008900	L-907
DOL-1205-W05MC	6025910	L-907
DOL-1205-W05M	6009869	L-907
DOL-1205-W10MC	6025911	L-907
DOL-1205-W10M	6010542	L-907
DOS-0803-G	7902077	L-908
DOS-0803-W	7902078	L-908
DOS-0804-G	6009974	L-908
DOS-0804-W	6009975	L-908
DOS-1204-GN	6028357	L-909
DOS-1204-G	6007302	L-909
DOS-1204-W	6007303	L-909
DOS-1205-G	6009719	L-909
DOS-1205-W	6009720	L-909
	0003120	F-909

Model name	Part no.	Page
DOS1204-WN	6028358	L-909
DSL-0804-G02MC	6036335	L-911
DSL-0804-G03M	6051283	L-911
DSL-0804-G05MC	6039090	L-911
DSL-0804-G0M6C	6039089	L-911
DSL-0804-G0M6	6034664	L-911
DSL-0804-G1M5	6042050	L-911
DSL-0804-G2M5	6051282	L-911
DSL-1203-B02MC	6025925	L-912
DSL-1203-B0M6C	6025924	L-912
DSL-1203-G02MC	6025923	L-912
DSL-1203-G0M6C	6025922	L-912
DSL-1204-B02MN	6028198	L-912
DSL-1204-B05MN	6028199	L-912
DSL-1204-B0M6N	6028197	L-912
DSL-1204-G01MC	6033244	L-912
DSL-1204-G02MC	6025927	L-912
DSL-1204-G02MN	6028195	L-912
DSI-1204-G05MC	6033245	L-912
DSL-1204-G05MN		
DSL-1204-G05M	6028196	L-912
DSL-1204-G0M6C	6022569	L-912
DSL-1204-GOM6N	6025926	L-912
DSL-1204-GOMON  DSL-1204-G10MC	6028194	L-912
	6033698	L-912
DSL-1205-B01MC	6029284	L-913
DSL-1205-B02MC	6029287	L-913
DSL-1205-B05MC	6029288	L-913
DSL-1205-B0M6C	6029283	L-913
DSL-1205-B1M5C	6029286	L-913
DSL-1205-G01MC	6029280	L-913
DSL-1205-G02MC	6025931	L-913
DSL-1205-G05MC	6029282	L-913
DSL-1205-G0M6C	6025930	L-913
DSL-1205-G10MC	6038954	L-913
DSL-1205-G15MC	6038956	L-913
DSL-1205-G20MC	6038957	L-913
DSL-2803-G02MC	6039184	L-911
DSL-2803-G05MC	6028664	L-911
DSL-2803-G0M6C	6039183	L-911
DSL-2804-G02MC	6039180	L-912
DSL-2804-G05MC	6039091	L-912
DSL-2804-G0M6C	6037595	L-912
DSL-8203-B02MC	6025917	L-910
DSL-8203-B05MC	6039185	L-910
DSL-8203-B0M6C	6025916	L-910
DSL-8203-G02MC	6025915	L-910
DSL-8203-G02M	6022572	L-911
DSL-8203-G05MC	6030608	L-910
DSL-8203-G0M6C	6025914	L-910
DSL-8203-G0M6	6022570	L-911
DSL-8204-B02MC	6025921	L-911
DSL-8204-B05MC	6039182	L-911
DSL-8204-B0M6C	6025920	L-911
DSL-8204-G02MC	6025919	L-911
DSL-8204-G02M	6022573	L-911
DSL-8204-G05MC	6039181	L-911
DSL-8204-G05M	6034403	L-911
DSL-8204-G0M6C	6025918	L-911

Model name	Bort no	Podo
DSL-8204-G0M6	Part no. 6022571	Page L-911
DSI-8204-G10M	6034404	L-911
DSL-8204-G20M	6034405	L-911
EL3-F2415	1043961	I-694
EL3-P2415	1043960	I-694
EL4-F2415	1044684	I-694
EL4-P2415	1044683	I-694
EN2-2EX-1	6041096	L-921
EN2-2EX-3	6041095	L-921
ET3-F2215	1045196	1-694
ET3-F3215	1045189	I-694
ET3-F4215	1045193	I-694
ET3-F5215	1045200	I-694
ET3-P2215	1045195	I-694
ET3-P3215	1045187	I-694
ET3-P4215	1045191	I-694
ET3-P5215	1045199	1-694
FC	5304141	L-867
GL10-N1111	1065880	G-435
GL10-N1112	1065882	G-435
GL10-N1211	1065888	G-435
GL10-N1212	1065889	G-435
GL10-N1551	1065892	G-436
GL10-N4111	1065883	G-435
GL10-N4112	1065884	G-435
GL10-N4211	1064700	G-435
GL10-N4212	1065891	G-435
GL10-P1111	1065876	G-435
GL10-P1112	1065877	G-435
GL10-P1211	1065885	G-435
GL10-P1212	1065886	G-435
GL10-P4111	1065878	G-435
GL10-P4112	1065879	G-435
GL10-P4211	1065890	G-435
GL10-P4212	1065887	G-435
GL10-P4551	1064702	G-436
GL10-P4554	1065893	G-436
GL10-R3711	1065896	G-435
GL10-R3712	1065897	G-435
GL10-R3811	1064689	G-435
GL10-R3812	1065898	G-435
GL10G-N1251	1064705	G-436
GL10G-N1252	1065895	G-436
GL10G-P4251	1064704	G-436
GL10G-P4252	1065894	G-436
GL2S-E1311	1063009	F-188
GL2S-E1312	1064424	F-188
GL2S-F1311	1064358	F-188
GL2S-F5311	1063008	F-188
GL2S-N1311	1064360	F-188
GL2S-N1312	1064423	F-188
GL2S-P5311	1064359	F-188
GL6-N1111	1050709	F-200
GL6-N1112	1051780	F-200
GL6-N1212	1060814	F-200
GL6-N4112	1051778	F-200
GL6-N4211	1059631	F-200
GL6-N6212	1062588	F-200

Model name	D. of our	Deste
Model name GL6-P1111	Part no.	Page
GL6-P1111	1050708	F-200
GL6-P1112 GL6-P1212	1051779	F-200
GL6-P1212	1060815	F-200
GL6-P4111	1050706	F-200
GL6-P4211	1051777	F-200
9-24 - 1-2-	1059241	F-200
GL6-P6111	1060234	F-200
GL6-P6112 GL6-P6211	1060235	F-200
020 / 0211	1058851	F-200
GL6-P6212	1062753	F-200
GL6-P7111 GL6-P7112	1052966	F-200
	1053590	F-200
GL6G-N1211	1059925	F-200
GL6G-N1212 GL6G-N4211	1060811	F-200
5,-5 5,	1059633	F-200
GL6G-N4212	1060809	F-200
GL6G-P1211 GL6G-P1212	1059924	F-200
	1060812	F-200
GL6G-P4211	1059632	F-200
GL6G-P4212 GRL18S-E1331	1060810	F-200
GRL185-E1331 GRL18S-E1336	1059537	I-701
5	1059530	I-701
GRL18S-F1331 GRL18S-F1336	1059541	I-701
GRL185-F1338	1059532	I-701
GRL18S-F2331	1059535	I-701
GRL18S-F2336	1058198	I-701
GRL18S-F2338	1059533	I-701
GRL18S-F233W	1058211	I-701
GRL18S-F233Y	1058209 1058206	I-701 I-701
GRL18S-N1331	1059538	I-701
GRL18S-N1336	1059531	I-701
GRL18S-P1331	1059542	I-701
GRL18S-P1336	1059534	I-701
GRL18S-P1338	1059536	I-701
GRL18S-P2331	1058199	I-701
GRL18S-P2336	1058192	I-701
GRL18S-P2338	1058212	I-701
GRL18S-P233W	1058210	I-701
GRL18S-P233Y	1058207	I-701
GRL18SG-F1337	1062231	I-702
GRL18SG-F2332	1059555	I-701
GRL18SG-F2337	1059553	I-702
GRL18SG-F2339	1059554	I-702
GRL18SG-F233X	1059557	I-701
GRL18SG-F233Z	1059556	I-701
GRSE18S-E1331	1059548	I-702
GRSE18S-E1336	1059543	I-702
GRSE18S-F1336	1059544	I-702
GRSE18S-F2331	1059549	I-702
GRSE18S-F2336	1058214	I-702
GRSE18S-F2338	1059546	I-702
GRSE18S-F233W	1059551	I-702
GRSE18S-P1336	1059545	I-702
GRSE18S-P2331	1059550	I-702
GRSE18S-P2336	1058215	I-702
GRSE18S-P2338	1059547	I-702
GRSE18S-P233W	1059552	I-702

Madelmone	-	_
Model name	Part no.	Page
GRTE18S-E231Z	1059409	I-700
GRTE18S-E234Z GRTE18S-F2319	1059483	I-700
GRTF18S-F231X	1059406	I-700
GRTE18S-F231X GRTE18S-F231Z	1059438	I-700
GRTE18S-F2312 GRTE18S-F2349	1059435	I-700
3	1059480	I-700
GRTE18S-F234X GRTF18S-F2347	1059488	I-700
GRTF18S-N1312	1059486	I-700
G. ( ) 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2 2	1058201	I-700
GRTE18S-N1317 GRTE18S-N1342	1058194	I-700
GRTE18S-N1347	1058202	I-700
	1058393	I-700
GRTE18S-N2312	1059408	I-700
GRTE18S-N2317	1059378	I-700
GRTE18S-N231Z GRTF18S-N2342	1059432	I-700
G. (12200 1120 12	1059482	I-700
GRTE18S-N2347	1059441	I-700
GRTE18S-N234Z	1059484	I-700
GRTE18S-P1312	1058203	I-700
GRTE18S-P1317	1058195	I-700
GRTE18S-P1342	1058205	I-700
GRTE18S-P1347	1058197	I-700
GRTE18S-P2312	1058204	I-700
GRTE18S-P2317	1058196	I-700
GRTE18S-P2319	1059407	I-700
GRTE18S-P231X	1059440	I-700
GRTE18S-P231Z	1059436	I-700
GRTE18S-P2342	1058200	I-700
GRTE18S-P2347	1058193	I-700
GRTE18S-P2349	1059481	I-700
GRTE18S-P234X	1059489	I-700
GRTE18S-P234Z	1059487	I-700
GSE10-N1111	1065901	G-437
GSE10-N1112	1065902	G-437
GSE10-N1211	1065904	G-437
GSE10-N1212	1065905	G-437
GSE10-N1221	1065908	G-437
GSE10-N1222	1065909	G-437
GSE10-P4111	1065899	G-437
GSE10-P4112	1065900	G-437
GSE10-P4211	1064706	G-437
GSE10-P4212	1065903	G-437
GSE10-P4221	1065906	G-437
GSE10-P4222	1065907	G-437
GSE10-R3711	1065910	G-437
GSE10-R3712	1065911	G-437
GSE10-R3721	1065913	G-437
GSE10-R3722	1065914	G-437
GSE10-R3811	1064691	G-437
GSE10-R3812	1065912	G-437
GSE2S-E1311	1063070	F-189
GSE2S-F1311	1064363	F-189
GSE2S-F5311	1063072	F-189
GSE2S-N1311	1064365	F-189
GSE2S-P5311	1064364	F-189
GSE6-N1111	1052449	F-201
GSE6-N1112	1052453	F-201
GSE6-N1211	1060791	F-201

Madal nama		
Model name	Part no.	Page
GSE6-N4111	1052447	F-201
GSE6-N4112	1052451	F-201
GSE6-N6111	1054849	F-201
GSE6-N6112 GSF6-N7111	1054852	F-201
4020111211	1054833	F-201
GSE6-N7112	1054835	F-201
GSE6-P1111	1052448	F-201
GSE6-P1112 GSF6-P1211	1052452	F-201
4010 / 1111	1060792	F-201
GSE6-P1212 GSE6-P4111	1061398	F-201
GSE6-P4111	1052446	F-201
5.5 - 5	1052450	F-201
GSE6-P4211 GSE6-P4212	1061394	F-201
GSE6-P6111	1061396	F-201
GSE6-P6111 GSF6-P6112	1054848	F-201
GSE6-P0112 GSE6-P7111	1054850	F-201
GSE6-P7111 GSF6-P7112	1054830	F-201
40201122	1054831	F-201
GTB10-N1211 GTB10-N1212	1065858	G-433
GTB10-N1212 GTB10-N4211	1065859	G-433
GTB10-N4211 GTB10-N4212	1065860	G-433
GTB10-N4212 GTB10-P1211	1065861	G-433
GTB10-P1211 GTB10-P1212	1065854	G-433
GTB10-P1212 GTB10-P4211	1065856	G-433
GTB10-P4211	1064694	G-433
GTB10-F4212 GTB10-R3811	1065857	G-433
GTB10-R3812	1064686	G-433
GTB10-R3821	1065862 1065863	G-433
GTB10-R3822	1065864	G-433 G-433
GTB2S-E1311	1064348	G-433 F-188
GTB2S-E1331	1064354	F-188
GTB2S-E1451	1064342	F-188
GTB2S-E5451	1064344	F-188
GTB2S-F1311	1064346	F-188
GTB2S-F5311	1064347	F-188
GTB2S-F5331	1064353	F-188
GTB2S-F5451	1064341	F-188
GTB2S-N1311	1062840	F-188
GTB2S-N1331	1062929	F-188
GTB2S-N1451	1060203	F-188
GTB2S-N5311	1064349	F-188
GTB2S-N5451	1064343	F-188
GTB2S-P1311	1064345	F-188
GTB2S-P1331	1064351	F-188
GTB2S-P1451	1060205	F-188
GTB2S-P5311	1062872	F-188
GTB2S-P5331	1062930	F-188
GTB2S-P5451	1060204	F-188
GTB6-N1211	1052441	F-199
GTB6-N1212	1052445	F-199
GTB6-N4211	1052439	F-199
GTB6-N4212	1052443	F-199
GTB6-N6211	1058774	F-199
GTB6-N6212	1058769	F-199
GTB6-P1211	1052440	F-199
GTB6-P1212	1052444	F-199
GTB6-P4211	1052438	F-199

Model name	Deutse	D. di
GTB6-P4212	Part no.	Page
GTB6-P5211	1052442	F-199
GTB6-P6211	1059333	F-199
	1059320	F-199
GTB6-P7211	1057705	F-199
GTE10-N1211	1065868	G-434
GTE10-N1212	1065869	G-434
GTE10-N4211	1065871	G-434
GTE10-N4212	1065872	G-434
GTE10-P1211	1065865	G-434
GTE10-P1212	1065866	G-434
GTE10-P4211	1064697	G-434
GTE10-P4212	1065867	G-434
GTE10-R3811	1064688	G-434
GTE10-R3812	1065873	G-434
GTE10-R3821	1065874	G-434
GTE10-R3822	1065875	G-434
GTE6-N1211	1050713	F-198
GTE6-N1212	1051784	F-198
GTE6-N4211	1050711	F-198
GTE6-N4212	1051782	F-198
GTE6-P1211	1050712	F-198
GTE6-P1212	1051783	F-198
GTE6-P4211	1050710	F-198
GTE6-P4212	1051781	F-198
GTE6-P7211	1053589	F-198
GTE6-P7212	1053628	F-198
I/O box extension, 4 in/8 out	6037654	L-903
I/O extension module, 8 out	6037750	L-903
I/O module, 2 extra digital inputs	6039038	L-903
IOLSHPB-P3104	6032904	L-921
IRT-P211A10	1063117	E-151
IRT-P211A11	1063118	E-152
IRT-P211C63	1063127	E-152
IRT-P211E41	1063107	E-152
IRT-P212A10	1063123	E-151
IRT-P212A11	1063124	E-152
IRT-P212C63	1063116	E-152
IRT-P212E40	1063108	E-151
IRT-P212E41	1063109	E-152
IRT-P231C83	1063101	E-152
IRT-P232C83	1063100	E-152
LL3-DA01	5308127	J-832
LL3-DA02	5308130	J-832
LL3-DA03	5326465	J-832
LL3-DA04	5326466	J-832
LL3-DA05	5326467	J-832
LL3-DA06	5326468	J-832
LL3-DA07	5326469	J-832
LL3-DB01	5308074	J-806
LL3-DB02	5308083	J-813
LL3-DB03	5313021	J-806
LL3-DB04	5325990	J-806
LL3-DB05	5326002	J-812
LL3-DB06	5326006	J-813
LL3-DB07	5325988	J-807
LL3-DB08	5326004	J-813
LL3-DB09	5325991	J-809
LL3-DB10	5325999	J-808

Daniel mana	-	_
Model name LL3-DC03	Part no.	Page
LL3-DC04	5326020	J-811
LL3-DC05	5326018	J-811
LL3-DC06	5326016	J-816
LL3-DC07	5326017	J-810
LL3-DC08	5326019	J-811
LL3-DC09	5326029 5326028	J-810 J-810
LL3-DC38	5322472	J-810 J-816
LL3-DC39	5322472	J-816
LL3-DC47	5324268	J-810
LL3-DC57	5324269	J-810
LL3-DE01	5325285	J-810
LL3-DE02	5324497	J-810
LL3-DE03	5325986	J-811
LL3-DE04	5325987	J-811
LL3-DF02-S01	5321924	J-817
LL3-DF04	5326035	J-817
LL3-DF05	5326034	J-817
LL3-DF07	5326033	J-817
LL3-DH01	5308091	J-815
LL3-DH02	5308092	J-815
LL3-DH03	5324787	J-815
LL3-DH04	5326022	J-813
LL3-DH05	5326021	J-812
LL3-DH06	5326026	J-810
LL3-DH07	5326031	J-815
LL3-DH08	5326025	J-810
LL3-DH09	5326030	J-815
LL3-DH10	5326023	J-811
LL3-DH11	5326024	J-811
LL3-DJ01	5325989	J-806
LL3-DJ02	5325992	J-806
LL3-DK04	5313020	J-808
LL3-DK06	5313019	J-807
LL3-DK21	5313023	J-807
LL3-DK33	5313031	J-813
LL3-DK43	5313030	J-812
LL3-DK4Z	5313026	J-808
LL3-DK63Z	5313027	J-812
LL3-DK66	5313024	J-807
LL3-DK67	5313025	J-807
LL3-DM01 LL3-DM02	5308071	J-807
	5308077	J-807
LL3-DM03 LL3-DP01	5308084	J-812
LL3-DR01	5325998	J-808
LL3-DR02	5308078	J-807
LL3-DR03	5308079	J-806
LL3-DR04	5308080	J-808
LL3-DR05	5308081 5308087	J-808 J-812
LL3-DR06	5308087	J-812 J-806
LL3-DR07	5308082	J-806 J-812
LL3-DR08	5326007	J-812 J-807
LL3-DR09	5325528	J-807 J-811
LL3-DR10	5326005	J-811
LL3-DR11	5326000	J-813
LL3-DR12	5326001	J-808
LL3-DS06	5308073	J-806
	2300010	3 000

Model name	Part no.	Page
LL3-DT01	5308076	J-806
LL3-DT02	5308085	J-812
LL3-DT03	5308072	J-808
LL3-DT04	5308086	J-812
LL3-DT05	5313028	J-812
LL3-DV01	5308088	J-813
LL3-DV02	5308089	J-813
LL3-DV03	5308090	J-813
LL3-DV05	5322549	J-809
LL3-DV06	5322550	J-809
LL3-DV07	5322551	J-809
LL3-DW01	5315234	J-815
LL3-DW02	5325608	J-817
LL3-DY01	5308093	J-815
LL3-DZ01	5326013	J-813
LL3-DZ02	5326014	J-814
LL3-DZ03	5326015	J-814 J-814
LL3-RB01	5326010	J-814 J-816
LL3-RB02	5326010	J-816
LL3-RG01		
LL3-RR01	5326012	J-816
LL3-TA01	5326008	J-816
LL3-TAO1S	5308128	J-828
	5326461	J-828
LL3-TA02	5308129	J-828
LL3-TAO3	5326462	J-828
LL3-TA04	5326463	J-828
LL3-TA05	5326464	J-828
LL3-TB01	5308050	J-818
LL3-TB02	5308048	J-818
LL3-TB03	5308056	J-823
LL3-TB05	5325924	J-823
LL3-TB06	5325916	J-820
LL3-TB07	5325919	J-819
LL3-TB08	5325917	J-818
LL3-TE01	5325807	J-821
LL3-TE02	5325910	J-821
LL3-TE03	5325908	J-822
LL3-TE04	5325911	J-821
LL3-TE05	5325914	J-821
LL3-TF01	5324242	J-827
LL3-TG01	5325940	J-826
LL3-TG02	5325943	J-826
LL3-TG03	5325942	J-826
LL3-TG04	5324499	J-826
LL3-TG05	5325921	J-819
LL3-TH01	5308064	J-825
LL3-TH02	5308065	J-825
LL3-TH06	5325926	J-819
LL3-TH07	5325977	J-820
LL3-TH08	5325978	J-825
LL3-TH09	5325979	J-825
LL3-TH10	5325970	J-825
LL3-TH11	5325971	J-825
LL3-TH12	5325972	J-825
LL3-TH13	5325973	J-825
LL3-TH14	5325974	J-825
LL3-TH15	5325975	J-820
LL3-TH16	5325976	J-820
	-3200.0	- 0_0

Model name	D. at an	D. 4
Model name LL3-TH17	Part no.	Page
LL3-TJ01	5325967	J-825
LL3-TK05	5325915	J-818
LL3-TK16	5313034	J-819
LL3-TK16	5313038	J-823
LL3-TM01	5313035	J-818
	5308068	J-818
LL3-TM02 LL3-TM03	5308069	J-818
	5308070	J-819
LL3-TP01 LL3-TR01	5325925	J-823
LL3-TR01	5308052	J-818
	5308053	J-818
LL3-TR03	5308054	J-819
LL3-TR04	5325918	J-819
LL3-TR05	5325808	J-821
LL3-TR06	5325912	J-821
LL3-TR08	5325984	J-820
LL3-TR09	5325985	J-820
LL3-TR10	5325920	J-819
LL3-TR11 LL3-TR12	5325906	J-822
	5325907	J-822
LL3-TR13	5325909	J-822
LL3-TS07	5308049	J-819
LL3-TS08	5308061	J-823
LL3-TS10	5308063	J-824
LL3-TS12 LL3-TS14	5308062	J-823
LL3-TS22M	5313039	J-824
LL3-TS22	5325968	J-826
LL3-TS40	5325944	J-826
LL3-T701	5323971 5308057	J-824 J-823
LL3-TV01	5308057	J-823
LL3-TV02	5308058	J-823
LL3-TV04	5308059	J-823
LL3-TV05	5322546	J-820
LL3-TV06	5322547	J-820
LL3-TV07	5322548	J-820
LL3-TV08	5325922	J-819
LL3-TW01	5315233	J-825
LL3-TX02	5325046	J-818
LL3-TY01	5308066	J-827
LL3-TY02	5308067	J-827
LL3-TY03	5325982	J-820
LL3-TY04	5325981	J-827
LL3-TY05	5325980	J-827
LL3-TZ05	5325937	J-824
LL3-TZ06	5325938	J-824
LL3-TZ09	5326598	J-824
LL3-TZ10	5326599	J-824
MHL15-N3236V	1043812	I-716
MHL15-N3336V	1043813	I-716
MHL15-P3236V	1043814	I-716
MHL15-P3336V	1043815	I-716
MHSE15-N3236V	1043816	I-717
MHSE15-N3336V	1043817	I-717
MHSE15-P3236V	1043818	I-717
MHSE15-P3336V	1043819	I-717
MHT15-N3217V	1043803	I-716
MHT15-N3247V	1043808	I-716

Model name	Part no.	Page
MHT15-N3317V	1043804	I-716
MHT15-N3347V	1043809	I-716
MHT15-P3217V	1043805	I-716
MHT15-P3247V	1043810	I-716
MHT15-P3317V	1043806	I-716
MHT15-P3347V	1043811	I-716
MHTB15-N3267V	1047159	I-716
MHTB15-N3367V	1046536	I-716
MHTB15-P3267V	1047160	I-716
MHTB15-P3367V	1046537	I-716
OBS-W24	2015069	L-866
OBW-KHS-M01	2023240	L-866
OBW-W24	2015070	L-866
OP60-00	1000141	L-892
OP60-20	1000141	L-892
OP61-00	1002627	L-892
P25-2	5318969	
P250F	5318969	L-892
P250H		L-890
P250 CHEM	5315124	L-892
P250 CHEIVI	5321097	L-890
	5304812	L-889
P25F-1	5319385	L-890
P25	5315172	L-892
P32	5314001	L-889
P34	5313922	L-892
P40	5313923	L-889
P41F	5315128	L-890
P42	5314825	L-889
P45A	5320027	L-889
P50-1	5322673	L-892
P55F	5313924	L-890
P55	5318680	L-892
PL100	5321625	L-889
PL10F CHEM	5321636	L-890
PL10FB-CHEM	5327722	L-890
PL10F	5311210	L-890
PL150	5315548	L-889
PL15F	5313849	L-890
PL180E01	1013289	L-889
PL18F	5319994	L-890
PL20A	1012719	L-889
PL20F-CHEM	5326089	L-890
PL20F	5308844	L-890
PL20 CHEM	5321089	L-892
PL21A	1015172	L-889
PL22-1	1003546	L-892
PL22-2	1003621	L-892
PL22-3	1003021	L-892
PL30A	1002314	L-889
PL30F	5326523	L-890
PL31A	1002315	L-889
PL34-1		
PL40A Antifog	5322257	L-892
PL40A Antilog	5322011	L-892
	1012720	L-889
PL40B-CHEM	5326088	L-893
PL40B	5320134	L-889
PL50A	1000132	L-889
PL50HK	1011545	L-893

Model name	Part no.	Page
PL50HS	1009871	L-893
PL51A	1001628	L-889
PL53A	1000382	L-893
PL72-2	5322723	L-889
PL80A	1003865	L-890
PL81-1F	5325060	L-890
PL81	5322795	L-890
PLH25-D12	2063404	L-893
PLH25-M12	2063403	L-893
PLV14-A	2063405	L-893
REF-3290-K	4018696	L-891
REF-3290	5301885	L-891
REF-3930-K2	2057035	L-891
REF-7610-0K4	5600079	L-891
REF-7610-K	4018617	L-891
REF-AC1000-28	4067881	L-891
REF-AC1000-56	4063030	L-891
REF-AC1000-73P01	2061557	L-891
REF-AC1000	5319429	L-891
REF-APM	4025097	L-891
REF-DG-K	4019634	L-891
REF-DG	5320565	L-891
REF-IRF-56	5314244	L-891
REF-PLUS-25-K	4051184	L-891
REF-Plus-3436	5321337	L-891
REF-PLUS-50-K	4051185	L-891
REF-PLUS-R100-K	4071461	L-891
REF-PLUS-R100	5319915	L-891
REF-PLUS-R25	5319929	L-891
REF-PLUS-R50	5319981	L-891
REF-PLUS-R76	4071462	L-891
REF-Plus-R76	5322215	L-891
REF-Plus-RED-2550	5320285	L-891
RT-B1117	1063153	E-151
RT-B1221	1063174	E-151
RT-B2117	1063178	E-151
RT-B2221	1063175	E-151
RT-M1117	1063194	E-151
RT-M2117	1063197	E-151
RT-N3117	1063180	E-151
RT-N3221	1063162	E-151
RT-P3117	1063179	E-151
RT-P3221	1063129	E-151
RTF-M1117	1063195	E-151
RTF-M2117	1063198	E-151
RTF-P3117	1063181	E-151
RTF-P3221	1063171	E-151
RTN-M1117	1063196	E-151
RTN-M2117	1063199	E-151
RTN-P3117	1063182	E-151
RTN-P3221	1063172	E-151
RTQ-B1117	1063184	E-151
RTQ-B1221	1063177	E-151
RTQ-P4117	1063183	E-151
RTQ-P4221	1063173	E-151
SiLink2 Master	1061790	L-921
STE-0803-G	6037322	L-909
STE-0804-G	6037323	L-910

Model name	Part no.	Page
STE-1204-GN	6028359	L-910
STE-1204-G	6009932	L-910
STE-1204-W	6022084	L-910
STE-1205-G	6022083	L-910
STE-1205-W	6022082	L-910
STL-1204-G02MC	6028077	L-908
STL-1204-G05MC	6048170	L-908
STL-1204-G0M3C	6011311	L-908
STL-1204-G10MC	6041750	L-908
STL-1204-G15MC	6048171	L-908
STL-1204-W05MC	6037472	L-908
STL-1204-W15MC	6037473	L-908
STL-1205-G01MC	6037741	L-908
STL-1205-G02MC	6051951	L-908
STL-1205-G05MC	6051952	L-908
STL-1205-G10MC	6051953	L-908
SW50	1000131	L-893
VL18-4N2240V	6035498	I-735
VL18-4N3140V	6035496	I-735
VL18-4P2240V	6035497	I-735
VL18-4P3140V	6035495	I-735
VL180-2F32331	6043458	1-749
VL180-2N41131	6041816	1-749
VL180-2N41136	6037493	1-749
VL180-2N41138	6043835	1-749
VL180-2N42431	6041817	1-749
VL180-2N42433	6043830	I-749
VL180-2N42436	6037494	1-749
VL180-2N42438		
VL180-2P32431	6043836	I-749
VL180-2P32431 VL180-2P32433	6044030	I-749
VL180-2P32438	6044032	I-749
VL180-2P41131	6044033	I-749
VL180-2P41131 VL180-2P41133	6041818	I-749
VL180-2P41136	6043832	I-749
VL180-2P41136 VL180-2P41138	6037495	I-749
VL180-2P41136 VL180-2P42431	6043837	I-749
	6041819	I-749
VL180-2P42433	6043834	I-749
VL180-2P42436	6037496	I-749
VL180-2P42438	6043838	I-749
VL18L-3F324	6034330	I-726
VL18L-4N324	6027432	I-726
VL18L-4N344	6027436	I-726
VL18L-4P324	6027430	I-726
VL18L-4P344	6027434	I-726
VS/VE18-4N3140V	6035500	I-735
VS/VE18-4P3140V	6035499	I-735
VSE180-2N41132	6041820	I-750
VSE180-2N41134	6043847	I-750
VSE180-2N41137	6037497	I-750
VSE180-2N41139	6043851	I-750
VSE180-2N42432	6041821	I-750
VSE180-2N42434	6043848	I-750
VSE180-2N42437	6037498	I-750
VSE180-2N42439	6043852	I-750
VSE180-2P32434	6044036	I-750
VSE180-2P32439	6044037	I-750
VSE180-2P41132	6041822	I-750

Model name	Part no.	Page
VSE180-2P41134	6043849	I-750
VSE180-2P41137	6037499	I-750
VSE180-2P41139	6043853	I-750
VSE180-2P42432	6041823	I-750
VSE180-2P42434	6043850	I-750
VSE180-2P42437	6037500	I-750
VSE180-2P42439	6043854	I-750
VSE18L-4N324	6027933	I-726
VSE18L-4N344	6027937	I-726
VSE18L-4P324	6027931	I-726
VSE18L-4P344	6027935	I-726
VTB18-4N1240V	6035494	I-734
VTB18-4P1240V	6035493	I-734
VTB180-2F32412	6044019	I-745
VTB180-2F32417	6044020	I-745
VTB180-2N41112	6043867	I-745
VTB180-2N41117	6043871	I-745
VTB180-2N42412	6043868	I-745
VTB180-2N42417	6043872	I-745
VTB180-2P41112	6043869	I-745
VTB180-2P41117	6043873	I-745
VTB180-2P42412	6043870	I-745
VTB180-2P42417	6043874	I-745
VTE18-4N4240V	6035490	1-734
VTE18-4N8240V	6035492	1-734
VTE18-4P4240V	6035489	1-734
VTE18-4P8240V	6035491	1-734
VTE180-2F32342	6042576	1-747
VTE180-2F32444	6044025	1-747
VTE180-2F32449	6044026	1-747
VTE180-2F32484	6044028	
VTE180-2F32487		I-748
VTE180-2F32489	6044027	1-748
VTE180-2N41142	6044029	1-748
VTE180-2N41144	6041804	1-747
VTE180-2N41144 VTE180-2N41147	6043812	1-747
VTE180-2N41147 VTE180-2N41149	6037481	1-747
VTE180-2N41149 VTE180-2N41182	6043816	1-747
VTE180-2N41184	6041808	1-748
VTE180-2N41187	6043820	1-748
VTE180-2N41187 VTE180-2N41189	6037485	1-748
VTE180-2N41139 VTE180-2N42442	6043824	1-748
VTE180-2N42444 VTE180-2N42444	6041805	1-747
VTE180-2N42444 VTE180-2N42447	6043813	1-747
VTE180-2N42447 VTE180-2N42449	6037482	1-747
VTE180-2N42449 VTE180-2N42482	6043817	1-747
	6041809	I-748
VTE180-2N42484	6043821	1-748
VTE180-2N42487	6037486	I-748
VTE180-2N42489	6043825	1-748
VTE180-2P32447	6043946	1-747
VTE180-2P32482	6043945	I-748
VTE180-2P41142	6041806	1-747
VTE180-2P41144	6043814	I-747
VTE180-2P41147	6037483	I-747
VTE180-2P41149	6043818	I-747
VTE180-2P41182	6041810	I-748
VTE180-2P41184	6043822	I-748
VTE180-2P41187	6037487	I-748

Madal nama	5 .	Б
Model name	Part no.	Page
VTE180-2P41189	6043826	I-748
VTE180-2P42442	6041807	I-747
VTE180-2P42444	6043815	I-747
VTE180-2P42447	6037484	I-747
VTE180-2P42449	6043819	I-747
VTE180-2P42482	6041811	I-748
VTE180-2P42484	6043823	I-748
VTE180-2P42487	6037488	I-748
VTE180-2P42489	6043827	I-748
VTE18L-4N324	6027420	I-726
VTE18L-4N344	6027424	I-726
VTE18L-4P324	6027418	I-726
VTE18L-4P344	6027422	I-726
VTF18-4N1240V	6035488	I-734
VTF18-4P1240V	6035487	I-734
VTF180-2F32412	6044021	I-746
VTF180-2F32414	6044023	I-746
VTF180-2F32417	6044022	I-746
VTF180-2F32419	6044024	I-746
VTF180-2N41112	6041799	I-746
VTF180-2N41114	6043803	I-746
VTF180-2N41117	6037477	I-746
VTF180-2N41119	6043807	I-746
VTF180-2N42412	6041801	1-746
VTF180-2N42414	6043804	1-746
VTF180-2N42417	6037478	I-746
VTF180-2N42419	6043808	I-746
VTF180-2P41112	6041802	I-746
VTF180-2P41114		
VTF180-2P41117	6043805	I-746
VTF180-2P41117	6037479	I-746
VTF180-2P42412	6043810	I-746
VTF180-2P42414	6041803	I-746
VTF180-2P42414 VTF180-2P42417	6043806	I-746
	6037480	I-746
VTF180-2P42419	6043811	I-746
WL100-2N1429	6052381	F-407
WL100-2N1439	6052357	F-407
WL100-2N3429	6052382	F-407
WL100-2N3439	6052358	F-407
WL100-2N4429	6052383	F-407
WL100-2N4439	6052359	F-407
WL100-2P1429	6052384	F-407
WL100-2P1439	6052360	F-407
WL100-2P3429	6052385	F-407
WL100-2P3439	6052361	F-407
WL100-2P4429	6052386	F-407
WL100-2P4439	6052362	F-407
WL100L-E1131	6030711	F-414
WL100L-E2131	6030712	F-414
WL100L-E2231	6030713	F-414
WL100L-F1131	6030708	F-414
WL100L-F2131	6030709	F-414
WL100L-F2231	6030710	F-414
WL11-2N1130	1041388	G-495
WL11-2N2430	1041387	G-495
WL11-2P1130	1041386	G-495
WL11-2P2430S05	1056080	G-495
WL11-2P2430	1041385	G-495

Madalasas		
Model name	Part no.	Page
WL11-2P2432	1048542	G-495
WL11G-2B2531	1041390	G-506
WL11G-2K3431	1048313	G-506
WL12-3N1131	1041441	G-532
WL12-3N1141	1041447	G-532
WL12-3N1151	1041451	G-533
WL12-3N1161	1041455	G-533
WL12-3N1731	1041442	G-532
WL12-3N2431	1041440	G-532
WL12-3N2441	1041446	G-532
WL12-3N2451	1041450	G-533
WL12-3N2461	1041454	G-533
WL12-3P1131	1041437	G-532
WL12-3P1141	1041445	G-532
WL12-3P1151	1041449	G-533
WL12-3P1161	1041453	G-533
WL12-3P1731	1041438	G-532
WL12-3P2431	1041436	G-532
WL12-3P2441	1041444	G-532
WL12-3P2451	1041448	G-533
WL12-3P2461	1041452	G-533
WL12-3V2431	1041537	G-532
WL12C-3P2432A70	1067775	G-533
WL12C-3P2432A71	1067776	G-533
WL12C-3P2432A91	1067777	G-533
WL12C-3P2432	1067774	G-533
WL12G-3B2531	1041456	G-522
WL12G-3N2572	1053530	G-522
WL12G-302431	1041457	G-522
WL12G-3P2572T01	1053546	G-523
WL12G-3P2572	1053535	G-522
WL12G-3P2582 WI 12G-3V2572	1053536	G-522
WL12G-3V2572 WL12G-3W2572	1053537	G-523
WL12GC-3P2472A70	1053538	G-523
WL12GC-3F2472A70 WL12GC-3P2472A71	1067778	G-523
WL12GC-3P2472A71 WL12GC-3P2472A91	1067779 1061063	G-523
WL12GC-3P2472		G-523
WL12L-2B520	1054087	G-523
WL12L-2B530	1018253	G-512
WL12L-2B531	1018252	G-512 G-512
WL12I-2P130	1047959 1022041	G-512
WL14-2K930S11	1046864	G-512
WL14-2N130	1026047	G-547
WL14-2N430	1026048	G-547
WL14-2P030S13	1051200	G-547
WL14-2P130	1026050	G-547
WL14-2P430S03	1029850	G-547
WL14-2P430	1026049	G-547
WL14-2P431	1050271	G-547
WL15-A1130	1046279	I-769
WL15-A2430	1043323	I-769
WL15-B1130	1046280	I-769
WL15-B2430	1043324	I-769
WL15-E1133	1046149	I-769
WL15-E2433	1043318	I-769
WL15-F1133	1046150	I-769
WL15-F2433	1043319	I-769

Model name	Part no.	Page
WL15-N1130	1044304	I-769
WL15-N2430	1043320	I-769
WL15-P1130	1044303	I-769
WL15-P2430S01	1054623	I-769
WL15-P2430	1043321	I-769
WL18-3N130	1025913	G-560
WL18-3N430	1025915	G-560
WL18-3N630	1025916	G-560
WL18-3N730	1026030	G-560
WL18-3P130	1025909	G-560
WL18-3P430	1025911	G-560
WL18-3P630	1025912	G-560
WL18-3P730	1026029	G-560
WL18X-3P930	1029902	G-560
WL2000-B1302	7023044	H-674
WL2000-B1322	7023046	H-674
WL2000-B4300	7024002	H-674
WL2000-B5300	7023047	H-674
WL2000-B5320	7023049	H-674
WL2000-R1302	7023050	H-675
WL2000-R1322	7023052	H-675
WL2000-R5300	7023053	H-675
WL2000-R5320	7023055	H-675
WL23-2N2430	1027787	H-583
WL23-2P1130	1027784	H-583
WL23-2P2430S01	1041159	H-583
WL23-2P2430	1027785	H-583
WL23-2P2460	1044165	H-583
WL23-2P3430	1027786	H-583
WL24-2B230	1015852	H-593
WL24-2B240	1017859	H-593
WL24-2B430	1017860	H-593
WL24-2B440	1017879	H-593
WL24-2R230	1017857	H-594
WL24-2R240	1017858	H-594
WL24-2V230	1017880	H-593
WL24-2V240	1018024	H-593
WL24-2V530S04	1023550	H-593
WL24-2V530	1017881	H-593
WL24-2V540	1018025	H-593
WL24-2X230	1026036	H-604
WL24-2X430	1026037	H-604
WL250-2F2431	6044702	H-643
WL250-2N1131	6044695	H-643
WL250-2N2431	6044696	H-643
WL250-2P1131	6044697	H-643
WL250-2P1231	6044698	H-643
WL250-2P2431	6044699	H-643
WL250-2R1531	6044700	H-644
WL250-2R1631	6044701	H-644
WL27-3E2631	1027773	H-620
WL27-3F2631	1027772	H-620
WL27-3K2430	1028069	H-620
WL27-3P1102S16	1050825	E-136
WL27-3P1131	1027768	H-620
WL27-3P2402S18	1051577	E-136
WL27-3P2430S01	1028057	H-620
WL27-3P2430	1027769	H-620

Model name	Part no.	Page
WL27-3P2431	1027982	H-620
WL27-3P2450	1027771	H-620
WL27-3P2451	1027770	H-620
WL27-3P2460S14	1047908	H-620
WL27-3P2461	1044166	H-620
WL27-3P3402S13	1046538	E-136
WL27-3P3402S15	1048230	E-136
WL27-3P3402S17	1051529	E-136
WL27-3P3402S19	1056382	E-136
WL27-3P3402S20	1060755	E-136
WL27-3P3431	1029081	H-620
WL27-3P3460	1047955	H-620
WL27-3R2631	1027776	H-621
WL27-3S1531	1027775	H-621
WL27-3V2430	1028063	H-620
WL27X-3P1831	1027989	H-634
WL27X-3P3431	1029955	H-634
WL280-2H1531	6044739	H-657
WL280-2H1631	6044740	H-657
WL280-2H4331	6044738	H-657
WL280-2N1131	6044735	H-656
WL280-2N2431	6044737	H-656
WL280-2N4331	6044733	H-656
WL280-2P1131	6044734	H-656
WL280-2P2431	6044736	H-656
WL280-2P4331	6044732	H-656
WL280-2R1531	6044761	H-657
WL280-2R4331	6044760	H-657
WL2S-2E1330	1064596	F-220
WL2S-2F1330	1064591	F-220
WL2S-2F3130	1064593	F-220
WL2S-2K3230	1064594	F-220
WL2S-2N1130	1063571	F-220
WL2S-2N1330	1064595	F-220
WL2S-2P1330	1064590	F-220
WL2S-2P3130	1064592	F-220
WL2S-2P3230	1063572	F-220
WL2SG-2E1135	1065930	F-234
WL2SG-2F3235	1063647	F-234
WL2SG-2N1135	1065934	F-234
WL2SG-2P3235	1065939	F-234
WL2SGC-2P3234	1063648	F-234
WL4-3E1330	1028156	F-242
WL4-3E2130	1028158	F-242
WL4-3F1330	1028152	F-242
WL4-3F2130	1028155	F-242
WL4-3N1330	1028133	F-242
WL4-3N2130	1028151	F-242
WL4-3P1330	1028131	F-242
WL4-3P2130	1028143	F-242 F-242
WL4-3P2230	1028147	F-242 F-242
WL4S-3E1330V		F-242 F-264
WL4S-3E1330V WL4S-3E1330	1046420	
WL4S-3E1330 WL4S-3E1332	1042072	F-301
WL4S-3E1332 WL4S-3E2130V	1042081	F-264
WL4S-3E2130V WL4S-3E2130	1045097	F-264
WL4S-3E2130V	1042071	F-301
WL4S-3E2132V WL4S-3E2132	1046435	F-264
WLTO-JLZIJZ	1042080	F-301

Madalasas		_
Model name	Part no.	Page
WL4S-3F1330	1042068	F-264
WL4S-3F1332V	1046430	F-264
WL4S-3F1332	1042076	F-301
WL4S-3F2130V	1045096	F-264
WL4S-3F2130	1042065	F-301
WL4S-3F2132V	1046428	F-264
WL4S-3F2132	1042074	F-301
WL4S-3N1130H	1048116	F-323
WL4S-3N1132H	1048119	F-323
WL4S-3N1330	1042073	F-264
WL4S-3N1332	1042082	F-264
WL4S-3N2132V	1046432	F-301
WL4S-3N2432V	1054722	F-301
WL4S-3P1330V	1048044	F-301
WL4S-3P1332V	1046427	F-301
WL4S-3P2130	1042069	F-264
WL4S-3P2132V	1046424	F-264
WL4S-3P2132	1042077	F-301
WL4S-3P2230V	1045095	F-264
WL4S-3P2230	1042066	F-301
WL4S-3P2232V	1046421	F-264
WL4S-3P2232	1040421	F-301
WL4S-3P2432V	1042078	
WL4S-3P3230H		F-301
WL4S-3P3230H	1048115	F-323
WL4S-3P5232H WL4S-3P5230H	1048117	F-323
WL4S-3V2232V	1057052	F-323
	1046422	F-265
WL4S-3V2232	1042079	F-302
WL4S-3V3232H	1048118	F-323
WL4S-3W1132	1042083	F-264
WL4SC-3P2232A70	1067760	F-264
WL4SC-3P2232A71	1067761	F-264
WL4SC-3P2232A91	1067762	F-264
WL4SC-3P2232	1065315	F-264
WL4SL-3E1134	1061566	F-280
WL4SL-3F2234	1061562	F-280
WL4SL-3F3234	1061564	F-280
WL4SL-3N1132	1061565	F-280
WL4SL-3P2232	1061561	F-280
WL4SL-3P3232	1061563	F-280
WL4SLC-3P2232	1061569	F-281
WL4SLG-3E1134	1058248	F-292
WL4SLG-3F2234V	1058260	F-292
WL4SLG-3F2234	1058244	F-352
WL4SLG-3F2434V	1058263	F-352
WL4SLG-3F3234	1058246	F-292
WL4SLG-3F4134H	1058283	F-366
WL4SLG-3F5234H	1058278	F-366
WL4SLG-3N1132	1058247	F-292
WL4SLG-3N4132H	1058284	F-366
WL4SLG-3P1132V	1058266	F-352
WL4SLG-3P2232V	1058258	F-292
WL4SLG-3P2232	1058243	F-352
WL4SLG-3P2432V	1058261	F-352
WL4SLG-3P3232	1058245	F-292
WL4SLG-3P4132H	1058282	F-366
WL4SLG-3P5232H	1058276	F-366
WL4SLGC-3P2432V	1058262	F-352
	1000202	1-332

Model name	Part no.	Page
WL4SLGC-3P5232H	1058277	F-366
WL8-N1131V	6041477	F-389
WL8-N1131	6033176	F-374
WL8-N2131V	6041478	F-389
WL8-N2131	6033179	F-374
WL8-N2231V	6041479	F-389
WL8-N2231	6033181	F-374
WL8-P1131V	6041481	F-389
WL8-P1131	6033177	F-374
WL8-P2131V	6041482	F-389
WL8-P2131	6033180	F-374
WL8-P2231V	6041483	F-389
WL8-P2231	6033182	F-374
WL8G-N1131	6033183	F-382
WL8G-N2131	6033185	F-382
WL8G-N2231	6033187	F-382
WL8G-P1131	6033184	F-382
WL8G-P2131	6033186	F-382
WL8G-P2231	6033188	F-382
WL9-3N1130	1049069	G-451
WL9-3N1132	1049070	G-452
WL9-3N1162	1049068	G-451
WL9-3N2230	1049071	G-451
WL9-3N2430	1049073	G-451
WL9-3N2432	1049074	G-452
WL9-3N2462	1049072	G-451
WL9-3P1130	1049055	G-451
WL9-3P1132	1049056	G-452
WL9-3P1162	1049054	G-451
WL9-3P1232	1049057	G-452
WL9-3P2230	1049059	G-451
WL9-3P2232	1049060	G-452
WL9-3P2262	1049058	G-451
WL9-3P2430	1049062	G-451
WL9-3P2432	1049063	G-452
WL9-3P2462	1049061	G-451
WL9-3P3430	1049066	G-451
WL9-3P3432	1049067	G-452
WL9-3P3462	1049065	G-451
WL9G-3N1132	1049085	G-464
WL9G-3N2432	1054152	G-464
WL9G-3P1132	1049081	G-464
WL9G-3P2232	1049082	G-464
WL9G-3P2432	1049083	G-464
WL9G-3P3432	1049084	G-464
WL9L-3N2232	1058172	G-473
WL9L-3N2432	1058172	G-473
WL9L-3P1132	1058233	G-473
WL9L-3P2232	1058174	G-473
WL9L-3P2432	1058174	G-473
WL9L-3P3432	1058175	G-473
WL9LG-3P1132	1058176	
WL9LG-3P2232		G-486
WL9LG-3F2232 WL9LG-3P2432	1058234	G-486
WL9HG-3F2432 WL9M4-3N1132	1058235	G-486
WL9M4-3N1132 WL9M4-3N2232	1051892	G-452
WL9M4-3N2232 WL9M4-3P1132	1051893	G-452
WL9M4-3P1132 WL9M4-3P2232	1051894	G-452
WESWIT-SI ZZSZ	1051895	G-452

	_	
Model name	Part no.	Page
WL9M4-3P2432	1051896	G-452
WL9M4-3P3432	1051907	G-452
WL9M4G-3N1132	1051897	G-464
WL9M4G-3P1132	1051898	G-464
WL9M4G-3P2232	1051899	G-464
WL9M4G-3P2432	1051900	G-464
WL9M4G-3P3432	1051910	G-464
WL9M4L-3P1132	1058229	G-473
WL9M4L-3P2232	1058227	G-473
WL9M4L-3P2432	1058228	G-473
WLG4-3E1332	1028131	F-256
WLG4-3E2132	1028132	F-256
WLG4-3F2132	1028127	F-256
WLG4-3F2234	1028130	F-256
WLG4-3F3434	1043683	F-256
WLG4-3P1332	1042844	F-256
WLG4-3P2132	1029567	F-256
WLG4S-3E1134H	1048124	F-336
WLG4S-3E1134V	1048027	F-314
WLG4S-3E1134	1042085	F-274
WLG4S-3E1135H	1048126	F-336
WLG4S-3E1135V	1046438	F-314
WLG4S-3F2234V	1047653	F-314
WLG4S-3F2234	1042084	F-274
WLG4S-3F2235V	1045098	F-314
WLG4S-3F2434V	1054727	F-314
WLG4S-3F3234H	1048121	F-336
WLG4S-3N1132H	1048123	F-336
WLG4S-3N1132V	1046450	F-314
WLG4S-3N1332	1046111	F-274
WLG4S-3N2432V	1054728	F-314
WLG4S-3P1132V	1055044	F-314
WLG4S-3P2232V	1046446	F-274
WLG4S-3P2232	1044186	F-314
WLG4S-3P2234	1052999	F-274
WLG4S-3P2432V	1054725	F-314
WLG4S-3P3232H	1048120	F-336
WLG4S-3P5232H	1057053	F-336
WLG4S-3V1132	1057055	F-274
WLG4S-3V2232V	1046447	F-314
WLG4S-3V2232	1040447	F-274
WLG4S-3V3232H	1042087	F-336
WLG4S-3W1132		
WLG45-3W1132 WLG4SC-3P2232A70	1042086 1067763	F-274 F-274
WLG4SC-3P2232A70	1067765	
WLG4SC-3P2232A71 WLG4SC-3P2232A91		F-274
WLG4SC-3P2232	1067766	F-274
WLL170-2N132	1057177	F-274
	6029515	J-792
WLL170-2N162	6029531	J-792
WLL170-2N192	6029523	J-792
WLL170-2N330	6029517	J-792
WLL170-2N360	6029533	J-792
WLL170-2N390	6029525	J-792
WLL170-2N430	6029518	J-792
WLL170-2N460	6029534	J-792
WLL170-2N490	6029526	J-792
WLL170-2P132	6029511	J-792
WLL170-2P162	6029527	J-792

Model name	Part no.	Page
WLL170-2P192	6029519	J-792
WLL170-2P330	6029513	J-792
WLL170-2P360	6029529	J-792
WLL170-2P390	6029521	J-792
WLL170-2P430	6029514	J-792
WLL170-2P460	6029530	J-792
WLL170-2P490	6029522	J-792
WLL170T-2N132	6033951	J-793
WLL170T-2N162	6033960	J-793
WLL170T-2N192	6033957	J-793
WLL170T-2N330	6033952	J-793
WLL170T-2N360	6033961	J-793
WLL170T-2N390	6033958	J-793
WLL170T-2N430	6033953	J-793
WLL170T-2N460	6033962	J-793
WLL170T-2N490	6033959	J-793
WLL170T-2P132	6033948	J-793
WLL170T-2P162	6033963	J-793
WLL170T-2P192	6033954	J-793
WLL170T-2P330	6033949	J-793
WLL170T-2P360	6033949	J-793 J-793
WLL170T-2P390	6033955	J-793
WLL170T-2P430	6033950	J-793 J-793
WLL170T-2P460	6033950	J-793 J-793
WLL170T-2P490	6033965	J-793 J-793
WLL180T-E232	6033930	J-793 J-801
WLL180T-E333	6049838	J-801 J-801
WLL180T-E434	6039104	J-801 J-801
WLL180T-E632		
WLL180T-F232	6050763	J-801
WLL180T-F333	6039098	J-801
WLL180T-F434	6042429	J-801
WLL180T-L333	6039102	J-801
WLL180T-L432	6049837	J-800
WLL180T-L434	6039099	J-800
WLL180T-M333	6039103	J-800
WLL180T-M432	6042428	J-800
WLL180T-M434	6039097	J-800
WLL180T-M634	6039101	J-800
WLL180T-N432	6050760	J-800
	6039094	J-800
WLL180T-N434 WLL180T-N474	6039096	J-800
	6039619	J-800
WLL180T-P432	6039093	J-800
WLL180T-P434	6039095	J-800
WLL180T-P474	6039618	J-800
WLR2100-D1311	7027185	E-162
WLR2100-D1312	7027753	E-162
WLR2100-D1321	7027754	E-162
WLR2100-D1322	7027755	E-162
WLR2100-D2311	7027808	E-162
WLR2100-D2312	7027811	E-162
WLR2100-D2321	7027809	E-162
WLR2100-D2322	7027810	E-162
WLT280L-2N1536	6048072	H-668
WLT280L-2N2536	6048070	H-668
WLT280L-2P1536	6048071	H-668
WLT280L-2P2536	6048069	H-668
WS/WE100-2N1439	6052363	F-407

Madalyana		_
Model name	Part no.	Page
WS/WE100-2N3439	6052364	F-407
WS/WE100-2N4439	6052365	F-407
WS/WE100-2P1439	6052366	F-407
WS/WE100-2P3439	6052367	F-407
WS/WE100-2P4439	6052368	F-407
WS/WE100L-E1131	6030717	F-415
WS/WE100L-E2131	6030718	F-415
WS/WE100L-E2231	6030719	F-415
WS/WE100L-F1131	6030714	F-415
WS/WE100L-F2131	6030715	F-415
WS/WE100L-F2231	6030716	F-415
WS/WE12L-2N410	1018257	G-513
WS/WE12L-2N430	1018255	G-513
WS/WE12L-2P410	1018256	G-513
WS/WE12L-2P430	1018254	G-513
WS/WE12L-2P431	1047960	G-513
WS/WE14-2N130	1026432	G-547
WS/WE14-2N430	1026433	G-547
WS/WE14-2P130	1026430	G-547
WS/WE14-2P430	1026431	G-547
WS/WE18-3N130	1025925	G-560
WS/WE18-3N630	1025926	G-560
WS/WE18-3P110	1025928	G-560
WS/WE18-3P130	1025922	G-560
WS/WE18-3P410	1025927	G-560
WS/WE18-3P430	1025923	G-560
WS/WE18-3P630	1025924	G-560
WS/WE2000-B1102	7025964	H-675
WS/WE2000-B1122	7025966	H-675
WS/WE2000-B4100	7028604	H-675
WS/WE2000-B5100	7025965	H-675
WS/WE2000-B5120	7025967	H-675
WS/WE2000-R1102	7025968	H-676
WS/WE2000-R1122	7025970	H-676
WS/WE2000-R5100	7025969	H-676
WS/WE2000-R5120	7025971	H-676
WS/WE24-2B230	1017861	H-593
WS/WE24-2B240	1017862	H-593
WS/WE24-2B430	1017853	H-593
WS/WE24-2B440	1017875	H-593
WS/WE24-2R230	1017863	H-594
WS/WE24-2R240	1017864	H-594
WS/WE24-2V230	1017876	H-593
WS/WE24-2V530S01	1023549	H-593
WS/WE24-2V530	1023349	H-593
WS/WE2F-E110	6030554	F-210
WS/WE2F-F110	6030569	F-210 F-210
WS/WE2F-F210	6030569	F-210 F-210
WS/WE2F-F410	6030570	F-210 F-210
WS/WE2F-N110	6030571	F-210 F-210
WS/WE2F-P110	6030340	F-210 F-210
WS/WE2F-P110 WS/WE2F-P210		
WSE11-2N1130	6030566	F-210
WSE11-2N1130 WSE11-2N2430	1057574	G-495
WSE11-2N2430 WSE11-2P1130	1057573	G-495
WSE11-2P1130 WSE11-2P2430	1057572	G-495
WSE11-2P2430 WSE12-3N1131	1057571	G-495
WSE12-3N2431	1041463	G-533
WOLIZ-ONZ431	1041462	G-533

WSE12-3P1131 1041460 G-533 WSE12-3P2431 1041459 G-533 WSE12-3P2431 1067781 G-534 WSE12-3P2430A71 1067782 G-534 WSE12-3P2430A91 1067783 G-534 WSE12-3P2430A91 1067783 G-534 WSE12-3P2430 1067780 G-534 WSE15-A1130 1046285 I-769 WSE15-B1130 1046286 I-769 WSE15-B1130 1046286 I-769 WSE15-B2430 1043327 I-769 WSE15-B2430 1043328 I-769 WSE15-B2430 1043328 I-769 WSE250-2P2431 G044706 H-643 WSE250-2P1311 G044709 H-643 WSE250-2P131 G044704 H-643 WSE250-2P131 G044704 H-643 WSE250-2P131 G044705 H-644 WSE250-2P131 G044707 H-644 WSE250-2P131 G044707 H-644 WSE250-2P131 G044708 H-643 WSE250-2P131 G044707 H-644 WSE27-3P2431 G044708 H-643 WSE25-3P2431 G044707 H-644 WSE27-3P2431 G044708 H-643 WSE27-3P2450 1027792 H-621 WSE27-3P110 1028059 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2450 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE280-2H1331 6044744 H-657 WSE280-2H1331 6044744 H-657 WSE280-2H1331 6044744 H-657 WSE280-2H331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044746 H-657 WSE280-2P1331 6044762 H-657 WSE280-2P330 1064586 F-221 WSE27-3P300 1028175 F-242 WSE25-2P330 1064586 F-221 WSE25-2P330 1064586 F-221 WSE25-2P330 1028166 F-242 WSE4-3P130 1028167 F-242 WSE4-3P130 1028169 F-242 WSE4-3P130 1028160 F-242	Model name	Denter	Deste
WSE12-3P2431 1041459 G-533 WSE12C-3P2430A70 1067781 G-534 WSE12C-3P2430A71 1067782 G-534 WSE12C-3P2430A91 1067783 G-534 WSE12C-3P2430A91 1067783 G-534 WSE12C-3P2430 1067780 G-534 WSE15-A1130 1046285 I-769 WSE15-A2430 1043327 I-769 WSE15-B1130 1046286 I-769 WSE15-B2430 1043328 I-769 WSE250-2P2431 6044706 H-643 WSE250-2P131 6044709 H-643 WSE250-2P131 6044701 H-643 WSE250-2P131 6044703 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044707 H-644 WSE250-2P2431 6044707 H-644 WSE250-2P131 6044708 H-643 WSE250-2P131 6044707 H-644 WSE25-2P131 6044708 H-641 WSE27-3P2430 1027792 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027795 H-622 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027795 H-622 WSE27-3P2430 1027795 H-622 WSE27-3P2430 1027795 H-621 WSE27-3P2430 1027795 H-620 WSE27-3P2430 1027795 H-621 WSE20-2P1331 6044748 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1330 1064586 F-221 WSE2S-2F3330 1064588 F-221 WSE2S-2F3330 1064586 F-221 WSE2S-2P3330 1063650 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P130 1028163 F-242		Part no.	Page
WSE12C-3P2430A70 1067781 G-534 WSE12C-3P2430A71 1067782 G-534 WSE12C-3P2430A91 1067783 G-534 WSE12C-3P2430A91 1067780 G-534 WSE12C-3P2430 1067780 G-534 WSE15-A1130 1046285 1-769 WSE15-A2430 1043327 1-769 WSE15-B1130 1046286 1-769 WSE15-B2430 1043328 1-769 WSE250-2P2431 6044706 H-643 WSE250-2P131 6044709 H-643 WSE250-2P131 6044701 H-643 WSE250-2P131 6044703 H-643 WSE250-2P131 6044703 H-643 WSE250-2P131 6044705 H-643 WSE250-2P2431 6044707 H-644 WSE250-2P2431 6044707 H-644 WSE27-3P2431 6044708 H-643 WSE250-2P131 6044708 H-643 WSE250-2P131 6044708 H-641 WSE27-3P2430 1027792 H-621 WSE27-3P2430 1027792 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 1027791 H-621 WSE20-2P1331 6044744 H-657 WSE280-2H1331 6044744 H-657 WSE280-2H1331 6044744 H-657 WSE280-2H331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 604586 F-221 WSE2S-2F3330 1064586 F-221 WSE2S-2F3330 1064586 F-221 WSE2S-2P3330 1064586 F-221 WSE2S-2P3330 1063581 F-221 WSE2S-2P3330 1063581 F-221 WSE2S-2P3330 1063586 F-242 WSE4-3F1330 1028167 F-242 WSE4-3F1330 1028163 F-242 WSE4-3F1330 1028163 F-242 WSE4-3F1330 1028166 F-242 WSE4-3F1330 1028166 F-242 WSE4-3F1330 1028166 F-242 WSE4-3F1330 1028163 F-242			
WSE12C-3P2430A71 1067782 G-534 WSE12C-3P2430A91 1067783 G-534 WSE12C-3P2430 1067780 G-534 WSE15-A1130 1046285 I-769 WSE15-A2430 1043227 I-769 WSE15-B130 1046286 I-769 WSE15-B130 1046286 I-769 WSE15-B2430 1043328 I-769 WSE250-2P2431 6044706 H-643 WSE250-2P131 6044709 H-643 WSE250-2P131 6044701 H-643 WSE250-2P131 6044703 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044707 H-644 WSE250-2P131 6044707 H-644 WSE250-2P131 6044707 H-644 WSE250-2P131 1027793 H-621 WSE27-3P2430 1027792 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P3830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1531 6044748 H-657 WSE280-2H1531 6044744 H-657 WSE280-2H1531 6044744 H-657 WSE280-2H1531 6044744 H-657 WSE280-2H131 6044744 H-657 WSE280-2H331 6044744 H-657 WSE280-2H331 6044744 H-657 WSE280-2P131 6044745 H-657 WSE280-2P131 6044745 H-657 WSE280-2P131 6044762 H-657 WSE280-2P131 6044762 H-657 WSE280-2P1330 1064586 F-221 WSE25-2P1330 1064586 F-221 WSE25-2P1330 1064586 F-221 WSE25-2P1330 1064586 F-221 WSE25-2P1330 1064584 F-221 WSE25-2P1330 1064586 F-224 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028166 F-242			
WSE12C-3P2430A91 1067783 G-534 WSE12C-3P2430 1067780 G-534 WSE15-A1130 1046285 I-769 WSE15-B1130 1043327 I-769 WSE15-B1130 1046286 I-769 WSE15-B2430 1043328 I-769 WSE15-B2430 1043328 I-769 WSE250-2P2431 6044706 H-643 WSE250-2P1431 6044709 H-643 WSE250-2P131 6044701 H-643 WSE250-2P131 6044704 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044705 H-643 WSE250-2P131 6044707 H-644 WSE27-3P2631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P1710 1028059 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027795 H-622 WSE27-3P2450 1027791 H-621 WSE27-3P2430 1027991 H-634 WSE280-2H1631 6044748 H-657 WSE280-2H1631 6044748 H-657 WSE280-2H1631 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044762 H-657 WSE280-2P1330 1064586 F-221 WSE25-2P1330 1064586 F-221 WSE25-2P1330 1064584 F-221 WSE25-2P1330 1064584 F-221 WSE25-2P330 1064586 F-221 WSE25-2P330 1064586 F-221 WSE25-2P330 1064586 F-221 WSE25-2P330 1064586 F-224 WSE4-3P130 1028167 F-242 WSE4-3P130 1028166 F-242 WSE4-3P130 1028166 F-242		20002	
WSE12C-3P2430		1067782	G-534
WSE15-A1130		1067783	G-534
WSE15-A2430		1067780	G-534
WSE15-B1130		1046285	I-769
WSE15-B2430 1043328 1-769 WSE250-2F2431 6044706 H-643 WSE250-2N1131 6044709 H-643 WSE250-2N1131 6044709 H-643 WSE250-2P1231 6044701 H-643 WSE250-2P1231 6044704 H-643 WSE250-2P1231 6044705 H-643 WSE250-2P1231 6044705 H-643 WSE250-2P1231 6044707 H-644 WSE250-2R1631 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE27-3E2631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3P130 1047803 H-621 WSE27-3N130 1047803 H-621 WSE27-3N1430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2430 1027791 H-621 WSE27-3P2430 104749 H-657 WSE280-2H1631 6044748 H-657 WSE280-2H1631 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P330 1064586 F-221 WSE28-2E1330 1064586 F-221 WSE28-2F330 1064586 F-221 WSE28-2P330 1065940 F-221 WSE28-2P1330 1063523 F-221 WSE28-2P1330 1063521 F-221 WSE28-2P1330 1063521 F-221 WSE28-2P1330 1064584 F-221 WSE28-2P1330 1064586 F-221 WSE28-2P1330 1064584 F-221 WSE28-2P1330 1063521 F-221 WSE28-2P1330 1064586 F-221 WSE28-2P1330 1064589 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028169 F-242	WSE15-A2430	1043327	I-769
WSE250-2F2431 6044706 H-643 WSE250-2N1131 6044709 H-643 WSE250-2N2431 6044711 H-643 WSE250-2P1131 6044703 H-643 WSE250-2P1231 6044704 H-643 WSE250-2P1231 6044705 H-643 WSE250-2P2431 6044707 H-644 WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044707 H-644 WSE250-2R1631 1027793 H-621 WSE27-3F2631 1027792 H-621 WSE27-3N2430 1027792 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P1710 1028059 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-622 WSE27-3R2631 6044748 H-657 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N4131 6044744 H-657 WSE280-2N431 6044746 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044746 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P330 1064586 F-221 WSE28-2B1330 1064586 F-221 WSE28-2F1330 1065584 F-221 WSE28-2P1330 10655940 F-221 WSE28-2P1330 10655940 F-221 WSE28-2P1330 1065594 F-221 WSE28-2P330 1065650 F-221 WSE28-2P330 1065650 F-221 WSE28-2P330 1064586 F-224 WSE4-3P130 1028167 F-242 WSE4-3P130 1028167 F-242 WSE4-3P130 1028169 F-242 WSE4-3P130 1028169 F-242 WSE4-3P130 1028169 F-242 WSE4-3P130 1028169 F-242	WSE15-B1130	1046286	I-769
WSE250-2N1131 6044709 H-643 WSE250-2N2431 6044701 H-643 WSE250-2P1131 6044703 H-643 WSE250-2P1231 6044704 H-643 WSE250-2P1231 6044705 H-643 WSE250-2P1231 6044707 H-644 WSE250-2R1631 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE27-3R2631 1027792 H-621 WSE27-3R2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N1130 1028072 H-621 WSE27-3P2430 1028072 H-621 WSE27-3P24410 1048199 H-620 WSE27-3P2440 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H1631 6044744 H-657 WSE280-2N2431 6044744 H-657 WSE280-2N2431 6044744 H-657 WSE280-2N4331 6044742 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044741 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P331 6044741 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044762 H-657 WSE280-2P331 6044762 H-657 WSE280-2P331 6044762 H-657 WSE28-2P330 1064586 F-221 WSE2S-2F330 1064586 F-221 WSE2S-2F330 1064586 F-221 WSE2S-2P330 1063523 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 106350 F-221 WSE2S-3P330 1028167 F-242 WSE4-3P1330 1028163 F-242	WSE15-B2430	1043328	I-769
WSE250-2N2431 6044711 H-643 WSE250-2P1131 6044703 H-643 WSE250-2P1231 6044704 H-643 WSE250-2P1231 6044705 H-643 WSE250-2R1531 6044707 H-644 WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE27-3E2631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2410 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-651 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2P131 6044746 H-657 WSE280-2P131 6044741 H-657 WSE280-2P131 6044741 H-657 WSE280-2P131 6044741 H-657 WSE280-2P131 6044741 H-657 WSE280-2P1331 6044741 H-657 WSE280-2P1331 6044741 H-657 WSE280-2P1331 6044741 H-657 WSE280-2P3331 6044745 H-657 WSE280-2P3331 6044763 H-657 WSE280-2P3331 6044763 H-657 WSE280-2P3330 1063563 F-221 WSE2S-2P3330 1063560 F-221 WSE2S-2P3330 1063560 F-221 WSE2S-2P3330 1063650 F-221 WSE3-3P330 1028168 F-242 WSE4-3P330 1028167 F-242 WSE4-3P1330 1028163 F-242	WSE250-2F2431	6044706	H-643
WSE250-2P1131 6044703 H-643 WSE250-2P1231 6044704 H-643 WSE250-2P2431 6044705 H-643 WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE250-2R1631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3P2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-625 WSE27-3P2450 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H131 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2P1131 6044744 H-657 WSE280-2P1131 6044744 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044763 H-657 WSE280-2P4331 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R1330 1064586 F-221 WSE2S-2F1330 1064588 F-221 WSE2S-2F1330 1064584 F-221 WSE2S-2P1330 1064584 F-221 WSE2S-2P1330 1064584 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028172 F-242 WSE4-3F1330 1028167 F-242 WSE4-3P1330 1028163 F-242	WSE250-2N1131	6044709	H-643
WSE250-2P1231 6044704 H-643 WSE250-2P2431 6044705 H-643 WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE250-2R1631 6044708 H-644 WSE27-3E2631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3N2130 1028072 H-621 WSE27-3N2130 1028079 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-622 WSE27-3P2450 1027791 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H1631 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N2431 6044746 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P1131 6044741 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P330 1064586 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064586 F-221 WSE28-2-21330 1064584 F-221 WSE28-2-21330 1064586 F-242 WSE4-3-2130 1028167 F-242 WSE4-3-3-1330 1028163 F-242	WSE250-2N2431	6044711	H-643
WSE250-2P2431 6044705 H-643 WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE27-3P2631 1027793 H-621 WSE27-3P2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027795 H-622 WSE27-3P2450 1027791 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044747 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2P4331 6044744 H-657 WSE280-2P4331 6044744 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P331 6044763 H-657 WSE280-2P331 6044762 H-657 WSE280-2R1531 6044762 H-657 WSE280-2R1531 6044762 H-657 WSE28-2F3130 1064586 F-221 WSE2S-2F3130 1064586 F-221 WSE2S-2F3130 1064584 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028175 F-242 WSE4-3F1330 1028167 F-242 WSE4-3F1330 1028167 F-242 WSE4-3P1330 1028163 F-242	WSE250-2P1131	6044703	H-643
WSE250-2R1531 6044707 H-644 WSE250-2R1631 6044708 H-644 WSE27-3E2631 1027793 H-621 WSE27-3F2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N1430 1028072 H-621 WSE27-3P2410 1028059 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-622 WSE27-3R2631 6044748 H-657 WSE280-2H1531 6044749 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N2431 6044744 H-657 WSE280-2N4331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044743 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P331 6044746 H-657 WSE280-2P331 6044763 H-657 WSE280-2R331 6044762 H-657 WSE280-2R331 6044762 H-657 WSE280-2R330 1064586 F-221 WSE2S-2F330 1064588 F-221 WSE2S-2F330 1063523 F-221 WSE2S-2P330 1063523 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063560 F-221 WSE2S-2P330 1063560 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028175 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028167 F-242 WSE4-3P1330 1028165 F-242	WSE250-2P1231	6044704	H-643
WSE250-2R1631 6044708 H-644 WSE27-3E2631 1027793 H-621 WSE27-3F2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1531 6044749 H-657 WSE280-2H1631 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N2431 6044745 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044741 H-657 WSE280-2P331 6044741 H-657 WSE280-2P331 6044763 H-657 WSE280-2R331 6044763 H-657 WSE280-2R331 6044763 H-657 WSE280-2R331 1064586 F-221 WSE2S-2E330 1064586 F-221 WSE2S-2F330 1064584 F-221 WSE2S-2P330 1063523 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063560 F-221 WSE2S-2P330 1028175 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028166 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242	WSE250-2P2431	6044705	H-643
WSE27-3E2631 1027793 H-621 WSE27-3F2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1028059 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2450 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3P2450 1027791 H-622 WSE27-3P2450 1027791 H-624 WSE27-3P2450 1027795 H-622 WSE27-3P1830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N2431 6044742 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P1331 6044741 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044763 H-657 WSE280-2R4331 6044763 H-657 WSE280-2R4331 6044763 H-657 WSE28-2P3130 1064586 F-221 WSE2S-2E1330 1064586 F-221 WSE2S-2F3130 1064584 F-221 WSE2S-2P3130 1063523 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028175 F-242 WSE4-3P1330 1028175 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242	WSE250-2R1531	6044707	H-644
WSE27-3F2631 1027792 H-621 WSE27-3N1130 1047803 H-621 WSE27-3N2430 1028072 H-621 WSE27-3P2410 1048199 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2450 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044744 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P1331 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044745 H-657 WSE280-2P331 6044763 H-657 WSE280-2P331 6044763 H-657 WSE280-2R331 6044762 H-657 WSE280-2R331 1064586 F-221 WSE2S-2E3130 1064586 F-221 WSE2S-2F3130 1064584 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028172 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028164 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242	WSE250-2R1631	6044708	H-644
WSE27-3N1130	WSE27-3E2631	1027793	H-621
WSE27-3N2430 1028072 H-621 WSE27-3P1710 1028059 H-620 WSE27-3P2410 1048199 H-620 WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27-3R2631 1027795 H-622 WSE27-3P1830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N131 6044744 H-657 WSE280-2N2431 6044745 H-657 WSE280-2P131 6044745 H-657 WSE280-2P131 6044745 H-657 WSE280-2P431 6044745 H-657 WSE280-2P3131 6044763 H-657 WSE280-2P4331 6044763 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R331 6044762 H-657 WSE28-2R330 1064586 F-221 WSE2S-2F3130 1064586 F-221 WSE2S-2F3130 1064584 F-221 WSE2S-2P3130 1063523 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1028172 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028164 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028169 F-242	WSE27-3F2631	1027792	H-621
WSE27-3P1710  WSE27-3P2410  WSE27-3P2430  WSE27-3P2430  USE27-3P2450  WSE27-3P2450  WSE27-3P2450  WSE27-3R2631  WSE27-3R2631  WSE27-3R2631  WSE280-2H1531  WSE280-2H1631  WSE280-2H4331  WSE280-2N4331  WSE280-2N4331  WSE280-2N4331  WSE280-2P4331  WSE280-2P330  WSE280-2P330  WSE280-2R4331  WSE280-2P330  WSE280-2R4331  WSE280-2P330  WSE280-2R4331  WSE280-2P330  WSE280-2P330  WSE280-2P330  WSE280-2P330  WSE28-2P330  WSE28-3P330  WSE38-3P330  WSE4-3P1330  WSE4-3	WSE27-3N1130	1047803	H-621
WSE27-3P2410  WSE27-3P2430  WSE27-3P2430  USE27-3P2450  WSE27-3P2450  WSE27-3R2631  WSE27-3R2631  WSE27-3R2631  U027795  H-621  WSE27-3R2631  U027795  H-622  WSE27X-3P1830  1027991  H-634  WSE280-2H1531  6044748  H-657  WSE280-2H1631  6044749  H-657  WSE280-2H4331  6044744  H-657  WSE280-2N1131  6044744  H-657  WSE280-2N2431  6044742  H-657  WSE280-2P1131  6044743  H-657  WSE280-2P131  6044745  H-657  WSE280-2P2431  6044741  H-657  WSE280-2P4331  6044741  H-657  WSE280-2P4331  6044763  H-657  WSE280-2R4331  6044762  H-657  WSE280-2R4331  6044762  H-657  WSE28-2E1330  1064586  F-221  WSE2S-2E3130  1064588  F-221  WSE2S-2F3130  1063523  F-221  WSE2S-2F3130  1063523  F-221  WSE2S-2P1330  1063523  F-221  WSE2S-2P1330  1063520  F-221  WSE2S-2P1330  1063521  F-221  WSE2S-2P3130  1063521  F-221  WSE2S-2P3230  1063650  F-221  WSE2S-2P330  1063650  F-221  WSE3-3P1330  1028172  F-242  WSE4-3F1330  1028167  F-242  WSE4-3P1330  1028167  F-242  WSE4-3P130  1028163  F-242  WSE4-3P130  1028163  F-242	WSE27-3N2430	1028072	H-621
WSE27-3P2430 1027790 H-621 WSE27-3P2450 1027791 H-621 WSE27-3R2631 1027795 H-622 WSE27X-3P1830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H131 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N2431 6044742 H-657 WSE280-2N4331 6044742 H-657 WSE280-2P4331 6044743 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R4331 6044763 H-657 WSE280-2R4331 6044763 H-657 WSE280-2R330 1064586 F-221 WSE2S-2E3130 1064586 F-221 WSE2S-2F3130 1064588 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N130 1063523 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028169 F-242	WSE27-3P1710	1028059	H-620
WSE27-3P2430 WSE27-3P2450 WSE27-3P2450 WSE27-3P2631 WSE27-3R2631 U027795 H-622 WSE27X-3P1830 U027991 H-634 WSE280-2H1531 G044748 H-657 WSE280-2H1631 G044749 H-657 WSE280-2H4331 G044744 H-657 WSE280-2N2431 G044746 WSE280-2N2431 G044742 WSE280-2N4331 G044743 H-657 WSE280-2N4331 G044744 H-657 WSE280-2P131 G044745 WSE280-2P2431 G044745 WSE280-2P431 G044745 WSE280-2P331 G044741 H-657 WSE280-2P4331 G044763 WSE280-2R4331 G044763 WSE280-2R4331 G044762 WSE280-2R4331 G044762 WSE280-2R331 G044762 WSE2S-2E1330 U064586 F-221 WSE2S-2E3130 U064588 F-221 WSE2S-2F3130 U064584 F-221 WSE2S-2P3130 U063523 F-221 WSE2S-2P1330 U063523 F-221 WSE2S-2P1330 U063521 F-221 WSE2S-2P1330 U063521 F-221 WSE2S-2P330 U063521 F-221 WSE2S-2P330 U063650 F-221 WSE2S-2P330 U028175 F-242 WSE4-3F1330 U028167 F-242 WSE4-3P1330 U028167 F-242 WSE4-3P1330 U028167 F-242 WSE4-3P1330 U028165 F-242 WSE4-3P1330 U028166	WSE27-3P2410	1048199	H-620
WSE27-3R2631 1027795 H-622 WSE27X-3P1830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N2431 6044744 H-657 WSE280-2N4331 6044742 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P131 6044745 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R1531 6044762 H-657 WSE280-2R330 1064586 F-221 WSE2S-2E1330 1064586 F-221 WSE2S-2F1330 1064588 F-221 WSE2S-2F1330 1063650 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1130 1063521 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P330 1028172 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242	WSE27-3P2430	1027790	
WSE27-3R2631 1027795 H-622 WSE27X-3P1830 1027991 H-634 WSE280-2H1531 6044748 H-657 WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N2431 6044742 H-657 WSE280-2N2431 6044743 H-657 WSE280-2P131 6044743 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R4331 6044763 H-657 WSE280-2R4331 6044763 H-657 WSE280-2R331 1064586 F-221 WSE2S-2E3130 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2P3130 1063523 F-221 WSE2S-2N130 1063660 F-221 WSE2S-2N130 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242	WSE27-3P2450	1027791	H-621
WSE27X-3P1830         1027991         H-634           WSE280-2H1531         6044748         H-657           WSE280-2H1631         6044749         H-657           WSE280-2H4331         6044747         H-657           WSE280-2N1131         6044744         H-657           WSE280-2N2431         6044746         H-657           WSE280-2P1131         6044743         H-657           WSE280-2P2431         6044745         H-657           WSE280-2P4331         6044741         H-657           WSE280-2R4331         6044763         H-657           WSE280-2R4331         6044762         H-657           WSE28-2E1330         1064586         F-221           WSE2S-2F3130         1064588         F-221           WSE2S-2F3130         1063523         F-221           WSE2S-2N1130         1063660         F-221           WSE2S-2P330         1064584         F-221           WSE2S-2P330         1063521         F-221           WSE2S-2P330         106350         F-221           WSE4-3E1330         1028172         F-242           WSE4-3F2130         1028175         F-242           WSE4-3F2130         1028164         F-242	WSE27-3R2631	1027795	
WSE280-2H1531       6044748       H-657         WSE280-2H1631       6044749       H-657         WSE280-2H4331       6044747       H-657         WSE280-2N1131       6044744       H-657         WSE280-2N4331       6044742       H-657         WSE280-2P1131       6044743       H-657         WSE280-2P2431       6044745       H-657         WSE280-2P4331       6044741       H-657         WSE280-2R1531       6044763       H-657         WSE280-2R4331       6044762       H-657         WSE28-2E1330       1064586       F-221         WSE2S-2E3130       1064588       F-221         WSE2S-2F1330       1063523       F-221         WSE2S-2N1130       1063660       F-221         WSE2S-2N1330       1064584       F-221         WSE2S-2P330       1063650       F-221         WSE2S-2P330       1063521       F-221         WSE2S-2P330       1063650       F-221         WSE4-3E1330       1028172       F-242         WSE4-3F2130       1028168       F-242         WSE4-3F2130       1028167       F-242         WSE4-3P1330       1028167       F-242         WSE4-3P130	WSE27X-3P1830		
WSE280-2H1631 6044749 H-657 WSE280-2H4331 6044744 H-657 WSE280-2N2431 6044746 H-657 WSE280-2N2431 6044742 H-657 WSE280-2N4331 6044743 H-657 WSE280-2P1131 6044745 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P431 6044741 H-657 WSE280-2P4331 6044763 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R1531 6044762 H-657 WSE280-2R331 1064586 F-221 WSE2S-2E1330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242	WSE280-2H1531		
WSE280-2H4331 6044747 H-657 WSE280-2N1131 6044744 H-657 WSE280-2N4331 6044742 H-657 WSE280-2N4331 6044742 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2P4331 6044763 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R330 1064586 F-221 WSE2S-2E1330 1064588 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063650 F-221 WSE2S-2P3130 1063650 F-221 WSE2S-2P3130 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028165 F-242	WSE280-2H1631		
WSE280-2N1131 6044744 H-657 WSE280-2N2431 6044746 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P431 6044741 H-657 WSE280-2P431 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R1531 6044762 H-657 WSE280-2R3130 1064586 F-221 WSE2S-2E1330 1064588 F-221 WSE2S-2E3130 1063523 F-221 WSE2S-2F1330 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N130 1063521 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P1330 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028169 F-242	WSE280-2H4331		
WSE280-2N2431 6044746 H-657 WSE280-2N4331 6044742 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063523 F-221 WSE2S-2N1130 1063521 F-221 WSE2S-2N130 1065940 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242	WSE280-2N1131		
WSE280-2N4331 6044742 H-657 WSE280-2P1131 6044743 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R4331 6044762 H-657 WSE28-2E1330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F1330 1063523 F-221 WSE2S-2F1330 1063523 F-221 WSE2S-2N1130 1063523 F-221 WSE2S-2N130 1063523 F-221 WSE2S-2N130 1063521 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242	WSE280-2N2431		
WSE280-2P1131 6044743 H-657 WSE280-2P2431 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R331 6044762 H-657 WSE280-2R330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F3130 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N130 1063521 F-221 WSE2S-2N130 1065940 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242	WSE280-2N4331		
WSE280-2P2431 6044745 H-657 WSE280-2P4331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R4331 6044762 H-657 WSE2S-2E1330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2V1130 1063523 F-221 WSE2S-2N130 1063523 F-221 WSE2S-2N130 1063521 F-221 WSE2S-2N130 1065940 F-221 WSE2S-2P330 1063521 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242	WSE280-2P1131		
WSE280-2P4331 6044741 H-657 WSE280-2R1531 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE280-2R4331 1064586 F-221 WSE2S-2E1330 1064588 F-221 WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N130 1064584 F-221 WSE2S-2N130 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3P1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242	WSE280-2P2431		
WSE280-2R1531 6044763 H-657 WSE280-2R4331 6044762 H-657 WSE2S-2E1330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N130 1063523 F-221 WSE2S-2N130 1063660 F-221 WSE2S-2N130 1064584 F-221 WSE2S-2N330 1064584 F-221 WSE2S-2P330 1065940 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028165 F-242	WSE280-2P4331		
WSE280-2R4331 6044762 H-657 WSE2S-2E1330 1064586 F-221 WSE2S-2E3130 1064588 F-221 WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N130 1063523 F-221 WSE2S-2N130 1063660 F-221 WSE2S-2N130 1064584 F-221 WSE2S-2P330 1065940 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE2S-2P330 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3F1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028168 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028163 F-242 WSE4-3P1330 1028163 F-242			
WSE2S-2E1330			
WSE2S-2E3130 1064588 F-221 WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028163 F-242			
WSE2S-2F1330 1965941 F-221 WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028163 F-242			
WSE2S-2F3130 1063523 F-221 WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N1330 1028167 F-242 WSE4-3N1330 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1330 1028163 F-242			
WSE2S-2N1130 1063660 F-221 WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028168 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE2S-2N1330 1064584 F-221 WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E1330 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE2S-2P1330 1065940 F-221 WSE2S-2P3130 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E2130 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028167 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028163 F-242			
WSE2S-2P3130 1063521 F-221 WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E2130 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F1330 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE2S-2P3230 1063650 F-221 WSE4-3E1330 1028172 F-242 WSE4-3E2130 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F2130 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P1330 1028169 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3E1330 1028172 F-242 WSE4-3E2130 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F2130 1028164 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028165 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3E2130 1028175 F-242 WSE4-3F1330 1028168 F-242 WSE4-3F2130 1028171 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3F1330 1028168 F-242 WSE4-3F2130 1028171 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3F2130 1028171 F-242 WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3N1330 1028164 F-242 WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3N2130 1028167 F-242 WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3P1330 1028159 F-242 WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3P1430 1029645 F-242 WSE4-3P2130 1028163 F-242			
WSE4-3P2130 1028163 F-242			
1020100			
WSE4-3P223U 1028160 F-242			
	WSE4-3P223U	1028160	F-242

Model name	Part no.	Page
WSE4S-3E1330H	1052868	F-324
WSE4S-3E1330V	1052869	F-302
WSE4S-3E1330	1052867	F-265
WSE4S-3E2130V	1052877	F-302
WSE4S-3E2130	1052876	F-265
WSE4S-3E3130H	1052870	F-324
WSE4S-3F1330V	1052880	F-302
WSE4S-3F1330	1052879	F-265
WSE4S-3F2130V	1052891	F-302
WSE4S-3F2130	1052890	F-265
WSE4S-3F3130H	1052882	F-324
WSE4S-3N1330H	1052873	F-324
WSE4S-3N1330V	1052874	F-302
WSE4S-3N1330	1052872	F-265
WSE4S-3N2130V	1052878	F-302
WSE4S-3P1330V	1052887	F-302
WSE4S-3P2130V	1052893	F-302
WSE4S-3P2130	1052892	F-265
WSE4S-3P3130H	1052888	F-324
WSE4S-3P5230H	1054896	F-324
WSE4SC-3P2230A70	1067768	F-265
WSE4SC-3P2230A71	1067769	F-265
WSE4SC-3P2230A91	1067770	F-265
WSE4SC-3P2230	1067767	F-265
WSE4SL-3N1137V	1058270	F-344
WSE4SL-3N1137	1058250	F-281
WSE4SL-3P2237V	1058267	F-344
WSE4SL-3P2237	1058249	F-281
WSE4SL-3P2437V	1058249	F-344
WSE4T-3E1430	1029648	F-252
WSE4T-3F1430	1029648	F-252 F-252
WSE4T-3P1430		
WSE8-N1131V	1029646	F-252 F-389
WSE8-N2131V	6041485	
WSE8-N2231V	6041486	F-389
WSE8-P1131V	6041487	F-389
WSE8-P2131V	6041489	F-389
WSE8-P2231V	6041490	F-389
WSE9-3N1130	6041491	F-389
	1049079	G-452
WSE9-3N2230	1055041	G-452
WSE9-3N2430 WSE9-3P1130	1049080	G-452
	1049075	G-452
WSE9-3P2230	1049076	G-452
WSE9-3P2430	1049077	G-452
WSE9-3P3430	1049078	G-452
WSE9L-3N2237	1058179	G-474
WSE9L-3N2437	1058180	G-474
WSE9L-3P1137	1058915	G-474
WSE9L-3P2237	1058182	G-474
WSE9L-3P2437	1058181	G-474
WSE9M4-3N1130	1051914	G-453
WSE9M4-3N2230	1052938	G-453
WSE9M4-3P1130	1051911	G-453
WSE9M4-3P2230	1051912	G-453
WSE9M4-3P2430	1051913	G-453
WSE9M4-3P3430	1054435	G-453
WSG1-01	1018470	L-866
WT100-2N1419	6052375	F-406

Model name	Part no.	Page
WT100-2N1439	6052369	F-406
WT100-2N3419	6052376	F-406
WT100-2N3439	6052370	F-406
WT100-2N4419	6052377	F-406
WT100-2N4439	6052371	F-406
WT100-2P1419	6052378	F-406
WT100-2P1439	6052372	F-406
WT100-2P3419	6052379	F-406
WT100-2P3439	6052373	F-406
WT100-2P4419	6052380	F-406
WT100-2P4439	6052374	F-406
WT100L-E1141	6030705	F-414
WT100L-E2141	6030706	F-414
WT100L-E2241	6030707	F-414
WT100L-F1141	6030702	F-414
WT100L-F2141	6030703	F-414
WT100LF2141 WT100LF2241		
WT100E-12241 WT12L-2B510	6030704	F-414
WT12L-2B530	1017959	G-512
	1018250	G-512
WT12L-2B540	1018251	G-512
WT12L-2B550T01	1018582	G-512
WT12L-2B550	1017904	G-512
WT12L-2B551	1047958	G-512
WT14-2N111	1026060	G-546
WT14-2N122	1026053	G-546
WT14-2N132	1026072	G-546
WT14-2N411	1026062	G-546
WT14-2N422	1026054	G-546
WT14-2N432	1026057	G-546
WT14-2P111	1026058	G-546
WT14-2P122	1026051	G-546
WT14-2P132	1026055	G-546
WT14-2P411	1026059	G-546
WT14-2P422S03	1041679	G-547
WT14-2P422	1026052	G-546
WT14-2P432S08	1045104	G-546
WT14-2P432	1026056	G-546
WT18-3K420	1061203	G-559
WT18-3N110	1025891	G-559
WT18-3N130	1025897	G-559
WT18-3N131	1028040	G-559
WT18-3N210	1025892	G-559
WT18-3N410	1025893	G-559
WT18-3N430	1025898	G-559
WT18-3N431	1026035	G-559
WT18-3P110	1025887	G-559
WT18-3F111	1025087	G-559
WT18-3P120		
WT18-3F120 WT18-3P130	1025904	G-559
WT18-3P131	1025895	G-559
WT18-3P210	1026034	G-559
	1025888	G-559
WT18-3P230	1026559	G-559
WT18-3P410	1025889	G-559
WT18-3P411	1026031	G-559
WT18-3P420	1025905	G-559
WT18-3P421	1026383	G-559
WT18-3P430	1025896	G-559
WT18-3P431	1026032	G-559

Madalyana	-	
Model name	Part no.	Page
WT18X-3P920	1029901	G-559
WT2000-B1102	7023056	H-674
WT2000-B1122	7023058	H-674
WT2000-B4100	7024001	H-674
WT2000-B5100	7023059	H-674
WT2000-B5120	7023061	H-674
WT2000-R1102	7023062	H-675
WT2000-R1122	7023064	H-675
WT2000-R5100	7023065	H-675
WT2000-R5120	7023067	H-675
WT23-2K2421	1028068	H-582
WT23-2N2421	1028073	H-582
WT23-2P2421	1027778	H-582
WT23-2P2441	1027779	H-582
WT23-2P3441	1028066	H-582
WT24-2B210	1016931	H-592
WT24-2B220	1017882	H-592
WT24-2B240	1017813	H-592
WT24-2B250	1017883	H-592
WT24-2B410	1016933	H-592
WT24-2B420	1017885	H-592
WT24-2B440	1016934	H-592
WT24-2R210	1016932	H-594
WT24-2R220	1016854	H-594
WT24-2R240	1017854	H-594
WT24-2R250	1016820	H-594
WT24-2V220	1017886	H-592
WT24-2V250	1017887	H-592
WT24-2V510	1017855	H-592
WT24-2V540	1017888	H-592
WT24-2V550S12	1019468	H-592
WT24-2X200	1041910	H-604
WT24-2X400	1040722	H-604
WT27K-2F430	1059239	H-612
WT27L-2F430	1016019	H-612
WT27L-2N430	1026165	H-612
WT2F-E150	6043902	F-210
WT2F-N140	6030583	F-210
WT2F-N150	6030576	F-210
WT2F-N170	6030587	F-210
WT2F-N180	6030572	F-210
WT2F-P140	6030584	F-210
WT2F-P150	6030580	F-210
WT2F-P170	6030588	F-210
WT2F-P180	6030573	F-210
WT2F-P240	6030575	F-210
WT2F-P250	6030581	F-210
WT2F-P270	6030589	F-210
WT2F-P280	6030574	F-210
WT2F-P440	6030586	F-210
WT2F-P450	6030582	F-210
WT2F-P470	6030590	F-210
WT2F-P480	6030590	F-210 F-210
WTB11-2N1131	1041379	G-494
WTB11-2N2431	1041379	G-494 G-494
WTB11-2N2461	1041378	G-494 G-494
WTB11-2N2401 WTB11-2P1131	1041377	G-494 G-494
WTB11-2P1131 WTB11-2P2431		
MIDIT-ZI ZTOT	1041376	G-494

Model name	Part no.	Page
WTB11-2P2461	1044442	G-494
WTB12-3N1111	1041429	G-530
WTB12-3N1131	1041418	G-530
WTB12-3N1711	1041430	G-530
WTB12-3N2411	1041427	G-530
WTB12-3N2413	1041428	G-530
WTB12-3N2431	1041416	G-530
WTB12-3N2433	1041417	G-530
WTB12-3P1111	1041424	G-530
WTB12-3P1131	1041413	G-530
WTB12-3P1711	1041426	G-530
WTB12-3P2411	1041422	G-530
WTB12-3P2413	1041423	G-530
WTB12-3P2431	1041411	G-530
WTB12-3P2433	1041412	G-530
WTB12-3P2441	1041421	G-530
WTB12-3P2461S01	1051967	G-530
WTB12-3P2461S58	1047850	G-531
WTB12C-3P2432A70	1067772	G-531
WTB12C-3P2432A71	1067773	G-531
WTB12C-3P2432A91	1060222	G-531
WTB12C-3P2432	1067771	G-531
WTB15-A1131	1046281	I-768
WTB15-A2431	1043325	I-768
WTB15-R2451	1046282	I-768
WTB15-B2431	1040282	I-768
WTB15-N1131		I-768
WTB15-N2431	1046283	
WTB15-N2431 WTB15-P1131	1044306	I-768
WTB15-P131	1046284	I-768
WTB250-2F2441	1044305	I-768
WTB250-2N1131	6044685	H-642
WTB250-2N1131	6044672	H-642
WTB250-2N1141 WTB250-2N1151	6044678	H-642
WTB250-2N1151 WTB250-2N1251	6044686	H-643
WTB250-2N2431	6044687	H-643
	6044673	H-642
WTB250-2N2441	6044679	H-642
WTB250-2N2451	6044689	H-643
WTB250-2P1131	6044674	H-642
WTB250-2P1141	6044680	H-642
WTB250-2P1151	6044690	H-643
WTB250-2P1241	6044681	H-642
WTB250-2P1251	6044691	H-643
WTB250-2P2431	6044675	H-642
WTB250-2P2441	6044682	H-642
WTB250-2P2451	6044692	H-643
WTB250-2R1531	6044676	H-643
WTB250-2R1541	6044683	H-643
WTB250-2R1551	6044693	H-643
WTB250-2R1631	6044677	H-643
WTB250-2R1641	6044684	H-643
WTB250-2R1651	6044694	H-643
WTB27-3E2411	1027755	H-619
WTB27-3E2611	1027757	H-619
WTB27-3E2641	1027747	H-619
WTB27-3F2411	1027753	H-619
WTB27-3F2611	1027756	H-619
WTB27-3F2641	1027746	H-619

Model name	Part no.	Page
WTB27-3N1111	1044855	H-619
WTB27-3N1161	1051644	H-619
WTB27-3N2413	1027761	H-619
WTB27-3N2483	1056385	E-132
WTB27-3P1111	1027752	H-619
WTB27-3P1113	1027759	H-619
WTB27-3P1211	1028065	H-619
WTB27-3P2411	1025994	H-619
WTB27-3P2413	1027760	H-619
WTB27-3P2421	1027754	H-619
WTB27-3P2441	1027744	H-619
WTB27-3P2443	1027745	H-619
WTB27-3P2461	1044163	H-619
WTB27-3P2483	1056384	E-132
WTB27-3P3411	1044438	H-619
WTB27-3P3441	1029082	H-619
WTB27-3P3461	1048546	H-619
WTB27-3R2611	1027763	H-621
WTB27-3R2641	1027750	H-621
WTB27-3S1511	1027762	H-621
WTB27-3S1541	1027749	H-621
WTB27X-3P1811	1027749	H-634
WTB2S-2F1310		
WTB2S-2E1310 WTB2S-2E1330	1064397	F-218
WTB2S-2F1310	1064580	F-218
WTB2S-2F1330	1064394	F-218
WTB2S-2F1360	1064574	F-218
	1064606	F-219
WTB2S-2F3110	1064396	F-218
WTB2S-2F3130	1064576	F-218
WTB2S-2F3160	1064608	F-219
WTB2S-2N1130	1063321	F-218
WTB2S-2N1145	1063552	F-219
WTB2S-2N1151	1066113	F-219
WTB2S-2N1310	1064249	F-218
WTB2S-2N1330	1064578	F-218
WTB2S-2N1360	1064609	F-219
WTB2S-2N3230	1064581	F-218
WTB2S-2N3251	1066114	F-219
WTB2S-2P1145	1064614	F-219
WTB2S-2P1151	1066110	F-219
WTB2S-2P1175	1064621	F-219
WTB2S-2P1310	1064393	F-218
WTB2S-2P1330	1064573	F-218
WTB2S-2P1360	1064605	F-219
WTB2S-2P3110	1064395	F-218
WTB2S-2P3130	1064575	F-218
WTB2S-2P3160	1064607	F-219
WTB2S-2P3210	1063314	F-218
WTB2S-2P3230	1063517	F-218
WTB2S-2P3245	1064615	F-219
WTB2S-2P3251	1066111	F-219
WTB2S-2P3260	1063545	F-219
WTB2S-2P3275	1064620	F-219
WTB2SC-2P3244	1063550	F-219
WTB2SC-2P3274	1063646	F-220
WTB4-3E1361	1028108	F-240
WTB4-3E2161	1028110	F-240
WTB4-3F1361	1028105	F-240

Model name	Part no.	Page
WTB4-3F2161	1028107	F-240
WTB4-3N1161	1028102	F-240
WTB4-3N1164	1028090	F-240
WTB4-3N1192	1059272	E-126
WTB4-3N1362	1028087	F-240
WTB4-3N1371	1028125	F-241
WTB4-3N1461	1057301	F-240
WTB4-3N2161	1028104	F-240
WTB4-3N2162	1028088	F-240
WTB4-3N2171	1028126	F-241
WTB4-3P1161	1028096	F-240
WTB4-3P1264	1041890	F-240
WTB4-3P1361	1028094	F-240
WTB4-3P1362	1028081	F-240
WTB4-3P1371	1028121	F-241
WTB4-3P2161	1028099	F-240
WTB4-3P2162	1028084	F-240
WTB4-3P2171	1028123	F-241
WTB4-3P2192	1058268	E-126
WTB4-3P2261	1028100	F-240
WTB4-3P2262	1028085	F-240
WTB4-3P2271	1042190	F-241
WTB4-3P2292	1062850	E-126
WTB4S-3E1331	1042064	F-262
WTB4S-3E1361	1042047	F-263
WTB4S-3F2131	1042060	F-262
WTB4S-3F2132V	1046404	F-300
WTB4S-3F2161	1042044	F-263
WTB4S-3F2162V	1046389	F-301
WTB4S-3F2234VS08	1053075	F-300
WTB4S-3N1131	1042063	F-262
WTB4S-3N1132H	1048098	F-322
WTB4S-3N1132	1051563	F-262
WTB4S-3N1134	1042052	F-262
WTB4S-3N1135H	1048101	F-322
WTB4S-3N1162H	1048095	F-322
WTB4S-3N1162V	1046391	F-301
WTB4S-3N1165H	1048107	F-322
WTB4S-3N1331	1042062	F-262
WTB4S-3N1332V	1046406	F-300
WTB4S-3N1332	1042055	F-262
WTB4S-3N1361	1042046	F-263
WTB4S-3N2131	1042061	F-262
WTB4S-3N2132V	1046405	F-300
WTB4S-3N2161	1042045	F-263
WTB4S-3N2232	1051872	F-262
WTB4S-3N2432V	1054674	F-300
WTB4S-3N2462V	1054703	F-301
WTB4S-3P1132V	1046402	F-300
WTB4S-3P1162H	1046402	F-300
WTB4S-3P1331	1031983	F-262
WTB4S-3P1332	1052284	F-262
WTB4S-3P1361	1052284	
WTB4S-3F1301 WTB4S-3P2131		F-263
WTB4S-3F2131 WTB4S-3P2132V	1042056	F-262
WTB4S-3P2132V	1046397	F-300
WTB4S-3P2161	1042053	F-262
WTB4S-3P2161 WTB4S-3P2162V	1042040	F-263
VV 1 D43-3 F Z 1 U Z V	1046384	F-301

Model name	Part no.	Page
WTB4S-3P2204VS02	1047652	F-300
WTB4S-3P2205VS01	1046214	F-300
WTB4S-3P2231	1042057	F-262
WTB4S-3P2232	1054282	F-262
WTB4S-3P2234VS05	1050833	F-300
WTB4S-3P2234	1042050	F-262
WTB4S-3P2235V	1045093	F-300
WTB4S-3P2261	1042041	F-263
WTB4S-3P2262V	1046383	F-301
WTB4S-3P2402VS09	1054706	F-300
WTB4S-3P2432V	1054672	F-300
WTB4S-3P2462V	1054675	F-301
WTB4S-3P3232H	1048096	F-322
WTB4S-3P3235H	1048100	F-322
WTB4S-3P3262H	1048094	F-322
WTB4S-3P3265H	1048102	F-322
WTB4S-3P5204HS02	1054865	F-322
WTB4S-3P5232H	1054864	F-322
WTB4S-3W1331	1050573	F-263
WTB4SC-3P2262A70	1067756	F-263
WTB4SC-3P2262A71	1067757	F-263
WTB4SC-3P2262A91	1067758	F-263
WTB4SC-3P2262	1042033	
WTB4SL-3N1161	1058242	F-263
WTB4SL-3N1161V		F-280
WTB4SL-3N1102V WTB4SL-3N2261	1058257	F-344
WTB4SL-3N2262V	1058240	F-280
	1058252	F-344
WTB4SL-3N2462V WTB4SL-3N3261	1058254	F-344
	1058241	F-280
WTB4SL-3N4162H	1058275	F-360
WTB4SL-3P1161	1058239	F-280
WTB4SL-3P1162V	1058256	F-344
WTB4SL-3P2261	1058237	F-280
WTB4SL-3P2262V	1058251	F-344
WTB4SL-3P2462V	1058253	F-344
WTB4SL-3P3261	1058238	F-280
WTB4SL-3P4162H	1058274	F-360
WTB4SL-3P5262H	1058271	F-360
WTB4T-3N1264	1028092	F-252
WTB4T-3P1264	1028091	F-252
WTB8-N1111V	6041453	F-388
WTB8-N1111	6033210	F-374
WTB8-N1131V	6041461	F-388
WTB8-N1131	6033204	F-374
WTB8-N2111V	6041454	F-388
WTB8-N2111	6033212	F-374
WTB8-N2131V	6041462	F-388
WTB8-N2131	6033206	F-374
WTB8-N2211V	6041455	F-388
WTB8-N2211	6033214	F-374
WTB8-N2231V	6041463	F-388
WTB8-N2231	6033208	F-374
WTB8-P1111V	6041457	F-388
WTB8-P1111	6033211	F-374
WTB8-P1131V	6041465	F-388
WTB8-P1131	6033205	F-374
WTB8-P2111V	6041458	F-388
WTB8-P2111	6033213	F-374
	3333213	. 5.7

Model name	Part no.	Page
WTB8-P2131V	6041466	F-388
WTB8-P2131	6033207	F-374
WTB8-P2211V	6041459	F-388
WTB8-P2211	6033215	F-374
WTB8-P2231V	6041467	F-388
WTB8-P2231	6033209	F-374
WTB8L-N1111	6033222	F-400
WTB8L-N1131	6033216	F-400
WTB8L-N2111	6033224	F-400
WTB8L-N2131	6033218	F-400
WTB8L-N2211	6033226	F-400
WTB8L-N2231	6033220	F-400
WTB8L-P1111	6033223	F-400
WTB8L-P1131	6033217	F-400
WTB8L-P2111	6033225	F-400
WTB8L-P2131	6033219	F-400
WTB8L-P2211	6033227	F-400
WTB8L-P2231	6033221	F-400
WTB9-3N1111S14	1050948	G-450
WTB9-3N1161	1049052	G-450
WTB9-3N2461	1049053	G-450
WTB9-3P1111S14	1052173	G-450
WTB9-3P1111	1049042	G-450
WTB9-3P1161	1049043	G-450
WTB9-3P1261	1049044	G-450
WTB9-3P2211S14	1052171	G-450
WTB9-3P2211	1049045	G-450
WTB9-3P2261	1049047	G-450
WTB9-3P2411S14	1052172	G-450
WTB9-3P2411	1049048	G-450
WTB9-3P2461	1049049	G-450
WTB9-3P3411S14	1054431	G-450
WTB9-3P3461	1034431	G-450
WTB9L-3N2261		
WTB9L-3N2291	1062523	G-472
WTB9L-3N2461	1058146 1062524	G-472 G-472
WTB9L-3N2491		
WTB9L-3N3461	1058149	G-472
WTB9L3N3401 WTB9L3N3491	1062525	G-472
WTB9L-3P1161	1058152	G-472
WTB9L-3P2261	1058232	G-472
WTB9L3F2201 WTB9L3F2291	1058230	G-472
WTB9L-3F2291 WTB9L-3P2461	1058150	G-472
	1058231	G-472
WTB9L-3P2491 WTB9L-3P3461	1058151	G-472
	1058916	G-472
WTB9M4 2N44 C4	1058153	G-472
WTB9M4-3N1161	1051882	G-451
WTB9M4-3N2261	1051885	G-451
WTD0M4-204141	1055145	G-451
WTB9M4-3P1111	1051886	G-451
WTB9M4-3P1161	1051887	G-451
WTB9M4-3P2211	1051888	G-451
WTB9M4-3P2261	1051889	G-451
WTB9M4-3P2411	1051890	G-451
WTB9M4-3P2461	1051891	G-451
WTB9M4L-3P1161	1058188	G-473
WTB9M4L-3P1191	1058226	G-473
WTB9M4L-3P2261	1058186	G-473

Model name	Part no.	Page
WTB9M4L-3P2291	1058224	G-473
WTB9M4L-3P2461	1058187	G-473
WTB9M4L-3P2491	1058225	G-473
WTD20E-V2414	1064778	E-116
WTD20E-V2445	1065772	E-116
WTD20E-W1114	1064779	E-116
WTD20E-W1145	1065773	E-116
WTD20EC-V2419	1064782	E-117
WTD20EC-V2449	1064783	E-116
WTE11-2N1132	1041384	G-495
WTE11-2N2432	1041383	G-495
WTE11-2P1132	1041382	G-495
WTE11-2P2432	1041381	G-495
WTE15-A1111	1046277	I-768
WTE15-A2411	1043316	I-768
WTE15-B1111	1046278	I-768
WTE15-B2411	1043317	I-768
WTE15-N1111	1046147	I-768
WTE15-N2411	1043313	I-768
WTE15-P1111	1046148	I-768
WTE15-P2411	1043314	I-768
WTE23-2N2412	1027782	H-582
WTE23-2P2412	1027781	H-582
WTE280-2H1531	6044731	H-657
WTE280-2H4331	6044730	H-657
WTE280-2N1131	6044727	
WTE280-2N2431		H-656
WTE280-2N4331	6044729	H-656
WTE280-2P1131	6044725	H-656
WTE280-2P1131	6044726	H-656
WTE280-2P4331	6044728	H-656
WTE280-2F4531 WTE280-2R1531	6044724	H-656
WTE280-2R4331	6044759	H-657
WTE8-N1131V	6044758	H-657
WTE8-N2131V	6041469	F-389
	6041470	F-389
WTE8-N2231V	6041471	F-389
WTE8-P1131V	6041473	F-389
WTE8-P2131V	6041474	F-389
WTE8-P2231V	6041475	F-389
WTF11-2P2431	1041380	G-494
WTF12-3N1131	1041410	G-531
WTF12-3N2431	1041408	G-531
WTF12-3N2433	1041409	G-531
WTF12-3N2441	1041403	G-532
WTF12-3P1131	1041406	G-531
WTF12-3P1141	1041402	G-532
WTF12-3P2431	1041404	G-531
WTF12-3P2433	1041405	G-531
WTF12-3P2441	1041400	G-532
WTF12-3P2443	1041401	G-532
WTF12G-3N2432	1066279	E-144
WTF12G-3P2432	1065719	E-144
WTF4S-3P2262V	1046410	F-301
WTF4S-3P2265V	1045094	F-301
WTF4S-3P3264H	1048109	F-323
WTT280L-2N1531	6048067	H-668
WTT280L-2N1536	6048068	H-668
WTT280L-2N2531	6048063	H-668

Madel name	Dentag	D. d.
Model name	Part no.	Page
WTT280L-2N2536	6048064	H-668
WTT280L-2P1531	6048065	H-668
WTT280L-2P1536	6048066	H-668
WTT280L-2P2531	6048061	H-668
WTT280L-2P2536	6048062	H-668
WTV2S-2P1320	1064660	F-220
WTV2S-2P3120	1064662	F-220
WTV2S-2P3220	1064661	F-220
WTV4-3N1171	1046898	F-241
WTV4-3N1321	1029885	F-241
WTV4-3N1341	1028115	F-241
WTV4-3N2141	1028116	F-241
WTV4-3N2221	1048995	F-241
WTV4-3P1321	1029888	F-241
WTV4-3P1341	1028111	F-241
WTV4-3P2141	1028113	F-241
WTV4-3P2241	1028114	F-241
WTV4-3P2271	1046644	F-241
ZL1-F2415	1045498	I-779
ZL1-F2421	1045502	I-779
ZL1-F2431	1045506	I-779
ZL1-P2415	1045497	I-779
ZL1-P2421	1045501	I-779
ZL1-P2431	1045505	I-779
ZL2-E2415	1045390	I-779
ZL2-E2428	1045372	I-779
ZL2-F2415	1045389	I-779
ZL2-F2428	1045371	I-779
ZL2-F2438 ZL3-E2421	1045385 1045536	I-779 I-779
ZL3-E2421 ZL3-E2431	1045540	1-779
ZL3-E2451 ZL3-F2415	1045531	1-779
7L3-F2421	1045535	1-779
ZL3-F2431	1045539	I-779
ZL3-P2415	1045530	I-779
ZLM1-B1111A10	7027768	E-166
ZLM1-B1111A11	7027769	E-167
ZLM1-B1211A10	7027784	E-166
ZLM1-B1211A11	7027785	E-167
ZLM1-B1451A10	1052126	E-166
ZLM1-B1612E42	7028842	E-166
ZLM1-B1612E43	7028843	E-167
ZLM1-B2111A10	7027770	E-166
ZLM1-B2111A11	7027771	E-167
ZLM1-B2211A10	7027786	E-166
ZLM1-B2211A11	7027787	E-167
ZLM1-B5612E41	7028428	E-167
ZLM1-C1111A10	7027764	E-167
ZLM1-C1111A11	7027765	E-167
ZLM1-C1211A10	7027780	E-167
ZLM1-C1211A11	7027781	E-167
ZLM1-C1451A10	7029987	E-167
ZLM1-C1451A11	7029988	E-167
ZLM1-C2111A11	7027767	E-167
ZLM1-C2211A10	7027782	E-167
ZLM1-C2211A11	7027783	E-167
ZT1-N3215	1045562	I-778
ZT1-P3215	1045563	I-778

Model name	Part no.	Page
ZT1-P3221	1045579	I-778
ZT1-P3231	1045595	I-778
ZT1-P4215	1045567	I-778
ZT1-P4221	1045583	I-778
ZT1-P5215	1045559	I-778
ZT1-P5221	1045575	I-778
ZT1-P5231	1045591	I-778
ZT2-N3215	1045407	I-778
ZT2-P3215	1045408	I-778
ZT2-P3228	1045473	I-778
ZT2-P3238	1045489	I-778
ZT2-P4228	1045477	I-778
ZT2-P4238	1045493	I-778
ZT2-P5228	1045469	I-778
ZT2-P5238	1045485	I-778

## SICK AT A GLANCE

SICK is a leading manufacturer of intelligent sensors and sensor solutions for factory, logistics, and process automation. With more than 6,000 employees and over 40 subsidiaries worldwide, we are always close to our customers. A unique range of products and services creates the perfect basis for controlling processes securely and efficiently, protecting individuals from accidents and preventing damage to the environment.

We have extensive experience in various industries and understand their processes and requirements. With intelligent sensors, we can deliver exactly what our customers need. In application centers in Europe, Asia and North America, system solutions are tested and optimized in accordance with customer specifications. All this makes us a reliable supplier and development partner.

Comprehensive services round out our offering: SICK LifeTime Services provide support throughout the machine life cycle and ensure safety and productivity.

For us, that is "Sensor Intelligence."

## Worldwide presence:

Australia, Belgium/Luxembourg, Brasil, Česká republika, Canada, China, Danmark, Deutschland, España, France, Great Britain, India, Israel, Italia, Japan, Magyarország, México, Nederland, Norge, Österreich, Polska, România, Russia, Schweiz, Singapore, Slovenija, South Africa, South Korea, Suomi, Sverige, Taiwan, Türkiye, United Arab Emirates, USA.

Please find detailed addresses and additional representatives and agencies in all major industrial nations at: www.sick.com

